Nuts & Volts

U.S. $3.50
CANADA $4.50

Exploring Electronics And Technology For The Hobbyist And Professional

October 1998 Vol. 19 No. 10

SPI AND THE PRINTER PORT

BUILD A STEPPER MOTOR CONTROLLER

FAMILY RADIO SERVICE RADIOS - FACTS AND MUCH FICTION

A SONAR SENSOR FOR AMATEUR ROBOTICS PLATFORMS

10>
0 74470 89295 3

BOTH SINGLE AND DUAL DRIVE MODELS AVAILABLE.

MULTIMEDIA PROCESSOR ACCELERATES DUPLICATION.

EXTERNAL SCSI-II PORT WORKS LIKE A STANDARD CD WRITER FOR CREATING CUSTOM DISKS.

TOTALLY SELF CONTAINED, NO CONNECTION TO A PC IS REQUIRED.

INTERNAL A/V HARD DRIVE STORES DISK IMAGES FOR MULTIPLE COPIES, AND CUSTOM AUDIO DISKS.

ADVANCED FORMAT DETECTION PRODUCES PERFECT DUPLICATES ON STANDARD CD-R MEDIA.

COPY ANY CD INSTANTLY. NO PC REQUIRED.

CD DUPE-IT!

Instantly duplicate CD-ROM disks for software distribution. Make backup copies of your favorite software on rugged, permanent media. Produce disks quickly and economically. No mastering or multimedia experience is required.

Insert your original disk and press "start." The multimedia processor quickly copies any disk to the internal A/V hard drive. Insert blank disks and make as many copies as you like. You'll produce identical, bit-for-bit duplicates. The system is totally self contained—no connection to a PC or Mac is required. Just plug in the power cord and press "start"—it's that easy.

BUY MANUFACTURER DIRECT: $1095

408 330-5524

You can even make your own custom audio disks without a PC! Insert your original CD's, select the tracks you want, and CD Dupe-It will copy them to the internal hard drive. Then insert a blank CD, and you'll have a custom audio disk with just the songs you want.

With the included CD mastering software, CD Dupe-It will work overtime as your personal CD mastering system. Just attach a SCSI cable to your PC or Mac, and you're ready to design and create your own original CD's. Similar systems used in duplication houses cost over $10,000. Now you can easily copy disks yourself for a fraction of the price.

CSC

CORPORATE SYSTEMS CENTER

3310 WOODWARD AVE., SANTA CLARA, CA 95054

WWW.CORPSYS.COM

Software publishers—ask about our high-volume multi-drive duplication systems.
CD Dupe-It is sold and intended for backup and in-house design purposes only. Copyright laws must be observed.

Write in 76 on Reader Service Card.

HSC Electronic Supply

Serving Silicon Valley since 1964!

...brings you a potpourri of high-tech goodies for the techno-tinkerer!
For thirty years we have been your source for Silicon Valley exotica!

PCI-Bus 56K Modem!

- Lucent PCI-Bus 56K Modem at unheard-of price!
- Data, FAX, voice, full V.90 compatibility
- Voice from handset
- Windows 95/98 or NT only (Not Win 3.1 compatible)
- Uses latest Lucent chipset, comes with Lucent drivers
- New OEM pack, with Trio application software on CD
- Warranty

HSC#17532 **$39.95**

USB Video Camera!

- Compaq "Proshare" color videoconferencing camera
- Made by Intel -- supported Win 95 plug & play device
- Universal Serial Bus (USB) interface
- Comes with USB cable, manuals
- No drivers or software supplied

HSC#17539 **$59.00**

Ruby Laser Returns!

- That's right, we found some more of the popular Laser Rangefinder modules we featured a few months ago!
- Optics module from Q-switched Ruby Laser includes cavity, ruby rod (3"), flash tube, spinning prism with high-speed DC motor, hall-effect switch, thermistor, etc.
- Factory refurbished units with spec. / test sheets
- Does not include power supply or control circuitry
- Caution...high power bursts -- not for amateurs!
- Overall measurements 8" long x 2.5" x 1.5" (excl. motor)

HSC#17263 **$99.00**

Tiny Field Strength Analyzer!

- The Protek 3201 is the world's first hand held RF Field Strength Analyzer! Menu-select functions, LCD display
- Wide band reception range of 100 KHz to 2060 MHz
- Ideal tool for field RF technicians: test, install and maintain Mobile Telecommunications Systems, Cellular and Cordless Phones, Ham Radios, CBs, Paging Systems, Cable and Satellite TV systems
- Measures and demodulates Narrow Band FM (N-FM), Wide Band FM (W-FM), AM, Single Side Band (SSB)
- Built-in 2 GHz frequency counter
- PLL tuning system for precise frequency tuning
- Up to 160 channels may be scanned and displayed on the 192 x 192 pixel backlit LCD
- Built-in speaker, RS-232 and parallel interfaces

HC Protek 3201 **$2049.00**

FM Tuner for your PC!

- Listen to FM radio while using your computer!
- Set up to 24 programmable stations
- Even works as an alarm clock (sorry, no snooze button!)
- Compatible with DOS/Windows/Win95/Win98
- ISA-bus card, receives from 87.5 to 108 MHz
- New OEM pack with antenna, audio cable, software, set-up guide -- works in combination with your sound card.
- 90-day warranty

HSC#17533 **$12.50**

External SCSI Drive Cases

- Bargain case for 5.25" drives, brand new!
- 7" x 4.5" x 10.5" overall size
- 50-pin SCSI connectors
- SCSI ID switch
- 65W Power supply (lots of power for hard drives, etc.)
- Fan-cooled, uses standard IEC Power cord (not included)

HSC# 17130 **$39.95**

- High quality low profile case for 5.25" drives, brand new!
- 7" x 2.25" x 11" overall size
- 50-pin SCSI connectors, RCA Audio connectors
- SCSI ID switch, termination switch
- *Tiny* 12W Power Supply (5VDC @ 1.4A, 12VDC @ .4A, probably only good for CD-ROM's)
- Fan-cooled, uses standard IEC Power cord (not included)

HSC# 17357 **$29.95**

- High quality case for 3.5" drives, used, like new!
- 6.5" x 2.5" x 10" overall size, good for tape drives!
- 50-pin SCSI connectors, SCSI ID switch
- Drive bay snaps out for easy access to cables
- 40W Power Supply (5VDC @ 2A, 12VDC @ 2.5A)
- Fan-cooled, uses standard IEC Power cord (not included)

HSC# 17356 **$19.95**

Drive-bay Amp & Equalizer

- Made by NEC, fits into standard 5.25" drive bay
- 5-Band equalizer has 4 channels, 6 watts RMS/channel
- 25 watts RMS total power output
- Headphone jack on front panel
- Connects to drive power connector
- No special software or drivers required!
- Compatible with any sound card
- 90-day warranty

HSC#17534 **$19.95**

ATX Pentium Power!

- Support for Intel Pentium 90-200, 166-200 MMX CPU's
- Also supports Cyrix/IBM 6x86 P, PR 150 & 166 CPU's
- Also supports AMD K5, and, with special VRM, K6 CPU's
- 4 PCI slots, 4 ISA slots (one shared), 16-bit stereo sound
- 4 DIMM RAM sockets, parity or non-parity, ECC, EDO, FP
- On-board 2 x IDE, 2 x 16550 Serial ports, 1 parallel port
- New, 90-day warranty (CPU not included)

HSC# 80437 **$49.95**

- ATX style Midtower case, fits above motherboard
- "Netpower" logo on front, never used, 90-day warranty

HSC# 17517 **$29.95**

ATX Power Supply

- Perfect for use with case, motherboard at left!
- 250W supplies have 5V @ 25A as well as 3.3V @15A
- Brand New, 90-day warranty

HSC#80445 **$39.95**

PCMCIA Sound Card!

Media Vision PCMCIA Sound Card

- Great for Portables, Laptops with PCMCIA Slot
- External pod has joystick port, mic. input, line in & line out jacks, volume control.
- Installation software, instructions included
- Windows 3.x, Windows 95 compatible
- New in OEM packaging (no box), 90-day HSC warranty
- We had these before at $39.95 and they went fast!

HSC#17036 **$29.95**

Mitsumi 16X CD-ROM

- Great price on a great upgrade -- Mitsumi 16X CD-ROM
- IDE interface, ATAPI compatible, model CRMCFX140S2
- New, pulled from unused equipment, 90-day warranty

HSC#17490 **$29.95**

HP ScanJet Special

- Wow! HP ScanJet 3P flat-bed greyscale scanners at $49!
- Complete with stand, PC SCSI adapter, cables, Mac software (IBM drivers not included) at an unreal price!
- SCSI Interface, works with Mac or PC (Mac s/w incl.)
- 300dpi resolution (native mode), 1200dpi with dithering
- Information provided on where to download PC drivers
- Dealer display models & shelf stock returns (boxes may be opened, but scanners are unused)
- Scan rate of 10 seconds for letter-size page
- Factory RMA's from dealers, unused, 90-day warranty
- Hurry, the ones with document feeder are already gone, these won't last at this great price!

HSC#17392 **$49.00**

Infrared Connections!

- IBM "Options" series ISA-Bus and PCMCIA card adaptors will add industry standard infrared communications capability to your desktop PC (with ISA slots) or notebook computer! (Win95 instructions available on our website)
- Allows wireless connection to compatible notebooks, workstations, printers, and other peripherals supporting the Infrared Data Association (IrDA) standard.
- Also will emulate a COM port for cable-less hook-ups
- Communicates up to 115KBps, or up to 1.152MBps with the included TranXit Software.
- Operates over distances up to 3 meters (10 ft.)
- Includes Card, transceiver module, driver disk & book
- Both styles new in box, 90-day warranty

HSC#16483 PCMCIA Version **$19.95**
HSC#16813 ISA-Bus Version **$19.95**
Or a package deal...get both for **$29.95**

Hand-held UV Lamp

- "Derma-spec" lamp was made for Avon products to examine the face for "problem" cosmetic areas!
- Works fine for counterfeit bill & credit card detection, minerology, fluorescent art effects, etc.
- We wouldn't use these on *our* faces for too long...

HSC#17383 **$12.95**

Parallel-Port Keyboard!

- Perfect for notebook computers, laptops, palm-tops, etc.
- Full-size 101 keyboard by ALPS, model LPT 101
- Includes manual, installation diskette
- New in OEM box, 90-day warranty
- New Price!



HSC#17160 **$39.95**

Video-hacker Dream!

- Logitech Videoman Video-conference camera & interface
- These units were sold with Hewlett Packard S-700 workstations for videoconference capability
- We do not have technical data, software or manuals
- All we have is cameras with stand, and SCSI-II interface
- The camera is on a weighted stand that extends from 13" tall to over 20" tall, and has a stereo microphone
- Color camera is digital output only (not NTSC) as far as we can tell -- but who knows?
- Interface box has two SCSI-II ports on back, and a DC power input (we do not have the adapter), and on the front it has a mic. out jack, composite video out (BNC), and the connector for the camera cable.
- Note: HP and Logitech will provide no information on these

HSC#17503 **$39.95**

Corel Office Professional 7

- Great Software Bundle -- Amazing Value!
- Includes Corel Wordperfect 7, Corel Quattro Pro 7, Paradox 7, Corel Presentations 7, CorelDRAW 6, CorelFLOW 3, Sidekick 95, Netscape Navigator, Dashboard 95, 1000 fonts, 10000 clip-art images, more!
- For Windows 95, Windows NT 3.51 and Windows NT 4.0
- Distributed on CD-ROMs, with hefty manual pack
- New, shrink-wrapped in box, 90-day warranty

HSC#80436 **$47.50**

Stepping-Motor Setup!

- Used Compumotor indexer, driver & motor, with cables!
- Model 172 indexer, LE series driver, & LE57-51 motor
- Sorry, no other information available -- 30 day warranty

HSC#17397 **$125.00**

Quick, Cheap, Easy IDE!

- What more could you want in an IDE controller?
- Creative Technology CT1871 Plug and Play card
- Perfect for CD-ROM's, other non-bootable IDE drives
- 16 bit short ISA card has minimum parts count
- Supports up to two CD-ROM drives
- All settings are PnP settable, supports all ATAPI drives
- New, OEM bag with spec. sheet, 90-day warranty

HSC#17358 **$3.95**

Halted specialties co. / HSC Electronic Supply

Toll Free (Orders Only) 1-800-4 HALTED (1-800-442-5833)
Internet World Wide Web: http://www.halted.com
3500 Ryder St., Santa Clara, CA 95051 (408) 732-1573
4837 Amber Ln., Sacramento, CA 95841 (916) 338-2545
5681 Redwood Dr., Rohnert Park, CA 94928 (707) 585-7344

-or-

FAX your orders to: (408) 732-6428

Visit HSC's Website!

- Pay us a virtual visit on the World Wide Web!
- Simply point your browser to *http://www.halted.com*
- Site is constantly being revised, please visit often!
- Check out the amazing "Gizmo of the Week" feature!

HSC Catalog online!

- That's right, get HSC's catalog on the World-Wide Web!
- Simply go to www.halted.com and follow the big red link.
- Adobe .PDF files are available for download and viewing.
- Or drop on by and pick one up...we'd love to see you!

Terms: Some quantities limited; all items subject to prior sale. **Minimum order: $10.00 plus shipping.** Orders under $20.00 subject to $2.00 handling fee, in addition to shipping. All orders shipped FOB Santa Clara, CA (this means you pay freight!) by UPS Surface (no P.O. Boxes) unless otherwise specified, in which case prevailing carrier rate plus $5.00 handling fee applies. Prepaid orders that don't include shipping charges will be shipped freight COD. There is a $5.00 UPS charge added to shipping charges for COD shipments. If you have questions about your order, please call Customer Service at (408) 732-1854 M-F 9AM to 5PM PST.

Write in 80 on Reader Service Card.

Volume 19 No. 10 • OCTOBER 1998

Contents

ARTICLES

EMERGENCY TODDLER FINDER *Kenton Chun* 6

With holiday shopping just around the corner, this device may be a relief to have with you when you're out with your child.

FAMILY RADIO SERVICE RADIOS – FACTS AND MUCH FICTION *Gordon West* 10

Find out what's hype and what's not about FRS.

SECURITY ELECTRONICS SYSTEMS AND CIRCUITS – PART 9 *Ray Marston* 20

Take a look at a miscellaneous collection of security circuits in this next to the last installment.

SPI AND THE PRINTER PORT *Karl Lunt* 35

Add up to eight devices to a single printer port, using little more than a ribbon cable and some C software.

A SONAR SENSOR FOR AMATEUR ROBOTIC PLATFORM *Lawrence Foltzer* 44

Incorporate this "sensitive" device into your own homebrew projects.

BUILD THIS STEPPER MOTOR CONTROLLER

David Williams 48

If you're interested in robotics, motion control, or just want to learn about stepper motors, then you should try building this versatile stepper motor controller.

THE COMPUTER CONTROLLED WORLD: *Ryan Sheldon* ... 95

Pictures for Windows: Control up to eight graphic LCD displays from Visual Basic 5 for Windows (part 2).

DEPARTMENTS

ADVERTISER'S INDEX 74
CLASSIFIED AD INFO 74
DEALER DIRECTORY 41
EVENTS CALENDAR 42
NEW PRODUCT NEWS 9
NEWS BYTES 15
NV ADMART 52-53
ELECTRONICS Q & A 28
READER FEEDBACK 14
TECH FORUM 13

Nuts & Volts Magazine encourages article submissions and queries. Send a SASE for a copy of our writer's guidelines.All submissions should be on 5-1/4 or 3-1/2 inch diskettes and include hard copy as well.If return of materials is requested, include a SASE with your submission.

Deadlines should be discussed in advance with the editor, but generally all material should be submitted two weeks prior to the 1st of the month for the next month's issue.

COLUMNS

AMATEUR ROBOTICS NOTEBOOK *Robert Nansel* 80

Making progress "the hard way" on Breadbot with the help of BS2, SIMMStick, VROC, and solder smoke.

OPEN CHANNEL *Joseph J. Carr K4IPV* 16

Some more tools for radioscience observers.

RESOURCE BIN *Don Lancaster* 91

New secrets of military surplus (part 1).

ELECTRONICS Q&A *TJ Byers* 28

You Win with Nuts & Volts!

Subscribe today and be automatically entered in our *new* MONTHLY PRIZE DRAWING!!!

See page 47 for details!!

OCTOBER PRIZE

BASIC Stamp II Professional Package

Provided compliments of

PARALLAX, Inc.

NOVEMBER PRIZE

HARD DRIVE DUPE-IT! PRO from CORPORATE SYSTEMS CENTER

CLASSIFIED AD INDEX

10. Ham Gear for Sale 54
20. Ham Gear Wanted 55
30. CB/Scanners 55
40. Music & Accessories 56
50. Computer Hardware 56
60. Computer Software 60
70. Computer Equip. Wanted 61
80. Test Equipment 61
85. Security 66
90. Satellite Equipment 67
95. Military Surplus Electronics ... 68
100. Audio/Video/Laser 68
110. Cable TV 69
115. Telephone/Fax 71
120. Components 72
125. Microcontrollers 73
130. Antique Electronics 73
135. Aviation Electronics 73
140. Publications 73
145. Robotics 76
150. Plans/Kits/Schematics 76
155. Manuals/Schematics Wanted 77
160. Misc. Electronics For Sale. 77
170. Misc. Electronics Wanted 79
175. BBS & Online Services 85
180. Education 85
190. Business Opportunities 85
200. Repairs/Services 85

Nuts & Volts Magazine is published monthly for $19.00 per year by T&L Publications, Inc., 430 Princeland Court, Corona, CA. POSTMASTER: Send address changes to Nuts & Volts Magazine, 430 Princeland Court, Corona, CA 91719.

Published Monthly By
T & L Publications, Inc.
430 Princeland Court
Corona, CA 91719
(909) 371-8497
FAX (909) 371-3052

E-Mail
editor@nutsvolts.com
URL
http://www.nutsvolts.com

Subscription Order ONLY Line
1-800-783-4624

Publisher
Jack Lemieux *N6ZTD*

Editor
Larry Lemieux *KD6UWV*

Managing Editor
Robin Nelson *KD6UWS*

On-The-Road Exhibit Coordinator
Audrey Lemieux *N6VXW*

Subscriptions
Abby Madain

Classified Ads
Natalie Sigafus

Copyright 1998
by **T & L Publications, Inc.**
All Rights Reserved

All advertising is subject to publisher's approval. We are not responsible for mistakes, misprints or typographical errors. Nuts & Volts Magazine assumes no responsibility for the availability or condition of advertised items or for the honesty of the advertiser. The publisher makes no claims for the legality of any item advertised in Nuts & Volts. This is the sole responsibility of the advertiser. Advertisers and their agencies agree to indemnify and protect the publisher from any and all claims, action or expense arising from advertising placed in Nuts & Volts. Please send all subscription orders, correspondence, UPS, overnight mail and artwork to: 430 Princeland Court, Corona, CA 91719.

The closing date for each issue is the 5th of the prior month, e.g., the closing date for the June issue is May 5th. Ad copy to be typeset by Nuts & Volts should be received one week prior to the closing date. Call or write for current advertising rates.

CHANGE OF ADDRESS

If you are moving, notify us AS SOON AS POSSIBLE so we can continue your subscription without interruption.

Your magazine **WILL NOT** automatically be forwarded to you by the post office, so it's important to submit your change of address directly to Nuts & Volts. We will not be able to replace missed issues of the magazine due to unreported address changes.

When you send in your new address, include a current mailing label from the magazine with your account number on it. If you do not have a mailing label, be sure to include your old address and the name(s) under which the subscription was submitted.

DON'T MISS A SINGLE ISSUE!!

SUBSCRIBE TODAY!!

To Subscribe to NUTS & VOLTS

USA ONLY
$19.00 – 1 Year $35.00 – 2 Years $51.00 – 3 Years

MAILED FIRST CLASS — FOREIGN ONLY
$37.00 – Canada/Mexico $100.00 – Foreign/Air Mail
$50.00 – Foreign/Surface

Send payment to the address below or call 1-800-783-4624 and use your Visa or MasterCard.
Nuts & Volts Magazine, 430 Princeland Court, Corona, CA 91719

THE WORLD'S MOST POPULAR DESIGN TOOL CHOSEN BY OVER
100,000 USERS!

Electronics Workbench® Personal Edition





TRUE MIXED ANALOG/DIGITAL
FULLY INTERACTIVE SIMULATION
PRO SCHEMATIC EDITOR
6 VIRTUAL INSTRUMENTS
ON-SCREEN GRAPHS
OVER 4,000 MODELS
8 POWERFUL ANALYSES
FREE TECHNICAL SUPPORT

$299

Full-featured schematic capture and SPICE circuit simulation!

The world's most popular circuit design tool that sets the standard for powerful, insightful SPICE simulation. Create professional looking schematics and then with the flick of a switch, display simulated waveforms live on a suite of virtual instruments. Includes 15 powerful analyses and a library of over 4,000 robust component models.

Electronics Workbench® Layout Personal Edition



AUTOROUTING
REROUTE WHILE MOVE
32 ROUTING LAYERS
50" X 50" BOARD SIZE
OVER 3,500 LIBRARY SHAPES
EXTENSIVE OUTPUT
REAL TIME DESIGN RULE CHECK
DENSITY HISTOGRAMS
FREE TECHNICAL SUPPORT

$299

Power-packed PCB layout with autorouting and real-time DRC!

EWB Layout is a powerful board layout package for producing high-quality, multi-layer printed circuit boards. Offering tight integration with our schematic capture program, EWB Layout is the best way to quickly produce well-designed boards.

BUY BOTH AND SAVE! ~~$598~~ $548

CALL FOR INFORMATION AND PRICING ON OUR PROFESSIONAL EDITION.

800.263.5552

30-DAY MONEY-BACK GUARANTEE

Fax: 416-977-1818
E-mail: ewb@interactiv.com

INTERACTIVE

For a free demo, visit our website at www.electronicsworkbench.com

EMERGENCY TODDLER FINDER

by Kenton Chun

If you have one or more toddlers in your family, you probably have experienced the terror of going to the shopping mall or a family outing and temporarily losing a child. This happens far too often and too easily for comfort. Perhaps you are involved in a store display and in a moment of inattention, the child wanders off. Sometimes the child will outrun the parent. It happens to everyone.

Unfortunately, many children have been abducted or injured after getting lost in this manner. According to some sources, there are more than 100,000 reported attempted child abductions a year in the United States alone.

In many cases, the lost child is not very far away, and the frightened parent actually makes things worse by going into a panic and placing more distance between themselves and the lost child by engaging in a random search pattern.

Nobody likes to admit they make mistakes like this, and usually a meticulous job of managing children will prevent an episode. But as children mature, they want more freedom and will sometimes go out of their way to explore on their own.

It simply is not possible for a parent to always know exactly where the child is at every second. When a child gets lost, every second counts if the child is in any kind of danger.

This month's project is an electronic toddler finder which will locate a lost child if he or she is within several hundred yards of the parent. It can be used as a means of last resort for locating a lost child in the (hopefully unlikely) event that the child is at risk.

The project is essentially an interface which you can build to allow you to connect an ordinary pocket pager to a personal attack alarm (PAL). A personal attack alarm is a small device about the size of a pack of cigarettes, which emits a piercing audio alarm in excess of 140 dB when a lanyard is pulled out of it. It can be heard for distances of nearly a mile in quiet conditions.

When a child is deemed lost and in possible danger, all the parent need do is to take their cellphone out and dial the number of the pager/PAL combo that the child is carrying. The PAL will sound and allow the parent to quickly locate the missing child. The design has the added benefit that if the child is in the process of being abducted, when the alarm sounds, the abductor is likely to discontinue the abduction for fear of attracting too much attention.

While I do not suggest that everybody use pagers and personal attack alarms in this fashion, it is a last resort method of locating a lost child when the threat of injury or abduction is deemed possible by the parent. Responsible use of this technology will save lives. Misuse of it will result in just another mindless public irritation, like the bleating car alarms in the mall parking lot. Please remember this if you decide to construct and use this project.

Design and Implementation

There are many different pagers and PALs on the market today. I decided to use a project implementation which would work on virtually all pagers and PALs, however, this means it is possible the experimenter will have to do some testing and tweaking of their implementation to verify that it works properly and reliably.

In addition to this, I wanted an implementation which would allow the pager and the PAL to be used for their original purposes and not be permanently connected together as a dedicated toddler alarm. Toddlers after all, eventually grow up.

I chose to use an infrared optocouple which allows the two devices to be easily interfaced, and still fit the design criteria mentioned above.

Infrared Optocouplers

An optocoupler consists of a light-emitting diode (LED) and phototransistor pair. The LED emits light in an extremely narrow band in the infrared wavelength of the light spectrum, usually in the range of 880 to 940 nM or so. The light output is not visible to the naked eye. This is good for several reasons.

One is that it allows essentially invisible operation. Another is that infrared (IR) LEDs can emit 10 or more times the output of a visible LED as they are more efficient in the infrared spectrum.

The most important to our



Figure 1
Disassembling the Pager



Figure 2
Modifying the Pager



Figure 3 Schematic

project is that they begin to operate at forward voltages of 1.2 volts, which is just about all we have available in a standard "cheapie" pocket pager running on a single AA pen-cell.

The phototransistor is usually matched to be sensitive to the same wavelength of light emitted by the IR LED. This increases sensitivity to control signals, and reduces the chances of a false signal from spurious light sources.

The most common is an NPN junction transistor with a large base region exposed to the outside world. Photons entering the device through a small lens replace the base-emitter current of ordinary bipolar NPN transistors, switching the device on.

Optocouplers come in many configurations, and are generally used to provide extremely high electrical isolation between circuits. Other types are arranged to have an accessible gap between the LED and phototransistor in order to "sense" objects or to count events.



Figure 4 Modifying the PAL

Getting Started – Prepare the Pager

Begin by acquiring the IR LED and phototransistor pair. I used a General Electric L14F1123 and LED which come as a matched pair from Radio Shack. Almost any IR LED can be used, however, it must begin to output infrared at 1.2 volts, or the device will not work in this application. Generally, the more sensitive phototransistors have three leads (base lead exposed) instead of two.

Next, open up the pager. Remove the battery. Remove the two hex allen screws at the top of the case and lift the back away. With a small screwdriver, carefully pry out the white plastic keeper that holds in the LCD display.

Then, carefully pry out the plastic tang at the bottom of the case which locks the PC board down enough to free the board. Don't break it or the LCD display! The entire PC board and LCD assembly should now lift out (Figure 1).

Drill a hole in the center of the front of the pager case which will accommodate the IR LED you are using. You want it to fit through the hole snugly. It should stick out of the front of the case. If you are a master craftsman, you can use a Dremel tool and, with a fine cutoff wheel, cut the IR LED as close to the array junction as you dare.

If you do this right, you can actually mount the IR LED inside of the pager case. If the pager case is a semi-transparent plastic, it will actually work without a hole.

Next, mount the IR LED with a dab of epoxy or Super Glue. Make sure that the back of the LED will clear the circuit board before gluing it down! Trim the leads close to the LED and quickly solder a length of fine insulated wirewrap hookup wire to each lead.

The pager PC board assembly actually consists of two small circuit boards connected by an eight-pin header connector. Separate the two boards by carefully prying them apart at the header connector. Be careful not to break the boards. On the lower board, you will see a small motor with a weight attached to the shaft. This is the "vibrate" pager motor.

When the beeper is in silent mode instead of the audible alarm, this motor whirls a small eccentric weight around the shaft causing the pager to vibrate. It will have two wires, red and blue. The red wire is positive, the blue negative. You can confirm which wire is which because one of them will go directly to one of the battery terminals.

Unsolder the red motor wire. Solder a 20-ohm resistor to the terminal land the red motor wire was on. Re-solder the motor wire to the other lead of the resistor. I used two 10-ohm surface mount resistors (SMTs) in series.

There is plenty of space for a conventional 1/8-watt carbon or epoxy resistor, if that is all you have. Solder the anode wire of the LED to the positive or red wire terminal. Solder the cathode wire of

Learn MICROCONTROLLERS EMBEDDED SYSTEMS and PROGRAMMING...

with the AES learning system/ embedded control system. Extensive manuals guide you through your development project. All programming and hardware details explained. Complete schematics. Learn to program the LCD, keypad digital, analog, and serial I/O. for your applications.

THREE MODELS AVAILABLE. Choose from an Intel 8051, Intel 8088, or Motorola 68HC11 based system. All models come with:

• 32K Byte ROM, 32K Byte RAM • 2 by 16 Liquid Crystal Display • 4 by 5 Keypad • Digital, Analog, and Serial I/O • Interrupts,timers, chip-selects • 26 pin expansion connector • Built-in Logic Probe • Power Supply (can also be battery operated) • Powerful ROM MONITOR to help you program • Connects to your PC for programming or data logging (cable included) • Assembly, BASIC, and C programming(varies with model) • Program disks with Cross Assembler and many, well documented, program examples • User's Manuals: cover all details(over 500 pages) • Completely assembled and ready to use • Source code for all drivers and MONITOR • Optional Text Book

Everything you need. From $279
Money Back Guarantee
Call for Free Info Pack, or see
WEB at http://www.aesmicro.com
714-550-8094, FAX 714-550-9941

Call 1-800 -730-3232

AES
Advanced Educational Systems

AES 575 ANTON BLVD., SUITE 300, COSTA MESA, CA 92626, USA

The RF Connection
213 North Frederick Ave.
Suite 11NV
Gaithersburg, MD USA
20877

http://www.therfc.com/

Complete Selection of MIL-Spec Coax, RF Connectors and Relays

UG-21B/U N Male for RG-213/214.....$5.00
UG-21D/U N Male for RG-213/214.....$3.25

N Connectors for 9913/Flexi4XL/9096

UG-21B/9913.....$6.00 Pins Only.....$1.50
UG-21D/9913.....$4.00 Extra Gasket.....75

Amphenol 83-1SP-1050 PL-259.....$0.90
UG-176/U Reducer RG-59/8X. .25 or 5/$1.00
UG-175/U Reducer RG-58/58A .25 or 5/$1.00
Silver Teflon PL-259/Gold Pin.....
.....$1.00 or 10/$9.00

MIL-Spec Coax Available (Teflon, PVC IIA)

New Product: Belden 9913F. 9913 with High Density PE Foam dielectric, stranded center cond. and Duobond III Jacket.....
.....80/ft or $76.00/100ft

Also New: 9092, RG8X with Type II Jacket
Intro Price.....$23.00/100ft

Call for Specials of the Month

Full Line of Audio Connectors for Icom, Kenwood, and Yaesu

8 Pin Mike Female.....$2.50
8 Pin Mike Male Panel.....$2.50
13 Pin DIN for Kenwood.....$2.75
8 Pin DIN for Icom.....$1.00
8 Pin DIN for Kenwood.....$1.50

Prices Do Not Include Shipping

Orders 800/783-2666
Info 301/840-5477
FAX 301/869-3680



Figure 5
Coupling the Pager and the Personal Attack Alarm

the LED to the negative or blue wire terminal. In my pager, this is also the negative battery contact. You should end up with something that looks like (Figure 2).

Re-assemble the pager, making sure not to break or cram any of the components. Re-insert the battery and turn the pager on. Usually, pagers have a test mode at turn-on time. You can test for proper operation of the IR LED by turning the pager on in vibrate or silent mode and watching it with a night vision scope. It should light up like a Christmas tree.

If you do not have an IR night vision scope, connect your phototransistor to an ohmmeter and hold it next to the pager case when the vibrator is activated.

You should see a noticeable drop in resistance across the phototransistor's emitter and collector as it begins to conduct. The 20-ohm resistor will not have any noticeable effect on the operation of the vibrator, except that perhaps the pager will no longer jingle your keys. The resistor is necessary to leave enough current to drive the IR LED, however.

Prepare the PAL

Remove any clips from the back of the PAL. It must fit snugly against the front of the pager. Good quality PALs have removable clips. If you are using a "cheapie" PAL, you may need to cut the clip off. Line the pager and the PAL up, and mark exactly where the LED is pointing at the back of the PAL. Drill a hole in the back of the PAL at this location which will accommodate the phototransistor. It should fit snugly, or you will have to use epoxy or Super Glue to fasten it in place.

Most PALs employ a shorting subminiature jack as the trigger mechanism. A lanyard with a dummy plug is inserted in the PAL jack which opens the contacts in the jack.

In the event of an attack, the lanyard is jerked and the dummy plug comes out of the jack causing the shorting contacts to close. This activates the alarm. Instead of using the lanyard, we will be using a transistor switch to supply power to the PAL (Figure 3).

The circuit is simple enough that it is not necessary to mount the components on a circuit board – it will suffice to find any empty space in the PAL case and mount them by soldering them point-to-point. When the phototransistor PT1 is switched by the incoming IR beam from the pager, it turns on NPN transistor Q1 which supplies power to the PAL.

Depending on the way your particular PAL is designed, it is possible to wire the transistor switch in parallel with the PAL trigger jack. I choose to switch the PAL power supply instead because this method should work for all PALs, irregardless of their trigger design (Figure 4).

Parts List:

R1	10-Ohm 1/8-watt Resistor or SMT
R2	50-Kohm Potentiometer
Q1	2N2222 NPN transistor
IR1	Infrared LED (See Text)
PT1	GE- L14F1123 IR Photo Transistor (See Text)

Putting It All Together

Depending on how much your LED and phototransistor stick out, you may need to use a rubber grommet or an "o" ring as a spacer and coupler between the pager and the PAL. What is important is that they align properly. When they do, rubber band or zip tie the two units together (Figure 5).

Test the system by first inserting the PAL batteries. Do not insert the trigger lanyard. If it goes off, move into a darker place to assemble the two units. After putting the two units together so the IR LED and phototransistor align properly, turn the pager on in silent mode. It should begin to vibrate and the PAL should be blowing your ears off. Adjust potentiometer R2 for reliable operation, but with the lowest sensitivity to stray light.

Finally, put the system through some rigorous tests to determine if you can make it "false" alarm. It may be possible to have false alarms if too much light is allowed to leak into the phototransistor from outside sources. Placing the project in direct sunlight is a good test. It should NOT go off.

Depending on the quality of the transistor you use, there should be less than 30 microamps of current drawn on the PAL battery when the units are coupled together. The standby current draw will be practically zero if the IR LED and phototransistor are coupled properly, and there is no light leakage from the outside (Figure 6).

Using the Toddler Finder

You must not use a pager that a zillion people call everyday. Obviously this will be useless as an emergency indicator. You should place the pager/PAL combo on the child by either clipping it to them, or in a backpack or other article they are carrying. Ideally, the pager/PAL combo should be on their person. Do not convert or use a pager for this application that you do not own.

Finally, should you decide to build this project, neither myself or the publisher can be held responsible or liable for damage to pagers altered, or for any uses the project may or may not be put to.

Conclusion

The Emergency Toddler Finder should only be activated if you believe your child may be in imminent danger. It should not be used as a substitute for attentive parenting. It will provide a last-resort indication of where your lost child is and may even save their life. It is my hope that I never hear one of these go off at the mall!

Remember to have fun, whatever you do! **NV**

Figure 6
The Finished Project

New product News

ATRV-2

Real World Interface, Inc. announces their second All Terrain Robot Vehicle – the ATRV-2.

The ATRV-2 is designed to provide the robotics researchers and scientists who are pioneering tomorrow's rovers with a vehicle capable of supporting demanding missions including security, land mine detection, reconnaissance, surveillance, and remote operation in hazardous areas.

ATRV-2 is a rugged four-wheel drive, differential steered, all terrain robot vehicle. With 40 cm all terrain tires on four aluminum wheels, the ATRV-2 has excellent off-road traction and can traverse asphalt, grass, rocks, and sand with ease. The fully enclosed rugged aluminum body protects electronics from the elements.

The ATRV-2 features an internal PC that provides an ideal interface for a wide range of sensors including: laser range finders, stereo vision, and more more of your choice.

For more information, contact:

REAL WORLD INTERFACE, INC.
32 FITZGERALD DR. P.O. BOX 375
DEPT. NV, JAFFREY, NH 03452
603-532-6900 FAX: 603-532-6901
E-MAIL: lwoodbury@rwii.com
WEB: http://www.rwii.com

COLOR VIDEO PEN CAMERA

American Innovations, Inc., announces the release of their new VP-300 Color Video Pen Camera. To the casual observer, the unit looks like an ordinary pen in your pocket. Hidden inside is a micro-miniature color CCD camera that delivers unparalleled picture quality.

Images can be recorded using a standard portable video recorder or fed into a video transmitter for remote real-time recording and/or observation.

Perfect for Law Enforcement operations, private investigators, and undercover news reporters, this unit is the most revolutionary way to record live events that require the utmost discretion.

All optional components (Sony 8 mm video recorder, battery pack) fit neatly into a small waist pack so there is no cumbersome video equipment to carry. This unit is so small and easy to use, you will keep it on hand every day. Set up takes seconds.

The VP-300 Color Video Pen boasts over 330 (H) TVL resolution, low two-lux sensitivity, and delivers 92 degree FOV through its 3.6 mm pinhole lens. By incorporating special engineering and advanced circuitry, the video pen can also capture video in low light settings.

The special introductory price for the VP-300 is only $2,400.00.

I-SPY CLOCKS



The MC-985 Mahogany Clock Cam and the CL-985 Carriage Clock Cam are the two latest I-Spy cameras manufactured by American Innovations, Inc.

These clocks blend into any home or office setting making them ideal for every undercover operation.

Each covertly conceals a 380 (H) TVL resolution color camera, with a super low two-lux sensitivity rating.

These cameras also have built-in backlight compensation thus enabling the color camera to function in a room with minimal lighting. The custom designed pinhole lens offers an astonishing 92 degrees FOV through an opening measuring only 2 mm!

The MC-985 Mahogany Clock Cam and the CL-985 Carriage Clock Cam were designed for use in the office to monitor employee's performance; place them in a store to protect your merchandise and your profits. These cameras are perfect for the working parent who wants to keep an eye on their nanny and/or housekeeper while they are away or at work.

Since the camera utilizes standard video signals it can be connected to your own TV or VCR. You can set the timer function on your VCR to monitor an area at predetermined times and/or intervals.

The special introductory price for these two I-Spy Color Clock Cameras is only $350.00.

For more information on these products, contact:

AMERICAN INNOVATIONS, INC.
119 ROCKLAND CENTER, Ste. 315, DEPT. NV, NANUET, NY 10954
914-735-6127 FAX: 914-735-3560 WEB: http://www.spysite.com

SVR8-T SERVO CONTROLLER



The SVR8-T provides eight channels of standard PWM servo control along with eight channels of 16-bit torque feedback using standard unmodified hobby servos. This patent-pending technology enables new or existing devices which utilize servos for motion control to be enhanced with the sense of touch without adding any additional sensors.

Examples of feedback systems include: 1. Low-cost servo walker that can adapt to the terrain. Sense and avoid a drop-off, all without adding a single sensor. 2. Low-cost servo gripper that can sense an object's presence and/or weight and only apply the correct amount of pressure to grab the object. 3. Multi-axis arm or leg that can sense and adjust to its own or external forces.

The SRV8-T sells for $99.95.

For more information, contact:

NETMEDIA, INC.
10940 N. STALLARD PL., DEPT. NV, TUCSON, AZ 85737
520-544-4567 FAX: 520-544-0800
http://www.web-hobbies.com



DTMF-8 DECODER BOARD

The DTMF-8 board is great for remotely controlling most equipment like a repeater via radio or any other audio source with its eight relay outputs.

Relay contacts are rated at one amp and can be programmed for momentary, latching (or combination), or mutually exclusive one of eight.

Password programming adds security and allows multiple DTMF-8 boards attached to the same audio source to control even more equipment.

Requires 12 to 14 VDC at up to 250 mA.

The cost is $119.00.

For more information, contact:

INTUITIVE CIRCUITS, LLC
2275 BRINSTON AVE., DEPT. NV, TROY, MI 48083
248-524-1918 E-MAIL: sales@icircuits.com
WEB: http://www.icircuits.com

Continued on page 100

FAMILY RADIO SERVICE RADIOS — FACTS AND MUCH FICTION

by Gordon West

Suzy West operates a Kenwood FRS radio while snowboarding last winter.

The Family Radio Service (FRS) is almost two years old, and founder Bob Miller K3RM, of RadioShack is quite pleased on how his simple proposal to the Federal Communications Commission (FCC) has revolutionized the way that we can now stay in touch. No license required. Fourteen channels of FM quality communications. And everybody getting into the act producing little FRS radios to help our economy. And little lightweight transceivers that have been documented as lifesavers in several emergencies throughout the United States.

Yes, FRS on its second birthday is working just fine as envisioned by Miller and RadioShack.

The Oregon Scientific two-way radio.

Before we talk about some of the slightly misrepresented claims about the equipment and what it can and cannot do, plus some of the things that people have been doing with the equipment that Miller hadn't even thought of, let's take a look at what FRS is, and a little about what manufacturers are doing to maneuver themselves in the marketplace.

The small FRS transceiver is ideal for boat-to-car communications during launching.

. . . 14 frequencies times 32 privacy codes may not lead you to "hundreds" of vacant channels. Advertisements for one- and two-mile range are indeed accurate, but 10-mile to 20-mile range is quite common . . .

The FRS is governed by the FCC under the Code of Federal Regulations, Title 47, Part 95 — Personal Radio Services. The FRS's general provisions are found in Subpart B, specifically Rules 95.191, 95.192, 95.193, and 95.194. The simple rules say that you can use these little radios as long as you are not a representative of a foreign government. You must also share the 14 channels with other users.

The rules also state that you can use these radios anywhere the FCC has jurisdiction, but you cannot use them aboard a boat or aircraft without the permission of the captain. You cannot cause intentional interference, either.

You may not use these little sets to commit a crime. You will use these sets to conduct two-way voice communications with someone else, and the FRS is not intended as a one-way broadcasting service to play talk show host. You cannot tie your FRS into a telephone system, either.

The rules also state you cannot go inside your little FRS set and jack up the power, or make modifications to its required built-in (only) antenna.

But the rules leave wide open all of the neat LEGAL things that you can do with this equipment, realizing some of their inherent limitations by design to keep this radio system short-range.

The small FRS radios work well inside metal buildings.

Compact FRS transceivers can communicate over 50 miles under the right conditions!

- Effective radiated power output shall not exceed 1/2 watt.
- Deviation must not exceed ±2.5 KHz.
- Audio frequency response must not exceed 3.125 KHz.
- No external antenna connections are allowed.
- Frequency tolerance required is .00025%.

These little handhelds operate on interstitial frequencies to the more powerful general mobile radio service. Channels 1 to 7 fall between powerful GMRS output frequencies, and FRS Channels 8 through 14 fall between sensitive GMRS repeater input frequencies.

FRS CHANNEL FREQUENCIES

FRS Channel #	MHz
1	462.5625
2	462.5875
3	462.6125
4	462.6375
5	462.6625
6	462.6875
7	462.7125
8	467.5625
9	467.5875
10	467.6125
11	467.6375
12	467.6625
13	467.6875
14	467.7125

And here is something they probably didn't tell you in the brochure that comes with FRS equipment — on FRS 462 MHz Channels 1 through 7, you share your channel with mobile and base station GMRS system users who could run up 10 times more power and twice as much modulation bandwidth as your little tiny handheld. FCC Rule 95.29(f) gives GMRS licensed users full access to these same "interstitial" channels to talk simplex. Now you are beginning to understand why you might have been drowned out when you are trying to use your little handheld in the local shopping mall — a powerful voice came over your channel, and that was that. It's legal.

But take heart — you still have FRS Channels 8 through 14 to use. But if you're out on a hiking trip, and you get close to that big mountain peak where there are a lot of powerful

Motorola's TalkAbout Plus two-way radio.

repeater stations on that peak, refrain from using FRS Channels 8 through 14. The reason is because many of those GMRS repeaters may be operating in the GMRS service, and talking from your little 1/2-watt set close to these repeaters and their sensitive input frequency could wipe out legitimate FCC-authorized GMRS calls. So stay off of the otherwise quiet FRS Channels 8 through 14 when hiking among the trees and big repeater aluminum towers.

And speaking of hiking, is there a common FRS channel in case of an emergency? Nope, not at all. Your best source of getting help in an emergency over FRS would be to dial through the channels and try to break into an ongoing conversation that you may hear loud and clear.

A year ago, you could go to the top of most buildings or hills, and spin through the channels and not hear much. But now the channels are beginning to blossom with activity, so chances are you could break in for some help if the two folks communicating leave a couple of seconds between their ongoing conversation. In fact, anyone out in the wilderness should always pause a couple of seconds before resuming a conversation for that purpose of letting someone else come in with emergency traffic.

I suggest using the international distress word, "Mayday," which in almost any language means stop transmitting and handle my emergency call. Say it three times and hopefully someone will hear a call for help.

On less expensive FRS equipment, you won't have the luxury of dialing around to find an either open or occupied channel. Some sets only come with one channel, and there appears to be no set channel that is a single channel unit. Most single-channel sets cost around $59.00. Two-channel sets cost around $69.00 each, and 14-channel sets cost about $149.00 each. I think this is more a marketing ploy than what it costs to produce a 14-channel set versus a two-channel set, but nonetheless, these are the latest price points observed.

And the most channels there are will be 14.

38 TALK GROUPS COMBINED WITH 14 CHANNEL CAPACITY OFFERS 1,064 PRIVACY CIRCUITS TO COMMUNICATE.

Other ads tone it down a bit and indicate their privacy codes combined with "all frequency capabilities" may lead to hundreds of private "channels." Not really.

The privacy codes are the common EIA CTCSS sub-audible tone codes. Many multi-channel FRS handhelds feature full decode CTCSS capabilities. I can begin to see the advertising logic — if everyone out there has a different channel dialed in and a different CTCSS encode, YOUR likelihood of having someone come through loud and clear over your specific channel that is on tone decode is rather remote up to maybe 1,000 tries. And you could even increase your odds of no one else coming over YOUR set by using equipment with voice scrambling to further reduce the likelihood of some stranger coming over your

TWO-WAY COMMUNICATION FOR MOTORISTS?

by Robert Leef

Just about everyone is interested in cars. It's only a short jump from automobile interest to transportation, and from there to communications. Historically, one has led to another in the development of our country. The Pony Express, telegraph, Henry Ford's invention, and our highway system are all connected. But has one aspect of the picture fallen behind by about 90 years?

Motorists come into contact with some form of communications every day. In the most simple way, it's the broadcast radio we listen to while driving. Besides this "one-way" radio — and possibly a mobile scanner — the vehicle may also be equipped with two-way radio such as business band, CB, amateur, GMRS, cellular, and maybe others.

Each of these pieces of equipment is designed to establish contact with another unit like itself, and usually with a specific person at another location. Herein lies the problem. None of these mobile two-way communications devices connect with all other nearby vehicles on the road. Private airplanes communicate with each other, and so do most boats. Why don't cars?

Instead, we use hand signals, flash the lights, or yell to try and convey important information to another driver. We travel along in our steel and plastic cells in a kind of frustrated solitary confinement, unable to talk to the person in the car right next to us!

In the 1970s, we seemed to be headed in the right direction with CB. Sales were high. Approximately one out of every 10 cars and trucks had that kind of radio, and it was growing. Many motorists could talk to each other, or just listen to what was going on around them if they preferred. Even General Motors was an active participant with CB. However, due to a number of reasons, it never reached all vehicles and now is basically flat or even in decline in some areas.

THE NEED

As it is now, we're unable to communicate properly with almost all nearby drivers. Messages that might be passed include:

a) A traffic problem ahead.
b) Giving warning of a dangerous road condition (fog, etc.).
c) Asking for help.
d) Requesting directions.
e) Advising the driver in front he has a tire going flat, or something else out of the ordinary.

We might even see a restoration of civility and courtesy between drivers.

THE DETAILS

If there is to be communication between all drivers, a two-way radio must be in all cars, and left on. Or, if left off, it must be automatically turned on and tuned to the "emergency and assistance" channel by receipt of a signal. The "advanced alert system" is already used in Europe. It sends out broadcast signals in the FM band that automatically turn on car radios to inform drivers of road hazards. Technology from this, and possibly our own commercial sources, would undoubtedly lead to a "smart" two-way radio.

Such a radio would not be a costly car accessory. One source estimates less than $100.00 and, with an adapter, it could use the car's existing AM/FM antenna. Would there be a big sales loss for CB marketers? Probably not. These companies could contract with the automakers to supply their assembly lines with this new concept radio as a required factory installed item. Either coming as standard equipment in new cars or available in aftermarket for existing vehicles through electronics retailers, public safety and convenience would be enhanced significantly.

This past winter, there were numerous cases of motorists trapped in deep snow, and unable to summon help. This and other kinds of weather-related emergencies happen every year. Not everyone wants or can afford a cellular telephone, and CB is not dependable. No product has focused on the universal need of a required common communications device.

This new kind of two-way wouldn't have to be a replacement for CB. Some drivers, and many truckers, still need or want the capability of talking longer distance. And, beyond this — for 50 to 75 mile range — another choice still remaining would be the General Mobile Radio Service with its repeaters. These and other easily obtainable services would not be displaced.

SPECIFICATIONS

a) FM, 1/2 watt except 2 watts on channel 9.

b) Automatic squelch; controls for channel selection, off-on-volume.

c) Button for 38 CTCSS tones. May be enabled or disabled.

d) Monitor button. Used if CTCSS is enabled.

e) Busy scan feature. May be enabled or disabled.

f) Mobile and handheld models.

g) MOBILE: If factory-installed, coupled to existing car antenna. If sold in aftermarket, coupler or separate antenna available. HANDHELD: Built-in antenna included. Capable of external antenna.

h) Automatic transmitter identification ("ATI"). When radio is keyed, it sends its own distinctive code. This would be a deterrent to misusage.

i) Available accessory to decode above ATI. REACT and other public service organizations interested in maintaining the integrity of the service would want to buy this in order to identify troublemakers. There would be a structure for handling misusage rather than the current extremes of being unconcerned or having vigilantes as in CB. The system would be similar to the "Official Observor" program in amateur radio.

j) 1. A $5.00 license fee collected at point of sale and mailed by seller to the FCC.

2. License application to be short and simple: name and address of buyer, verified by driver's license or other document. License to be good as long as buyer owns radio. (RADIO is licensed.)

3. License application to be packed with radio and show ATI code. Last four digits will be radio owner's on-air identification.

k) Frequencies: (All are transmit and receive except 9.)

CHANNEL	MHZ
1	462.5625
2	462.5875
3	462.6125
4	462.6375
5	462.6625
6	462.6875
7	462.7125
8	462.6750 short-range emergency and assistance
9	467.6750 transmit, 462.6750 receive (repeater)
10	467.5625
11	467.5875
12	467.6125
13	467.6375
14	467.6625
15	467.6875
16	467.7125

l) Channel 9 operates through a repeater — already operational on GMRS throughout many areas of the US, and is recognized as the emergency and assistance channel for long range.

m) When radio is on ("awake"), channel 9 will be scanned for priority. A "Defeat" button will take it out of priority after 10 seconds of pause on a received transmission on 9. It must be "defeated" for additional 10-second intervals as long as the listener does not want to hear the transmission on 9.

n) When the radio is off ("asleep"), there is automatic turn-on if a signal is received on channel 9. After 10 seconds, it automatically turns off if not manually turned on.

CONCLUSION

The type of radio being proposed wouldn't need a lot of development. We're already using a low-power handheld on the new Family Radio Service (FRS) frequencies which are the same as those being suggested except for channels 8 and 9. Performance has been good. With a little redesign for car use, a new "Driver's Radio Service" could be a prompt reality.

The safety aspect alone should get the attention of some agency such as the National Highway Transportation Safety Administration, the US Department of Transportation, the Federal Highway Administration, or others. The commercial aspect should be attractive to opportunistic companies.

Some new cars have GPS and a display that shows road maps. This satellite-based technology is great. But it appears we have skipped over a more basic and widespead need for a number of years. A "Driver's Radio Service" would be the answer. NV

spouse's handheld and carrying on an illicit conversation. Yup, I can see there might be more than 1,000 combinations to lock everyone else out.

But I wouldn't necessarily advertise them as private channels. Maybe a thousand different ways to make YOUR conversation private among yourselves.

But even if you do transmit with full CTCSS encode and decode, it doesn't mean that your conversation won't be overheard by anyone else with a simple FRS 14-channel set. While you might not hear anyone else on channel, someone running open squelch will definitely hear YOU on channel.

But Kenwood Corporation has gone one positive step forward to minimize eavesdroppers — a Kenwood radio UBZ-LF14 incorporates digital speech scrambling, and only another Kenwood radio can descramble the call if they're on the right frequency and have their tone decode circuit shut off.

"At the push of a button, Kenwood transmissions will be electronically altered so that casual listeners with other brand FRS radios cannot understand your conversations while your Kenwood friends and family can," comments Paul Middleton of Kenwood Corporation. "When combined with the 14-channel capacity, and the 38 talk groups, scrambling gives Kenwood owners 1,064 ways to communicate strictly between themselves," adds Middleton. Okay, I can buy that. Good feature.

The rules also permit brief tone calls over the airwaves. Many FRS radios may carry up to four unique user-programmable call tones that may ring the other person's FRS radio to let them know there is incoming traffic. Cobra, the king of CB 27 MHz radios, has a terrific feature called "Vibralert" that physically vibrates the FRS radio when it receives an incoming page call. They also advertise 532 CTCSS "sub-channels," but I think they are using just the regular 30-some CTCSS tones, and multiplying by the number 14 to come up with "sub-channels." But I like the Vibralert Cobra FRS equipment — it's a little smaller than most other FRS sets, and indeed it does its thing when an incoming specific call is received.

Midland also joins in on the circuit with 14-channel access with 38 privacy tones that "... give 532 channel/code combinations to eliminate crosstalk and interruptions." Maybe. Even though you may be decoding for a specific tone, someone else closer on the same frequency CAN interrupt the incoming call so all you hear is nothing. It's called capture effect — and even though the closer signal won't pop through your decode circuit, the station you do want to hear is effectively blocked from coming through. I wouldn't say that CTCSS may eliminate crosstalk or interruptions. You just won't know that you are getting jammed out!

Motorola does a good job of describing their Talk About handheld CTCSS "interference eliminator codes." They say, "It is a sub-channel code that lets you customize channels. When you select a channel, lots of other people may be using it, too. When you set a code, you tailor the channel to filter out other people's messages," writes Motorola. This is to lead to greater "flexibility" claims Motorola when operating the radio in congested or busy areas. Well, maybe.

If you're operating the radio on the same channel as someone else nearby, having your set on CTCSS full decode may lull you into thinking there is no one calling you, when actually the congestion is so heavy there indeed may be the kids screaming "Mommy, I'm lost." Something to think about. I would prefer to operate without my decoder turned on. This way, I'll recognize that the channel may be a popular one for a specific shopping mall, and have everyone in my party switch over to a slightly quieter frequency.

When it comes to maximum range, manufacturers and advertising agencies have been remarkably restrained. Most won't claim any greater range than one to two miles. Every now and then, you may see an ad saying "under optimum conditions up to three miles line-of-sight." This is a very conservative estimate when you consider signal propagation at 462 MHz in the summertime.

A 1/2-watt on 462 MHz might go as much as 100 miles when looking at free space attenuation tables. If the signal path is visible from mountain peak to mountain peak, and if there is no one on the same channel as the two of you are on, I would indeed expect the capabilities of establishing a narrow-band FM communications path. But to get a 100-mile path line-of-sight range, each of your minimum elevations will need to be no less than 2,500 feet up. And nothing in between. And not raining or snowing. And on a hot summer day when the wind is not blowing.

It's quite common for UHF signals to get ducted well beyond the calculated line-of-sight horizon. Ducting of FRS signals occurs when a widespread temperature inversion associated with a high-pressure system overlays you and the other FRS operator on a distant mountain top. When the temperature inversion reaches 10 degrees or greater, the refractive index is suitable for bending 1/2-watt UHF signals well beyond the normal line-of-sight range. Over water, the furthest record I have heard of using FRS equipment has been 160 miles between a mountain top in Ventura, CA, to another FRS operator on a small fishing boat well south of the Mexican border. And they indicate their signals were full quieting, which leads me to believe the range could have easily been extended if the channel remained clear of other FRS traffic.

Down in the shopping malls and at street level, the little FRS radios won't go much beyond a couple of blocks. Simply too much metal. While signals on 462 MHz take some good bounces within a building, usually the third bounce will do them in. It just depends on how much metal is between you and the other operator, and exactly where you have positioned your equipment.

I am told that security guards at a Chicago high rise can always make contact by operating their equipment near the elevator shafts. Whether the doors are open or not, the signals seem to propagate best near the elevators.

Worst range? 462 MHz does not work well in foliage. Hikers report that big pine trees will literally eat up the signal after about a half mile. Same thing with a rocky terrain — granite tends to absorb the signals, rather than reflect them. And this winter when out skiing or snowmobiling, an incoming snowstorm can put you off the air quickly when your distance exceeds about 3/4 mile on an absolute line-of-sight basis.

But on the other hand, if you get buried in an avalanche, hold onto your radio and continuously squawk for help. Ski patrols say that the little FRS signals can easily get out from under the snow 10 to 15 feet below. I wonder when we will see ski patrols announce a specific frequency for emergency use only to receive calls for help by injured or partially buried skiers?

In fact, here in Southern California, Bob Leef of Crest REACT has some very good ideas on how we might make better use of the 462 MHz-467 MHz band and come up with specific channels for highway and byway use with some of these 1/2-watt communicators. (See his mini-article included here.)

Finally, no one has come up with any magic way to dramatically increase the capabilities of range on these little 1/2-watt communicators. Attempts to inductively couple the antenna to a larger antenna proved cumbersome, and hardly worth the effort. I did see one ingenious set-up of two FRS transceivers hooked up to voice-operated headsets and operating on channel extremes (1 and 14) as a quasi-voice-activated repeater. It required everyone to transmit on one frequency, and then listen on another, and the system was more complicated than useful.

I have also heard some extremely loud conversations coming over the FRS channels, not necessarily from GMRS radios on the lower seven channels. This leads me to believe modified ham radio equipment at 5 KHz deviation is finding its way onto the splinter FRS frequencies, and this is well beyond the intended use of the limited number of FRS channels.

The number of "saves" through the use of FRS equipment is fast coming to the attention of public safety officials. A boater was able to call out to some fishermen using FRS on a breakwater that he was taking on water and sinking fast. Luckily the breakwater fisherman had a cellular phone, and ultimately the Coast Guard came to the rescue of the sinking boat owner.

Plenty of "saves" on the ski slopes. Other FRS users would overhear someone talking about an ankle that is definitely going in the wrong direction, and summoned ski patrol officials that finally were able to track down the injured party. While there are indeed 462/467 MHz Doppler automatic direction-finders, I doubt that you'll find many of these in service to track down the local FRS signals.

If I were running a ski patrol or boat rentals out on a lake where there was a lot of FRS use, I would buy myself a simple ham radio three-element beam for 70 cm and use the simple three-element beam to help track down lost signals.

FRS is good. And talking to Bob Miller, it's actually exceeded his wildest expectations when it comes to public acceptance and the variety of equipment now available. Certainly RadioShack stores have the lion's share of selling FRS, but you can find FRS transceivers just about everywhere and in the mail order catalogs.

But take some of the ads with a grain of salt — powerful transmitters, hundreds of channels, absolute privacy, and calling out in an emergency may slightly over-embellish the FRS as it is today. But useful it is; and if you have a scanner, and if your scanner can tune in interstitial frequencies 12.5 KHz off of the regular channels, then take a listen for yourself.

There is plenty of activity, and you may never be ALONE with a small FRS transceiver. **NV**

LITTLE RADIOS INTERFERE WITH LICENSED REPEATERS

FCC-licensed GMRS repeater users are having interference problems because of FRS units using CTCSS on encode. Tests show an alarming problem with any FRS radio encoding tone. When the FRS handheld is keyed on a frequency adjacent to an FCC-licensed GMRS repeater input frequency, using a tone known to be in the repeater, the repeater will key up. Although voice won't necessarily pass through the keyed-up repeater, the interference takes the form of the repeater cycling on and off. This is a serious condition when one of the repeaters was activated at a whopping seven miles from where the FRS set was operated, and another repeater triggered up 13 miles away.

I encourage everyone operating FRS to stay off of Channels 8 through 14. These are the channels that are interstitial to GMRS repeater inputs. A real problem is that casual FRS users will probably never know that they may be interfering with licensed GMRS repeater operation. We strongly encourage everyone using FRS to stay on Channels 1 through 7, so as not to risk interference with repeater inputs.

Bob Leef KB6DON
28826 Paseo Malaga
Mission Viego, CA 92692

Questions & Answers
TECH FORUM

This is a READER TO READER Column. All questions AND answers will be provided by *Nuts & Volts readers* and are intended to promote the exchange of ideas and provide assistance for solving problems of a technical nature. All questions submitted are subject to editing and will be published on a space available basis if deemed suitable to the publisher. All answers are submitted by readers and *NO GUARANTEES WHATSOEVER* are made by the publisher. The implementation of any answer printed in this column may require varying degrees of technical experience and should only be attempted by qualified individuals. Always use common sense and good judgement!

QUESTIONS

Send all material to **Nuts & Volts Magazine**, 430 Princeland Court, Corona, CA 91719, OR fax to (909) 371-3052, OR E-Mail to **forum@nutsvolts.com**

I have inherited three Fortune Systems Corp. 1000 terminals. They all have switches on the back for int. video/ext. video presumably so you could use them also for monitors. Well they work good in the ext. video mode as monitors.

What I would like to know is what the dot pitch is on these monitors? They all have the same picture tubes #R14APDB-DH.

I want to do some PC board designing on them and was wondering if the dot pitch is fine enough?

10981 **Joseph W. Baldwin**
Warren, MI

My Bel-Tronics Caller ID automatically gives a message saying we don't accept anonymous calls to those who call block. Unfortunately, many government and business numbers simply show up as unknown. How can I send a similar message to these unknown numbers i.e., Caller ID addition or answering machine, or a message stating identify yourself with a return number?

10982 **Grant Maxwell**
British Columbia, Canada

I would like to make the VT 420 interface to an 8051 project using RS232. There is a "com" punch out on the back for a D-type connector or something.

The VT 420 circuit board has a strange pattern of plated through holes for a connector with 90° pins adjacent to the comm punch out.

Also what interface is the other DEC-type connector?

10983 **Bill Jackson**
Kensington, MD

I would like to use the serial output port of one computer to input the keyboard input of a second computer in a universal kind of LAN. I envision using a UART to receive the serial data and through a ROM converting the binary characters to their equivalent character code numbers, entering the keyboard of a second computer in parallel with its own keyboard.

10984 **George Bateman**
Winter Park, FL

I have a Magitronic A-PIO411C-A, model 486-PI02, DOC 14580. It has award bios chip 486DXAWARD Software, Inc., FA263867 1.121BI01.

I need the information on jumper settings JC1, JC2, JC3, JC4, and JC5. All other settings are marked on the board.

10985 **Robert W. Ritchey**
Vandalia, IL

I have an old TV antenna rotor, but lost the controller. From the rotor is a cable with five wires: brown, white, black, green, and red.

I would like to know which wires take the 24 VAC and how to use the remaining three wires to indicate direction?

10986 **work@salus.uvm.edu**

I need an IC 8909-02A (8908-02A) for a Goldstar 14" TV. I haven't been able to find one.

10987 **Peter Decarolis**
Buffalo, NY

I noticed the memory expansion on my Hewlett Packard Laserjet II has a proprietary connection. Is there a board that will connect to this memory expansion slot that will use SIMMs?

10988 **Scott Edwards**
Mona, UT

I am a student of MSC Applied Physics in Karachi University (Pakistan).

I am going to design a "universal IR remote receiver." I need help from someone who knows about the data format of IR remote or any ICs used in that type of work.

10989 **Riaz Ali Khan**
via Internet

I am looking for a schematic for a circuit to convert an IDE interfaced hard drive to a parallel port interface, so I can hook up a hard drive to one of my parallel ports for more storage space. I realize they make such kits, but I want the knowledge of how it works, plus I can't afford such kits, at this time.

109810 **D. Gross**
Via Internet

I would like to build an "amplifier power output meter." Along the lines of a meter LED or panel for each channel i.e., L, C, R, LR, RR speaker output.

Any ideas or directions for information?

109811 **Manuel R. Sandoval**
via Internet

I need a transistorized switch that will transfer my backup battery instantly to the DC bus when power fails.

I have a 12V gel-cell with a float charger. The power supply is 12.0 volts and, now when the transfer relay drops out when the power supply fails, there is a momentary power loss while the relay's contacts change state. This causes my gentran switch PLC to hang up and have to reboot. I only need to switch 2-3 amps at 12V.

109812 **Brent Miller**
via Internet

I need "voice" or "audio" frequency readout for a Yaesu FT1000D. The operator is partially blind and needs "voice" readout for HF radio.

109813 **David M. Schertzer**
via Internet

How do I de-compress a hard drive? I recently upgraded my 540 MB drive with a 2.1 GB drive. The problem is that the new drive was compressed somehow in the data transfer, and I don't need to have the new one compressed because there is more than adequate space.

109814 **Al Gordon**
Del Mar, CA

I intend to write a VB program that uses the microphone (or line) input from my Soundblaster compatible card to obtain weather satellite images from a SSB receiver.

I have the schematics for the electronics required, but now I want to digitize the analog signal using my soundcard.

I am desperately looking for a way to read incoming data from the DSP chip on my 16 bits Soundblaster under Visual Basic.

In the old days, using DOS and Professional Basic, I could do this using the INP and OUT instructions to certain ports. VB does not have these instructions, but I found a DLL which could do the job. The only problem is that I do not receive anything but 128 or 255, no matter what signal comes into the soundcard.

109815 **Hans Middelbeek**
via Internet

ANSWER INFO

- Include the question number that appears directly below the question you are responding to.
- Payment of $25.00 will be sent if your answer is printed.
- In most cases, only one answer per question will be printed.
- Your name, city, state, and E-Mail address, (if submitted by E-Mail), will be printed in the magazine, unless you notify us otherwise with your submission.
- Due to space limitations, we can not reprint the original questions with the answer. The question number and the issue it appeared in are printed above the answer.
- Unanswered questions from a past issue may still be responded to.
- Comments regarding answers printed in this column may be printed in the Reader Feedback section if space allows.

QUESTION INFO

TO BE CONSIDERED FOR PUBLICATION

All questions should relate to one or more of the following:
1) Circuit Design 3) Problem Solving
2) Electronic Theory 4) Other Similar Topics

INFORMATION/RESTRICTIONS

- No questions will be accepted that offer equipment for sale or equipment wanted to buy.
- Selected questions will be printed one time on a space available basis.
- Questions may be subject to editing.

HELPFUL HINTS

- Be brief but include all pertinent information. If no one knows what you're asking, you won't get any response (and we probably won't print it either).
- Write legibly (or type). If we can't read it, we'll throw it away.
- Include your Name, Address and Phone Number. Only your name will be published with the question, but we may need to contact you.

ANSWERS

ANSWER TO #89813 - AUG. 1998

It is my opinion that 2.88 floppy drives never really took off because CD-ROM drives were introduced around the same time. All the major

Continued on page 87

Modern computing and standard surge suppressors... a recipe for disaster.

Almost all surge protection devices use MOV's (metal oxide varistors) as their active element. MOV's are sacrificial/wear/limited life components. Surge suppressors based on this technology are doomed to failure. These surge "suppressors" also don't suppress a thing. They divert powerline surges equally to the ground and neutral wire. When you put current on the common ground wire of interconnected equipment some of that current will flow (through the inherent ground loops) to the data lines. This is a major cause of lock-ups and misoperations that plague today's computer environments. Another fact; all modern computers use switch mode power supplies. During surges the power supply capacitors must charge to the clamping level of the MOV before the MOV turns on. A recent study has shown that it takes a 3000A surge 15 microseconds (15,000 nanoseconds) to charge the typical capacitors of these power supplies to that level. The surge is virtually over before the MOV reacts. ***(See five things you probably don't know about your surge suppressor at www.fivethings.com.)***

THE POINT: Standard surge suppressors allow too much current to hit the computer. Standard surge suppressors divert surge current to the ground wire and disrupt data transfer. Standard surge suppressors eventually fail without warning. Modern computers have logic voltage levels (the signals that transmit the data) and power supply voltages that are dramatically lower than that of their recent predecessors. Modern computers use integrated circuits with transistors of ever decreasing physical geometries. Modern computers are virtually always interconnected to other computers or peripheral equipment. The bottom line; ***modern computers are much more sensitive and susceptible to powerline anomalies.***

INTRODUCING BRICK WALL SURGE FILTERS. . .

The World's Best Surge Suppressor

Initially engineered for critical, non-fail industrial applications, this patented device protects indefinitely and sets a new standard for every measure of surge suppressor and powerline filtering performance.

A Brick Wall 1) Utilizes NO MOV'S or Any Other Sacrificial Components (a two pound inductor and nine capacitors are the heart of the unit) 2) Has No Joule Rating or Surge Current Limitations *3) HAS BEEN TESTED AND CERTIFIED BY UL TO THE MOST DEMANDING CLASSIFICATION OF A NEW GOVERNMENT SPECIFICATION; CLASS I, GRADE A. Which Means: UL PUT ONE THOUSAND 3OOOA, 6000V SURGES (this is the largest surge an interior environment can experience) THROUGH A UNIT (at 60 second intervals) AND DOCUMENTED NO FAILURE OR PERFORMANCE DEGRADATION OF ANY KIND WHATSOEVER..*

i.e.: A Brick Wall Will Not Fail.

We know of no cord connected, MOV based surge protection device that has, or can pass this test.



A Brick Wall possesses UL's lowest Suppressed Voltage Rating (let-through voltage) of 330V. This is the lowest rating they will grant. In that test of one thousand 6000V, 3000A surges, *UL NEVER SAW THE LET-THROUGH VOLTAGE EXCEED 290V. YOU CANNOT DO BETTER THAN THIS FOR A POINT-OF-USE SURGE PROTECTION DEVICE.* Once again, we know of no other surge protection device that could come close to this performance level.



A Brick Wall is a current activated *Series Mode* device. *Since it is not wired in parallel, nor voltage activated, it does not have to wait for the capacitors of the power supply to charge before it becomes effective. YOUR EQUIPMENT IS PROTECTED INSTANTANEOUSLY (and indefinitely).*

Available in Modular Form

These devices were engineered utilizing a current limiting/surge filtering technology. *THEY DO NOT DIVERT ANY SURGE CURRENT TO THE GROUND WIRE. They Will Not Cause Your Computer System To LOCK-UP, CRASH OR MISOPERATE as a consequence of surge diversion. Your current surge "suppressor" will.*

Powerline Filtering

In addition to all this, Brick Wall Surge ***FILTERS*** *are the best AC powerline filters you can buy (that we have been able to find anyway). Industrial machinery, copiers, coffee makers, laser printers, fluorescent lights, refrigerators, etc., all cause powerline noise that can cause your computer to misoperate. A Brick Wall Surge Filter will make powerline noise related problems disappear.*

You Can't Buy a Better Surge Protection/Powerline Filtering Device... Anywhere.

SO. . . HOW IMPORTANT IS YOUR SYSTEM?

BRICK WALL

BRICK WALL DIV., PRICE WHEELER CORP.
1-800-528-0313
Fax: 1-800-528-6623 E-Mail: info@brickwall.com
Web: www.brickwall.com
Visa - MC - AMEX

ASK ABOUT OUR NEW IN-LINE UPS/SERVER PROTECTOR

reader FeedBack

Dear Nuts & Volts:

Several months ago, author Gordon West wrote an excellent article about GPS equipment and the included inland mapping from flash memory. West brought up several good points about what flash memory mapping can and cannot do. I wish to amplify on one of those points about embedded land maps for use out on the water.

I purchased a Garmin GPS III (Serial No. 40130662), as an aid to navigation in my small boat. I was led to select this unit over other models because of its display of some of the significant rivers and lakes that I use in this boat, as well as other bodies of water that I may wish to use. It came well recommended for the display of shoreline data.

For this capability, I paid a considerable premium over the otherwise similar GPS II or other units having a lesser display capability.

Before purchasing this unit, I put it into Simulator mode and reviewed the display of several bodies of water and was generally satisfied with the level of detail provided. I did not expect the level of detail provided in a CD-ROM or C-Map cartridge unit.

After using this unit in a number of bodies of water, I find that it substantially mislocates shoreline features in most every place I found myself in so far. In many cases, the actual shoreline was represented on the GPS III screen up to 1/2 mile from the actual shoreline. This was not simply a matter of GPS selective availability as the position location was repeated over several days in all cases.

The problem appears to be in the representation of the shoreline in the land data provided. For reference, the unit that I purchased has software version 2.04 and the land data is version 1.03.

I offer the following examples:

1) The Colorado River where it provides the boundary between the states of Nevada and Arizona between the latitudes of N35° 15' and N35° 45'. The river (and Lake Mojave) in this area is between 1/2 and 3 miles wide, but the display often shows the west shoreline between 1/4 and 1/2 mile east of its actual location. Thus, while the boat is positioned on the west bank of the river (or lake), the GPS position arrow may show up to 1/2 mile inland and, while the boat is positioned on the east bank, the GPS position arrow shows it still to be in the water by a substantial margin.

2) Lake McClure in California between N37° 35' -N37° 42' and W120° 07'-W120° 18'. The same problem with misplaced shoreline representation occurs with this body of water as was found in case 1.

In addition, the GPS III shows the head of lake navigation to be at N37° 40', W120° 74' whereas, with the lake at least 20 feet below the high water mark, the head of lake navigation is upriver to at least N37° 36', W120° 06'. The display shows the lake as it would be if its level were 150-200 feet below the high water mark.

3) New (sic) Don Pedro Reservoir in California between N37° 41'-N37° 53' and W120° 19'-W120° 25'. The same problem with misplaced shoreline representation occurs with this lake as was found in cases 1 and 2.

It appears that the shoreline of all three bodies of water mentioned

Continued on page 94

Weeder Technologies Add $4 ship/hand **FREE CATALOG!** Visa MasterCard **Pro-Kit**

PO Box 2426, Ft. Walton Beach, FL 32549 **850-863-5723**

Stackable RS-232 Kits

Digital I/O - 12 I/O pins individually configurable for input or output. DIP switch addressable; stack up to 16 modules on same port for 192 I/O points. Turn on/off relays. Sense switch transistions, button presses, 4x4 matrix decoding using auto-debounce and repeat. **$32**

Analog Input - 8 input pins. 12-bit plus sign self-calibrating ADC. Returns results in 1mV steps from 0 to 4095. Software programmable alarm trip-points for each input. DIP switch addressable; stack up to 16 modules on same port for 128 single-ended or 64 differential inputs. **$49**

Home Automation (X-10) - Connects between a TW523 and your serial port. Receive/transmit all X-10 commands with your home-brewed programs. Full collision detection with auto re-transmission. **$39**

Caller ID - Decodes the caller ID data and sends it to your serial port in a pre-formatted ascii character string. Example: *12/31 08:45 850-863-5723 Weeder, Terry <CR>*. Keep a log of all incoming calls. Block out unwanted callers to your BBS or other modem applications. **$35**

Touch-Tone Input - Decodes DTMF tones and sends them to your serial port. Keep a log of all outgoing calls. Use with the Caller ID kit for a complete in/out logging system. Send commands to the Home Automation and/or Digital I/O kits using a remote telephone. **$34**

50 MHz Freq Counter

Reads frequency from 1Hz to 50MHz and displays up to 7 digits on a 16 character LCD. Auto-range feature provides floating decimal point and automatic placement of suffix (Hz, KHz, or MHz). Microcontroller based provides for very small parts count. **$48**

DTMF Decoder/Logger

Keep track of all numbers dialed or entered from any phone on your line. Decodes all touch-tones and displays them on a 16 character LCD. Holds the last 240 digits in a non-volatile memory which can be scrolled through. Connect directly to radio receiver's speaker terminals for off-air decoding of repeater codes, or numbers dialed on a radio program. **$55**

IR Remote Control Receiver

Learns and responds to the data patterns emitted by standard infrared remote controls used by TVs, VCRs, Stereos, etc. Lets you control all your electronic projects with your TV remote. 7 individual output pins can be assigned to any button on your remote, and can be configured for either "toggle" or "momentary" action. **$32**

Telephone Call Restrictors

Two modes of operation; either prevent receiving or placing telephone calls (or call prefixes) which have been entered into memory, or prevent those calls (or call prefixes) which have "not" been entered into memory. Use touch-tone phone to program.

Block out selected outgoing calls. Bypass at any time using your password. **$35**

Block out selected incoming calls. Calls identified using Caller ID data. **$46**

EPROM+

A professional system for product design and service!

A DEVICE PROGRAMMER FOR BENCH AND FIELD

FIRST GENERATION EPROMS (24 PIN) 2708, TMS2716*, 1702*
SECOND GENERATION EPROMS (24,28,32 PIN) 2516,32,64,68764/66
2716,32,64,128,256,512,513,011,010,101,1001,020,2001,040,4001,080,8001
(40,42 PIN*) 27C210,1024,220,2048,240,4002,4096,27C400,800, 27C160
EEPROMS/NVRAMS (18-32 PIN) X2210/12,2804,16,17,64,65,256,512,010,ER5901,12XXX
FLASH EPROMS (28,32 PIN) [28F] [29C] [29EE] [29F] 256,257,512,001BX,010,101,020,040
*SERIAL EEPROMS** (8 PIN INCLUDES C,CS,LC,E) [2401] 02,04,08,16,21,32,44,64,65,256 [25010]020,040,080,160,320,640,128
[59C11]13,22 [8572]82,92 [9306]13,14,46,56,66,86 [95010] 020,040,080 [35C102]104,108 (14 PIN) ER1400, M58657
*BIPOLAR PROMS** (16 THROUGH 24 PIN) 82SXXX AND 74SXXX FAMILIES *FPGA CONFIGURATORS* [17C65] 128,256
*MICROCONTROLLERS** (8 BIT) [8041] 42 48 49 [8741],42,48,49 [8751] C51,5X,C5XX, 6XX [87C750] 87C751 87C752
*ATMEL FLASH MICROS** (8 - 40 PIN) [89C51] 52,55 [89C1051] 2051 [89S8252] 53 [90S1200] 2313, 2323, 2343, 4414, 8515
*PIC MICROS** [12CXXX] [16C54] 55,56,57,58,55X [16C61] 62,63,64,65,6XX [16C71] 73,74,71X [16C84] [16F8X] [14000]
*MOTOROLA MICROS** [68705P3] U3,R3 [68HC705C8] C9,J2,P9 [68HC711E9] D3
*REQUIRES SNAP-IN ADAPTER (DIAGRAMS INCLUDED OR PURCHASE ASSEMBLED AND TESTED)

- READ, PROGRAM, COPY, COMPARE, DISK FILE LOAD & SAVE (PLUS MORE!)
- FULL SCREEN BUFFER EDITOR WITH 25 COMMANDS PLUS BYTE & WORD MODES
- READS INTEL HEX/EXTENDED HEX, MOTOROLA S-RECORD AND BINARY FILES
- SOFTWARE RUNS UNDER DOS, WINDOWS 3.1,95 OR 98 ON ANY SPEED MACHINE
- PARALLEL PRINTER CABLE AND POWER PACK STORE INSIDE UNIT (9"X6"X3")
- 1 YEAR WARRANTY - 30 DAY MONEY BACK GUARANTEE

$289

$5.00 SHIPPING - $5.00 C.O.D.
VISA • MASTERCARD • AMEX

COMPLETE SYSTEM INCLUDES: PROGRAMMING UNIT, SOFTWARE PRINTER PORT CABLE, POWER PACK AND PRINTED MANUAL

ANDROMEDA RESEARCH, P.O. BOX 222, MILFORD, OHIO 45150
(513) 831-9708 FAX (513) 831-7562
website - www.arlabs.com email - arlabs@worldnet.att.net MADE IN THE U.S.A.

News Bytes

Check out some neat stuff to use on your computer ...

CREATE GIFTS OR START YOUR OWN BUSINESS WITH ANIMATED SCREEN

PY Software, Inc., has released Animated Screen for Windows 95/NT, a program that lets you create Windows screen savers and stand-alone presentations that you can give to your friends, employees, customers, and colleagues. You can also use Animated Screen to start your own screen saver business, selling custom shareware screen savers, with your company listed as the author. There are no distribution fees and, as an Animated Screen owner, you can distribute the screen savers that you create in unlimited quantities, royalty-free.

When you purchase an Animated Screen home license for $49.00, you can sell or give away the screen savers that you create, but they will list PY Software as the author in the program's "settings" box. When you purchase the Animated Screen commercial license for $99.00, you can enter your company into the program's "settings" box, and create shareware screen savers with shareware reminders, registration names, and registration keys that allow users to register your screen savers with your company. Site licenses are also available.

You can look at sample animations, or download a fully-functional trial version of Animated Screen from http://www.pysoft.com. In the United States, the program can be purchased from Kagi Shareware at (510) 652-6589.

C-COVER 4.0 MAKES CODE COVERAGE MEASUREMENT EASY

Bullseye Testing Technology has released C-Cover 4.0 for Windows NT and Windows, a full-featured code coverage analyzer for C++ and C.

This version contains new features aimed at making code coverage analysis easier and more productive than ever before. A new graphical coverage viewer gives developers and testers a hassle-free way to find untested code.

For more information or to receive a free evaluation copy of C-Cover, contact Bullseye Testing Technology, on the web http://www.bullseye.com, by E-Mail info@bullseye.com, or by phone 1-800-278-4268.

SPACE WATCH V3 — PIN DOWN SPACE USE QUICKLY AND EASILY

SharpeWare has released Space Watch v3, a program that lets PC and network users search and analyze disk space use quick-

Continued on page 90

0% FINANCING for 2 Months

2 Easy Payments Any Product

eem Complete Catalogs of ALL Major Component Manufacturers

2 payments $29 — 97 EEM CD
2 payments $44 — 98 EEM CD

97 ICM CD — 2 payments $75
97 for Moderate Design
97 ICM Books — 2 payments $65

2 payments $59 — 96 ICM CD
96 for Lite Design & Service
2 payments $52 — 96 ICM Books

98 ICM CD — 2 payments $99
98 for Advanced Design
98 ICM Books — 2 payments $93

Save Time with "REFEREE"

#1 Choice of Service Centers

CROSS REFERENCE & SPEC
Quarter Million Transistors, ICs & Diodes

A Specialist in "Hard to Cross House Numbers"
Easy, Powerful & Fast.
The Most Comprehensive Software Sold.

A selection yields Device Specifications & 75 to 250 Potential Replacements!
Replacement Numbers are Totally Global including Domestic, Asian, European, House Branded, as well as ECG, NTE, SK & GE. Displays Case Drawings, Lead Configuration & Pin-outs for many Devices. Coverage of Replacement Numbers is Very Impressive. **7 Disk Set** (17 Meg decompressed) For DOS, Win3.1 & 95 Latest Version 7.11 Includes Many Helpful Conversion Utilities, Tables & Formulas.

Includes: 4 HUGE Consumer Electronics Industry Directories
1- Consumer Electronics Parts Sources (Service) 2- Consumer Electronics Manufacturers
3- The Entire Computer Industry 4- Semiconductor Manufacturers
Perfect for Service, Engineering and Purchasing.

2 payments $15 Only available with another item

Shop the way the Pro's do, Use Their Tools!
These are the books that find the "Gold". For many years they've been used by the Sharpest Purchasing Agents. Look under every rock... they're impossible to find at ANY price, let alone a great deal like this: Find: Distributors, Manufacturers and Service providers for **Products, Services or ANY Component Parts imaginable from USA & Canada.** Sources for Everything from Gears to Semiconductors to Foreign Assembly Services.



the Perfect Gift
Only a few left:

2 Payments *$239 NEC 486 DX2-50*
12m - 340m - 9.5"active - W95 - PCMIA

Real Beauties !

2 Payments *$282 Compac 486 DX4 -100*
16m - 710m - 10.4"ds - W95 - PCMIA

may differ from illustration

All Cards & COD We don't sell semiconductors / NO catalog **FAX 516-826-7776**
Netcom 800-733-3733 ext 6300 516-826-1808 10-9 EST 7Days

Open Channel

Some More Tools for RadioScience Observers

by Joseph J. Carr

The only topic that generates more E-Mail from readers than the distance learning topics are the various radioscience observing pieces that I've done. There are some ideas and circuits that can be of use to anyone doing that type of work. This month, we will look at some of the analog signal processing circuits that can be used in radioscience observing.

"Analog, did he say?" I know it's the computer age, but a large percentage of the radioscience observers out there use analog set-ups. Indeed, the noise generated by computers raises hob with some radioscience observing set-ups. At VLF through HF, for example, computer-generated hash often makes the receiver unusable.

Rectifier-Integrators

An integrator is a circuit that performs the mathematical operation called integration on an input waveform. The output of the integrator is a voltage that represents the time average of the input signal. When designed and used correctly, the integrator can detect and track changes of the applied signal level.

Figure 1 shows two integrators that can be used on receivers that have an audio output jack. These circuits are based on similar circuits made popular by Jeff Lichtman of Radio Astronomy Supplies (190 Jade Cove Drive, Roswell, GA 30075; E-Mail jmlras@juno.com, website http://nitehawk.com/rasmit/jml0.html).

The version shown in Figure 1A is the simpler of the two. It consists of a half-wave voltage doubler circuit (D1/D2/C1/C2) that is driven by the audio output of the receiver (applied to V_{IN}). Capacitor C2 also sets the time-constant (T) of the integrator. This parameter determines the manner in which the integrator tracks input signals. The higher the value of C2, the more sluggish the integrator.

The idea in many circuits (where filtering is sought) is to find a value that will allow gradual changes to appear in the output, but high-frequency noise to be ineffective.



Figure 1.
A) Simple rectifier-integrator
B) More advanced rectifier-integrator.

There are two outputs from this rectifier-integrator. One output is a DC meter movement (M1). The meter movement that I used was a 0-200 µA, but anything from 0-50 µA to 0-1 mA can be used with suitable changes in the value of R1. Keep in mind, however, that the full-scale range of the meter movement sets its sensitivity. The potentiometer R1 is used to set the output to "near full-scale" when the strongest normal signal is present. This is a subjective determination, and you will have to find the setting empirically.

The other output is a current output that is used to drive a current-input strip chart recorder such as the Gulton. Selection of too low a meter full-scale rating can adversely affect the operation of the circuit ... the meter will be pegged much of the time.

The diodes (D1 and D2) used in this circuit can be silicon 1N4148 style devices, but the germanium 1N60 devices are a bit more practical. The reason is that the junction voltage is lower.

Another version is shown in Figure 1B. This circuit is transformer coupled (T1) to the audio output of the receiver. The transformer can be a 600-Ω:600-Ω line transformer, or something similar (e.g., 8-Ω:600-Ω, 50-Ω:1000-Ω). I have seen the use of 8-Ω:1000-Ω transformers in this application, but the output voltage may be too high in some cases. The 8-Ω winding is connected to the receiver output.

The rectifier, in this case, is a bridge rectifier stack (BR1). These devices have four silicon diodes inside. The ends of the transformer are connected to the "AC" terminals of BR1. These terminals are sometimes marked with the sinewave symbol. The negative (-) terminal of BR1 is grounded, while the positive (+) terminal is connected to the integrator.

The integrator of this circuit has five different capacitors, representing five different time constants. The capacitors are selected by a single-pole-five-throw rotary switch. The shortest time constant is at position "A," while the longest is at position "E."



Figure 2.
R-C integrator.



Figure 3.
Simple Miller integrator.



Figure 4.
Practical Miller integrator.

Integrator Circuits

There are times when you might want to use an integrator without the rectifier. In this section, we will take a look at some simple integrator circuits. The circuit shown in Figure 2 is a simple resistor-capacitor (R-C) integrator. The time-constant of this integrator is:

$$T = R \times C \quad [1]$$

Where:

T is the time-constant in seconds (s)
R is the resistance in ohms (Ω)
C is the capacitance in farads (F)

The general rule for selecting a time-constant is to make it greater than, or equal to, the period of the lowest frequency waveform applied to the integrator input (V_{IN}).

Time constants for radioscience observing tend to be rather long. For example, for solar noise integration it is 15 seconds or so. For a 15-s integrator, a 1-megohm resistor requires a 15-µF capacitor.

Solar noise is often observed in the 150-152 MHz radio astronomy band. A high gain Yagi or similar antenna is aimed at the sun. One radio astronomy club in England uses a 151-MHz receiver with several adjustable bandwidths of 50 to 280 KHz, and an AM detector. The output integrator receives the amplified output of the AM detector.

Figure 3 shows the basic active integrator. The DC power supply terminals are deleted for the sake of simplicity. This circuit is based on the operational amplifier, and is usually called the Miller integrator after its inventor. The equation for this circuit



Figure 5.
Precise rectifier ("absolute value") circuit.



Figure 6.
Mean value amplifier.

is: $V_O = \frac{-1}{R1\,C1} \int V_{IN}\,dt + V_k$ [2]

Where:

V_O is the output voltage
V_{IN} is the input voltage
V_K is any voltage that was on C1 when the integration began (may be zero).
R1 is in ohms
C1 is in farads

The term "-1" indicates that a phase inversion takes place in the amplifier (the inverting input is used). The term -1/R1C1 is the gain of the device. This term also sets the time-constant of the integrator. However, there is often a trade-off necessary to balance two competing situations.

First, we need an adequate time constant. Second, we need to keep the gain as low as possible consistent with the requirements. Consider the case of a 10K resistor and a 0.01 uF capacitor:

Time-constant = 10^4 x 10^{-7} farads = 0.001 seconds
GAIN = -1/(10^4 x 10^{-7} farads) = -1,000

The gain of -1,000 can cause a problem. Suppose the operational amplifier is operated from ±15 volt DC power supplies, so will probably output voltages as high as ±14 volts. The input voltage that will saturate the output of the operational amplifier is 14/1,000 = 0.014 volts = 14 mV. If kept under control, however, the active integrator can be a very powerful instrumentation circuit.

There are, however, some other problems. One problem is an undesired DC component stored in capacitor C1. This potential is accounted for by the V_K term in Equation 2. This problem can be overcome by shunting a switch across C1 to discharge it either before the integration takes place, or periodically as the charge on the capacitor accumulates.

The offset voltages of the operational amplifier, or an undesired DC component of the input signal, will tend to charge the capacitor. The result is a rising baseline for the output voltage that is not related to the input signal. The output therefore drifts towards either the positive or negative DC power supply rail.

One solution to the drive problem is to use an operational amplifier with very low input bias currents and output offset voltages for A1. I've successfully used the CA-3130, CA-3140, CA-3160, CA-3240 (two CA-3140 in one package), and CA-3260 in integrator circuits. These op-amps are BiMOS devices, so have extremely high input impedances.

Another solution is shown in Figure 4. Three methods are used in this circuit. First, a high value resistor (R2) is shunted across the capacitor. This resistor bleeds charge, but does not affect the integration sufficiently to be a problem. The second approach is to use an offset null circuit (R3, R4, R5, and R6). The input terminals are shorted together, the switch is momentarily closed and then re-opened, and then potentiometer R4 is adjusted to produce a stable zero output voltage.

It is necessary to perform this adjustment several times to home in on the correct setting. The third approach is the discharge or reset switch shunted across the capacitor (C1).

The capacitor used in any integrator should be a very low leakage type. Select capacitors with polethylene or similar dieletrics. For very long time-constant integrators, tantulum capacitors are better than aluminum electrolytics.

Precise Rectifier (Absolute Value) Circuit

A rectifier is a device or circuit that produces a unidirectional fluctuating DC voltage from a bi-directional AC input signal. The rectifier is also called an absolute value circuit because it produces an output that is the absolute value of the input voltage. An ordinary PN diode can be used as a rectifier (see Figure 1A again).

However, when weak signals are encountered, the non-linear portion of the diodes I-vs-V curve is in effect. The lower portion of the curve is called the square law region because the current through the diode changes as the square of the applied voltage. This region is usually between 0V and 0.3V for germanium diodes, and 0V to 0.7V for silicon diodes. When the applied voltage increases above this point, the I-vs-V curve straightens out and becomes linear. This region is called the linear region or the ohmic region.

The circuit in Figure 5 shows an active fullwave precise rectifier. This circuit is linear throughout its range. The actual rectifier circuit in op-amp

JFETS
ULTRA LOW NOISE
LS843 - 3nV/Hz typ
TIGHT MATCHING
LS843 - 1 mV max
◇ N & P Channel
◇ Duals & Singles
◇ Custom Screening
◇ Die, SMT, Thru-Hole
◇ No Order Minimum
◇ COD's Accepted
Second Source for Domestic & Foreign JFETs & Bipolars
Full Service U.S. Manufacturer of Specialty Linear Products
LINEAR SYSTEMS
4042 Clipper Court
Fremont, CA 94538
510-490-9160/510-353-0261(Fax)
E-mail: 3623671@MCIMAIL.COM

Tiny FBasic Computer

(Shown 85% Actual Size - 40 pin DIP)
The TICkit 62 module is like a Parallax Basic Stamp®II, but has 4 times the program space installed (expandable to 64K). It also has 4 times the variable space (96 bytes), and uses a modern structured language similar to BASIC only more powerful.
– Only tool you need is a PC
– Inexpensive $45/module, $16/IC
– Development Kit only $45
– Huge library of I/O function
– Structured FBasic Language
– Easy to learn and use
– Powerful enough for large projects
ASK ABOUT OUR STAMP COMPATIBLE PERIPHERAL COMPONENTS
VersaTech™ Electronics
PHONE: (303) 828-9156, FAX: (303) 828-9316
e.mail: versatech@csn.net
Web: //www.csn.net/versatech
11170 Flatiron Drive, Lafayette, CO 80026
Basic Stamp is a registered trademark of Parallax, Inc.

A2 and the surrounding components. Amplifier A1 is an AC-coupled input buffer, while A3 is an output buffer. These amplifiers are used to isolate the precise rectifier from other circuits. It is possible for the diodes of the precise rectifier to distort waveforms in the circuit, so the buffers are highly desirable.

Mean Value Amplifier

The mean value amplifier of Figure 6 couples a Miller integrator with a precise rectifier circuit to form a circuit that outputs the time-average value of the input circuit. The output voltage approximates the root-mean-square (RMS) value of the input signal. The values of the resistors are either R or 2R, with R being determined by the required time constant. The output voltage of Figure 6 is:

$$V_{MEAN} = \frac{-1}{RC} \int_0^T V_{IN}(t)\ dt \quad [4]$$

Where:

VMEAN is the mean value of the input voltage
VIN(t) is the input voltage
R is in ohms
C is in farads
T is the time-constant (RC)

It is a good idea to use low temperature coefficient resistors for this circuit. The diodes can be 1N4148 silicon diodes, or equivalent.



Figure 9. Analyzer2000 spectrum display.



Figure 10. Analyzer2000 waterfall display.

Minimum Value Circuit

The detection and recording of hiss signals is something of a problem, especially when there are high amplitude transient signals such as lightning pulses present in the atmosphere. Figure 7 shows a minimum value amplifier that will allow recording of the hiss, while rejecting the transient signals. This circuit has two time-constants: one for charging of the capacitor (C1 x R1) and the other for discharging (C1 x R2). These values are 0.01 seconds and 20 seconds, respectively.

The resistors setting the gain of the op-amp (R3/R4) can be either equal (gain-of-two or higher as needed. If no gain is required, then delete the resistors and connect the output of the op-amp to the inverting input. This makes the op-amp into a non-inverting unity gain follower.



Figure 7. Minimum value amplifier.



Figure 8. DC power supply connections for op-amps.

DC Power Supply Connections to Op-Amps

Figure 8 shows the DC power supply connections for all operational amplifiers used in the above circuits. These connections were deleted for the sake of simplicity in the other illustrations, but are presented here. The V- and V+ DC power supplies are not two sides of a single supply, but rather two different power supplies. The V- is negative with respect to ground, while the V+ is positive with respect to ground. The ground connection between them is also the input and output signal common.

Capacitors are used to decouple the DC power supply lines. These capacitors should be mounted as close as possible to the body of the operational amplifier.

The pins shown on the op-amp in Figure 8 are the so-called "industry standard" for single devices (i.e., one op-amp in an eight-pin package). Most single op-amps will use this pattern (e.g., 741, CA-3140, etc.).

Analyzer2000™ Spectrum Analysis Software

There are a number of applications for audio spectrum analyzer software, including radioscience observing. A program I recently obtained looks like it might have real potential: Analyzer2000™ by Brown Bear Software in Germany. It runs on Windows 95 and Windows NT machines. It is a "... fast, high resolution time-frequency analyzer." Features include fast spectral analysis with FFT display for time and frequency variant signals using an inexpensive PC sound card. If your computer is equipped with a Sound Blaster compatible sound card, then no additional hardware is needed. Features include:

- Time Analysis with Oscilloscope Display
- Sonagraphic Analysis with Waterfall Display Measurement
- Tools like markers, frequency rulers, level rulers, time rulers
- Multi channel operation
- Multi morse decoder

You can do simultaneous recording directly from the PC sound card to standard wave (*.WAV) files. The producers claim that it can be used for adapting various DSP hardware running on MS-Windows-NT or MS-Windows95.

Figure 9 shows the user interface screen with a spectrum display. Note that this is a smoothed spectrum, rather than the bar graph or "histogram" form you might have seen elsewhere. The particular spectrum shown here is a natural radio "whistler" recorded in Northern California some years ago.

Figure 10 shows the "waterfall" display of the same signal. It is basically a 3-D display, although that is a little hard to see in the picture. It displays frequency, amplitude, and time. The curved feature is the whistler tone, while the long dark lines are from lightning crashes (the static you hear in your AM BCB radio).

The only criticism I have of the software is the lack of a printing facility. To make a print of the screen you must hit the "Print Screen" button on your computer's keyboard to move the image to the clipboard. You can then paste it to a graphics program. I tried it on both Microsoft Photo Editor and Visio Technical 5.0, and it worked on both. The problem, however, is that you get the entire screen, not just the display. Hopefully, that will be corrected in the future.

The Analyzer2000™ software is obtained by downloading. Two web sites can be accessed: http://members.aol.com/btf1 and http://www.shareit.com/programs/101176.htm. You can download a demo version for free, but it is limited to 30 days and 15 minutes per session. A fee of $98.00 will get you a registration number that frees the demo version for unrestricted use. For support and technical questions contact Thomas Braunstorfinger (**E-Mail: btf1@aol.com**) or for other questions, contact Martin Hisch (**mhbaer@aol.com**). **NV**

Connections ...

I can be reached by snail mail at P.O. Box 1099, Falls Church, VA 22041, or via E-Mail at CARRJJ@AOL.COM.

new!



SOLAR-POWERED ROBOT BUG KIT

No batteries required! It uses photosensitive eyes to seek light and dual feelers to avoid obstacles. Kit includes circuit board, solar cells, miniature motors, all parts and easy-to-follow instructions.

98K001 **$59.00 each**

12/14.5 VAC POWER TRANSFORMER

110VAC input. 12VAC or 14.5VAC out @ 25A (tapped primary). Specs included.

98E005 **$29.99 each**

80-PIN SCSI EXTERNAL CABLE

Two feet long.

98C030 **$24.95**



BASIC PARALLEL CABLE FOR pcANYWHERE

Six-ft. "competition yellow" DB-25M to DB-25M laplink cable.

98W005 **$5.95 each**



LAPLINK SERIAL CABLE

Six foot double-headed (DB9F to DB25F) cable. Works with DOS 6.2 and Windows 95, for direct copying directly from one computer to another.

97W002 **$5.95 each**

LEDs By The Hundreds!

SE5011S - T1-3/4 Red
SE5021S - T1-3/4 Green

Special! 100 For $5.95





COAXIAL CABLE BY THE 1000'

RG58/U - 98W018S
or
RG59/U - 98W003S
Good through 11/31/98
While Supply Lasts

Special! 1000' box - $50.00

12 VDC BUEHLER GEARMOTOR

No Load: 60 mA, 62 RPM. Full Load: 155 mA, 47 RPM. Load Torque: 17 oz./in, Gear Ratio: 106:1. Cast case, sintered bronze bearings. Dimensions: 40 x 40 x 29 mm. Shaft: 3 mm dia x 10 mm long. Rotation: clockwise, facing shaft.

98M005 **$11.95 each**

36VDC, 4.2A REGULATED POWER SUPPLY

120-220VAC input. Attractive black shock-proof case, 4.75" x 3" x 10.5".

92E026 **$19.95 each**

MERCURY TILT SWITCH

Shown actual size.

98B015 **$1.99 each**



ROTARY COAXIAL CABLE STRIPPER

For RG-58, RG-59, RG-62 type cables.

97Z025 $9.95

HANDY KEYCHAIN LASER

High quality laser pointer sports attractive finish. Projects up to 1000 feet on tiny AG-3 watch batteries (included). Weighs in at only 0.6 OZ. 650nm 5mW class IIIA.

98L007 **$14.95 each**

GENERAL INSTRUMENTS UNIVERSAL REMOTE CONTROL

Model XRC110. 44-button transmitter controls up to four units, i.e., TV, VCR, Cable Box, and Auxiliary - second TV, VCR, Digital Audio Tuner or services such as Music Choice (MC) and Digital Music Express (DMX). Slim, lightweight, easy to handle. Easily programmed as your needs change. Programmed functions not lost when replacing batteries. Uses two "AA" cells. Indicator lights show which device is being controlled. Volume control may be programmed to work even though the rest of the transmitter is in a different mode. Works with equipment from many manufacturers. Will do a "code search" for the correct code, if needed. Batteries, detailed instructions and device code tables included.

98V011 **$9.95 each**

GENUINE 14X JEWELER'S LOUPE

High-quality glass Hastings Triplet flat field loupe made in the USA by Bausch & Lomb. If you're in the field searching part numbers on components or serial numbers on equipment, this little gem could pay for itself the first time you use it.

98Z012 **$16.00 each**

ATX CASE

Three 5.25" bays, 1 floppy bay, 250W power supply. New. Use with ATX motherboard.

98C033 **$69.95**

MULTIMEDIA SPEAKERS

Amplified, with cables and power supply. Size: 10.25"H x 2.5"W x 6"D.

98V004 **$9.95 Pair**

ATARI 2600 TRACKBALL

Also works with C-64 and C-128 computers. Smooth ball bearing action. Cable with DB-9F connector included. Try your hand at modifying this unit for your PC.

92C069 **$9.95 each**

AC-DC METER

Scale calibrated to 12/18/24 VDC and 120/240 VAC. 0 to 10 mA movement. Approximately 1.5 inches square.

98A002 **$2.95 each**

DIODE GRAB BAG

Thousands of diodes of all kinds, including Zeners, Power, Schottky, Signal, etc.

94S007 **One-Pound Mix - $14.95**

UNIPOLAR STEPPER MOTOR DRIVER IC

UCN5804. Drives a unipolar stepper in one of three operating modes: single phase, two phase or half step. Up to 1.25 Amps per phase. Step and direction input. Drive with a 555 timer, parallel port, etc. Build your own robot, anything that requires precision positioning.

93I002 **$4.50 each**

NIPPON PULSE MOTOR

7.5 deg./step, 48 s/rev, 5 V, stepper with brass gear mounted on shaft. NPM P/N PF42-48ES. With spec sheet.

92M010 **$3.95 each**

COMBO PACK!

One 93I002 IC and 92M010 motor (both shown above) with schematics.

93I003 **$7.95/set**

COMPUTER CASE & POWER SUPPLY

Mini tower case with 250W power supply, two 5.25" and two 3.5" external bays, plus one internal bay for hard drive. LEDs for power, turbo and HDD.

97C001 **$24.95**

PENTIUM 60/66 MOTHERBOARD

Supports only Pentium 60/66 CPUs. Four PCI, three EISA, two VLB slots. Comes with 256K cache, 16MB RAM and CPU. No docs. Jumper settings are silkscreened on the board.

98C013 **$45.00 each**



DELUXE 101-KEY KEYBOARD With Protective Cover

Uses membrane technology to protect keys from dust, liquids, etc.

97C002 **$9.95 each**



PCI IDE-ONLY CARD

Settings are silkscreened on card.

98C034 $9.95

LOW LIGHT MINI TV CAMERA

I/R LEDs allows this camera to "see" in the dark. Element: 1/3" monochrome CCD. Lens: Fixed 3.5mm, f:1.8. Field of view: 76° horiz., 55° vert. Automatic electronic iris. Resolution: 360 horiz., 420 vert. Illumination: Ambient light and/or I/R LEDs supply additional light in low light conditions. Sensitivity: 0.1 lux @ f1.8. Video output: EIA Std. 75 Ohm 2:1 interlace. 1.0 Volt P/P composite video. Output connections: 7" video and power leads. Power: 9 VDC ±1V @ 150 mA. Size 2.125" x 2.5" x 1.2". *Includes power supply, hookup cables and instructions, and six-month warranty!*

95V004 **$119.95 each**

DUKE'S DELIGHT

Five pounds of assorted electronic hardware - fasteners, nuts, bolts, screws, brackets, springs, standoffs, arms, gears, pulleys, and indescribable metal stuff scrounged from Silicon Valley's surplus to complement your hardware hoard.

92Z009 **5 Lbs for $4.95**



STEEL ENCLOSURES

Features include ventilation holes, self-adhesive rubber feet. Front and rear panels are 0.05" aluminum alodine painted white. Top and bottom covers are 0.04" phosphated steel painted black.

GC3119A (2.5" x 6" x 7") **$14.00**
GC3119F (2.5" x 17" x 11") **21.00**
GC3119K (3.5" x 17" x 11") **26.00**

ALLTRONICS

2300-D Zanker Road - San Jose, CA 95131-1114

World Wide Web: http://www.alltronics.com

(408) 943-9773 - Fax (408) 943-9776

Send $2.00 For Our Latest Catalog!

$4.00 Foreign. Refundable on First Order.

VISA

Store Hours: 9-6 M-F & 10-3 Sat. - Pacific
Visa, M/C, AmEx Accepted.
All Sales Final.
California Residents Add Sales Tax.
Shipping Additional on All Orders.
Prices Good 60 Days from Date of Publication

011098

SECURITY ELECTRONICS SYSTEMS AND CIRCUITS – Part 9

Ray Marston looks at a miscellaneous collection of security circuits in this penultimate episode of the series.

by Ray Marston

INTRODUCTION

Most of the previous episodes of this series have each looked at a specific class or type of electronic security circuit.

This month's episode looks at a miscellaneous collection of security circuits that can be used in the home or in commerce or industry, but which do not fit into any of the specific classes of circuits described in earlier articles.

These circuits include ones that are activated by the presence of a liquid, steam, or gas, by sound, by the failure of AC power supplies, by the close or near proximity of a person or object, by a human touch, or by the breaking of an ultrasonic beam.

LIQUID- AND STEAM-ACTIVATED CIRCUITS

BASIC PRINCIPLES AND CIRCUITS

Liquid- and steam-activated circuits have several practical applications in the home and in industry.

Liquid-activated circuits can be made to sound an alarm or activate a safety mechanism when the water in a bath or cistern or the liquid in a tank or vat reaches or exceeds (or falls below) a preset level, or when flooding occurs in a cellar or basement, or when an impact wave is generated as a person or object falls into a swimming pool or tank, etc.

Steam-activated circuits can be made to sound an alarm or activate a safety mechanism when high-pressure steam escapes from a valve or fractured pipe, or when steam emerges from the spout of a kettle or container as the liquid reaches its boiling point.

Impure water (including tap water, sea water, and most rain water, and steam) and many other liquids have a fairly low electrical resistance, but normal air has an ultra-high electrical resistance.

Consequently, one of the simplest *electronic* ways of detecting the presence or absence of conductive liquids (or vapors) is to use a pair of metal probes as sensors and to connect their outputs to a resistance-activated 'switch' circuit in the basic way shown in *Figure 1.*

Here, when the liquid is in contact with both probes simultaneously, the probe-to-probe resistance is relatively low and, under this condition, the output voltage of the resistance-activated switch is also low, but when the liquid is not in contact with both probes at the same time, their probe-to-probe resistance is very high and, under this condition, the output voltage of the switch is high. The circuit's output can thus be used to activate an alarm or other device when the liquid (or vapor) is present or absent, or is above or below a preset level.



Figure 1. Basic 'electronic' way of detecting conductive liquids via a pair of metal probes.



Figure 2. Basic 'electromechanical' way of detecting the critical level of a liquid.



Figure 3. Simple relay-output 'liquid-activated' circuit operates when less than 500K is applied across the probes.

In practice, the resistance appearing across the probes under the 'contact' condition depends on the type of medium that is being detected. In the case of rain or tap water, it may typically be in the range of 1K0 to 10K when the probes are 10mm apart, but in the case of steam or many oils, the resistance may be several megohms or greater. On some applications, the metal container or tank that holds the conductive liquid can act as one of the two metal 'contact' probes.

Note that the above liquid-detection technique is not suitable for use with highly volatile, corrosive, or highly-resistive liquids. In such cases, the presence/absence of the liquid may best be detected by using an electromechanical method, such as that shown in *Figure 2.*

Here, the liquid is contained in a sealed tank, and its level is sensed by a float that is anchored to a pivoted lever that drives a rod that passes out of the top of the tank via a close-fitting tube. The rod thus rises and falls in relation to the liquid level, and activates an external microswitch when the level goes above or below some preset limit.

Figure 3 shows a practical example of a simple non-latching liquid-activated circuit that operates a relay when a liquid with a resistance of less than about 500K contacts both probes simultaneously, e.g., when the water in a

PRIMECELL

IF YOU NEED NEW BATTERIES FOR YOUR ELECTRONIC EQUIPMENT DON'T PITCH EM' - SEND THEM FOR REBUILDING ! - SAVE $ $

CUNARD ASSOCIATES, R.D. 6 Box 104, Bedford, PA 15522

- WE INSTALL NEW NI-CAD OR NI-MH BATTERIES INTO YOUR ORIGINAL CASE.
- WE IMPROVE CAPACITY TO BETTER THAN ORIGINAL.
- WE FIX WHAT CAN'T BE FOUND. (OR AFFORDED)
- WE PROVIDE QUICK SERVICE. / EXTENDED LIFE FOR OLDER EQUIPMENT
- WE OFFER FREE QUOTES. / FREE RETURN IF QUOTE IS REFUSED.
- WE PROPERLY DISPOSE OF YOUR OLD CELLS BY RECYCLING.
- WE GIVE YOU A 12 MONTH WARRANTY.
- WE WILL BE HERE WHEN YOU NEED US / 12 YEARS IN BUSINESS.
- WE SAVE YOU **** MONEY **** $ $ $ $

- NO JOB IS TOO LARGE OR TOO SMALL ..... WE OFFER VOLUME DISCOUNTS TO LAW ENFORCEMENT / COMPANIES / FIRE DEPARTMENTS / UNIVERSITIES

GENERAL ELECTRIC
MPD/PLS - MPR/MPS/MPX
19A704850P(1200mAH) $ 34.95
19A704860P(1800mAH) $ 39.95
PL19D429763(777)G1/3 $ 37.95
MAXON SA-1155 1160 $ 39.95
TAD 1450 1510 1520 $ 21.95
MOTOROLA
P200 HT600 MT1000
NTN 4585 4824 5414 $ 37.95
NTN 5447 5521 5545 $ 37.95
MIDLAND
70-B10 B16 B19 B21 $ 39.95
70-B32 70-B36 $ 39.95

UNIDEN
APH56 APX500 $ 21.95
APX650 1050 $ 29.95
1000 1100 1200 $ 34.95
BP100/200/205 $ 14.95
205 Inc to 1350 $ 22.95
ICOM
BP2 / BP3 /BP22 $ 18.95
BP5 / BP23 / 24 $ 24.95
BP7 / CM7/ BP8 $ 34.95
YAESU
FNB 3 4 12 14 16 $ 32.95
FNB19 21 26 27 38 $ 32.95
FNB 17 25 35 $ 23.95

BENDIX KING
KR105/LAA125 $ 34.95
KENWOOD
PB2 / KNB3 $ 29.95
PB21/21H $ 14.95
PB25/H/26 $ 24.95
CORDLESS DRILLS
Any brand 7.2V $ 18.95
Any brand 9.6V $ 29.95
Any brand 12.0V $ 32.95
Any brand 14.4V $ 37.95
SURVEYING EQUIP.
COMPUTERS - PHONES
Send battery for quote.

FOR INFORMATION ABOUT YOUR REQUIREMENTS ..... CONTACT US:
PHONE OR FAX : (814) 623-7000 E-MAIL TO: PRIMECELL @ AOL.COM
SEND YOUR PACKS FOR FREE QUOTATION VIA UPS, RPS OR US MAIL
DOWNLOAD OUR CATALOG, WEB SITE: http://users.aol.com/PrimeCell

BATTERY REBUILD SERVICE

MANY OTHERS AVAILABLE - WRITE OR CALL
FREE CATALOG
ADD $ 4.50 SHIPPING & HANDLING PER ORDER
MasterCard VISA

Write in 113 on Reader Service Card.

ATTENTION
DEALERS/DISTRIBUTORS
BUY DIRECT FROM THE MANUFACTURER
THESE AND OTHER VIDEO SECURITY PRODUCTS NOW AVAILABLE!!! (DEALERS/DIST. ONLY) Minimum Order.

CCD Cameras	Qty 5	Qty 10	Qty 20	Qty 50+
B&W Board	$57	$52	$47	Call!
B&W Board/sound	$62	$57	$52	Call!
B&W Mini	$65	$60	$55	Call!
Color – Mini	$150	$142	$135	Call!

*B&W CCDs use Sansome Chips. Color CCDs use Sony.

Guardian Eye

CCD Camera Hidden Inside a "Magnavox" Clock

CCD Clock	Qty 5	Qty 10	Qty 20	Qty 50+
B&W Wired	$144	$129	$114	Call!
B&W Wireless	$289	$264	$248	Call!
Color Wired	$234	$218	$199	Call!
Color Wireless	$387	$362	$345	Call!

Wireless use 2.4Ghz standard transmitters and receivers.

Call ATN Today for the Best Prices and Quality Security Products.

American Technologies Network Corp. 1(800)910-2862
20 S. Linden Ave. #1B 1(650)875-0130
S. San Francisco, CA 94080 fax:1(650)875-0129
www.atncorp.com sales@atncorp.com

Write in 114 on Reader Service Card.



Figure 4. Sensitive relay-output 'liquid-activated' circuit operates when less than 20M is applied across the probes.



Figure 6. Basic LM1830 low-fluid-level warning circuit with LED output, using (a) separate probes and (b) a single probe.



Figure 5. Pin notations and simplified block diagram of the LM1830 'fluid-level detector' IC.



Figure 7. Low-fluid-level warning circuit with 700Hz tone output.



Figure 8. Low-fluid-level warning circuit with external reference resistor and boosted audio output.

bath or cistern reaches a certain level. The circuit uses a 12V supply, and the relay's RLA/1 contacts can be used to activate any type of external electrical device.

When the probes are open-circuit, Q1 and Q2 are cut off and the circuit consumes a standby current of less than 1µA, but when a resistance of less than about 500K is applied across the probes, sufficient current flows in Q1's base to drive Q1-Q2 and the relay on.

Note that the sensitivity of the *Figure 3* circuit can be reduced by simply reducing the value of R1; the *maximum* resistive sensitivity is roughly 18 x R1, and falls below 180K when R1 has a value of 10K, and below 60K at an R1 value of 3k3.

Conversely, the sensitivity can be greatly increased by raising the R1 value and using a super-alpha-connected pair of transistors in place of Q1, and *Figure 4* shows how the above circuit can be modified in this way, so that it can be activated by probe resistances of up to 20M, e.g., by steam or high-resistance liquids.

LM1830 IC CIRCUITS

When in use, liquid-level detector circuits of the simple types shown in *Figures 3* and *4* pass a small DC current through the liquid under test. In theory, this DC current can result in an electroplating action in which metal slowly migrates from one probe to the other, eventually degrading the 'source' probe.

This problem does not occur if an AC test current is used, and a dedicated 'fluid-level detector' IC that uses this technique is widely available, at modest cost. The device is manufactured by National Semiconductor and is known as the LM1830. *Figure 5* shows the outline and simplified internal circuit of the IC.

The LM1830 can be used to detect and indicate the presence or absence of water or any other liquid that presents a resistance of less than 100K between its pin 10 (detector input) and pin 11 (GND) 'probe' points.

The IC houses an oscillator (which gives AC drive to the water-detecting metal probe), a 13K reference resistor, a balance detector, and (available on pin 12) an open-collector npn common-emitter output stage that can sink up to 20mA maximum.

The oscillator frequency is set via an external capacitor (1n0 gives 7KHz operation) wired between pins 1 and 7, and the IC can operate from supplies in the 9V to 25V range and consumes a typical standby current of 5.5mA.

Figure 6 shows the LM1830 IC's basic application circuits as a low-liquid-level alarm with an LED output; note that the *(a)* circuit uses two separate probes, one of which is grounded, but that in the *(b)* circuit — in which the liquid is stored in a metal tank — the metal storage tank is grounded and acts as one of the circuit's two 'probes.' The IC's internal oscillator is set at 7KHz via C1, and the non-grounded metal probe is taken to the pin 10 'detector' input and is AC driven via C2 and the internal 13K reference resistor.

When the liquid level is 'high' (i.e., in contact with the probe), the probe-to-ground resistance is below the 13K reference value and, under this condition, the output LED is off. When the liquid level is low, the probe-to-ground resistance is high (greater than the 13K reference value) and, under this condition, the output LED is driven by a 7KHz squarewave signal and thus illuminates. The basic *Figure 6* circuit can be usefully modified in a variety of ways, as shown in *Figures 7* to *10*. *Figure 7* shows it modified to give an audible 700Hz tone output (set by C1) into an inexpensive piezo sounder.

The LM1830 IC has a mean output current limit of 20mA maximum, and *Figure 8* shows how the available output power can be boosted via an external emitter-fol-

Got A Battery Problem?

Get the *Ultimate* Battery Monitor

Fits 2" hole!

E-Meter ™

Perfect for...
...Emergency vehicles.
...Power hungry mobiles.
...Back up power systems.
...Cell /repeater monitoring.

"Batteries don't die, they're murdered"

Proven in thousands of marine, military, RV, and industrial applications, the ***E-Meter*** gives you the battery information you need to build and run reliable DC systems. A multi-color bar graph shows battery status at a glance. Big LED's display ***volts***, ***amps***, ***amp-hours***, ***time*** or ***percent of capacity remaining***, and ***kilowatt-hours***. Tracks historical information including battery *charge efficiency*, number of *discharge cycles*, *deepest* and *average depth of discharge*. Optional RS232, temperature sensor, and low battery/genrun contact. Models up to 500V @1000A. 12-24V @ ≤ 500 A units are priced under $250 w/ sensor!

Call ext. 12 with any application or OEM questions!

Cruising Equipment

5245 Shilshole Ave. NW, Seattle, WA 98107
(206) 782-8100 Fax: (206) 782-4336
See us on the web: http://cruisingequip.com

Write in 115 on Reader Service Card.

MORE POWER!

68HC11, 80C51 & 80C166

AM Research supports over 30 of the most popular Embedded controllers with both ***hardware*** and ***software***.



☑ More Microcontrollers
☑ Faster Hardware.
☑ Faster Software.
☑ More Productive.
☑ More Tools & Utilities.
☑ IIC Peripherials.
☑ Single Chip Capable.
☑ Outstanding Support.
☑ Custom designs.

Call or email for a free full line brochure



Orders (800) 949-8051
Info (916) 652-7472
fax (916) 652-6642
www.amresearch.com

AM Research, Inc.
PO Box 43
Loomis, CA 95650

The Embedded Controller Experts

lower stage, and also shows how the IC can be used with an external (rather than the internal) reference resistor of up to 100K maximum (1K0 minimum), to enable it to test liquids with resistance values of up to 100K.

Figure 9 shows the circuit modified to give relay output drive via pnp emitter-follower Q1, by using C3 to convert the output-stage driving signal to DC. This circuit also shows supply-line transient protection given to the IC via R1; this modification is recommended for use in automobile circuits, where — under very exceptional circumstances — supply transients may reach peak values of 40-50V.

Finally, *Figure 10* shows the relay-driving circuit modified to give an over-level warning action (in which the relay is off when the liquid level is low) by using npn common-emitter amplifier Q1 as the relay driver.



Figure 9. Low-level warning circuit with relay output and supply-transient protection.



Figure 10. Over-level warning circuit with relay output.



Figure 11. Basic gas detector circuit using 'hot-wire' gas sensors.



Figure 12. Practical gas-detector alarm circuit, powered from an external 12V DC supply.

A GAS-ACTIVATED ALARM CIRCUIT

Leaking highly-flammable gases such as isobutane, methane (natural or 'town' gas), hydrogen, and ethanol, etc., all present potentially explosive and life-threatening hazards, but can easily be detected — even in gas-to-air concentrations of less than 0.5% — by a simple and easy-to-use device that is readily available from major component suppliers and is known as a hot-wire gas sensor. The heart of this sensor is a coil of fine platinum wire that is coated with high temperature oxides and a special catalyzer.

A hot-wire gas sensor actually consists of a *pair* of thermally matched hot-wire elements, one of which is gas-sensitive and is known as the 'detector,' and the other of which is not gas-sensitive and is known as the 'compensator.' In some cases, the matched detector and compensator are supplied as individual units, which are each enclosed within an individual fire- and explosion-proof wire mesh, and in others they are combined in a single unit and share a common fire/explosion-proof mesh. In either case, they are meant to be used in the basic circuit shown in *Figure 11*.

In *Figure 11*, the compensator (R1) and detector (R2) are wired in series to form a gas-sensitive potential-divider on one side of a Wheatstone bridge, R3-RV1-R4 form an adjustable potential divider on the other side of the bridge, and RV1 is adjusted so that Vout is normally zero.

The compensator and detector have a low hot-wire resistance and, when wired as shown and powered from a suitable voltage source (typically 2.2V or 3V AC or DC), pass a current (typically 150mA to 400mA) that raises the hot-wire temperature to about 350°C in gas-free air.

The resistances of the detector and compensator both vary with ambient temperature and humidity levels, etc., but are matched so that they vary equally in both devices, so that (when wired as shown in *Figure 11*) they maintain a constant division ratio in the absence of gas.

When gas *is* present, the detector's special catalyzer effectively but safely burns the gas that strays within the safety mesh and which surrounds the hot-wire, thus raising the hot-wire's temperature and resistance, thereby reducing the voltage appearing on the detector/compensator junction and upsetting the balance of the bridge.

This action typically makes the circuit's Vout value fall by about 25mV at gas concentrations of 4000ppm (= 0.4%) with methane, or 2000ppm (= 0.2%) with isobutane.

Figure 12 shows the circuit of a practical gas alarm that is powered via an external 12V DC supply and which drives a ready-built solid-state commercial alarm/siren unit under the 'alarm' condition. Here, the basic gas detector (which is similar to that of the *Figure 11* circuit) is built around R2-RV2-R3-R4-R5 and is powered via a stable low-voltage DC supply derived from the 12V line via voltage regulator IC1, and has its output fed to the alarm/siren unit via voltage comparator IC2 and transistor switch Q1.

The circuit's action is such that the voltage on pin 2 of IC2 is normally about 25mV above that of pin 3 (settable via RV2) under 'clean air' conditions and, under this condition, IC2's output is low and Q1 and the alarm/siren are off, but the pin 2 voltage falls below

World Passing You By?

Are you interested in Microprocessors & Embedded Control Systems? If not you should be! Look around, just about everything these days has an embedded microprocessor in it. TVs, cars, radios, traffic lights & even toys have embedded computers controlling their actions. The Primer Trainer is the tool that can not only teach you how these devices operate but give you the opportunity to program these types of systems yourself. Examples & exercises in the Self Instruction manual take you from writing simple programs to controlling motors. Start out in Machine language, then move on to Assembler, & then continue on with optional C, Basic, or Forth Compilers. So don't be left behind: this is information you need to know!

Examples Include:
- Measuring Temperature
- Using a Photocell to Detect Light Levels
- Making a Waveform Generator
- Constructing a Capacitance Meter
- Motor Speed Control Using Back EMF
- Interfacing and Controlling Stepper Motors
- Scanning Keypads and Writing to LCD/LED Displays
- Bus Interfacing an 8255 PPI
- Using the Primer as an EPROM Programmer
- DTMF Autodialer & Remote Controller (New!)

The PRIMER is only $119.95 in kit form. The PRIMER Assembled & Tested is $169.95. This trainer can be used stand alone via the keypad and display or connected to a PC with the optional upgrade ($49.95). The Upgrade includes: an RS232 serial port & cable, 32K of battery backed RAM, & Assembler/Terminal software. Please add $5.00 for shipping within the U.S. Picture shown with upgrade option and optional heavy-duty keypad ($29.95) installed. Satisfaction guaranteed.

EMAC, inc.
11 EMAC WAY, CARBONDALE, IL 62901
618-529-4525 Fax 457-0110 BBS 529-5708
World Wide Web: http://www.emacinc.com

1985 - 1998 OVER 12 YEARS OF SERVICE

Write In 116 on Reader Service Card.

WHOLESALE CABLE BOXES
CONVERTERS · FILTERS

Call Us To Satisfy All Of Your Cable Equipment Needs!
WE CARRY ALL THE MAJOR BRAND NAMES!
THE BEST DEALER PRICING!
30 DAY MONEY BACK GUARANTEE!
1 YEAR WARRANTY
Call Now and Take Advantage!!!
MODERN ELECTRONICS
1-800-906-6664
2609 S. 156TH CIRCLE • OMAHA, NE 68130
VISIT OUR WEB SITE: http://www.modernelectronics.com
E-MAIL: modern@modernelectronics.com

Write In 117 on Reader Service Card.



Figure 13. Practical relay-driving sound-activated switch circuit.



Figure 14. Simple relay-output AC power-failure alarm.



Figure 15. Power-failure alarm with a piezo siren output.

that of pin 3 when significant gas concentrations are detected and, under this condition, IC2's output switches high and drives Q1 and the alarm/siren on.

Before starting to build the *Figure 12* circuit, first locate a suitable hot-wire gas sensor and find out its voltage and current ratings. With that current rating in mind, select a suitable 12V DC power supply. Now — *without wiring the gas sensor in place* — build the IC1 voltage regulator section of the circuit, taking care to fit IC1 to a heatsink that will dissipate 1W per 100mA of working load current, and then power it up and trim RV1 so that (when powering a dummy load) it produces the precise specified working voltage of the gas sensor (usually 2.2V or 3V).

Now build the rest of the circuit, fit the gas sensor in place, power the circuit up, and trim RV2 so that the alarm/siren is off. Let the unit warm up for a minute or two, then — using a high-impedance digital multimeter — trim RV2 so that pin 2 of IC2 is 25mV above that of pin 3.

The unit is now set and ready for use, and should activate the alarm if the sensor is temporarily placed in a box and exposed to a modest concentration of gas (such as a brief squirt of butane gas) for half a minute or so. Note that most flammable gases are heavier than air, and that in normal domestic situations, the gas sensor should thus be mounted a few inches above floor level, in a position where it is unlikely to be damaged by passing feet or by the movement of furniture, etc.

A SOUND-ACTIVATED SWITCH CIRCUIT

Prior to the advent of modern highly-reliable PIR movement detectors, sound-activated alarms were widely used in commercial security systems. Most of these alarms were, however, easily false-triggered by the natural sounds that occur inside buildings (such as the cracks or groans that occur as a building cools at night or warms up in the morning) or that originate outside the buildings but are audible within them (such as loud traffic or aircraft noise or thunder).

In some systems, the latter problem was overcome by using internal and external sound detectors and — by using sound-level comparison techniques — only activating the alarm if the internal sounds were louder than the external ones.

Today, sound-activated alarms are rarely used in security systems, but sound-activated *switches* are widely used. They are used mainly as relay-driving 'precautionary warning' devices that switch on a security light and/or a pre-recorded 'verbal warning' message or activate a sound- or video-recorder system whenever a suspicious sound is heard in a protected area.

In most of these sound-activated switches, the sounds are picked up via a cushion-mounted electret microphone insert (which thus responds mainly to air-conducted — rather than structure-conducted — sounds) and the resulting signals are then amplified, converted to DC via a rectifier and filter, and then fed to a non-latching relay-driver via a special signal-conditioning circuit.

Figure 13 shows a practical relay-driving sound-activated switch circuit that is powered from a 12V DC supply. Here, the cushion-mounted electret microphone insert is powered from a stable 4V7 supply derived from the +12V line via zener diode ZD1, and has its output amplified by common-emitter amplifier Q1 and then passed on to the pin 3 input of the 3140 op-amp via C3-R5. The 3140 op-amp can respond to input signals all the way down to zero volts, and in this circuit is used in the open-loop voltage comparator mode and acts as a super-efficient high-gain signal rectifier that has its 'threshold' level (and thus the circuit's sensitivity) fully variable from zero to +200mV via RV1; note that diodes D1-D2 act as clamps that limit the pin 3 peak-to-peak signal amplitudes to safe values, and *must* be germanium or Schottky (rather than silicon) signal diodes.

In *Figure 13*, D3-R8-C4-R9, and R10 act as the unit's special relay-driving signal-conditioning circuitry. Here, D3 and C4 peak-detect the pin 6 output voltage of the 3140 op-amp, and C4's resulting charge provides base drive to relay-driving common-emitter amplifier Q2.

Note that C4's 'charge' time (which protects the circuit against activation by brief noise transients) is controlled by R8, and its 'discharge' time (which ensures that

TELEPHONE LISTENING DEVICE WITH 12 HR. RECORDER

FCC Approved



Record telephone conversations in your office or home. Starts automatically when phone is answered, records both sides of phone conversation. Recorder stops when phone is hung up. $99.95 + $7 shipping. For telehone listening device separately $19.95 + $2 ship.

For comprehensive 50 page catalog of Micro Video, VHF transmitters,Surveillance, and Counter-surveillance and much more! Send $3.00

Call 407-725-1000

USI CORP

P.O. Box N2052 Melbourne,FL 32902

COD'S OK

PIC'n Books

LEARN ABOUT PIC16/17 MICROCONTROLLERS

EASY PIC'n
Beginner

- Programming techniques
  - Instruction set
  - Addressing modes
  - Bit manipulation
  - Subroutines
  - Sequencing
  - Lookup tables
  - Interrupts
- Using a text editor - source code
- Using an assembler
- Timing and counting
- Interfacing - I/O conversion
- Lots of examples

$29.95

PIC'n Up The Pace
Intermediate

- Serial communication
  - PIC16 to peripheral chips
  - PIC16 to PIC16
- Serial EEPROMS
- LCD interface
- Scanning keypads
- D/A conversion
- Sensors - analog voltage output
- A/D conversion
- Math routines
- Decimal interface
- PIC16F84 EEPROM data memory
- Lots of circuits and code

$34.95

+ $4 s/h in US for one book, $5 both books
VISA, MC, AMEX, MO, Check
CA residents please add 7.25% CA sales tax
PIC is a trademark of Microchip Technology Inc.

SQUARE 1 ELECTRONICS

P.O. Box 501, Kelseyville, CA 95451
Voice (707) 279-8881 FAX (707) 279-8883
http://www.sq-1.com
E-Mail sqone@pacific.net

Write in 118 on Reader Service Card.



Figure 16. Relay-output proximity-activated alarm circuit.



Figure 17. 'Hum-detecting' touch-activated relay switch.

— once they have been triggered on — Q2 and RLA only turn off again when all noise trigger signals has been absent for a few seconds) is controlled by R9, and that these components provide the circuit with good immunity to false-triggering and relay-chatter problems.

To set up the *Figure 13* circuit, connect an analog DC voltmeter between pins 6 and 4 of the 3140 op-amp, then trim RV1 so that the meter reading is zero at low sound input levels, but rises high enough to activate Q1 and RLA at the desired 'trigger' sound-amplitude level.

POWER-FAILURE ALARM CIRCUITS

Electrical power-failure alarms can be made to activate when AC power is removed from a deep-freeze unit, or when a burglar deliberately cuts the AC power lines, or when a machine overloads and blows its fuses. *Figure 14* shows a very simple relay-output power failure alarm that can activate any type of external alarm device via the relay's contacts.

Here, the power-line input is applied to a step-down transformer that gives an output of 12V at 100mA. This output is half-wave rectified by D1 and smoothed by C1, and the resulting DC directly powers the coil of relay RLA, which has a coil resistance of 220R or greater. RLA has one or more sets of n.c. change-over contacts that can be used to activate an external alarm device.

Thus, when AC power is applied to the *Figure 14* circuit, the relay is driven on and contacts RLA/1 are open, and the alarm is thus off; the circuit typically consumes about 820mW from the AC power lines under this condition. When AC power is removed from the circuit, the relay turns off and its RLA/1 contacts close, thus activating the external alarm.

Figure 15 shows a power-failure alarm that produces an output in a ready-built piezo siren unit. Here, when AC power is applied to the circuit, the AC input is stepped down to 12V by T1 and is rectified and smoothed by D1 and C1, and roughly 12V DC is developed on the D1-D2 and D2-D3 junctions, and LED1 is illuminated via R1.

Under this condition, Q1 is driven to saturation via R2, and Q1's collector pulls the R4-R5 junction down to near-zero volts; consequently, zero base drive is applied to Q2, so the piezo alarm is off and no current is drawn from the 9V battery.

When AC power is removed from the circuit's input, R1-LED1 rapidly discharge C1, and the D1-D2 junction quickly falls to zero volts and Q1 turns off. Under this condition, current reaches Q2's base from the 9V battery via D3-R4-R5, and Q2 and the siren thus turn on.

Note that the *Figure 15* circuit can, if desired, be used with higher battery and T1-secondary voltages, provided that the resulting V1 voltage is at least 2V greater than V2 (the battery voltage).

A PROXIMITY-ACTIVATED 'ALARM' CIRCUIT

A proximity-activated alarm is a circuit that activates when a person or large object touches or comes close to a sensing antenna. The antenna may simply consist of a length or loop of wire, or may be a metal object (such as a sheet of foil or wire mesh hidden under a carpet, a safe, or a storage cabinet) that is connected to one end of a wire antenna.

Most proximity-activated alarm circuits work on the capacitive loading principle, in which the gain of an L-C oscillator is adjusted to a critical point at which oscillation is barely sustained and, in which, the antenna forms part of the oscillator's tank circuit and, in which, the circuit's 0V supply line is grounded.

Consequently, any increase in the antenna-to-ground capacitance, such as is caused by touching or nearing the antenna, causes enough damping of the tank circuit to bring the oscillator gain below the critical level, and the oscillator ceases to operate. This cessation of oscillation is then used to make the alarm generator activate.

Figure 16 shows a practical relay-output proximity-activated alarm circuit that uses the above operating principle. Here, transistor Q1 is wired as a Colpitts oscillator, with gain adjustable via RV1, and the antenna is coupled to Q1 base via C5. The output of this oscillator, which operates at about 300KHz, is made available at a low impedance level across R4 via emitter-follower Q2.

This signal is rectified and smoothed via the C1-D1-D2-R6-C7 network, to produce a positive bias that is applied to the base of Q3 via R7. Q3 is wired as a common-emitter amplifier, with R8 as its collector load, and Q4 is wired as a common-emitter amplifier with the relay coil used as its collector load and with Q4's base connected directly to the collector of Q3.

Thus, when the *Figure 16* circuit is operating normally, the oscillator output produces a positive bias voltage that drives Q3 to saturation and thus removes Q4's base drive; Q4 and the relay are thus off under this condition. When the circuit's antenna is touched or externally loaded, however, the oscillator ceases to operate, thus removing Q3's base drive; Q3 thus turns off; with Q3 off, Q4 is driven to saturation via R8, and the relay is thus driven on under this condition.

Note that the Q1-Q2 section of the circuit is powered via a 6.2V regulated supply formed by R5 and ZD1, thus enhancing the oscillator's stability. Also note that D1 and D2 must be germanium or Schottky signal diodes, and that the circuit can — if desired — be used to give a directly-driven 'siren' output (via a ready-built piezo alarm module) by simply using the siren module in place of RLA and removing D3 from the circuit.

To set up the *Figure 16* circuit,

Remote I/O Control

Model HCON-1

The prefect solution for
Home Automation
Temperature Monitor/Control
Remote Relay Control
Remote Equipment Control

Only $119.00 plus shipping

RS-485 Full Duplex Communication
Up to 32 Devices Per Channel
Simple ACSII Command Set
1 to 20 Switch Input
20 Relay/LED Output 35ma
Quadrature Encoder Inputs
1-Wire Temperature Inputs
Dallas DS1820/21 Support
Input Power 8-15VDC
Small Size 1.9 X 2.8 Inches

J-Works, Inc
12328 Gladstone St., Unit 4
Sylmar, CA 91342
(818) 361-0787 Voice (818) 270-2413 Fax

Visit our Web site at
http://www.j-works.com
E-mail sales@ j-works.com

Write in 119 on Reader Service Card.

BUY • SELL • CONSIGN

WANTED
- Electronic Test Equipment
- Electronics Inventory
- Scientific Equipment
- Mfg. Shop Equip.
- Data/Telco
- Memory

DEXIS
9749 Hamilton Road
Eden Prairie, MN 55344

We Sell Nationwide!
Call our Fax-On-Demand System, or our Internet site for current availability.
Visit our 25,000 sq. ft.showroom warehouse
M-F 9 to 6; Sat 9 to 5

PHONE: (612) 944-7670
INTERNET: WWW.GO2DEXIS.COM
FAX: (612)942-9712 • FAX-ON-DEMAND: 1-800-547-4636 X 300

Write in 120 on Reader Service Card.



Figure 18. Ultrasonic beam transmitter module.



Figure 19. Relay-output ultrasonic beam receiver module.

simply connect a suitable antenna, trim RV1 so that the relay turns on, then back RV1 off slightly so that the relay just turns off again. Check that the relay turns on again if the antenna is touched or closely approached, and goes off again if the touch is removed; if necessary, trim RV1 for maximum sensitivity.

The final sensitivity of the *Figure 16* circuit depends on the setting of RV1 and on the size and type of antenna used. If the antenna is very small, such as a short length of wire, the circuit will act as little more than a touch alarm, but if the antenna is a large sheet of metal foil or wire mesh, the circuit may be sensitive enough to activate when a person approaches within a foot or two of the antenna.

It pays to experiment with different types of antenna, to get the 'feel' of the circuit. Remember, however, that the antenna must be well isolated from ground, and that the circuit's 0V rail must be wired to an effective ground connection.

A TOUCH-ACTIVATED CIRCUIT

Touch-activated circuits are intended to perform some kind of switching action when a person touches a fixed (rather than flexible or mobile) contact point, such as one or more metal studs. The best circuits of this type work on either the capacitive loading principle described in the preceding section of this article or, if they are designed for use only in the general vicinity of AC power lines, are activated by the power-line radiated AC 'hum' that is picked up by an electrical contact when touched by a human finger. *Figure 17* shows a practical circuit of the latter type.

The *Figure 17* 'hum-detecting' circuit activates relay RLA when a finger touches a single metal stud or contact point, and is designed around a CMOS 4001B quad two-input NOR gate IC and transistor Q1. Here, gate IC1a is wired as a simple pulse-inverting amplifier and has its high-impedance input terminal taken to the metal touch contact via R2; the contact is biased high via R1, and IC1a's output is thus normally low.

When a human finger touches the circuit's contact terminal, its induced AC 'hum' signal reaches IC1a's input, is amplified and inverted, and appears as a large amplitude squarewave at IC1a's output. This squarewave is rectified and smoothed via D1-C1-R3, is buffered by gates IC1b-IC1c (which act together as a non-inverting buffer), and then drives relay RLA on via R5 and Q1.

Note when using the *Figure 17* circuit that its 12V supply must be derived (via an isolating transformer) from the AC power lines, that the 0V supply rail must be grounded, that the relay's contacts can be used to activate external circuitry or alarms, etc., and that the circuit consumes a quiescent current of only 1µA or so.

The circuit's touch contact should not be larger than about 10 square centimeters (to avoid unwanted pick-up); if the contact is more than a few inches from IC1a's input terminal, the connecting leads may have to be screened to avoid unwanted pick-up.

AN ULTRASONIC 'BEAM' ALARM UNIT

This unit can be used in the same type of application as an IR light-beam alarm, but works on ultrasonic principles. It consists of an ultrasonic transmitter (Tx), operating at about 40KHz, which is aimed at a matching relay-driving ultrasonic receiver (Rx) unit. When an ultrasonic link exists between the Tx and Rx, the relay is off, but when the link is broken the relay turns on and activates an external alarm or some other electrical or electronic device. This particular unit is a very simple design, with a maximum operating range of only a few yards; it can be used to give security protection to passages and open doorways, etc.

The unit makes use of a modestly priced matched pair of ultrasonic transducers of the type used in many remote-control applications. These devices are normally designed to operate at about 40KHz, and consist of a dedicated Tx transducer and a matching dedicated Rx transducer. Devices of this type are readily available from major electronic component suppliers.

Figure 18 shows the circuit of the unit's transmitter module, which typically consumes an operating current of 2.5mA from a 9V supply or 3mA from a 12V supply. Here, Q1 and Q2 are configured as an emitter-coupled oscillator, with the Tx transducer used as the emitter coupling element, so that the circuit oscillates at the transducer's resonant frequency (about 40KHz) and radiates a matching ultrasonic signal.

Finally, *Figure 19* shows the circuit of the unit's receiver module. Here, the Rx transducer is pointed towards the transmitter and responds to the transmitted signal in much the same way as a directional microphone. The output of the Rx transducer is fed directly to the base of common emitter amplifier Q1, and appears in amplified form at the Q1 collector.

It is then fed, via C1, to the input of an amplifying detector stage that is built around Q2-D1 and C2. Normally, when the beam is unbroken, the output of this detector stage is high, so Q3 is driven to saturation and Q4 and the relay are cut off.

When the beam is interrupted, the output of the detector stage falls to near-zero volts, so Q3 turns off and Q4 and the relay are turned on via R7. An external alarm can be activated by the closing of the RLA/1 contacts. Thus, RLA is normally off, but turns on when the ultrasonic beam is interrupted.

The *Figure 19* circuit consumes a typical current of 5mA from a 12V supply. To set up the circuit, turn off the Tx unit, connect a DC voltmeter (with a sensitivity of at least 20KV) across C2, then trim RV1 so that the voltage just falls to near-zero; RLA should turn on under this condition. Now turn on the Tx unit, aim it at the Rx unit, and check that the C2 voltage rises to at least 2V and that RLA turns off.

If desired, RV1 can be further trimmed to obtain absolute maximum operating range. Next month's concluding episode of this series will deal with electronic security circuits designed for use in automobiles. **NV**

Miniature Transmitters and Receivers

❑ 2 Button - 3 Channel Remote Control Transmitter
❑ 59,049 Changeable Security Codes - 10 Trinary Bits
❑ Operates at 318mhz ❑ 12 Volt Battery Incl.
❑ Size - 1.25" x 2" ❑ 1 Inch Keyring

	Qty	1	5	10
RF300T	150' Range 2 Button Transmitter	24.95	20.95	16.95
RF300XT	300' Range 2 Button Transmitter	29.95	24.95	20.95

❑ 3 Channel Remote Control Receiver
❑ Input : 8-12vdc regulated or 11-24vdc unregulated
❑ Latched or Momentary Digital Outputs (x: L or M)
❑ PCB Board Size - 1.25" x 3.75"

RF300Rx	3 Channel Receiver	24.95	20.95	16.95
RF300RKx	3 Channel Receiver Kit	19.95	15.95	12.95

Visitect Inc. 510-651-1425
P.O. Box 14156 Fremont CA 94539 Fax 510-651-8454 Accept Visa, M/C, COD's
Write in 123 on Reader Service Card.

SATELLITE TV – HACKERS 'BIBLE'!

The SECRETS are REVEALED!

- The principles of security
- Descrambler building blocks
- Smart cards, information wars & stupid mistakes
- Cracking codes (includes DirecTv source code)
- Installing and hooking up descramblers
- Video manipulative systems...and much more...



CALL 800-483-2423

TO ORDER - Send $60 plus $4 s/h to:
Baylin Publications, 1905 Mariposa, Boulder, CO 80302
MASTER,VISA & AMEX /COD orders accepted

576 pages, 6" x 8-1/2"
NEW! 5th Edition

Telephone: 303-449-4551 *FAX: 303-939-8720* *E-Mail: fbaylin@baylin.com*

FREE CATALOG – Satellite TV books, videos and software
Write in 122 on Reader Service Card.

WESTERN TEST SYSTEMS

WE BUY AND SELL

Inquiries **303-438-9662** • Fax **303-438-9685**

Orders only **800-538-1493**

530 Compton St., Unit #C, Broomfield, Colorado 80020

OSCILLOSCOPES & ACCESSORIES

TO 100 MHz

TEK 7A22 1 MHz High CMRR Differential Amplifier $300.00
TEK 7B53A 100 MHz Dual Time Base $175.00
TEK SC502 15 MHz Dual Trace $375.00
Oscilloscope, TM500 series

ABOVE 100 MHz

TEK 2465 300 MHz 4-channel Oscilloscope $2,500.00
TEK 7104 1 GHz Oscilloscope, ... $4,500.00
with 7A29, 7A29-04, 7B10, 7B15
TEK 7844 400 MHz Dual Beam Oscilloscope frame $600.00
TEK 7844 400 MHz Dual Beam Oscilloscope $1,000.00
with 7A24,7A26,7B80,7B85
TEK 7904A 500 MHz System, ... $1,250.00
with 7A24, 7A26, 7B80, 7B85
TEK 7A13 105 MHz Differential Comparator $225.00
TEK 7A19 600 MHz Single Trace Amplifier $150.00
TEK 7A24 400 MHz Dual Trace Amplifier $300.00
TEK 7A26 200 MHz Dual Trace Amplifier $175.00
TEK 7A42 4-Channel Logic $500.00
Triggered Vertical Amplifier
TEK 7B15 1 GHz Delaying Time Base $450.00
TEK 7B80 400 MHz Delayed Time Base $175.00
TEK 7B85 400 MHz Delta Delaying Time Base $175.00
TEK 7B92A 500 MHz Dual Time Base $275.00
TEK 7633 100 MHz Storage Oscilloscope frame $600.00

STORAGE

TEK 7633 100 MHz Storage $900.00
Oscilloscope with (2) 7A26, (1) 7B92A

PROBES

HP 1122A Probe Power Supply $150.00
TEK 1101 Accessory Power Supply, for FET probes $250.00
TEK P6046 100 MHz Differential Probe $750.00
TEK P6133 150 MHz 10X Probe $75.00
TEK P6201 900 MHz 1X/10X/100X FET Probe $450.00
TEK P6202A 500 MHz 10X FET Probe $300.00
TEK P6701-opt.02 O/E Converter, ... $375.00
450-1050 nm/0-1 mW: DC-700 MHz, ST conn.

CALIBRATION

TEK 067-0587-01 Signal Standardizer $300.00
Calibration Fixture, 7000 series
TEK SG503 Level Generator, ... $600.00
250 kHz-250 MHz, TM500 series

WAVEFORM GENERATORS

FUNCTION

HP 3310B 5 MHz Function Generator, ... $325.00
monocycle & var.phase trigger
HP 3312A 13 MHz Function Generator $650.00
HP 3325A 21 MHz Synthesized $1,650.00
Function Generator, HPIB
HP 3325A-002 21 MHz Function $1,750.00
Generator, high voltage output option
HP 8165A-002,003 Prog. Signal Source, ... $2,000.00
1 mHz-50 MHz, log sweep, rear out
TEK AWG5102 Arb.Waveform Gen., ... $900.00
20 MS/s,12 bits,50ppm synthesis <1MHz
TEK AWG5105-opt.02 Arbitrary Waveform $1,250.00
Generator, dual channel option
TEK DD501 Digital Delay & Burst Gen., ... $275.00
for function & pulse gen's
TEK FG501 1 MHz Function Generator, TM500 series $225.00
TEK FG502 11 MHz Function Generator $300.00
TEK FG503 3 MHz Function Generator, TM500 series $250.00
TEK RG501 Ramp Generator, TM500 series $225.00
WAVETEK 288 20 MHz Synthesized $750.00
Function Generator, GPIB

PULSE

BERKELEY NUCLEONICS 7085B $750.00
Digital Delay Generator, 0-100 mS, 1 nS res.,5 Hz-5 MHz
HP 214B-001 10 MHz Pulse Generator, ... $1,750.00
50 V/50 ohms, counted burst opt
HP 8007B 100 MHz Pulse Generator $650.00
HP 8012B 50 MHz Pulse Generator, ... $600.00
variable transition time
HP 8080A/81A/83A/84A 300 MHz Word Generator $800.00
HP 8080A/91A/92A/93A 1 GHz Single $950.00
Channel Pulse Generator
HP 8111A 20 MHz Pulse / Function Generator $1,500.00
HP 8115A 50 MHz Dual $3,500.00
Channel Pulse Generator, HPIB
TEK PG502 250 MHz Pulse Generator, ... $600.00
Tr<1nS, TM500 series
TEK PG505 100 kHz Pulse Generator, ... $275.00
80 V peak, TM500 series
TEK PG508 50 MHz Pulse $500.00
Generator, TM500 series
WAVETEK 802 50 MHz Pulse Generator $300.00

VOLTAGE & CURRENT

VOLTMETERS

FLUKE 845AR High Impedance $500.00
Voltmeter / Null Detector
HP 3456A 6-1/2 Digit Voltmeter $750.00
HP 3478A 5-1/2 digit Multimeter, HPIB $700.00
KEITHLEY 181 6-1/2 digit $900.00
Nanovoltmeter, 10 nV sensitivity, GPIB
SOLARTRON 7081 8-1/2 digit Voltmeter $3,900.00
TEK DM501A 4-1/2 digit Multimeter, ... $225.00
TM500 series plug-in

CALIBRATION

FLUKE 510A AC Reference Standard, ... $450.00
10 VRMS, 0-10 mA
FLUKE 515A Portable Calibrator, ... $1,000.00
DC/AC/Ohms, line & battery power
FLUKE 5220A Transconductance $3,000.00
Amplifier, DC-5 kHz, 0-20 A
FLUKE 720A 7-decade Kelvin-Varley Voltage Divider $1,250.00
FLUKE 731B DC Reference Standard $350.00
FLUKE 732A DC Voltage Standard $2,000.00
HOLT 11 AC Thermal Converter Set, ... $3,000.00
0.5-1200 V, 20 Hz-30 MHz
VALHALLA 2703 AC Volt.Std.,0-120V/ $2,250.00
10 Hz-100 kHz;120-1200V/10 Hz-1 kHz

VOLTAGE SOURCES

HP 6115A Precision Dual Range Power $850.00
Supply, 50V 0.8A / 100V 0.4A
KEITHLEY 228 Programmable Voltage/Current Source $2,500.00

CURRENT METERS & SOURCES

HP 4140B Picoammeter / DC Voltage $2,000.00
Source, without test fixture
HP 6177C DC Current Source, to 50V, 500mA $500.00
HP 6181C DC Current Source, to 100 V, 250 mA $500.00
HP 6186C DC Current Source, to 300V, 100mA $750.00
KEITHLEY 220 Programmable Current Iim $2,000.00
Source, 0.5 pA-101 mA, 1-105 V
KEITHLEY 225 Current Source, ... $500.00
0.1 uA-100 mA, 10-100 V compliance
KEITHLEY 227 Current Source, ... $800.00
1 uA-1 A, 0-50 V compliance
KEITHLEY 261 Picoampere Source $375.00
KEITHLEY 614 Electrometer $800.00
KEITHLEY 642 Electrometer $2,900.00
TEK A6303 Current Probe, DC-15 MHz, ... $1,000.00
100 A max.,for use with AM503
TEK AM503/A6302/TM501 AC/DC Current Probe System $1,000.00
TEK CT-5 -opt.05 High Current Transformer $300.00
for P6021/A6302, to 1000A

IMPEDANCE & COMPONENT TEST

L.C.R.

BOONTON 62AD 1 MHz Inductance $550.00
Meter, 2-2000 uH
BOONTON 72BD 1 MHz Capacitance $650.00
Meter, 3-1/2 digit display
HP 4262A-101 3-1/2 digit LCR Meter, ... $2,250.00
120 Hz/ 1 kHz/ 10 kHz test, HPIB
HP 4275A-001 5-1/2 digit LCR Meter, ... $5,000.00
10 kHz-10 MHz, 0-35 V int. bias

STANDARDS

E.S.I. DB62-11K 6-Decade Resistor, ... $300.00
0-11,111.10 Ohms, 0.01 Ohm res.
E.S.I. SR1010 Resistance Transfer $550.00
Standards, 1 Ohm-100 K/step
E.S.I. SR1050-1M Resistance Transfer $2,000.00
Standard, 1 Megohm/step
GR 1404-A 1000 pF Reference Standard Capacitor $700.00
GR 1406 Standard Air Capacitors, ... $375.00
GR900 connector, 0.1% acc.
GR 1412-BC Decade Capacitor, 50 pF - 1.11115 uF $350.00
GR 1432-U 4-Decade Resistor, ... $125.00
0-111.10 Ohms, 0.01 Ohm resolution
GR 1433-J 4-Decade Resistor, ... $250.00
0-11,110 Ohms, 1 Ohm resolution
GR 1433-K 4-Decade Resistor, ... $250.00
0-1,110 Ohms, 0.1 Ohm resolution
GR 1433-L 4-Decade Resistor, 0-111, ... $250.00
100 Ohms, 10 Ohms resolution
GR 1433-N 5-Decade Resistor, 0-11, ... $300.00
111 Ohms, 0.1 Ohm resolution
GR 1433-U 4-Decade Resistor, ... $250.00
0-111.0 Ohms, 0.01 Ohm resolution
GR 1433-X 6-Decade Resistor, to 111, ... $350.00
111.0 Ohms, 0.1 Ohm res.
GR 1482-series Standard Inductors $275.00
VALHALLA 2724A Programmable $1,675.00
Resistance Standard, 0-11 Gigaohms, GPIB

HI & LO RESISTANCE

GR 1666 DC Resistance Bridge, ... $600.00
1 Micro-Ohm - 100 Kilohms
HP 4328A Milliohmeter $1,300.00
HP 4329A High Resistance Meter $1,200.00

CURVE TRACERS

TEK 577D1/177 Storage Curve Tracer, ... $2,250.00
with standard test fixture
TEK 577D2/177 Curve Tracer, ... $1,850.00
with standard test fixture

T.D.R.

TEK 1502-opt.04 Time Domain $1,400.00
Reflectometer, 0-2,000 feet, chart recorder
TEK 1503-opt.04 Time Domain Reflectometer, ... $1,400.00
0-50,000 feet,chart recorder

POWER SUPPLIES

SINGLE OUTPUT

HP 6002A-001 0-60 V/ 0-10 A/ 200 Watts max. $750.00
Autoranging Power Supply
HP 6200B Dual Range Supply, ... $200.00
0-20 V 0-1.5 A/ 0-40 V 0-750 mA CVCC
HP 6201B 0-20 V 0-1.5 A CV/CC Power Supply $175.00
HP 6207B 0-160 V 0-200 mA CV/CC Power Supply $300.00
HP 6256B 0-10 V 0-20 A CV/CC Power Supply $300.00
HP 6260B-027 0-10 V 0-100 A CV/CC $675.00
Power Supply; 208 VAC line
HP 6261B-027 0-20 V 0-50 A CV/CC $675.00
Power Supply; 208 VAC line
HP 6263B 0-20 V 0-10 A CV/CC Power Supply $400.00
HP 6266B 0-40 V 0-5 A CV/CC Power Supply $400.00
HP 6269B-028 0-40 V 0-50 A CV/CC $950.00
Power Supply; 230 VAC line
HP 6271B 0-60 V 0-3 A CV/CC Power Supply $400.00
HP 6274B 0-60 V 0-15 A CV/CC Power Supply $900.00
HP 6281A 0-7.5 V 0-5 A CV/CC Power Supply $175.00
HP 6284A 0-20 V 0-3 A CV/CC Power Supply $225.00
HP 6299A 0-100 V 0-750 mA CV/CC Power Supply $225.00
HP 6384A 4.0-5.5 V at 8 A CV/CL Power Supply $125.00
HP 6443B 0-120 V 0-2.5 A CV/CC Power Supply $450.00
KEPCO ATE 36-30M 0-36 V $900.00
0-30 A CV/CC Power Supply
KEPCO ATE 36-8M 0-36 V 0-8 A CV/CC Power Supply $375.00
SORENSEN DCR 20-25B 0-20 V $550.00
0-25 A CV/CC Power Supply
SORENSON DCR 600-0.75B 0-600 V $600.00
0-750 mA CV/CC Power Supply
SORENSON SRL 20-12 0-20 V $400.00
0-12 A CV/CC Power Supply
SORENSON SRL 60-8 0-60 V $600.00
0-8 A CV/CC Power Supply
TEK PS501-1 Power Supply, 0-20 V, ... $175.00
2 mV res., 400 mA, TM500 series

MULTIPLE OUTPUT

HP 6227B Dual 0-25 V 0-2 A CV/CC Power Supply $600.00
HP 6228B Dual 0-50 V 0-1 A CV/CC Power Supply $600.00
HP 6253A Dual 0-20 V 0-3 A CV/CC Power Supply $500.00
HP 6255A Dual 0-40 V 0-1.5 A CV/CC Power Supply $500.00
TEK PS5010 Programmable Triple $750.00
Power Supply, TM5000 series
TEK PS503A Dual Power Supply, TM500 series $200.00

MISCELLANEOUS

ACME PS2L-500 Programmable Load, ... $400.00
0-75 V / 0-75 A / 500 Watts max.
ELGAR 1751B/461 AC Power Source, ... $2,000.00
0-135 VAC, 1750 Watts, fixed freq.osc.
HP 59501B HPIB Isolated $175.00
DAC/Power Supply Programmer
HP 6825A Bipolar Power Supply/ Amplifier, +/- 20 V 2 A $800.00
KEPCO BOP 50-2M Bipolar $400.00
Op Amp/Power Supply, to 50 V 2 A
TRANSISTOR DEVICES DAL-50-15-100 ..... $200.00
Programmable Load, 0-50 V, 0-15 A, 100 Watts max.

TIME & FREQUENCY

UNIVERSAL COUNTERS

HP 5315A 100 MHz/100 nS Universal Counter $450.00
HP 5315A-002,003 100 MHz/100 nS $650.00
Univ. Counter, battery power, 1 GHz C-ch
HP 5315B 100 MHz/ 100 nS Universal Counter $500.00
HP 5316A 100 MHz/100 nS Universal Counter, HPIB $600.00
HP 5316A-001,003 100 MHz/ 100 nS $750.00
Univ. Counter, HPIB, TCXO, 1 GHz C-ch.
HP 5316B 100 MHz/ 100 nS Universal Counter, HPIB $1,000.00
HP 5334A 100 MHz Universal Counter, HPIB $850.00
HP 5334A-010,030,050 100 MHz $1,000.00
Univ.Counter; OCXO, DVM, 1.3 GHz C-ch., rear in
HP 5334B-010,060 100 MHz $1,000.00
Universal Counter, HPIB, OCXO
HP 5335A 200 MHz Universal / Statistical Counter $1,200.00
PHILIPS PM6665/431 120 MHz/ 100 nS $600.00
Universal Counter, 1.3 GHz C-ch., TCXO
TEK DC5004 Programmable $250.00
100 MHz/100nS Counter/Timer, TM5000 series
TEK DC5009 Programmable 135 MHz Univ. $400.00
Counter/Timer, TM5000 series
TEK DC5010 350 MHz / 3.125 nS $1,200.00
Universal Counter, TM5000 series

FREQUENCY COUNTERS

EIP 575 18 GHz Source Locking Counter, GPIB $2,500.00
EIP 578-opt.02,05 26.5 GHz Source $4,000.00
Locking Counter; power meas., OCXO
HP 5340A 18 GHz Frequency Counter $1,000.00
HP 5342A 18 GHz Frequency Counter $2,000.00
HP 5342A-001 18 GHz Frequency $2,200.00
Counter, OCXO reference
HP 5342A-001,011 18 GHz Frequency $2,400.00
Counter, OCXO reference & HPIB
HP 5342A-003 18 GHz Freq.Counter, ... $2,000.00
+22 dBm,-20 dBm dynamic range
HP 5342A-01,04,05 24 GHz $3,250.00
Frequency Counter, OCXO, DAC
HP 5343A-001 26.5 GHz Frequency $4,500.00
Counter, OCXO reference
HP 5345A/5355A/5356B 26.5 GHz $4,000.00
CW/Pulse Frequency Counter
TEK DP501 1.3 GHz Prescaler, ... $225.00
divide by 16, TM500 series

STANDARDS

HP 105A Quartz Oscillator, 0.1/ 1.0/ 5.0 MHz $750.00
HP 105B Quartz Oscillator, ... $1,500.00
0.1/ 1.0/ 5.0 MHz, battery power
HP 5087A-opt.033 Distribution $1,750.00
Amplifier; 12 outputs at 10 MHz

AUDIO & BASEBAND

SPECTRUM ANALYSIS

HP 3586C Selective Level Meter, ... $1,500.00
50 Hz-32.5 MHz, 50 & 75 ohms

Write in 77 on Reader Service Card.

VISA

90 DAY WARRANTY PARTS AND LABOR • 10 DAY INSPECTION
TEST EQUIPMENT WANTED CALL OR FAX LIST • OPEN ACCOUNTS

MasterCard

TEK 7L5/L3/R7603 Spectrum Analyzer, ... $1,500.00
20 Hz-5 MHz, 10 Hz min. res.,w/frame

DISTORTION ANALYZERS

HP 339A Distortion Analyzer, built-in low distortion osc. $1,250.00
HP 8903A-001 Audio Analyzer, ... $2,600.00
20 Hz-100 kHz; rear panel input
HP 8903B-001,013,051 Audio Analyzer, ... $3,500.00
20 Hz-100 kHz; C-message, CCITT
TEK DA4084 Programmable Distortion Analyzer $1,000.00

RMS VOLTMETERS

FLUKE 8920A True RMS Voltmeter, ... $500.00
180 uV-700 V, 10 Hz-20 MHz
FLUKE 8922A True RMS Voltmeter, ... $500.00
180 uV-700 V, 2 Hz-11 MHz

OSCILLATORS

HP 204C Oscillator, 5 Hz-1.2 MHz, 5 VRMS $150.00
HP 209A Sine/Square Wave Generator, ... $225.00
4 Hz-2 MHz, 5 VRMS max.
TEK SG5010 Programmable Oscillator, ... $2,750.00
10 Hz-163.8 kHz
TEK SG502 Sine/Square Osc., ... $200.00
5 Hz-500 kHz, 70 dB step atten.,TM500

MISCELLANEOUS

HP 3575A-001 Phase-Gain Meter, ... $850.00
1 Hz-13 MHz, dual display option
HP 4437A Step Attenuator, 0-119.9 dB, ... $175.00
DC-1 MHz, 600 ohms unbal.
HP 461A Amplifier, 20/40 dB, ... $125.00
1 kHz-150 MHz, 0.5 V/50 Ohms
KROHN-HITE 3103 High/Low Pass Filter, ... $400.00
10 Hz-3 MHz, 24 dB/octave
KROHN-HITE 3202 Dual HP/LP/BP/BR $500.00
Filter, 20 Hz-2 MHz, 24 dB/octave
KROHN-HITE 3342R Dual HP/LP Filter, ... $1,100.00
0.001 Hz-99.9 kHz, 48 dB/octave
KROHN-HITE 3750 LP/HP/BP/BR Filter, ... $700.00
0.02 Hz-20 kHz, 6/12/18/24 dB/oct.
ROCKLAND 852 Dual Highpass/ $1,000.00
Lowpass Filter, 0.1 Hz-111 kHz
TEK AF501 Tunable Bandpass Filter / $300.00
Amplifier, 3 Hz-35 kHz
TEK AM502 Differential Amplifier, ... $475.00
0.1 Hz-1 MHz, TM500 series

RF & MICROWAVE

SPECTRUM ANALYZERS

HP 11517A/19A/20A Mixer Set, ... $600.00
18.0-40.0 GHz, for HP 8555A/8569A
HP 11970A WR28 Harmonic Mixer, 26.5-40 GHz $1,100.00
HP 11970K WR42 Harmonic Mixer, 18.0-26.5 GHz $1,100.00
HP 11970Q WR22 Harmonic Mixer, 33-50 GHz $1,400.00
HP 11970U WR19 Harmonic Mixer, 40-60 GHz $1,400.00
HP 8444A-059 Tracking Generator, ... $1,250.00
0.5-1500 MHz, for 8554,8568,etc.
HP 8445B Preselector, 1.8-18.0 GHz, for HP 8555A $650.00
HP 8565A-100 Spectrum Analyzer, ... $4,500.00
10 MHz-22 GHz, 100 Hz min. res.
HP 8566B Spectrum An., 100 Hz-22 GHz, ... $37,500.00
HP calibration certificate
HP 8569B Spectrum Analyzer, ... $7,500.00
10 MHz-22 GHz, 100 Hz min.res.bw.
TEK 7L14/7603 Spectrum Analyzer, ... $2,250.00
10 kHz-1.8 GHz, 30 Hz min. res. bw.
TEK TR503 Tracking Generator, ... $1,000.00
0.1-1800 MHz, for 492/4/5/6
TEK WM782V WR15 Harmonic Mixer, 50-75 GHz $1,500.00

NETWORK ANALYZERS

HP 3577A/35677A/35678A Network $12,500.00
Analyzer, 5 Hz-200 MHz, w/S-Parameter & Cal.Kit
HP 85021C Directional Bridge, ... $1,000.00
0.01-18 GHz, 33 dB dir,for 8755/6/7
HP 8756A Scalar Network Analyzer $2,500.00

SIGNAL GENERATORS

FLUKE 6060A Synthesized Signal Gen., ... $2,750.00
0.1-1050 MHz, 10 Hz res., GPIB
FLUKE 6060A/AN Synthesized Signal Gen., ... $1,750.00
10 kHz-520 MHz, 10 Hz res.,GPIB
GIGATRONICS 600/10-18 Synthesized $3,000.00
Source, 10-18 GHz, 1 kHz res., GPIB
GIGATRONICS 875/50 Levelled $2,500.00
Multiplier, x4, 50.0-75.0 GHz output, -3 dBm
GIGATRONICS 875/86 Levelled Multiplier, ... $3,750.00
26.5-40.0 & 50.0-75.0 GHz outputs
GIGATRONICS 900/2-8 Synthesized $3,000.00
Signal/Sweep Gen., 2-8 GHz, 1 kHz res.,GPIB
HP 11720A Pulse Modulator, 2-18 GHz, 80 dB on/off ratio $750.00
HP 85100V Frequency Mult., ... $4,250.00
10-15 GHz in / 50-75 GHz out >0 dBm
HP 8640B-001,002 Signal Gen., ... $1,750.00
0.5-1024 MHz, AM, FM, var. audio osc.
HP 8656A Synthesized Signal Gen., ... $2,500.00
0.1-990 MHz, 100 Hz res., HPIB
HP 8660C/86602B-002 Synth. Sig. Gen., ... $3,250.00
1-1300 MHz, FM / Phase mod. w/86635A
HP 8660C/86603A-002 Synthesizer, ... $4,500.00
1-2600 MHz, FM / Phase Mod., w/86635A

SWEEP GENERATORS

HP 8350B/83592B-002 Sweep Generator, ... $14,500.00
10 MHz-20 GHz, 70 dB step attenuator
HP 8601A Generator/Sweeper, ... $400.00
0.1-110 MHz, +20 dBm levelled
HP 8620C Sweep Oscillator Frame $550.00
HP 8620C-011 Sweep Oscillator Frame, ... $675.00
HPIB programmable
HP 86222B-002 RF Plug-in, 10-2400 MHz, ... $1,500.00
+13 dBm levelled, 70 dB atten.
HP 86230B RF Plug-in, 1.8-4.2 GHz, ... $500.00
+10 dBm unlevelled
HP 86235A-001,002 RF Plug-in, ... $600.00
1.7-4.3 GHz, +14 dBm levelled, 70 dB atten.
HP 86240C RF Plug-in, 3.6-8.6 GHz, +16 dBm levelled $700.00
HP 86241A-001 RF Plug-in, ... $300.00
3.2-6.5 GHz, +8 dBm levelled
HP 86242D-004,008 RF Plug-In, ... $300.00
5.9-9.0 GHz, +10 dBm levelled
HP 86250D RF Plug-in, 8.0-12.4 GHz, ... $500.00
+10 dBm levelled
HP 86260A RF Plug-in, 12.0-18.0 GHz, ... $500.00
+10 dBm unlevelled
HP 86260A-H04 RF Plug-in, ... $500.00
10.0-15.0 GHz, +10 dBm unlevelled
HP 86290A RF Plug-in, 2.0-18.0 GHz, +7 dBm levelled $1,750.00
HP 86290B RF Plug-in, 2.0-18.6 GHz, +10 dBm levelled $2,000.00
WAVETEK 962 Sweep Generator, ... $1,500.00
1.0-4.0 GHz, markers, +12 dBm unlvld.
WILTRON 6619A Sweep Generator, ... $1,500.00
2-8 GHz, +10 dBm levelled

POWER METERS

ANRITSU MA72B Power Sensor, ... $300.00
-20 to +20 dBm, 0.01-18 GHz
ANRITSU MP-81B/ML-83A Power Meter, ... $2,500.00
75-110 GHz (WR10), -20 to +20 dBm
BIRD 4410A/4410-1 Wattmeter, ... $350.00
with 200-535 kHz 10 W-10 kW element
BOONTON 4200-01A,03/&-4A x2 Dual $1,500.00
Channel Microwattmeter, w/(2) 1 MHz-7 GHz sensors
BOONTON 42B/41-4B Analog Power $375.00
Meter, with 1 MHz-12 GHz sensor
BOONTON 42B/41-4E Analog Power $500.00
Meter, with 1 MHz-18 GHz sensor
GENERAL MICROWAVE 476/4240A $300.00
Power Meter & Sensor, 0.01-18 GHz, -35 to +10 dBm
HP 435A/8481A Power Meter, ... $900.00
10 MHz-18 GHz, -30 to +20 dBm
HP 435A/8482H Power Meter, ... $950.00
0.1-4200 MHz, -10 to +34 dBm
HP 435B-001/8482H Power Meter, ... $1,200.00
0.1-4200 MHz, AC or battery power
HP 8477A Power Meter Calibrator, for HP 432 series $500.00
HP K486A WR42 Thermistor Mount, ... $350.00
18.0-26.5 GHz, for 432 series
HP Q8486A Power Sensor, ... $1,500.00
33.0-50.0 GHz, WR22, for 435/6/7/8
HP R486A WR28 Thermistor Mount, ... $350.00
26.5-40 GHz, for 432 series
HP R8486A WR28 Power Sensor, ... $1,500.00
-30 to +20 dBm, 26.5-40 GHz

RF MILLIVOLTMETERS

RACAL 9303 TRMS Level Meter, ... $875.00
10 kHz-2 GHz, -77 to +23 dBm, GPIB

AMPLIFIERS, MISCELLANEOUS

BOONTON 82AD-opt.01A Modulation $900.00
Meter, AM, FM, 10-1200 MHz, GPIB
HP 11715A AM/FM Test Source $1,600.00
HP 415E SWR Meter $300.00
HP 465A Amplifier, 20/40 dB, ... $125.00
5 Hz-1 MHz, 1/2 Watt/50 Ohms
HP 8447E Amplifier, 22 dB, ... $750.00
0.1-1300 MHz, +13 dBm output
HP 8447F Preamplifier / Power Amplifier, 0.1-1300 MHz $1,200.00
HP 8901A Modulation Analyzer, 150 kHz-1300 MHz $3,000.00
HP 8901B-1,2,3 Modulation An., ... $4,000.00
0.15-1300 MHz, rear input, OCXO, ext.LO
HP 8970A Noise Figure Meter $5,000.00
HUGHES 1177H02F000 TWT Amplifier, ... $1,500.00
4.0-8.0 GHz, 10 Watts output
MICROWAVE SEMI.CORP. MC5112 ..... $275.00
Noise Source, 25.5 dB ENR, 1.0-12.4 GHz, N(m), +28 VDC
ROHDE & SCHWARTZ ESH2 ..... $5,000.00
Test Receiver, 9 kHz-30 MHz

COAXIAL & WAVEGUIDE

AMERICAN NUCLEONICS AM-432 ..... $95.00
Cavity Backed Spiral Antenna,LHC, 2-18 GHz,TNC(f) *NEW*
BIRD 8329-310 30 dB Attenuator, ... $650.00
2000 Watts, DC-1 GHz, LC(f)/N(f)
FXR/MICROLAB S3-02N Triple Stub Tuner, max., N(m/f) $125.00
200-1000 MHz, 100 Watts
GR 874-LTL Constant Impedance $400.00
Trombone Line, 0-44 cm, DC-2 GHz
GR 900-Q GR900 14mm Interseries Adapters $125.00
HP 11590A-001 Bias Network, 1.0-18.0 GHz, APC7 ..... $450.00
HP 11612A Bias Network, 45 MHz-26.5 GHz, APC3.5 ..... $550.00
HP 11691D Directional Coupler, 22 dB, 2-18 GHz $450.00
HP 774D Dual Directional Coupler, 20 dB, 215-450 MHz $275.00
HP 777D Dual Directional Coupler, 20 dB, 1.9-4.1 GHz $275.00
HP 778D-011 Dual Dir. Coupler, ... $450.00
20 dB, 100-2000 MHz, APC7 test port
HP 8470B Crystal Detector, ... $250.00
10 MHz-18 GHz, neg. pol., APC7
HP 8472A Crystal Detector, ... $150.00
10 MHz-18 GHz, neg. pol., SMA
HP 8494G-002 Programmable Step $350.00
Attenuator, 0-11 dB, DC-4 GHz, SMA
HP 8495G-002 Programmable Step $300.00
Attenuator, 0-70 dB, DC-4 GHz, SMA
HP 8495H-002 Programmable Step $400.00
Attenuator, 0-70 dB, DC-18 GHz, SMA
HP 8497K-004 Programmable Step $750.00
Attenuator, 0-90 dB, DC-26.5 GHz
HP K422A WR42 Flat Broadband Detector, 18.0-26.5 GHz $350.00
HP K532A WR42 Frequency Meter, 18.0-26.5 GHz $450.00
HP K870A WR42 Slide Screw Tuner, 18.0-26.5 GHz $275.00
HP K914B WR42 Moving Load, 18.0-26.5 GHz $350.00
HP Q752D WR22 Directional Coupler, 20 dB, 33-50 GHz $650.00
HP R375A WR28 Variable Attenuator, ... $375.00
0-20 dB, 26.5-40 GHz
HP R532A WR28 Frequency Meter, 26.5-40 GHz $500.00
HP R752A WR28 Directional Coupler, 3 dB, 26.5-40 GHz $450.00
HP R914B WR28 Moving Load, 26.5-40 GHz $300.00
HP V365A WR15 Isolator, 25 dB, 50-75 GHz $900.00
HP V752D WR15 Directional Coupler, ... $650.00
20 dB, 50-75 GHz
HP X870A WR90 Slide Screw Tuner $150.00
HUGHES 45111H-2000 WR28 ..... $450.00
Isolator, 25 dB, 26.5-40 GHz
HUGHES 45712H-1000 WR22 ..... $900.00
Frequency Meter, 33-50 GHz
HUGHES 45721H-2000 WR28 ..... $1,200.00
Precision Rotary Vane Atten., 0-50 dB, 26.5-40 GHz
HUGHES 45732H-1200 WR22 Level Set $250.00
Attenuator, 0-25 dB, 33-50 GHz
HUGHES 45772H-1100 WR22 Thermistor Mount, ... $400.00
-20 to +10 dBm, 33-50 GHz
HUGHES 45775H-1100 WR12 Thermistor Mount, ... $800.00
-20 to +10 dBm, 60-90 GHz
HUGHES 47316H-1111 WR10 Tuneable $600.00
Detector, 75-110 GHz, positive polarity
HUGHES 47323H-1211 WR19 Flat $650.00
Broadband Detector, negative, 40-60 GHz
HUGHES 47974H-1000 WR15 SPST $375.00
PIN Switch, 250 MHz speed, 60-62 GHz response
KAY 442D Step Attenuator, 0-101 dB, 75 ohms, BNC $100.00
KRYTAR 1818 Directional Coupler, ... $200.00
16 dB, 2-18 GHz, SMA(f)
M/A-COM 3-19-300/10 WR19 Directional $450.00
Coupler, 10 dB, 40-60 GHz
MIDWEST MICROWAVE 3537 DC Block, ... $40.00
0.1-12.4 GHz, SMA(m/f) *NEW*
MINI-CIRCUITS ZFDC-20-4 Directional $25.00
Coupler, 19.5 dB, 1-1000 MHz, SMA(f)
MINI-CIRCUITS ZHL-42 Amplifier, ... $400.00
30 dB gain, 0.7-4.2 GHz, +28 dBm, 15V, SMA
NARDA 25171 Level Set Attenuator, ... $100.00
0-17 dB, 2-8 GHz, SMA(f)
NARDA 26298 20 dB Attenuator, ... $200.00
150 Watts, DC-1 GHz, N(f/f)
NARDA 3000-SERIES Directional Couplers $150.00
NARDA 3024 Bi-Directional Coupler, 20 dB, 4-8 GHz $300.00
NARDA 3090-SERIES Precision High Directivity Couplers $225.00
NARDA 368NM Coaxial High $400.00
Power Load, 500 Watts, 2.0-12.4 GHz, N(m)
NARDA 369BNF High Power Termination, ... $325.00
175 Watts, 0.7-18 GHz, N(f)
NARDA 3753B Coaxial Phase Shifter, ... $1,250.00
0-55 deg./GHz, 3.5-12.4 GHz
NARDA 4000-SERIES SMA $75.00
Miniature Directional Couplers
NARDA 4245-10 Directional Coupler, ... $100.00
10 dB, 4-12 GHz, SMA(f)
NARDA 4799 Level Set Attenuator, ... $135.00
0-15 dB, 4-18 GHz, SMA(f)
NARDA 5070-SERIES Precision Reflectometer Couplers $300.00
NARDA 765-10 10 dB Attenuator, ... $135.00
50 Watts, DC-5 GHz, N(m/f)
NARDA 766-10 10 dB Attenuator, ... $100.00
20 Watts, DC-4 GHz, N(m/f)
NARDA 792FF Variable Attenuator, ... $375.00
0-20 dB, 2.0-12.4 GHz
NARDA 794FM Direct Reading Variable $375.00
Attenuator, 0-40 dB, 4-8 GHz
OMNI-SPECTRA 2085-6010-00 Crystal $50.00
Detector, 1-18 GHz, negative polarity, SMA(m/f)
PAMTECH KYG1014 WR42 Junction $250.00
Circulator, 18.0-26.5 GHz
SONOMA ENG. S-4901 WR15 ..... $125.00
Junction Isolator, 57-59 GHz, 30 dB isolation
SONOMA ENG. S-4906 WR15 Junction Isolator, ... $125.00
60-62 GHz, 30 dB isolation
SONOMA ENG. S-4907 WR15 ..... $125.00
Junction Isolator, 62-64 GHz, 30 dB isolation
SONOMA SCIENTIFIC 21A3 WR42 Circulator, ... $75.00
20 dB, 20.6-24.8 GHz
SPACEK LABS DQ-1 WR22 Flat $400.00
Broadband Detector, 33-50 GHz
SPACEK LABS K-2X Frequency Doubler, ... $350.00
9.0-13.25 GHz in/ 18.0-26.5 GHz out
SPACEK LABS KA-3X Frequency Tripler, ... $350.00
8.83-13.33 GHz in/ 26.5-40.0 GHz out
TRG B528 WR22 Direct Reading $1,250.00
Phase Shifter, 0-360 deg.,33-50 GHz
TRG V551 WR15 Frequency Meter, 50-75 GHz $600.00
TRG W551 WR10 Frequency Meter, 75-110 GHz $750.00
WAVELINE 100080 WR28 ..... $200.00
Terminated Crossguide Coupler, 30 dB
WEINSCHEL 1515 Power Divider, ... $125.00
2-Way, DC-18 GHz, SMA(m/f/f)
WEINSCHEL DS109 Double Stub $150.00
Tuner, 1-13 GHz, N(m/f)
WEINSCHEL DS109LL Double Stub $150.00
Tuner, 0.2-2.0 GHz, N(m/f)

COMMUNICATIONS

HP 59401A HPIB Bus Analyzer $700.00
TEK 1410R NTSC Gen., w/SPG2 sync. $800.00
generator, TSG7 color bars
TEK 1411R PAL Gen.,w/SPG12 sync; $750.00
TSG11 color bars;TSG13 linearity
TEK 1411R PAL Test Gen., ... $1,000.00
w/SPG12,TSG11,TSG13,TSG15,TSG16
TEK 1411R PAL Test Gen., ... $1,100.00
w/SPG12,TSG11,TSG12,TSG13,TSG15,TSG16
TEK 1411R-opt.04 PAL Test Gen.,w/
SPG12,TSG11,TSP11,TSG13,TSG15,TSG16 ..... $1,400.00
TEK 1420 NTSC Vectorscope $600.00
TEK 147A NTSC Test Signal $800.00
Generator, with noise test signal
TEK 148 PAL Insertion Test Signal Generator $700.00
TEK 520A NTSC Vectorscope $750.00
TEK 521A PAL Vectorscope $750.00

MISCELLANEOUS

P.A.R. 5206-95,98 Two-Phase Lock-in $1,500.00
Amp., 2 Hz-100 kHz, GPIB
P.A.R. 5209 Lock-in Amp., 0.5 Hz-120 kHz, ... $2,500.00
130 dB dynamic reserve
TEK TM5006 5000-series 6-slot $600.00
Programmable Power Module
TEK TM504 500-series 4-slot Power Module $175.00
TEK TM506 500-series 6-slot Power Module $250.00
TEK TM515 500-series 5-slot Traveller Power Module $275.00

ELECTRONICS Q & A

With TJ Byers

In this column, I answer questions about all aspects of electronics, including computer hardware and software. This column doesn't replace the Tech Forum that you've grown to love and support. Instead, it will supplement it, so feel free to participate as always with your questions and answers. You can send your questions to me by E-Mail at q&a@nutsvolts.com, or by snail mail at Nuts & Volts Magazine, 430 Princeland Ct., Corona, CA 91719.

What's Up:
Pinouts galore, including Universal Serial Bus. Monitor mania: PC on Mac, TV on PC, PGA, AT&T 6300, and Wyse. How to make a toroidal transformer and two schematic medleys.

Universal Serial Bus (USB) Pinout

Q. Could you supply me with a pinout of the USB connector for an IBM-compatible computer?

Dennis Volcansek
Lodi, OH

A. *USB (Universal Serial Bus) is an emerging technology which uses just two connector types that take the place of the serial, parallel, keyboard, mouse, and game ports. The two connector types are Series A (Type A) and Series B (Type B). All USB ports on your PC are Type A. Type A is also used on devices in which the external cable is permanently attached, like keyboards and mice. Type B is used in applications which require detachable external cable, like printers, scanners, and modems. Unlike today's PC ports, which sport five or more wires, the USB port has just four wires that are carefully color coded and defined as shown below.*

Signal Name	Wire Color	Pin Number
Vcc	Red	1
- Data	White	2
+ Data	Green	3
Ground	Black	4

USB can support up to 127 devices via hubs or daisy chaining (plugging one device into another) at speeds of up to 12 MB per second (10 times faster then a serial port). You can insert and remove USB devices while your computer is running; the USB bus will configure the change on the fly. USB is Plug-and-Play compliant and is fully supported in Windows 98. Now for the pinouts.



Generally, the USB cable has a Type A connector on one end and Type B on the other. Making your own cable, though, requires special tools and a source for the connectors and special USB cable. You can

HACKING THE INTERNET
The latest tricks and methods being used on the Net to pirate software (warez) and the newest hacking websites. Includes examples, countermeasures, password defeats, UNIX, Sprintnet, brute force techs, lots of tips. *More! $29.*

INTERNET TRACKING & TRACING: Scammers, spammers, stalkers, infectors, and others hide behind the Internet's anonymity to commit serious offenses. Learn from master hackers best methods to track & trace IDs and origins, and to protect your own privacy. *More! $29.*

INTERNET CONS & SCAMS: Internet cons, scams and related frauds now rake in $2+Billion annually! Most are done anonymously with impunity. Details how they're done, how to ID them, how to protect yourself. *More! $25.*

THE COOKIE TERMINATOR: When online, many websites track your every move! Browser cookie, history and cache files contain personal data readily accessible to Internet predators, scammers, spammers and snoops. Your financial, medical, political, habits, lifestyle, future plans data is exposed to the world! Step-by-step how to remove and stop cookies from destroying your privacy. *$25.*

Any 2 for $49, 3 for $64, all 4 for $79!

PBX HACKING
PBX hacking losses are at $5-$10 Billion annually! Details how PBXs are hacked, countermeasures. Author interview in Forbes! $24.

CELLPHONE MODIF. GUIDE
How cellphones operate and are modified. Vulnerabilities to hack attack and countermeasures. Cloning details for NAMs, ESNs, etc, control data formats, computing encoded MINs, ESNs, SIDHs, Op Sys, PROMs, forcing ACK, test mode and resets, cable diagrams, scanning, tracking, scanner restorations, freq allocations, roaming, step-by-step to keypad-reprogram 100+ popular cell phones. One FREE database search. *More! $49.*

PAGER (BEEPER) MANUAL: How Pagers work, different types and uses, freqs, advantages over and uses with cellphones, and tips and tricks. How Pagers are hacked/countermeasures. And plans for a Personal Pocket Paging System (xmitter and receiver). *More! $29.*

Both for only $69!

PHREAKING CALLER ID & ANI
How they work and dozens of ways of defeating Caller ID, ANI, *69, *57, Call Blocking, *67 etc. Describes ESS, SS7, CN/A, CAMA, DNR, Diverters, Centrex - *more! $25.*

HACKING FAX MACHINES
Details all known methods of hacking Faxes, countermeasures. Includes computer fax modems, crimes, interceptions, fax servers, fax-on-demand, protocols, parameters, compression, encryption, fax surveillance-type mods. *More! $29.*

VOICE MAIL HACKING
VMSs are hacked to penetrate PBXs to make outgoing calls, get free VMB usage, secretly read/change/delete messages, or damage the VMS (or its PBX) itself. Step-by-step on how it's done, countermeasures. $29.

STOPPING POWER METERS
As reported on "60 MINUTES"! New 6th Edition! Plans for devices that can slow down (even stop) watt-hour meters - while loads draw full power! Devices plug into one outlet and normal loads into other outlets. Describes meter creep, overload droop, pole meters, etc. *$29.*

SPM THE VIDEO: Now its easier to learn about KW-HR Power Meters than ever before! This educational video shows you how they work and their anatomy. Demonstrates SPMEM device and external magnetic methods used to slow and stop meters! Hosted by a top expert in the field. From the novice to the pro, an excellent source of info on these exciting devices! Great in combo with our SPM related manuals! $29.

THE I.G. MANUAL: External magnetic ways (applied to meter) to slow down and stop power meters while drawing full loads. Plans *$25.*

KW-HR METERS: How watt-hour meters work, calibration, error modes (many), ANSI Standards, etc. Demand and Polyphase Meters. Experimental results to slow and stop meters by others. *$25.*

Any 2 for $49, 3 for $64, all 4 for $79!

COMPUTER PHREAKING
Describes in detail how computers penetrate each other, and how VIRUSES, TROJAN HORSES, WORMS are implemented. Dozens of computer crime and abuse methods and countermeasures. Includes disk filled with hacker text files and utilities, and the legendary FLUSHOT+ protection system. Internet advice, password defeats, glossary - *much more*! Manual + PC Disk! *$39.*

THE HACKER FILES: 3 HD PC disks filled with choice raw, colorful and highly informative hacker, phreaker text files covering many topics! *$39.*

Both for only $69!

BEYOND VAN ECK PHREAKING
Plans for remote eavesdropping of TV video signals. Range up to 1 KM. Describes how van Eck systems work, and are also used in surveillance of computer systems. $29.The van Eck Demo Tape is $29. Both for only $49!

MANY MORE TITLES!
Beyond Phone Color Boxes - $29
Hacking Answer. Machines - $19
Casino Hacking - $25
Automatic Teller Machines - $39
Credit Card Scams - $29
Cons & Scams - $29
Social Engineering - $29
Polygraph Defeats - $25
By an Order of the Magnitude - $49
Ultimate Success Manual - $19
Stealth Technology - $19
Secret & Survival Radio - $19
High Voltage Devices - $29
Mind Control - $29
Under Attack! - $29
Radionics Manual - $29
Heal Thyself - $19
Secrets of Solderless BBs - $24
Secret & Alternate IDs - $15
Cryptanalysis Techniques - $29
Government Land Grab - $15
Rocket's Red Glare - $29
Survival Guns & Ammo - $19

THE DIRTY-2 DOZEN!
24+ *Hot* Hack/Phreak Disks!
See CATALOG!

SPECIAL PROJECTS

We will design & build just about anything electronic! Hardware done as SPECIAL PROJECTS only. See Catalog for details and SP Application Form, else: www.tsc-global.com/spaf-spp.html

TOP SECRET
CONSUMERTRONICS
2430 Juan Tabo, NE, #259, ABQ, NM 87112
P.O. Box 23097 ABQ, NM 87192
Fax: 505-292-4078 (all hours, orders only) Voice: 505-237-2073 (10-6, M-F)
Full Catalog: www.tsc-global.com/consumer.html Adventure: www.tsc-global.com
Established in 1971. Featured on CBS "60 Minutes," Forbes, New York Times. Add $5 total S/H (US, Canada). Postal MO is fastest! VISA, MC OK. No CODs. Take 10% OFF all Orders over $100, and Take $2.00 OFF all New Orders over $20 placed by Mail or Fax. Catalog $1 w/order, $3 w/o.
Sold for legal educational purposes only. See Catalog for LIMITED WARRANTY, SPECIAL PROJECTS and all other applicable policies.

find finished cables at most computer stores, but at a premium price. I expect that they'll soon drop in cost and show up in the surplus marts.

Hush Little Clock

Q. I read your reply in the Mar. '98 issue ("Simple Squarewave Generator") showing some approaches in oscillator circuits. I need a low-noise 2-MHz oscillator — one that's suitable for use as the system clock for a 20-bit ADC. I'm currently using an IC-type clock oscillator housed in an eight-pin metal DIP enclosure. The clock works, but since it has a very fast rise-time it radiates lots of noise. Do you have any recommendations on low-noise oscillators for this type of application?

Steve Roberts
via Internet

A. *This is a typical complaint about system clocks. The problem with a simple repetitive signal — like a system clock — is that all its spectral power becomes concentrated at a relatively small number of discrete frequencies. When these frequencies leak from the package into the outside world, they often raise havoc with radio and TV reception. The modern cure is to modulate, or dither, the clock frequency to break up the accumulated spectral power into a larger number of discrete frequencies, each with a reduced energy content. However, this a complex and expensive solution. If excessive radiation is a problem, you'd be better served using any combination of the following techniques.*

· Use a ground plane in your PC board.
· Use a thinner PC board to reduce the space from the trace to the ground plane.
· Use properly terminated transmission lines between the clock and the ADC.
· Slow the rise/fall time of the clock driver.
· Use surface mount technology, like a SOT-23 package.
· Use a lower-voltage 3.3V clock, like the DS1073 from ***Dallas Semiconductors*** *(**1-800-336-6933**; **http://www.dalsemi.com**) or the T-3390 from* ***MF Electronics Corp.*** *(**914-576-6570**; **http://www.mfelectronics.com**); the ADC voltage can stay at 5V.*

Here are how these techniques can be implemented.



Circuit (a) shows how to substitute a low-voltage DS1073 clock oscillator for your 5V tin can. The lower operating voltage has the advantage of less power dissipation and more rounded corners, which lowers spurious radiation. The DS1073 is a programmable clock oscillator with a frequency range of 30 KHz to 100 MHz. You can easily do the programming yourself using very simple circuits provided in the DS1073 data sheet found on the Dallas Semiconductor Web site. Circuits (b) and (c) show two ways to properly terminate a PC board transmission line. One is series terminated (b) and the other is parallel terminated (c). The series resistor is placed near the clock source and the parallel resistor is placed as near as possible to the ADC clock input. Circuit (e) shows how to increase the rise/fall times of a standard clock oscillator (d). The values shown in (e) are for unity gain (Av = 1) for frequencies up to 4 MHz. For more information on how to push this op amp to 90 MHz, download the LM7131 data sheet from the National Semiconductor Web site (http://www.nation al.com).

Davilyn CORP.
13406 Saticoy Street
North Hollywood, CA 91605
800-235-6222
818-787-3334 · F-818-787-4732
HTTP://WWW.Davilyn.com/Electronics
CALL FOR FREE CATALOG

THE BEST PRICE EVER ON THIS INDUSTRY FAVORITE
$1,095 + SHIPPING

HP 8640B SIGNAL GENERATOR OPT 003



CONDITION CODE "A"

Frequency: 500KHz to 512MHz. Indicates to 1024MHz. Requires external frequency doubler for 1024MHz (supplied with unit). Readout can be used as a frequency counter. Accuracy: 6.5 digits expandable to X10 and X100. Output: -145dBm to +19dBm (0.5 to 512MHz). Modulation: AM, FM, pulse, 400 and 1KHz, 1mV to 1V internal. Has input and output of modulation sources. PRICE: $1,095

EXCEPTIONAL CONDITION
LIMITED SUPPLY DUE TO OVER-WHELMING DEMAND

HP 200CD Oscillator	$95
HP 312B Selective Voltmeter	$695
HP 331 Distortion Analyzer	$249
HP 400E Voltmeter	$325
HP 412A Voltmeter	$95
HP 415E Voltmeter	$125
HP 3435A Multimeter	$295
HP 8160A Generator	$2,800
Krohn-Hite Model 4300A Oscillator	$395
PRD Type 2020 Vector Voltmeter w/sampling heads	$250
Systron Donner Spectrum Analyzer Consists of tuning unit Model 809-1, display unit Model 712-1	$1,995
Watkins Johnson WJ-8628-4 Receiver	$8,500

AN/URM-120 50 OHM THRU-LINE RF WATTMETER

Frequency range: 2MHz to 1000MHz. Power range: 10 watts to 1000 watts. USWR≤1.08 to 1. Uses three plug-in coupler elements (included). CU-753 2 to 30MHz 50 to 100 watts CU-754 25 to 250MHz 10 to 500 watts CU-755 200 to 1000MHz 10 to 500 watts. Connector: Type N. Case included. Size: 7"Wx6-5/8"Hx7-1/5"D. Weight: 6.5 lbs. **Price: $395**

TEKTRONIX 2336YA DUAL TRACE 100MHz PORTABLE OSCILLOSCOPE



Price: $795

Vertical: DC to 100MHz band with 5 mV per div. to 5V per div. maximum sensitivity of 2mV/div. Horizontal: Time Base A: 0.05 uS/div. 0.5 sec/div. X10 to 5 ns/div. Time Base B: 0.05 uS/div. to 50 mS/div. X10 to 5 ns/div. Has digital readout of delta time, delayed sweep, and XY input div.

LAMBDA LK344A-FM POWER SUPPLY



Front panel voltage and current meters. Con-vection-cooled, no blower. Voltage adjustable from 0 to 60 VDC at a maximum current of 4A. Regulation 0.015% or 1mV. Line or load. Series/parallel operation. Remotely programmable by voltage or resistance. Less than 500µV RMS ripple. Constant current/constant current. **NEW Price: $395**

HP 180A SCOPE (MIL SPEC AN/USM-281A)

Includes vertical plug-in 1801A (PL1186), horizontal plug-in 1821A (PL1187). Tested. Manual Reproduction: **15**

GREAT PRICE **$195**

TELEGRAPH KEYER

Unique item for military collectors. J37 telegraph key, new in original government package. **$49.95**

JONES MODEL 1600-1 TACHOMETER

Instrument tachometer centrifugal mechanical tach measures RPM scale 0-500 RPM, coupling shaft 1/8" accessories, various size rubber tipped drive couplings, case **new.** Also **Jones Model 1600-7** RPM scale 0-11,000 RPM w/accessories **new. $35/ea. or 2 for $50**

STACO TYPE 3PN1020

50/60 cycle, input 240 volts, output 0-240/280 volts, 3.5 amp. **$145 NEW**

SINGER CSM-1 COMMUNICATIONS SERVICE MONITOR

RF signal source: 0 to 600MHz in 100MHz steps plus 100Hz vernier. RF output: 110 to 0 dBm, built-in oscilloscope monitor. Inputs: RF, detected, vertical, horizontal, AM/FM. Outputs: audio, tone, RF. Functions: generate 2mV to 2mV. AGC: manual or auto. **$595**

AIRCRAFT CAMERA LENS

Mfg. Pacific Optical
Type I EEL 18 inch F4 format, 4.5x4.5 inches, wt. 15 lbs. **$90**

MORGAN DATA SYSTEMS MODEL 8609

Constant voltage or current power supply voltage range: 0 to 50 volts. Current range: 0 to 1.5A. Readout: 3 digit with 0.1 volt and 1mA current resolution. Regulation: linear; input voltage: 115V/220V. Adjustments: voltage and current has remote control adjustment capability. NEW. **Price: $195**

POWERSTAT TYPE 216CU

50/60 cycle, single phase, output voltage 0-280 3.5 amp

$85 NEW

EXTENSION CORD ROYAL ELECTRIC

15 ft. long (5 yards), general purpose 16-3-SJT, 13A/125V, 0-7215, UL approved. PRICE: $3.95 NEW

NICKEL CADMIUM BATTERY



G.E. Catalog No. 42B004KA01. Nominal volts 12 rated capacity 4.0aH, wt. 5 lbs. **NEW $55**

RT-202 RECTIFIER TRANSFORMER MFG. STANCOR

Primaries 117 volts, 50/60Hz solder lug termination, secondary multiple voltages and currents. Spec sheet available.

$15

Write in 129 on Reader Service Card.

Quality Reconditioned Test Equipment
90 DAY WARRANTY & 10 DAY INSPECTION
INVENTORY REDUCTION SALE
EVERYTHING IS 10% TO 35% OFF
Look for us at te-plus@primenet.com

HEWLETT PACKARD

10833A/B/C, HPIB Cables, 1/2/4 meter ..... 6 for $50
11720A, Pulse Modulator, 2-18GHz $400
180TR, Rack Mount Display $180
1980B, Automatic O'Scope Measurement System $600
214B, 10 MHz Pulse Generator, 200W Pulse/50 ohms $975
3311A, Function Generator, .1 Hz-1 MHz $150
3312A, Function Generator, 0.1 Hz-13 MHz $400
3325A, 21MHz Synth Function Generator, HPIB $1475
3325A-2, 21MHz Synth Func Gen, 40Vp-p, HPIB $1700
33320H, Prog Attn, DC-18GHz, 10dB range, 1dB steps ... $250
33322H, Prog Attn, DC-18GHz, 110dB range, 10dB steps $250
3400A, RMS Voltmeter, 10Hz-10MHz $125
3403C, Digital RMS Voltmeter, 2 Hz-100 MHz $250
3421A-201/44462A, Data Aquisition Control Unit, HPIB $335
3455A, 6.5 digit Multimeter, HPIB $300
3456A, 6.5 digit Multimeter, HPIB $625
3465A, 4.5 digit Multimeter $125
3488A, Switch/Control Unit $500
3575A, Gain/Phase Meter, 1 Hz-13 MHz $450
4274A, 5-1/2 digit LCR Meter, 100Hz-100KHz $2900
4328A-01, Milliohmmeter w/ battery opt $750
432A/478A, Power Meter, 10 MHz-10 GHz $150
432A/8478B, Power Meter, 10 MHz-18 GHz $225
435A, Power Meter $175
436A-022, Power Meter w/ sensor cable, HPIB $900
4437A, Step Attenuator, DC-1 GHz, 600 ohm $150
44421A, 20 Chan Relay Multiplexer, used on 3497A $50
44428A, 16 Chan Actuator/Digital Output, used in 3497A . $50
44462A/63A, 8 Chan MUX/2 Chan Actuator (3421A) $135
44465A, 8 Bit Data I/O (use in 3421A) $135
44711A, 24 Chan FET Multiplexer, used on 3852A $175
478A, Thermistor Mount, 10MHz-10GHz, -30 to +14dBm . $75
491C, Amplifier, 2 GHz-4GHz, 1 Watt, 30dB Gain $375
5300A w/5302A, 50 MHz Counter $90
5300A w/5303A, 500 MHz Counter $175
5314A, 100 MHz Counter $150
5316A, 100 MHz Counter, HPIB $300
5316B, 100MHz Counter, HPIB $475
5328A, 100 MHz Counter, HPIB $175
5328A-021-030, 512 MHz Counter w/DVM, HPIB $275
5328B, 1.3GHz Counter, Oven Osc, DVM, HPIB $575
5334A, 100 MHz Counter, HPIB $400
5334B, 100 MHz Counter, HPIB $500
5335A-040, 200 MHz Counter, HPIB $625
5342A, Microwave Counter, 18GHz $1400
5342A, Microwave Counter, 18GHz, Oven Osc, HPIB ... $1600
536A, Frequency Meter, 0.96-4.2 GHz $75
5370B, Time Int Counter, 100 MHz, 100 pS accuracy ... $1400
59306A, Relay Actuator, 6 form C relays, manual & HPIB $100
59309A, HPIB Clock $75
6002A-01, Pwr Sup, 200 W, 0-50V@0-10A, GPIB $500
6034L, Dig Autoranging Pwr Sup, 60V/10A/200W, HPIB $600
6110A, (Har) Pwr Sup, 0-3KV@6mA (cable kit incl) $200
6112A, Precision Pwr. Sup., 0-40V@0.5A $150
6181B, Constant Current Source, 100V, 250 mA $175
6214C, Pwr Sup, 0-10V@1A $50
6253A, Dual Pwr. Sup., 0-20V@3A $275
6255A, Dual Pwr Sup, 0-40V@1.5A $350
6261B-026, Pwr Sup, 0-20V @50A $400
6264B, Pwr Sup, 0-20V@20A $275
6271B, Pwr Sup, 0-60V@3A $275
6284A, Pwr Sup, 0-20V@3A $100
6289A, Pwr Sup, 0-40V@1.5A $100
6291A, Pwr Sup, 0-40V@5A $300
6294A, Pwr Sup, 0-60V@1A $100
6433B, Pwr Sup, 0-36V@10A $350
6515A, (Har), Pwr Sup, 0-1.6KV@5mA (cables incl) $225
652A, Test Oscillator, 10Hz-10MHz, +/-0.25% flatness ... $200
8007B, Pulse Generator, 100 MHz $350
8084A, Word Generator Plug-In, 300 MHz $200
8350B, Sweep Oscillator Mainframe $2500
8444A, Tracking Generator, 0.5-1500 MHz $400
8447A, RF Amp, 0.1-400MHz, 20dB gain, +6dBm out $325
8447D opt 1, RF Amp, 0.1-1300MHz, dual channel option, 25dB gain, +7dBm out $900
8478B, Thermistor Mount, 0.01-18GHz, -30 to +14dBm .. $150
8620C-011, Sweep Oscillator Mainframe, HPIB $350
86250D, RF Plug-In, 8.0-12.4 GHz $250
86602A, RF Plug-In, 1-1300 MHz $400
8660C opt 1-5-100, Synth Sig Gen MF, Oven Osc, HPIB $1000
8709B, Phase Lock Sync, locks sources to reference osc . $250
8750A, Storage Normalizer, for Spectrum & Network Anal $200
8770A-K01, Sync Sys Interface (used w/Arb Wave Gen) . $400
8901B-1-3, Modulation Analyzer, 150KHz-1300MHz $2250
9411B, Automatic Test Station Switch Cont, HPIB $675
P486A, Thermistor Mount, 12.4-18GHz, -30 to +14dBm ... $40
X486A, Thermistor Mount, 8.2-12.4GHz, -30 to +14dBm .. $40
X752D, Directional Coupler, 8.2 to 12.4GHz, -20dB port .. $40

TEKTRONIX

1240 opt 5, Logic Analyzer w/ (2) P6460 probes $600
2215A, 60MHz O'Scope $525
2236, 100MHz Dual Trace O'Scope w/ Counter & DMM . $850
2337, 100 MHz O'Scope $675
2430A, 150MHz Dig O'Scope, .0015% Time Base, GPIB $2700
475, 200 MHz Dual Trace Oscilloscope $575
577D1/177, Storage Curve Tracer w/ std test fixture $1425
7104, 1 GHz O'Scope Mainframe $1300
7603-1, 100 MHz O'Scope w/ 7A26, 7B53A $265
7A13, 105 MHz Differential Comparitor $135
7A18, 75 MHz Dual Trace Amplifier $45
7A22, 1 MHz High CMRR Differential Amplifier $175
7A24, 400MHz Dual Trace Amplifier $225
7A26, 200 MHz Dual Trace Amplifier $65
7B10, 1GHz Delayed Time Base $300
7B15, 1GHz Delaying Time Base $350
7B53A, 100 MHz Dual Time Base $65
7B70, 200 MHz Time Base $65
7B85, 400 MHz Delta Delaying Time Base $90
7B92A, 500 MHz Dual Time Base $135
7CT1N, Curve Tracer Plug-In $250
AM501, OpAmp (TM500 series) 40V@50mA $75
AM503, Current Probe Amplifier $300
DC5009, 135 MHz Universal Timer/Counter $225
DM501, 4.5 Digit Multimeter $125
FG504, 40MHz Function Generator $400
P6015, 40kV, 1000X, 75MHz High Voltage Probe $200
P6021, Current Probe, 120Hz-60MHz $150
P6106A, 10X Probe, 250MHz, incl gnd clip & hook $50
P6133, 10X Probe, 150MHz, incl gnd clip & hook $50
P6460, Data Aquisition Probe (for 1240/1241 Analyzer) .. $180
P6602, Temperature Probe $90
PS5010, Prog Tripple Pwr Sup, TM5000 series $375
PS503A, Tripple Pwr Sup, (2) 0-20@1A, 5V@1A $135
S-3A, Sampling Head, DC-1 GHz $75
T922R, 15MHz O'Scope, Front & Rear Inputs $325
TM5006, 6-slot Programmable Power Module $250
TM501, 1-slot Power Module $75

MISCELLANEOUS

AEMC SL206, AC/DC Current Probe, 2A & 80A ranges .. $65
AEMC MD400, AC/DC Current Probe, 400A range $65
BECO 315A, Universal Impedance Bridge $100
Bird 10A, Plug-in Element (Bird 43), 10W@25-60 MHz $35
Bird 100A, Plug-in Element (Bird 43), 100W@25-60 MHz $35
Cal Inst 101T/850T, AC Power Source, 105-135VAC, 45Hz-5KHz, 100 Watt $540
Cal Inst 101T/850T, AC Power Source, 0-600VAC, 45Hz-3KHz, 100 Watt $630
Clarke-Hess 5000, Phase Angle Standard, GPIB $900
Dranetz 606-3/101-103, Line Disturbance Alalyzer $225
Dranetz 626, Line Disturbance Analyzer, w/ PA-6002A, PA-6003, PA-6006, cables, and carying case $800
Ectron 760DLU, Differential Amplifier, DC-50KHz $200
EIP 548A-1-2-8-9, Microwave Counter, 10 Hz-26.5 GHz, DAC out, GPIB, rear input, power meter $2250
ESI 242D, Precision Resistance Measuring System, 10-ppm direct reading accuracy, 1-ppm comparison .. $3800
Fluke 5100B-3-5, Meter Calibrator, Wideband & GPIB . $2500
Fluke 6010A, Synthesized Func Gen, 10Hz-11MHz, GPIB $600
Fluke 8000A, 3.5 digit Multimeter $40
Fluke 80T-150, Temperature Probe, -50C to +150C $60
Fluke 8500A, 6.5 digit Multimeter, opt 2-4-5 ..... $200
Fluke 8860, 5.5 Digit Multimeter $125
Fluke 8920A, Digital RMS Voltmeter, 10 Hz-20 MHz $400
Fluke 8922A, Digital RMS Voltmeter, 2 Hz-11 MHz $400
GenRad 1433B, 6-Dec Res, 0-1,111,110 ohms, 0.01% $350
Heise 711B, Digital Pressure Gauge, 0 to 30 PSI, .05% $350
JC Systems JC520, Temperature Setpoint Programmer $150
Keithley 614, Electrometer (add $130 for new 6011 probe) $575
Kepco ATE150-3.5M, Pwr Sup, 150V@3.5A $350
Kepco BOP20-10M, Op Amp/Pwr Sup, +/-20V, +/-10A .. $300
Krohn-Hite 6620, Precision Phasemeter $400
Lambda LQ-532, Pwr. Sup., 0-40V@5A, Dig Display $100
Laser Precision TD-9920, OTDR w/ case & manual $500
Narda 1080, Dir Coupler, 8.2-12.4GHz, -40dB port $50
Narda 3045C-10, Dir Coupler, 7-12.4GHz, +/-0.2dB $50
Narda 3293-2, Directional Coupler, 1-12.4 GHz (N type) . $100
Oram Power Supply, 0-270V @ 10A $475
Phoenix 5500-624-1, T1 Interface Plug-in $175
PowerDesigns 6050C, Mulirange Variable Pwr Sup, 0-6V@5A, 0-15V@3A, 0-30V@2A, 0-60V@1A $175
Simco SS-2X, Electrostatic Locator w/ probe $90
Sorensen Pwr Sup, 5V +/-5% @ 200A $50
Sorensen DCR150-18B, Pwr Sup, 0-150V@18A $750
Sorensen DCR20-115B, Pwr Sup, 0-20V@115A $600
Sorensen STM28-24, Pwr Sup, 24-30V@24A $75
Spectroline PE-140T, UV EPROM Eraser $35
Valhalla 4440, 4-1/2 Digit Voltmeter / Counter $50
Varian VZU6998H5, 12.4-18GHz TWT Amp, 40dB gain .. $350
Wavetek 154, Prog. Waveform Gen., .001Hz-10MHz $75
Wavetek 175, Arbitrary Waveform Generator, GPIB $450
Wavetek 271-02, 12MHz Pulse/Func Gen, GPIB $400

TEST EQUIPMENT PLUS
(520) 575-6967, FAX (520) 575-6936
3331 W. Bright Terrace, Tucson, AZ 85741

MasterCard VISA

Topic Of Toroid

Q. In your Oct. '97 column on building a vacuum-tube power supply, you show a circuit to boost 12 volts up to 400 volts using a toroidal transformer that you say can be salvaged from a defunct PC power supply. I've opened up some defunct PC power supplies and haven't been able to find a toroidal transformer. Can I purchase the transformer from Digi-Key or RadioShack, maybe under the guise of a signal transformer?

Frank Kwok
via Internet

A. *Actually you won't find the specified transformer inside a PC power supply. It doesn't exist. What you will find instead is a toroidal magnetic core with copper-wire windings already on it. A toroidal core is a gray powdered-iron ring about an inch or so in diameter. There are actually three (sometimes only two) toroidal transformers in a PC power supply. You want the biggest one. First, you need to strip the transformer of its copper wires, and start anew using the wire gauges and turns listed in the original diagram, which are repeated below.*



PRI: 12T, CT, #18 AWG
SEC: 275T, #24 AWG
CORE: IND GEN 8231-1

This is the format used by every manufacturer for specifying a transformer. Let's take it apart and see what it means. Starting from the bottom, it specifies a toroidal core type. Depending on the application, it may or may not be critical. In a power-supply application like above, you simply need a core that doesn't saturate under a full load. The core specified was made by Indiana General, who is now out of business. Fortunately, it's an industry staple that measures about 1- 1/2" in diameter that you can get from several manufacturers, including Philips. Start with the secondary winding, which is 275 turns of #24 AWG magnet wire (#22 AWG will work; RadioShack 278-1345). The easiest way to do this is to first wind the wire on a bobbin or shuttle that fits through the hole, and thread the wire through the donut, counting the turns as you go. Over this layer, wind 12 turns of heavier #18 AWG wire. You can recover this wire from the salvaged transformer. After you've done six turns, scrape the insulation off and solder a tap wire – hat's what the CT designation in the formula means; it's a center tap. Coat the splice with clear fingernail polish and continue on to winding 12 and stop. That's it! You've just made a transformer.

PGA What?

Q. I have a acquired a True Blue IBM Professional Graphics Adapter (PGA) color monitor. This monitor hasn't been used on a system in over 10 years because the original owner couldn't find a PGA card to run it. I know this monitor is an odd duck that takes a special card, but I feel that I can make a modern video card meet its specs. I'd like to use it as a test monitor or on a server that I plan to build for WindowsNT or Win95 (Win98). While I've fiddled with several vintage color cards of one variant or another (MDA, CGA, and VGA), nothing works with this monitor. Do you have a pinout or conversion cable that will work?

Tim Edwards
via Internet

A. *Odd is hardly the word for this lame duck. It was VERY expensive and almost immediately replaced with the 8514/A. Basically, it's an analog monitor with an INTERLACED (can you say interlaced?) scan resolution of 1024 by 768. That puts the refresh rate at about 43 Hz, which flickers like an old Nickelodeon. The dot pitch is just 0.31mm (if I remember right) and it's not something you'd want to use with a WindowsNT system. Still, if you insist on using it, here's the pinout.*

Video Mode

Pin	***PGA***	***VGA***
1	Red	Red
2	Green	Green
3	Blue	Blue
4	Composite Sync	H. Sync
5	Mode Control	V. Sync
6	Red GND	Red GND
7	Green GND	Green GND
8	Blue GND	Blue GND
9	GND	GND

Write in 91 on Reader Service Card.

You see that the PGA connector is very close to that of a nine-pin VGA plug of that era – with a major exception. The sync is composite, not separated into horizontal and vertical sync. Here's a circuit that combines the separate syncs into a composite sync.



You probably won't find a PGA driver for your software, but an 8514/A driver should work.

LED Repeater

Q. I regularly come upon situations where I'd like to view an LED indicator at a remote location. For example, my current project is to move the status indicators from my computer's UPS off the floor to a location where they can actually be seen. What I'd like is a generic circuit that would "watch" an existing LED – either electronically or optically – on a variety of devices and simply light a duplicate LED some distance away.

Jeff Rothfus
via Internet

A. *There are several ways you can do this, depending on your access to the original LED and how you want the new display to look. The simplest solution is to use a fiber optical cable. One end attaches to the LED using a clear glue and the other end goes to your indicator panel. Inexpensive fiber optics can be purchased from Newark Electronics (1-800-639-2759; http://www.newark.com). It requires no power and is easily installed however, the light is less bright than the original LED. In which case, you'll want to use an external LED. Here's a medley of designs that'll work.*



Circuits (a), (b), and (c) are optically coupled and require that you only tape or glue the sensor over the existing LED. There is no electrical contact to the commercial device. Circuits (a) and (c) use a standard phototransistor, like the 276-145 from RadioShack. This transistor works best with red LEDs. I've also had good luck with clear LEDs substituting for the phototransistor. Design (a) uses the phototransistor with a 2N2222A in a Darlington configuration. When light strikes the phototransistor, it conducts – which turns on the 2N2222A and lights the LED. Circuit (c) is basically the same design with the 4001 logic gate replacing the 2N2222A. When the voltage at the gate's input (pins 1 and 2) exceeds about 2.4 volts, the output goes low and lights the LED. There are four gates in the 4001 (a 4011 works, too), which reduces the part count for multiple LEDs. Circuit (b) uses a photoresistive sensor connected between the reset input (pin 4) and Vcc. Again,

The Filter Company

Positive Notch Filters

Internet: www.gofilters.com

Large STOCK on all Available Channels
2 thru 30*, 95 thru 99
0,1,57,58,59,60,61,A1,A2,A3,A4,A5
ORDER BY SINGLE CHANNELS

We Specialize in Large Quantities on every Channel

Prices as low as $6.00ea

NOBODY BEATS OUR PRICES

Monday - Friday (8am to 5pm) Central Time
QUALITY METAL CYLINDER TYPE NON-TUNABLE
ABSOLUTELY NO DRIFTING PROBLEMS

Standard Positive Filters

1pc-$16.00 5pcs-$14.00 10pcs-$12.00
25pcs-$10.00 50pcs-$8.00

*Standard Positive Filters, Channels 26-30 add $3.00 more each.

Positive "G and S" Series Filters

1pc-$30.00 5pcs-$28.00 10pcs-$25.00

Tom G. - FL *Excellent Service, fast and quick. The only bad thing about this company is they don't sell Cable Boxes. We hope someday they will.....*

David P. - CA *We called around for help on filters and nobody had any answers except one, call the "THE FILTER COMPANY" we did and had an answer in a matter of seconds.....*

John B. - IL *Our company buys in the 100 quantities and needs a large selection of different channels. "The Filter Company" was the only one who was able to supply.....*

PHONE ORDERS:

1-800-235-8080

Visa, Mastercard and Discover
(UPS COD for established customers)

Anyone implying theft of Cable Service will be denied assistance
We do not sell Data Blockers, Bullets or FM Traps !!!!

A "TFC" Company

Give our 800 line a howl for the best service in the Country.....!!!!

light decreases the resistance of the photocell which turns on the 555, causing it to oscillate. This pulses the LED at a greater current than in the two previous designs, which increases the brightness of the lamp without increasing the average current draw from the battery. Finally, if you have access to the LED wiring inside the UPS, the circuit in Figure (d) is the most stable because it's totally immune to ambient room light. To use it you need to break the positive lead going to the existing LED and insert the optocoupler LED in series with the panel lamp. Whatever design you choose, place the circuit as close as possible to the light source to avoid noise interference, and locate the second LED at the remote site (LEDs are current operated, so voltage drop in the cable isn't a factor). The panel and remote LEDs are synchronized to go on and off at the same time by adjusting the variable pot.

PC Graphics on Mac Monitor

Q. I read your answer to Chuck Karbginsky in the Jun. '98 issue concerning his RGB to SVGA monitor problem. I have a similar problem. I have a Apple Performa Plus Monitor that I want to use on a PC. I know that this monitor has a composite sync, but I don't know if it's sync positive or negative. I got these specs from Apple. Can you make sense of them?

Dan Kilpatrick
via Internet

A. *I took the liberty of rendering down your list of specs to just those we need to discuss. Here they are.*

Input Signals
Video: Analog, modified RS-343
Sync: Composite horizontal and vertical sync
Scanning Frequencies
Horizontal: 35 KHz
Vertical: 66.7 Hz
Dot clock: 31.91 ns

To begin with, you don't have to worry about whether the sync is positive or negative – the RS-343 standard takes care of that. Your worry is whether or not the fixed scanning frequencies of this monitor fall within the range of a PC video standard. Here's a list of the PC video modes that come close.

Mode	Resolution	Horizontal Scan Rate	Vertical Scan Rate
EGA	640 x 480	37.40 KHz	72 Hz
VGA	800 x 600	35.20 KHz	56 Hz
	800 x 600	37.80 KHz	60 Hz

As with any electronic device, there's always a fudge factor – called tolerance – which may be enough to let your 35-KHz monitor sync at 37.80 KHz. Same for the 66 Hz vertical sync. If it doesn't happen, you might be able to tweak it in using adjustments you'll find under the cover – just be VERY careful! No, I'm not talking about the high voltages (which you have to respect), but your attention to selecting the right control. A couple tweaks in the wrong direction and you may never find your way back home. Of course, you need a composite sync converter, like the one described in the preceding "PGA What?" question. After that, you need a converter cable that mates the PC to the Mac monitor. Here's how they pair up.

Computer Video Connector Type	Mac DA-15	PC DB15
Pin	**Function**	**Function**
1	Red GND	Red
2	Red	Green
3	Composite TTL sync	Blue
4	Composite TTL GND	Monitor ID bit 2
5	Green	not used
6	Green GND	Red GND
7	not used	Green GND
8	not used	Blue GND
9	Blue	not used
10	not used	GND
11	not used	Monitor ID bit 0
12	not used	Monitor ID bit 1
13	Blue GND	Horizontal sync
14	not used	Vertical sync
15	not used	not used

You can buy Mac to VGA adapters from several sources, including Bottom Line Online (http://www2.blol.com), for about $29.00. Like I say, your worry is the scan rates.

Wyse Terminal Pinout

Q. I have several Wyse WY-150 workstation monitors that have a keyboard connector under the left front and three connectors on the back labeled Serial 1, Serial 2, and Parallel. I assume that the monitor is MDA (monochrome) and that the Serial 1 port carries keyboard and video data to the computer and back. If you are able to provide the pinout for the Serial 1 connector, I believe that I can use these monitors. I think the information might interest other readers, too, because they are readily available at low prices.

L. Hansen
via Internet

A. *Well, it's not really a monitor. It's a computer terminal with its own built-in motherboard. Unlike a "real" monitor, a terminal can only convey text data between the computer and itself – no graphics allowed. Think of it as a "chat" room conversation between you and the computer. Don't feel badly that it's not a real monitor, though, because it can be used to leave messages on the host computer from a remote site via its modem port (Serial 2) and do other*

WY-150e Serial 2 Port Assignments

Pin	Signal	Mnem	Dir
1	Data Carrier Detect	DCD	In
2	Receive Data (RX+)	RXD	In
3	Transmit Data (TX+)	TXD	Out
4	Data Terminal Ready	DTR	Out
5	Signal Ground (TX-RX-)		
6	Data Set Ready	DSR	In
7	Request To Send	RTS	Out
8	Clear To Send	CTS	In

12VDC OPERATED 15KV NEGATIVE ION GENERATOR

NEW

Compact negative Ion generator cleans air of impurities and provides a fountain of fresh air. Negative ions are produced during a thunderstorm and these are the same type that this 2 1/4" x 1 5/8" x 7/8" module produces. Operates from 12VDC (can even operate from a 9V battery at slightly reduced output). Simple to use, just connect 12VDC to the red and black power input leads and a tremendous quantity of negative ions will be emitted by the needle assembly shown. These are brand new factory fresh prime units perfect for homes, cars, offices, etc.

G9695 $12.95 ea. 2 for $25.00

XRC110 UNIVERSAL REMOTE CONTROL

If you've lost or damaged your old remote here's the perfect solution. The XRC110 has all the codes needed to program it to replace your old remote. It will control most TVs, VCRs, cable boxes, etc. Can even be used to replace 2 or 3 various remotes. Brand new by General Instrument. Comes with extensive programming code list or you can use the electronic code search function to program. Operates from 2AA batteries (not included) Size 8" x 1 3/4". Brand new in box.

G9735 $4.95 ea. 2 for $9.00

ELECTROMAGNETIC FIELD (EMF) DETECTOR



This is a complete EMF detector utilizing 3 SMD ICs and 10 bright LEDs that indicate relative strength of EMF energy. Operates on one 9V battery (not included). As soon as you press the on/off button, the unit runs a "self-test" by lighting all 10 LEDs then it resets itself and indicates the relative EMF strength by the quantity and color of LEDs that light. Size of unit is about 3 5/16" x 2 3/8". These are brand new and prime, but without the outer plastic case. They were made in 1995 and feature some of the latest technology in portable relative EMF detection. We suspect that when the board was installed in the case, the completed unit sold for $80.00-$100.00 retail but now you can buy it for a fraction of that price and make your own case (if you wish). We are amazed by the EMF energy emitted even from a small laptop computer within close proximity. We have no data or schematics, but all you need to do is connect a 9V battery and you're in business. Super blowout price!

G8317 $8.95 • 5/$40.00 • 100/$600.00

POWERFUL IR REMOTE

Brand new remote control "Tele Commander TC101" looks like it was made for TV, Cable and VCR use. Has red LED on indicator that lights up when any button is pushed. We aren't sure of the system that these were made for but we know they are new in manufacturer bags and operate on 2 "AAA" batteries (not included). Size 8" L x 2 3/8" W. Uses 2 IR LEDs and is perfect for making all kinds of IR remote activated projects. Sorry no data or other info available.

G9734 $1.49 ea. 10 for $12.00 100 for $100.00

BLUE LED SPECIAL

This month only, we are offering a pack of four of our bright blue TI (3mm) case blue LEDs for a very special price. These are the nicest brightest cool blue LEDs we have ever had. Our regular price is $2.25 each. Sorry we must limit the sales of these to one pack per order. Hurry sale ends Oct 31,1998 or when our supply is exhausted (if that happens first).

G9732 4 LED Pack $3.00

SONY IR MODULE

Makes IR detection a snap! Can light a LED or operate a relay over 20 ft away. Simple to use. (3 leads with hookup diagram) Matches the IR remote above perfectly! Type SBX1531.

G8155 $1.00 ea. Expires 10-31-98

CALLER ID BLOWOUT

These are used, good condition caller ID units with a large LCD display which shows name and phone # of caller (Unless blocked or out of area). Stores info on up to 72 callers. Operates on one 9V battery (not included). Call phone company to start caller ID service if you don't already have it. Hurry, don't miss out on this value!

G9771 $2.49 ea.

G9680 Modular Cord .79¢ ea. SALE

ELECTRONIC GOLDMINE
PO Box 5408
Scottsdale, AZ 85261

http://www.goldmine-elec.com

NOTE: All items subject to prior sale

For **Phone Orders** Call: **800-445-0697**
or **Fax** Your Orders to: **(602) 661-8259**
For a **Free Catalog** Call: **(602) 451-7454**
Foreign catalog request: send $5.00

Minimum Order: $10 (plus min. $5 Shipping and Handling). We accept MasterCard, Visa and personal checks, however, we cannot accept personal checks on orders outside the U.S. **Minimum Foreign Order Amount:** $50 (plus a minimum $10 S&H)

SUPER CIRCUIT BOARD BLOWOUT



Large (6 7/8"x 5 5/8") circuit board which contains a 6VDC compact electronic buzzer and various ICs including the popular LM386 audio amplifier IC, H11 opto coupler ICs and several other ICs. It also has a dip relay, a miniature color burst crystal and various resistors, tantalum capacitors, diodes, transistors, and a 4.00 MHZ crystal. These are sold for parts only as we have no data or hookup info.

G9740 2 for $1.00 10 for $4.00

Write in 92 on Reader Service Card.

2539 W. 237th Street, Bldg. F, Torrance, CA 90505
Order desk only: USA: (800) 872-8878 CA: (800) 223-9977
L.A. & Technical Info: (310) 784-5488 Fax: (310) 784-7590
OEM INQUIRIES WELCOME

TIMELINE INC.

Over 12 years and 30,000 customers and still growing

Minimum Order: $20.00. Minimum shipping and handling charge $5.00. We accept cashiers checks, MC or VISA. No personal checks or COD's. CA residents add 8.25% sales tax. We are not responsible for typographical errors. All merchandise subject to prior sale. Phone orders welcome. Foreign orders require special handling. Prices subject to change without notice. 20% restocking fee for returned orders.

Liquid Crystal Displays

240x64 dot LCD with built-in controller.
AND 4021ST-EO. *Unit is EL back-lit.* $59.00 or 2 for $109.00 *or*
OPTREX. DMF5005 *(non back-lit)* $49.00 or 2 for $89.00
20 character x 8 line
7¼L x 2½H
The built-in controller allows you to do text and graphics.

Alphanumeric—parallel interface

16x1 ..... $7.00	20x2 ..... $10.00	32x2 ..... $8.00
16x1 (lg. char.) $10.00	20x4 ..... $15.00	40x1 ..... $8.00
16x2 ..... $7.00	20x4 (lg. char.) $10.00	40x2 ..... 2 for $20.00
16x2 (lg. char.) $10.00	24x2 ..... $10.00	40x4 ..... $20.00
16x4 ..... $15.00	32x4 ..... $10.00	4x2 ..... $5.00

5V power required • Built-in C-MOS LCD driver & controller • Easy "microprocessor" interface • 98 ASCII character generator • *Certain models are backlit, call for more info.*

Graphics and alphanumeric—serial interface

size	Mfr.	price	size	Mfr.	price
640x480 (backlit)	Epson	$25.00	480x128	Hitachi	$10.00
640x400 (backlit)	Panasonic	$20.00	256x128	Epson	$20.00
640x200	Toshiba	$15.00	240x128 (backlit)	Optrex	$20.00
480x128 (backlit)	ALPS	$10.00	240x64	Epson	$15.00
			160x128	Optrex	$15.00

6" VGA LCD 640X480, Sanyo LMDK55-22 **$25.00**

Monitors

9" COLOR SVGA MONITOR $179.00
Fully Enclosed – Tilt and swivel type.

Monitors

Non-Enclosed TTL
Comes with pinout. 12V at 1.4 Amp input • Horizontal frequency 15Khz. • Ability to do 40 and 80 column.
5 inch Amber $25.00 • 7 inch Amber $25.00
9 inch Amber or Green $25.00

5" COLOR MONITOR $39.00
• Flat Faceplate • 320 x 200 Dot Resolution • CGA & Hercules Compatible
• 12 VDC Operation • 15.75 KHz Horiz. Freq. • 60 Hz Vert. Sync. Freq.
• Open Frame Construction • Standard Interface Connector • Degaussing Coil included • *Mfr. Samtron*
2 for $69.00

Hacker Corner

Encased Spread Spectrum RF Modem $99.00
The ProxLink Radio Module is a small communication device which replaces cables between RS-232 devices with wireless RF (Radio Frequency) technology. Attaching a pair of ProxLinks to any two devices with three wire asynchronous RS-232 ports allows wireless data transmittal at rates up to 19.2 Kbaud (full duplex) over a range of 500 - 800 feet. Modules use 900 MZ spread spectrum radio for communication which does not require an FCC site license. A variety of configuration information (radio channel, baud rate, serial port configuration, etc.) can be programmed into module's non-volatile memory by host PC to provide compatibility and avoid overlapping systems. Configuration changes are supported by menu driven, on-board software. Commonly used Terminal Emulation software and transfer protocols can be used for configuring modules and transferring data between computers. ProxLinks require only 6-9 VDC (350 mA), RS-232 (9 pin sub - D) interface, and small (~ 4") whip antenna for operation. Unit size is 4.0" x 6.5" x 0.75". Installation schematics and application details available. These are 100 Mw power.

Encased Black & White Composite CCD Camera with Adapter
IR viewing to 1000 nm 7 ½ L x 2 ¾ W x 1 ¾ H
Comes complete with CCD camera, mounting nut on bottom of casing, 12VDC power supply. Excellent low light capability, standard RCA NTSC video out. **$89.00**
Great for: entryway security/remote monitoring, video conferencing/desktop video conferencing **2 for $159.00**

Embedded 486 Computer $99.00

Complete enhanced Intel 486SX-33 based computer in ultra small (9-7/8L x 6-5/8W x 3-1/8H) case. Ideal for embedded operations or as a second computer. Features include: • One 16 bit ISA slot • 3 serial ports plus dedicated printer port • Parallel optical coupled adapter port • Built in IBM PC/AT keyboard port • On board VGA video and port • Uses standard SIMM up to 32 MB • BIOS is PC/AT compatible
Unit has a backup Ni-Cd battery system in case of power failure (5 min. backup time) and lockable front cover to prevent floppy drive access. Mounting / interface provisions for standard 3.5" laptop floppy and 2.5 inch hard drives. Comes with very comprehensive manual.

SONY Miniature Color LCD Display (LCX005BKB) $29.00
• 1.4 CM (0.55 inch) Diagonal Full Color Display • Built In Horizontal and Vertical Drivers • Delta Dot Pattern for High Picture Quality - 537 dots (H) x 222 dots (V) • Compatible with NTSC & PAL Format and Sync Inputs • 12 VDC Operation with -1 to +17 V RGB Signal and Driver Input Voltage • Excellent Display for Virtual Reality Projects, Viewfinders, and Miniature Test Equipment Displays • Pin Outs and Specification Included • Unit Requires Clock, Synchronization and Video

CELL SITE TRANSCEIVER $49.00 2 for $99.00
These transceivers were designed for operation in an AMPS (Advanced Mobile Phone Service) cell site. The 20 MHz bandwidth of the transceiver allows it to operate on all 666 channels allocated. The transmit channels are 870.030-889.980 MHz with the receive channels 45 HMz below those frequencies. A digital synthesizer is utilized to generate the selected frequency. Each unit contains two independent receivers to demodulate voice and data with a Receive Signal Strength Indicator (RSSI) circuit to select the one with the best signal strength. The transmitter provides a 1.5 watt modulated signal to drive an external power amplifier. channel selection is accomplished with a 10 bit binary input via a connector on the back panel. Other interface requirements for operation are 26 VDC (unregulated) and an 18.990 MHz reference frequency for the digital synthesizer. The units contain independent boards for receivers, exciter, synthesizer, tunable front end, and interface assembly (which includes power supplies and voltage-controlled oscillator). Service manual, schematics and circuit descriptions included.

COLOR CCD CAMERA $89.00
• 12 VDC • 1/3-inch, CCD area image sensor • 514 (horizontal) x 491 (vertical) • 2:1 interlaced • 15.734 kHz (horizontal), 59.94 Hz (vertical) • 330 horizontal and 350 vertical lines • 10 lx • 1V, NTSC signal format • Lens: 1/3-inch, fixed focus (F:2.8 f:5.6) • Dimensions: (W) 67 (2.63) x (H) 34 (1.45) x (D) 112.6 (4.43)

Write in 93 on Reader Service Card.

Electronics Q & A

WY-150e Serial 1 Port Assignments (DTE

Pin	Signal	Mnemonic	Direction
1	Ground	FG	
2	Transmit Data	TXD	Out
3	Receive Data	RXD	In
4	Request to Send	RTS	Out
*5	Clear to Send	CTS	In
6	Data Set Ready	DSR	In
7	Signal Ground	SGND	
*8	Carrier Detect	DCD	In
20	Terminal Ready	DTR	Out

Parallel Port Assignments

Pin	Signal	Dir	Pin	Signal	Dir
1	-Strobe	Out	10	-Ack	In
2	+Data 0	Out	11	+Busy	In
3	+Data 1	Out	12	+Paper	In
4	+Data 2	Out			
5	+Data 3	Out			
6	+Data 4	Out	15	-Error	In
7	+Data 5	Out			
8	+Data 6	Out	17	Select	Out
9	+Data 7	Out	18-25	Grounds	

messaging chores over phone lines (they're often used for off-track betting and the like). The parallel port should have been more properly labeled Printer, because that's what it's used for. Anyway, here are the pinouts for all three connectors. For more information on this product, including keyboard commands, contact the Wyse Web site at http://www.wyse.com/ter minal.

TV On PC Monitor

Q. I need to find a way to send composite video (like from a surveillance camera or VCR) to a 15-pin color computer monitor. I don't want to use a computer to process the signal, just a direct connection from the camera to the monitor. The composite video is B&W, so I'm not concerned about getting color on the screen.

Dean Thompson
via Internet

A. *Sure, this is an easy thing to do – but it's not a DIY (do-it-yourself) project. It's far too complex for anything short of a microprocessor-controlled converter, like the AVerMedia TVGenie (**http://www.aver.com/lite/index.html**).*

Why? Because the sweep rates of the VCR and PC monitor don't match. The horizontal scan rate of your VCR runs at the speed of a conventional TV receiver, which is 15.75 KHz. PC monitors have a horizontal scan rate between 30 KHz and 70 KHz – far out of the capture range. Furthermore, the TV screen is interlaced whereas the PC screen is non-interlaced. To convert from TV to PC you first have to separate the horizontal and vertical sync signals from the composite. Next the clock speed has to be doubled so that the 15.75 KHz refresh rate of the VCR becomes 31.5 KHz, which is supported by the VGA monitor. The last step is to remap the pixels to fit the new scan pattern – a task that can only be done by storing the pixels in a memory buffer and meting them out as their number is called. That's exactly what the TVGenie does for just $99.00 ($89.00 without the remote). This unique device is available from CompUSA, Good Guys, and many computer retailers.

Continued on page 93

"Let Us Cover Your Parts!"



- Eye-Catching Enclosures
- Exceptional Value
- Massive Inventory
- Custom Machining
- Quality Silkscreening
- EMI/RFI Shielding
- Over 50 Sizes

Call, Fax, or Visit On-Line for a FREE Catalog
email: simco@simcobox.com

SIMCO

(800) 780-9090 www.simcobox.com FAX (941) 452-6200

Write in 94 on Reader Service Card.

GHOULISHLY GOOD DEALS

TEK 2754, SPECTRUM ANALYZER, 50KHz to 21GHz !!

•Marker and center frequency accy: One part in 10^5, Built in signal processing: •Search, Sort, Mark, Pulse, Signal tracking.• Noise normalization to 1Hz • Memory waveform storage. •Direct keypad entry •Direct plot •1KHz resolution bandwidth



•Sensitivity up to -115dBm • Frequency responce +- 1.5dB @1GHz •Dual inputs, BNC or "N" •GPIB •Printer output• Super nice and in mint condition. New cost over $23000. ***TEK 2754 Spectrum Analyzer.....$3900.***

HP8656B, opt 001 Prog. Synthesized Sig. Generator.

±1 dB level accy, 0.1 dB res. calibrated output levels +13 to -127 dBm. Simultaneous and mixed modulation modes from internal (400 Hz and 1 KHz tones) or external sources. •100kHz to 990MHz freq. range. •AM and FM modulation •±1 dB level accy. •Amplitude offset & phase adjustments. •Resolution: 10



Hz, Timebase aging rate: ±2 ppm/year (typ) •Absolute accuracy: +7 dBm at 0.1 to 990 MHz •HP-IB, 100 Save/recall/sequence registers. •Size: 5.25 in x 16.75in. x 20.5 in., Weight: 40 lb, Mint condition.

HP8656B, opt 001 Signal Generator.....$1800.

TEKTRONIX 2465A/DM, 400 MHz, 4Chan. O'scope

Super 400 MHz four-channel scope. Sens: 2 mV at 400MHz. Risetime all channels: is 0.875 ns. Sweep: 500ps/Div. Voltage & Time cursors, screen readout. 1 Mohm /50-ohm input. Digitize, store and recall waveforms. Auto Setup, Sequencing & more. Accessories: 10X Probes (2), Pouch, Ops Manual, Cover, Pwr Cord. Option 01 = Digital Multimeter Option 05 = Video Waveform Measurement



Option 06 = Counter/Timer/Trigger Option 09 = Counter/Timer/Trigger and Word Recognizer Option 10 = IEEE 488 GPIB Interface. Mint condition.

TEKTRONIX 2465A/DM.....$2895

TWO MINI C-MOUNT CAMERAS, The super sensitive, GM410 or the general purpose GM412,

The GM-412 specs: B&W, size 1.5"sq. X 2.4"L, 250,000 Pixels, **380** Lines Resolution, Sensitivity **0.3** Lux, The GM410 specs: size only 1.5" SQ. x 1.6"L, >270,000 Pixels, **410** Lines Res., Sens. **0.05 LUX.**, Both cameras are 1/3" CCD with AGC & Electronic shutter. 12V @110mA power. NTSC out. IR SENSITIVE, BNC video out, Both use std. DC pwr. jack. Aluminum housings with dual threaded top and bottom mounting. True performance not hype! These cameras will outperform ***ANY*** camera in this magazine. Multi- lens options are available to exploit their superior performance. **GM412, less lens..$119, GM410, less lens..$169**

C-MOUNT LENS OPTIONS to ENHANCE YOUR IMAGE:

Fast Lenses for Low Light or General Purpose Normal Light

16mm, f1.6, 15° FOV $39	**4mm, 80° FOV $24**
8mm, f1.3, 30° FOV $49	**8mm, 40° FOV $24**
4mm, f1.4, 56° FOV $49	**12mm, 28° FOV $24**

PRICE BUSTER, DSP, COLOR, MINI C-MOUNT, CAMERA,

Brand New, model GM859, Size only: 2" x 2" x2.5"L, Latest 1/4" CCD technology. Res. 350 lines, sens. , <3lux, auto white balance, AGC. Auto iris connector. 9-12VDC @150ma power. BNC video out. Switchable gain. Superior cast aluminum housing with top and bottom mounting. Perfect for general surveillance. Less lens. Lens options listed below. **Reg. $299**

Save $100, GM859.....$199

SUPER! UNDERWATER (60 ft.) "LIPSTICK" CAMERA with INTEGRAL INFRA-RED ILLUMINATOR!

Sleek black anodized, BRASS, housing is O-Ring sealed & WATERPROOF. Adjustabe mount included. Specs: 1/3" CCD, 400 Lines resolution, 0.05 Lux sensitivity, AGC, Auto Shutter. Operates on 12VDC @225mA, 3.6mm, 92° FOV lens, A real glass lens. NTSC video out. Superior construction. SENSITIVE to IR. Ultra small Size only: 1.25"diam. X 2" long. With 60 ft. cable. Great for general outdoor use also.

REG. $299, **GM-300KIR.....$219**

END FIELD of VIEW GUESSWORK! 3.5 to 8mm VARIABLE FOCAL LENGTH LENS.



Brand New, super f1.8 lens allows you to smoothly adjust from a 97° FOV @ 3.5mm to a 44° FOV @ 8mm. Now you can frame your area of interest just the way you want it! Or use it as a tool to select a fixed lens of the proper field of view. Either way a handy item to have. Standard C-Mount with adjustable focus and iris.

SPECIAL.... $99ea. or 2 for $189

NEW! PRICE BUSTER...GM8-BQ, 2- PAGE REAL TIME, VIDEO QUAD

The GM8-BQ B&W quad processor, is an unbeatable value. The system offers 4 or 8 camera inputs. Full screen image, single or dual-page REAL TIME quad display, super high resolution: 960 x480, Independent brightness adj. for each chan. Alarm time (1-20 sec.) 8 alarm inputs. Auto Sequencing mode w ith adj. dwell:1-4 sec. User-friendly panel. Real quality video processing and a truly remarkable price. Specs: • 8 video inputs. •Video output: 1 monitor out and 1 quad out, •Quad Display: Single page or dual page switch. • Alarm input: 8 alarm inputs •Buzzer: Yes •Alarm output: 2 Alarm Out •Dim: 239 x166 x55 mm. •Pwr: AC 24V

SPECIAL! PRICE BUSTER, GM8-BQ.....$299ea.

MOTORIZED PAN and MOTORIZED TILT,

Now you can remotely PAN and TILT your video cams. Vicon model 3030 indoor units are NEW and operate on 24VAC provided. The complete system includes Pan & Tilt controller with internal power supply Easy hookup info included. Max load 7.5Lbs. Size: 5.25"W x 5.25"L x 5.25"H Approx. -10 ,to +50 deg. of tilt. Commercial quality unit.

VICON 3030.....$249

CHECK THIS! ULTRA MINI and WEATHERPROOF

Our "LIPSTICK" camera sets new standards. Sleek black anodized, aluminum, housing is O-Ring sealed & RAINPROOF. Adjustable tilting mount included. Specs: 1/3" CCD, 380 Lines resolution, 0.3 Lux sensitivity, AGC, Auto Shutter. Operates on 9 to 12VDC @100mA, 3.7mm, 90° FOV lens, A real glass lens. NTSC video out. 1/2 once! SENSITIVE to IR. Ultra small Size only: 23mm diam. X 50mm long. With 36" leads.

GM-200KSTD...$119 pwr. adapter..$4.95

"EMBEDABLE", PINHOLE LENS, "BULLET CAM" it's INCREDIBLE !

So tiny you can install it right into a door with merely an 0.9" diameter hole. Sleek black anodized, extruded aluminum housing. Similar construction as the lipstick camera above only smaller! 1/3" CCD, 410 Lines Res., 0.3 Lux sens., AGC, Auto Shutter. Power from 9 to 16VDC @100mA, 250k PIXELS, 90° FOV Pinhole lens. A real glass lens. Std. NTSC video out. 1/2 once! SENSITIVE to IR. Size only 23mm Diam. x 35mm long. With 36" leads. Think of the places you could put this little jewel. **GM-200KPH lens....$129**

NEW MICRO CAMERA, w/audio 1/3" CCD,

410 Lines Res., 0.3 Lux sens., AGC, Auto Shutter. Pwr. from 9 to 12VDC @100mA, 250k PIXELS, Std. model, 3.6mm, 92° FOV lens, Pinhole, 90° FOV. A real glass lens. Both focus from 10mm to infinity. Std. NTSC video out. 1/2 once! SENSITIVE to IR. Size Std: 1.25"sq. x 1"d. PH is 0.6"d, Both with 6" leads. **WARNING:** Don't confuse these models with LOW RESOLUTION, HIGH LUX C-MOS CAMERAS.

GM-1000A-STD.....$80	**GM-1000A-STD/Audio.....$85**
GM-1000A-PINHOLE.....$80	**GM-1000A-PH/Audio.....$85**
GM-1000A-C-MOUNT...$80	**GM-1000A-CMNT/Audio.$85**

C-Mount f2.0 Lenses	Micro Lenses for GM1000 series
4mm, 80°.....$24	2.5mm, 150°.....$22
6mm, 60°.....$24	4.3mm, 78° f1.8.....$22
8mm, 40°.....$24	6.0mm, f2.0.....$22
12mm, 28°.....$24	8.0mm, f2.0.....$22
	12.0mm, f2.0.....$22
	5mm, 70°PH.....$22

Please fax us your list of unique surplus material.

SONY, COLOR CONFERENCE CAMERA, 450Line, 8X, NTSC & Y/C OUT,

Serial Control of Pan, Tilt, Zoom, Auto Iris and Auto Focus too! Like having your own R2D2. Intended for use in fortune 500 board rooms. The video performance is stunning. Superior to almost anything we have seen. Camera and lens is an integral assembly. Excellent Condition. Rugged black ABS enclosure. 8 pin mini-DIN & Std. SVHS jack. Size: 8"Dx6.5"H. Sorry, we have no data on using the serial port. The units self test on power up and the video is active. Reg price over $4K **SPECIAL PRICE....$289ea.**



Brand New, Video Motion Sensor.

Model VM10. Attach to any standard video signal and you've got an electronic "watchman" diligently watching the entire scene. Or any adjustable sized area within the scene. Such as a doorway or even a drawer or cabinet. A state of the art security aid. The unit will close a contact when it senses a change. Use it to turn on a VCR or call the hounds. Auto or manual reset. Compact, ac powered. Adjustable sensitivity. Video loop through jack. **NEW VM-10.....$189.**

PRICE BUSTER, DSP, COLOR CAMERA,

Brand New, model GM550, Size: 1.6" x 1.6" x1.5"L, 1/3" CCD with SONY CCD & DSP technology. 4mm, f1.8 glass lens, 80° FOV. Resolution >350 lines, sensitivity, 0.3lux, AWB, AGC & auto electronic shutter 1/60 to 1/10,000 sec. Pwr. 12VDC @160ma. NTSC out. Budget color surveillance.

Reg. $269, SPECIAL GM550....$149ea.

MOTORIZED ZOOM LENSES, Up to 10X mag. and auto iris !

New, fabulous hi-res. optics with std. C-Mount. Superior Fujinon and Vicon lenses. Normally cost from $600 to $1500. There is no substitute for a good lens! All drive motors will operate from 6-12VDC. The Auto iris models have a built in amp which uses the camera video output for control. They will work with any camera whether or not it has an "auto Iris" connector.

Type A-10, 11 to 110mm, 10X, f1.8	$399
Type B-6, 12.5 to 75mm, 6X, f1.2	$229
ZOOM LENS CONTROLLER, NEW	$169

10V @ 2.5 AH SEALED, LEAD ACID, PACK

Each pack consists of five, 2 Volt cells. Each cell the size of a std. 'D' battery. They are arrainged as 1X5 cells. Enclosed in an ABS outer shell. (removed for photo) Mint condition. Perfect for robotics and other high drain applications. Buy several, make custom packs of any rating. Size: 7.5"L x 2.8"H x 1.5"D

5-five packs for $20, 30 for $99

WORLDS SMALLEST ••• 100mW ••• VIDEO TRANSMITTER,

Incredibly only 0.98" x 0.8" x 0.037" in size. Transmits crystal controlled hi-res. images with 100mW output! The transmitter you've been waiting for.

Shown actual size. Much smaller than the 9V battery which powers it. Draws only 35mA! Factory tuned ready to receive on cable channel 59. Will work with color or B&W cameras. UHF Bow tie antenna with balun and 3' F cable for TV Included. Perfect with our GM1000A cameras. Both will fit in a cigarette pack....with the battery! The best deal anywhere.

TVX-100...$199. with GM1000A-PH CAM...$279.

YOU CAN NEVER BE TOO THIN or TOO POWERFUL.

Unique "Thinline Energy Cell from Portable Energy Products. Their model PLA02V50. A super thin, high performance, patented technology, sealed lead acid battery. Each cell provides 2V@5AH. Their size is an amazing 3.1" x 5.3" x 0.3" thick! They can be mounted in any orientation. Can line the bottom of a briefcase or be covertly worn on the body. 30% higher energy density than conventional lead acid batteries. **Price 6 cells for $15 or 24 for $49**

RESOURCES UN-LTD.

300 BEDFORD STREET , MANCHESTER, NH 03101

VISA, MC, AMEX, DISCOVER, COD. ORDER: 800-810-4070 TECH. 603-668-2499 ORDER FAX: 603-644-7825 E-MAIL unltd4u@tiac.net

Write in 78 on Reader Service Card.

SPI and the Printer Port

by Karl Lunt

A small DOS-box computer doesn't leave you many options for attaching external devices such as sensors. Basically, you can use the serial ports or the printer ports. The serial ports work best for terminal-type equipment such as modems or RF links, but the printer ports can really shine when you need to hook up several medium-speed I/O devices.

In this article, I'll show you how you can add up to eight devices to a single printer port, using little more than a ribbon cable and some C software.

The SPI

Traditionally, hobbyists have used a printer port to drive ICs such as an eight-bit latch. This simple hookup lets you control eight latch output lines just by writing a value to the parallel port. But if you need more I/O capability, such as more latch output lines or even a few input lines, you end up with a much more complex design. The older parallel ports only had a few input lines, and even the newer Expanded Parallel Port (EPP) units aren't all that easy to use if you need a lot of input lines.

This I/O limitation hasn't stopped hobbyists from developing some clever designs, of course. One of the better projects that I've seen wired into a parallel port was a device that could read and write GameBoy game cartridges. I discussed this project in detail in a past *Nuts & Volts* Amateur Robotics column; you can look through your stack of back issues, or do a web search for GameBoy and ReadPlus (the name of the reader).

But to get the most mileage out of your parallel port, consider using it to drive a synchronous serial bus such as Motorola's Serial Peripheral Interface, or SPI.

Hooking up an SPI device, such as a latch, requires only three lines plus ground; a total of five if you include +5 VDC to drive the device. More importantly, each SPI peripheral needs only one dedicated printer output line. This means you can add up to eight SPI devices to a printer port.

Since the SPI bus is bidirectional, you can use any mix of input, output, or bidirectional devices you need. This means you wouldn't have any problem driving, say, 32 channels of A/D, a couple of eight-bit latches, and a pair of frequency synthesizers off of a single parallel port.

The SPI achieves this high capability because of the way it distributes data. All devices use the same serial input line, the same serial output line, and the same serial clock line; this last signal lets two devices synchronize bus operations. The device controlling the bus — known as the master — uses a dedicated line to each other device as a select line; bringing a select line low activates the device on that line. Only the selected device — known as a slave — will listen or respond to the host.

For example, if the master (your PC) wanted to exchange data with SPI device 3, it would bring printer output port line 3 low, leaving all other output lines high. Then, your PC could freely send commands serially over the common output line; only device 3 would process the commands. Similarly, your PC could receive data from the common input line, knowing that any data received would have been sent only by device 3.

The SPI exchanges data between two devices simultaneously. This means that each time the master sends a bit to the selected slave device, the master also reads a bit from the slave. The master device must provide the serial clock signal used by both devices for synchronizing this data exchange.

Putting this another way, no

DB-25 male (front view)



Pin	Signal	Direction (from PC)	Port & Bit
1	*Strobe	Output	Control, D0
2	D0	Output	Data, D0
3	D1	Output	Data, D1
4	D2	Output	Data, D2
5	D3	Output	Data, D3
6	D4	Output	Data, D4
7	D5	Output	Data, D5
8	D6	Output	Data, D6
9	D7	Output	Data, D7
10	*ACK	Input	Status, D6
11	*Busy	Input	Status, D7
12	PaperEmpty	Input	Status, D5
13	Select	Input	Status, D4
14	*AutoFeed	Output	Control, D1
15	*Error	Input	Status, D3
16	InitPrinter	Output	Control, D2
17	*SelectIn	Output	Control, D3
18-25	Ground		

THE SIGNALS AVAILABLE ON A PC PARALLEL PORT.

NEW PRODUCTS from IndustroLogic™

SMD-12 Stored Message Display $179

Display messages with switch closures or serial port. Twelve 32 character scrollable msgs, 8 character .56" green LED display, enter messages via internal keypad or serial port. 5.75"W x 2.75"H x 6"D. 20 oz. Stud mounted steel case incl.



SIO-1000 RS-232 Data Acquisition Interface Board $179

8 digital in, 8 digital out, dual 12 bit analog inputs & outputs, 10KHZ counter in, frequency out. WIN/DOS software, cable, ABS enclosure, power supply. 4.25" x 6.5" x 1.5" high. 12 oz.

Industrologic, Inc.
3201 Highgate Lane
St. Charles, MO 63301

(314) 707- 8818
9AM-5PM Central

Visit our web site to download complete product documentation:

www.industrologic.com

Write in 71 on Reader Service Card.

ELECTRONIC TOOLS ETC.

TWEEZERS,FORCEPS,SCISSORS
*PROBES(DENTAL PICKS)
*DREMEL® TOOLS,ROTARY TOOL EQUIPMENT
*OPTICAL AIDS(MAGNIFIERS)
*SCREWDRIVERS,TIPS,BITS
*PLIERS,ALL SHAPES,SIZES
*NEW,HARD TO FIND TOOLS EVERYDAY

TOLL FREE: 1-888-UTOPIA-2

SAVE $ HERE!

UTOPIA TOOLS
CALL OR WRITE
3899 BARNARD DR.
APT.#519
OCEANSIDE CA
92056
CALL:
(760)439-6682
FAX:
(760)439-6682

CALL NOW FOR FREE CATALOG



TIMING DIAGRAM SHOWING THE RELATIONSHIP BETWEEN CPOL and CPHA. MASTER SENDS BINARY 1001 TO SLAVE.

data are exchanged unless the master provides the necessary clocking pulses. This means that the master must always send something to the slave, even if the master just wants to read a byte of data.

Note that the SPI format doesn't prevent you from sending commands to more than one device at a time, should that be necessary. Just have the master pull all the necessary select lines low before sending any commands. However, this is a fairly rare occurrence. Generally, your software will deal with only one active device at a time.

There are some subtle timing requirements that you have to respect when using the SPI; refer to the sidebar for details. In a nutshell, though, the above paragraphs show that little is involved in moving data between a host device such as a PC and any of several different SPI devices on a bus. Anyone using the Motorola microcontrollers (MCUs), such as the 68hc11, likely will have already used or read about the SPI; it is built into almost all Motorola MCUs. Other chip makers, such as Atmel, also sell MCUs with built-in SPI.

The printer port

I've discussed the SPI in some detail, now I'll turn my attention to the printer port. In its simplest form, this is a multi-wire bidirectional port to the world; your PC software sees this port as three consecutive I/O registers. The first of these three registers is the data port, a byte-wide output port that your software can write to change the states of eight lines. The next higher register is the status port, a byte-wide input port that your software can read to sense the states of various signals from the printer. Finally, the control port is a byte-wide output port that your software can write to change the states of various signals to the printer.

Each printer port, known to your PC as LPT1 through LPT4, occupies three consecutive addresses beginning at any of three common I/O addresses, $3bc, $378, or $278. For example, if your PC assigns LPT1 to I/O address $3bc, then your software would use $3bc as the data port, $3bd as the status port, and $3be as the control port. The PC's BIOS

```
#include <stdio.h>
#include <conio.h>
#include <dos.h>
#include <stdlib.h>


#ifndef TRUE
#define FALSE 0
#define TRUE 0xffff
#endif

unsigned int            dataport;
unsigned int            controlport;
unsigned int            statusport;
unsigned char           controlvalue;
unsigned char           datavalue;
unsigned int            waits;
unsigned char           buffer[128];
unsigned char           cpol;
unsigned char           cpha;
unsigned char           MSBFirst;
unsigned int            addata;                 // returned a/d value
float                   fdata;
float                   fullscale;


void  SetMOSI(unsigned char  value);
void  ForceSCK(unsigned int  v);
unsigned char  ToggleSCK(unsigned char  in);
void  DeselectAll(unsigned char  value);
void  ToggleSelects(unsigned char  mask);
void  SetFormat(unsigned char  phase, unsigned char  polarity);
unsigned char  ExchangeSPI(unsigned char  value);


void  main(int argc, char *argv[])
{
        unsigned int            n;
        unsigned char           c;

        dataport = 0x378;                       // assume LPT1
        statusport = dataport+1;
        controlport = dataport+2;
        waits = 0;
        MSBFirst = TRUE;
        fullscale = 4.096;                      // for max1204 A/D
        if (argc > 1) {
                for (n=1; n<argc; n++) {
                        if (*argv[n] == '/') {          // if this is an argument...
                                c = *(argv[n]+1);       // get argument char
                                switch (c) {            // based on argument char...
                                        case 'w':
                                        waits = atoi(argv[n]+2);  // get number of wait
states
                                        break;
                                }
                        }
                }
        }
        DeselectAll(0xff);                      // all selects are active-low
        SetFormat(0, 0);                        // format: cpol=0, cpha=0
        while (!kbhit()) {                      // until user hits a key...
                printf("\r");
                ToggleSelects(0x01);                    // select device 0
                ExchangeSPI(0x8e);                      // chnl 0, uni, single, internal clk
                addata = ExchangeSPI(0x00);             // get msb of data
                                        addata <<= 8;   // move msb to top
                addata += ExchangeSPI(0x00);            // add lsb
                addata >>= 5;                           // finally, align data properly
                ToggleSelects(0x01);                    // deselect the device
                if (addata == 0x3ff) {                  // if all bits set...
                        printf("Overrange!");
                }
                else {
                        // no, got valid data
                        fdata = fullscale * ((float)addata / 1023.0);
                        printf("Data: %7.3f ", fdata);
                }
        }
        getch();                                        // clear kbd buffer
        printf("\n");
}


void  ForceSCK(unsigned int  v)
{
        unsigned char                   n;

        if (v) {                                        // if SCK should be high...
                controlvalue &= 0xfe;                   // *STROBE = 1 (active-low)
        }
        else {
                controlvalue |= 0x01;                   // *STROBE = 0 (active-low)
        }
        outportb(controlport, controlvalue);
        for (n=0; n<waits; n++) {
                outportb(controlport, controlvalue);
        }
}


unsigned char  ToggleSCK(unsigned char  in)
{
        unsigned char           v;
        unsigned char           n;

        if (!cpha) {                                    // if CPHA = 0...
                SetMOSI(in);                            // need to set MOSI now
                v = inportb(statusport);                // get value of MISO
        }
        outportb(controlport, controlvalue ^ 0x01);
        for (n=0; n<waits; n++) {
                outportb(controlport, controlvalue ^ 0x01);
        }
        if (cpha) {                                     // if CPHA = 1...
                SetMOSI(in);                            // need to set MOSI now
                v = inportb(statusport);                // get value of MISO
        }
        outportb(controlport, controlvalue);
        for (n=0; n<waits; n++) {
                outportb(controlport, controlvalue);
        }
        return  (v ^ 0x80) & 0x80;                      // invert *BUSY and strip other bits
}
```

records the assignment of each printer port to its I/O address in a table stored in RAM at address 0040:0008.

To look at the printer assignments of your PC, go to a DOS prompt and fire up the DOS debug program. When you get debug's prompt, enter the command:

d 0040:0008 L8

debug will respond by printing out the eight bytes of data stored at that address. The first pair of bytes gives the I/O address of LPT1, the second pair gives the I/O address of LPT2, etc. Note that since the PC uses an Intel-style processor, the I/O addresses are stored LSB first, so you will need to reverse the order of the two bytes in each address to determine the true I/O address.

Knowing how to use this table means your software can look up the I/O address associated with any desired LPT port, even if the BIOS or some other program switches port assignments at some time. This is important, because to control SPI devices using a printer port, your software must perform low-level accesses to the I/O registers.

Obviously, you want your software to bang the lines of the correct port, lest your laser printer suddenly go wacko and start spilling paper all over the place.

With most of the basics out of the way, we can start looking at the available lines on the printer port, to assign these lines to the necessary functions we need to support an SPI bus. Refer to the accompanying table of signals available on the printer port for details.

The most important line in the SPI bus is SCLK, which acts as the system clock signal. We will be bit-banging all of the SPI signals from the PC, so we could choose any line we want as our SCLK signal, but probably the easiest to remember is *Strobe. This signal appears on the printer connector as pin 1, and in the parallel port registers as bit 0 of the control port. Note the leading asterisk in the signal name, *Strobe. This indicates that this signal is active-low.

From the software viewpoint, you have to write this bit with the inverse of the desired signal. Thus, to pull *Strobe low, your software must set bit 0 of the control port high. Similarly, writing a 0 to bit 0 of the control port will bring the *Strobe output line high. This can take a little getting used to, but one function will be used for all manipulations of *Strobe, so you only have to get this concept right once, then you can forget about it for the rest of the program.

Next up, we need a signal to act as MOSI, the master device data output line. I chose *AutoFd, which is bit 1 of the control port and pin 14 of the printer connector, for this function. As with *Strobe, discussed previously, this is an active-low signal, so you have to write the inverse of the desired value whenever your software manipulates this bit.

Then we have MISO, the master device data input line. I chose *Busy for this signal because the documentation I was using for my design indicated that this line was active-high, meaning that my software wouldn't have to deal with the inversion discussed above. Unfortunately, the documentation was wrong; *Busy is active-low. I only discovered this after completing the software and seeing the inversion in my tests.

Rather than rewrite the software and mod the hardware at this point, I just added the inversion to the code and left *Busy as my MISO line. If you decide to rewrite my software, you might switch lines for MISO; PaperEmpty or Select might make better choices. For now, my code uses *Busy, which is bit 7 of the status port and pin 11 of the printer connector.

All that remains is assigning the SPI select lines. This software uses output lines D0 through D7 as the eight device select lines

Data Port (I/O address offset 0)
Output only from PC

D7	D6	D5	D4	D3	D2	D1	D0

Status Port (I/O address offset +1)
Input only to PC

*Busy	*ACK	PE	Select	*Error	*IRQ	---	---

Control Port (I/O address offset +2)
Output only from PC

---	---	Dir	IRQEnb	*SelectIn	Init	*AutoFd	*Strobe

THE THREE REGISTERS OF A PC PARALLEL PORT.

```
/*
 * DeselectAll     bring all chip selects to deselected state
 *
 * This routine accepts an unsigned char that indicates all
 * devices are not selected.  After writing this value to the
 * LPT data port, this routine saves the value in a global
 * variable for later use.
 */

void  DeselectAll(unsigned char  value)
{
        unsigned char                   n;

        datavalue = value;
        outportb(dataport, datavalue);
        for (n=0; n<waits; n++) {                       // for all wait states...
                outportb(dataport, datavalue);
        }
}



/*
 * ToggleSelects     toggle one or more chip.select lines
 *
 * This routine changes the chip select byte written to the
 * LPT data port.  Upon entry, the pattern in argument mask
 * is used to toggle bits in the current global value
 * datavalue.  This value is then sent to the LPT data port,
 * with waitstates.
 *
 * Note that you don't use this routine to turn bits on or
 * off, only to toggle them.  Thus, this routines serves as
 * both a device select and a device deselect routine.
 */

void  ToggleSelects(unsigned char  mask)
{
        unsigned char                           n;

        datavalue ^= mask;              // set the selected pattern
        outportb(dataport, datavalue);  // set it up
        for (n=0; n<waits; n++) {       // do the waiting
                outportb(dataport, datavalue);
        }
}



void  SetFormat(unsigned char  phase, unsigned char  polarity)
{
        cpol = polarity;                                // record clock idle state
        ForceSCK(cpol);                                 // set clock to proper idle state
        cpha = phase;                                   // record CPHA setting
}



void  SetMOSI(unsigned char  value)
{
        unsigned char                           n;

        if (!value) {                                   // if sending a 0...
                controlvalue |= 0x02;   // set MOSI to 0 (active-low)
        }
        else {                                          // nope, must be 1...
                controlvalue &= 0xfd;   // set MOSI = 1 (active-low
        }
        outportb(controlport, controlvalue);
        for (n=0; n<waits; n++) {               // wait it out...
                outportb(controlport, controlvalue);
        }
}



unsigned char  ExchangeSPI(unsigned char  value)
{
        unsigned char                           v;
  unsigned char                         n;
        unsigned char                           indata;

        indata = 0;
        if (MSBFirst) {                                 // if sending MSB first...
                for (n=0; n<8; n++) {   // for all bits in byte...
                        v = ToggleSCK(value & 0x80);    // clock it
                        indata <<= 1;                   // move new data left one bit
                        if (v)  indata += 1;            // add the bit we just read
                        value <<= 1;                    // now move out byte left
                }
        }
        else {
                for (n=0; n<8; n++) {   // no, sending LSB first...
                        v = ToggleSCK(value & 0x01);    // clock it
                        indata >>= 1;                   // move new data right one bit
                        if (v)  indata += 0x80;         // add the bit we just read
                        value >>= 1;                    // now move out byte right
                }
        }
        return  indata;
}
```

C PROGRAM



SCHEMATIC FOR CONNECTING A MAX1204 A/D CONVERTER USING THE PC'S PARALLEL PORT

supported by this project. This makes it easy to remember which device goes to which connector pin. If you need even more SPI devices hooked to your port, you can write extra code that uses the last two control lines, *InitPrinter and *SelectIn, to add two more devices.

Now it's time to get into the software. Refer to the accompanying listing of my C program. This is not a finished piece of software, so I've cut a few corners. I encourage you to build on this program to make it better for your own application.

I compiled this code using Borland C/C++, version 4.52, as a DOS standard application using the large memory model. The only non-ANSI feature that I'm aware of in this program is the use of the outportb() library function, which writes a byte to the desired I/O port, but most compilers support a similar function. Refer to your compiler's manual for details.

The program's main() function begins by assigning default values to several important variables. The variable **dataport** holds the base address of the parallel port's I/O registers. The value written here, 0x378, serves as the I/O address of my system's LPT1. As you can see, I have not implemented the BIOS lookup scheme described above. Feel free to add the lookup yourself, if you choose. If not, at least use a utility such as Microsoft's MSD to locate the I/O address used by your target printer port, and change the value written to **dataport** accordingly.

The variable **waits** is vital to the proper operation of this program, and deserves study. Most SPI devices run at a top clock speed of one to two Mbits per second. The newer PCs, however, can pump data out the printer port at much higher rates than the SPI devices can handle. In order to slow the newer machines down so the SPI devices can keep up, I've added a wait-state feature. **waits** holds the number of wait-states to insert in any SPI bus operation.

On my little 486 DOS-box, which I use for data collection, this program can only change the SPI SCLK line at about 500 KHz, well within reach of most SPI devices. The default value of **waits**, which is 0 in this code, is good enough for my little system. You can change the value of **waits** on the command line by using the **/wxxx** option, where **xxx** is the number of wait-states you want to insert.

Adding wait-states gets a little tricky. You can't use a simple counting loop, as some compilers will optimize out such loops, and the newer machines run too fast to make such loops meaningful.

To insert wait-states, my code simply repeats the most recent I/O operation **waits** times. I/O operations are timed independently of the PC's CPU, so each wait-state will actually occur, and will be of a known duration.

For an example of how the wait-states are inserted, look at the code in ForceSCK(). It is an instructive exercise to hook an oscilloscope to your printer port's *Strobe line, then run this program with different values for **waits** and watch the effect of the wait-states on the SCLK pulse length.

I've included the routine SetFormat() so you can quickly change the active SPI format. You might have devices hooked to your printer port that require different SPI polarities or phases, and this routine lets your software adjust the system's format before beginning a transfer. I've also added routines for controlling the eight printer data lines, used as SPI device select lines.

The function DeselectAll() allows you to write a value to the data port that turns off all SPI devices. Since your design might use a mix of active-high and active-low SPI devices, DeselectAll() allows you to pass a value that constitutes all devices off. Another routine, ToggleSelects(), lets your software change the state of particular SPI device select lines. Note that you don't specify whether the line goes high or low, only that it changes. Your software can blend usage of DeselectAll() and ToggleSelects() to control the SPI devices without having to know what state any device select line should be in.

Taking the bus for a SPIn

All of this software doesn't mean beans until you actually hook up a device. You have a bewildering assortment of SPI devices available to you. Perhaps the most commonly used SPI device is the 74hc595 serial-in/parallel-out octal latch. I've done a couple of articles on hooking this device to the SPI; see some of my earlier *Nuts & Volts* Amateur Robotics columns for details on using this chip to drive, for example, a liquid-crystal display (LCD).

But hooking up yet another '595 seemed so boring, considering the number of other possible choices. So I plugged into Maxim's web site at **www.maxim-ic.com** and started looking around for cheap A/Ds. After a few minutes, I settled on the MAX1204, an eight-channel 10-bit serial A/D that needs a single +5 VDC supply to operate.

Maxim has built some nice features into this chip. One feature I like in particular allows you to configure it as either eight single-ended analog inputs, or four differential inputs. You can even mix and match, should you need, say, five single-ended and one differential.

You can order a couple of these devices directly from Maxim, via their samples desk. The device is also available from Digi-key for about $4.50 each.

Inside the SPI

Motorola's Serial Peripheral Interface (SPI) uses three bus wires and additional chip-select lines to implement a synchronous bus that runs at speeds in excess of one megabit per second. Widely used in the embedded control industry, the SPI makes a good choice for moving high volumes of data across short distances (less than one foot) or among several different devices. The following paragraphs describe the various signals used in the SPI bus.

SCLK (or SCK) is the main clock signal for synchronizing data transfers between the master device and the selected slave device. This signal is provided by the master device. SCLK may idle either high or low. To generate a clock pulse, the master device momentarily brings SCLK to the active state, then returns it to the idle state. Each such clock pulse constitutes a single bit time, used to synchronize the exchange of one data bit.

MOSI (master-out-slave-in) is the SPI output line from the master device. At the correct point in each clock pulse, the master device outputs a level on MOSI corresponding to the bit value to send to the slave device. MOSI is connected to the input lines on all slave devices on the bus. The selected slave device will sample the value of MOSI at the correct point in each clock pulse to determine the value of the data bit sent by the master device.

MISO (master-in-slave-out) is the SPI input line to the master device. MISO is connected to the output lines of all slave devices on the bus. At the correct point in each clock pulse, the selected slave device outputs a level on MISO corresponding to the bit value to send to the master device. The master will sample the value of MISO at the correct point in each clock pulse to determine the value of the data bit sent by the slave device.

***CS** is the chip-select line used by the master to select a slave device. Generally, the master must provide a single chip-select line for every slave on the SPI bus, though some bus configurations can use one chip-select line to control multiple slave devices. By convention, SPI slave devices use an active-low chip-select line, though some SPI devices, such as the Dallas DS1305 real-time clock, use an active-high select line. The master leaves all chip-select lines in their inactive states until a data exchange is required. At that time, the master drives the proper chip-select line to its active state, selecting that slave device. After exchanging one or more bytes of data with the slave device, the master returns that select line to its inactive state, deselecting the slave device.

The timing for data exchange on the SPI bus depends on the SCLK signal and the agreed-upon format between the master and slave devices. The two devices may use any of four different timing formats, based on the idle state of SCLK (either high or low) and which edge of SCLK (either leading or trailing) marks the presence of valid data. Motorola refers to these two criteria as CPOL and CPHA. CPOL, or clock polarity, is 0 if SCLK idles low or 1 if SCLK idles high. CPHA, or clock phase, is 0 if data are valid on the leading edge of SCLK or 1 if data are valid on the trailing edge. Thus, an SPI bus that uses the format CPOL=0 and CPHA=0 relies on SCLK idling low, with data valid whenever SCLK changes from low to high.

As you can see from the accompanying schematic, the wiring is dirt simple; you get eight channels of A/D for little more than a couple of caps and a socket. I've added a trimpot (R1) and current-limiting resistor (R2) to channel 0 so I can dabble a little.

Note that the *CS line — pin 18 — connects to only one of the Dn lines on the printer port connector; if you want to use this schematic with the software listed here, hook *CS to printer connector pin 2 (D0). Also make sure you hook at least one of the ground lines on the printer connector (pins 18 through 25) to the ground line in the schematic. You will also need to supply a source of +5 VDC for this MAX1204; this can be a wall-wart or a set of batteries with a suitable voltage regulator.

The physical layout of this circuit is not critical; you could make up a little printed circuit board (PCB), or just use one of the RadioShack experimenter's boards. I chose to build my circuit on one of those white plastic prototyping blocks, offered by a number of mail-order vendors.

The tricky bit involves hooking wires to the printer connector. I opted to start with a 18-inch long 26-pin ribbon cable, available surplus nearly anywhere for a buck or so; mine even had a female 26-pin IDC connector on one end.

I stripped back the 26th wire from the opposite end of the cable, then pressed a male IDC DB-25 connector onto that end. This gave me a ribbon cable of suitable length, with one end I could plug into the LPT port of my PC and another end that I could plug into a 26-pin male dual-row header.

All that remained was coming up with a dual-row header that I could plug into my prototyping block. I started with a 26-pin wirewrap header gleaned from my junk box. Working carefully with a set of needle-nose pliers, I bent each of the long 26 pins to the proper shape. When complete, I had widened the gap between the two rows of long pins so the header would straddle the wide channel down the center of my prototyping block. When I plug the header into the block, each pin is isolated from the others.

Now I can plug the 26-pin female connector on the end of my ribbon cable into the prototyping block and complete my wiring. Note that such modified dual-row headers are also available from several mail-order houses, if you don't feel like taking the time to construct your own.

With the wiring complete, I just needed to add some code to my program that is specific to the MAX1204 A/D. See the code in routine main() for details. After some setup, all of the code for reading and processing the MAX1204 is handled by the large while-loop at the bottom of main().

To take a reading, my software first toggles select line 0, then uses ExchangeSPI() to send a read command to the MAX1204. The command sent, 0x8e, takes a reading from channel 0 in unipolar, single-ended mode, using the MAX1204's internal clock.

To collect the data from the MAX1204 after it finishes reading, my software must send two bytes of 0 and save the responses. This is done with the two successive calls to ExchangeSPI() and the manipulation of variable **addata**.

Finally, my code examines the value saved in **addata**. If the variable holds 0x3ff (all bits set), the code assumes an overrange and prints out an error message. If the value returned is valid, my code converts it into a floating-point number, scaled to a maximum of +4.096 VDC, and displays the result. This loop of read, collect, and display continues until the user presses a key to halt the program.

That's a wrap

As you can see, hooking SPI devices to the PC's printer port requires very little hardware and only a moderate amount of software. The program given here should get you well on your way.

Originally, I had intended to do a single, general-purpose program that could handle everything, but the different configurations of SPI devices are simply too great. In the end, I chose to do a collection of functions that you could use to accommodate nearly any SPI device. You could also transcribe this code to any of the various dialects of PC BASIC, should you be more comfortable with that language.

The SPI bus is a natural for grafting onto the PC's parallel port. The wide variety of devices, the ability of the bus to handle many different devices easily, and the simplicity of the software involved add up to a potent combination. Give this technique a try on your next data collection or robot control project. I think you'll like the results.

Much of my information on the line-printer port came from a superb web site maintained by Peter H. Anderson, a professor in the department of Electrical Engineering at Morgan State University.

He and his students have developed many different printer-port projects, and their web-site is loaded with terrific information and project designs. You can even buy books and circuit boards for several projects.

Check this page out at **www.et.nmsu.edu/~etti/fall96/computer/printer/printer.html**. NV

Digital Storage Oscilloscopes

From $189?

ATC modules connect to your PC printer port and transform it into a full-function DSO, spectrum analyzer, logger, & DVM. Units DC to 25MHz



Captured Waveforms Pico Tech ADC-200 in Windows

O-Scope II in DOS

ATC proudly announces the addition of Pico Technology Ltd. products to our product line. Pico is based in Britain and offers a variety of data logging and virtual instrument modules.

O-Scope Ip (ST 50KHz).....$189
O-Scope II (DT 500KHz).....$349
ADC-100 (DT 12bit 50KHz)..... $449
ADC-200/20 (DT 10MHz).....
ADC-200/50 (DT 25MHz)..... CALL
Loggers 1-22 ch. (8-16 bit) from $99
Shipping UPS $7.50 grnd, $11.50 (2 day)

800-980-9806
Allison Technology Corporation
8343 Carvel, Houston, TX 77036
Fax: 713-777-4746 Technical: 713-777-0401
BBS: 713-777-4753 **email: atc@accesscomm.net**
http://www.atcweb.com

Go Wireless With Our Modules

SILRX/TXM

SILRX – $26.00 ea.
TXM – $15.50 ea.

The TXM and SILRX modules are a transmitter and receiver pair which can achieve a one-way radio data link-up to a distance of 200m over open ground.

Both units are supplied in space-saving single-in-line packages and offer SAW controlled, wide band FM transmission/reception.

The modules are particularly suited to battery-powered, portable applications where low power and small size are critical design criteria.



TX2/RX2

TX2 – $19.50 ea.
RX2 – $38.50 ea.

The TX2 and RX2 radio transmitter and receiver pair enable the simple implementation of a data link at up to 40kbit/s at distances up to 75m in-building and 300m open ground. Both modules combine full screening with extensive internal filtering to ensure EMC compliance by minimizing spurious radiations and susceptibilities. The TX2 and RX2 modules will suit one-to-one and multinode wireless links in applications including car and building security, EPOS and inventory tracking, remote industrial process monitoring, and computer networking.

Because of their small size and low power requirements, both modules are ideal for use in portable, battery-powered applications such as hand-held terminals.

Lowest Prices!

RPC

RPC – $99.00 ea.

The RPC module is an intelligent transceiver which enables a radio network link to be simply implemented between a number of digital devices. The module combines an RF circuit with processor-intensive low-level packet formatting and recovery functionality, requiring only a simple antenna and 5V supply to operate with a microcontroller or a PC.



BiM

BiM – $69.00 ea.

The BiM module integrates a low-power UHF FM transmitter and matching superhet receiver together with data recovery and TX/RX change over circuits to provide a low-cost solution to implementing a bi-directional short-range radio data link.

Lemos International Co., Inc.
65 Southbridge Street, Auburn, MA 01501
Phone (508) 798-5004 ♦ Fax (508) 798-4782
www.lemosint.com ♦ lemosint@ma.ultranet.com
All products available in either 418 or 433 MHz

CALL TOLL FREE
(800) 292-7711 orders only
Se Habla Espãnol

C&S SALES
EXCELLENCE IN SERVICE

CALL OR WRITE FOR OUR NEW FREE 64 PAGE CATALOG!
(800) 445-3201

REPAIR SYSTEM SOLDERING AND DESOLDERING Model SL-916

$425.00

Top-of-the-line repair system will handle desoldering. Temperature controlled soldering from 300°F to 790°F (150°C to 420°C), desoldering temperature range 410°F to 900°F (210°C to 480°C). The system is based on principle of vacuum absorption of the solder from the PC board.

SL-928 - Desoldering System with Digital Display also available. **$325.00**

Elenco Scopes
Free Dust Cover and Probes



S-1325	25MHz		$325
S-1330	25MHz	Delayed Sweep	$439
S-1340	40MHz		$475
S-1345	40MHz	Delayed Sweep	$569
S-1360	60MHz	Delayed Sweep	$749
S-1390	100MHz	Delayed Sweep	$895

DIGITAL SCOPE *SUPER* SPECIALS

DS-203	20MHz/10Ms/s Analog/Digital	$695
DS-303	40MHz/20Ms/s Analog/Digital	$895
DS-603	60MHz/20Ms/s Analog/Digital	$995

Four Functions In One
Model MX-9300

$459.95

Features:
- One instrument with four test and measuring systems:
  - 1.3GHz Frequency Counter
  - 2MHz Sweep Function Generator
  - Digital Multimeter
  - Digital Triple Power Supply - 0-30V @ 3A, 15V @ 1A, 5V @2A

NEW Tektronix DMMs
- 40,000 count
- High Accuracy
- Tektronix quality
- 3yr warranty

DMM 912	~~$169~~	$179
DMM 914	~~$239~~	$229
DMM 916	~~$265~~	$275

20MHz Sweep / Function Generator with Frequency Counter Model 4040

- 0.2Hz to 20MHz
- AM & FM modulation
- Burst Operation
- External Frequency counter to 30MHz
- Linear and Log sweep

10MHz Model 4017 $309
5MHz Model 4011 $239

$399

Fluke Scopemeters

123. . .NEW. . . .	$950
92B	$1445
96B	$1695
97	$1695
99B	$2095
105B . NEW. . .	$2495

ALL FLUKE PRODUCTS ON SALE

Technician Tool Kit
Model TK-1500

28 tools plus a DMM contained in a large flexible tool case with a handle ideal for everyone on the go.

$49.95

Fluke Multimeters

Model 26III	$195	Model 12	$84
Model 70III	$85	Model 83	$235
Model 73III	$115	Model 85	$269
Model 75III	$139	Model 87III	$299
Model 77III	$154	Model 863E	$475
Model 79III	$175	Model 867BE	$650

B&K Precision Multimeters

Model 389	$109	Model 388A	$99
Model 390	$127	Model 2707	$75
Model 391	$143	Model 2860A	$79
Model 5360	$195	Model 5370	$219
Model 5380	$265	Model 5390	$295

NEW DIGITAL LCR METER
Model LCR-1810

- Capacitance .1pF to 20MF
- Inductance 1µH to 20H
- Resistance .01Ω to 2000MΩ
- Temperature -20°C to 750°C
- DC Volts 0 - 20V
- Frequency up to 15MHz
- Diode/Audible Continuity Test
- Signal Output Function
- 3 1/2 Digit Display

$99.95

B&K High Current DC Power Supply

- Variable 3-14 VDC
- Thermal Protection
- Current Limiting

Model 1686 12A $159
Model 1688 25A $239

B & K 13.8V Fixed DC/Power Supplies
Model 1680 6A $39
Model 1682 15A $75

Quad Power Supply
Model XP-4

4 Fully Regulated DC Power Supplies in One Unit
4 DC voltages: 3 fixed - +5V @ 1A, -5V @ 250mA, +12V @ 500A • 1 Variable 0-12V @ 500mA



$29.95

Digital Multimeter
Model M-1740

$39.95

Free Holster

11 functions including freq to 20MHz, cap to 20µF.
2 Year Warranty

Family Radio
Model FRS-14
by Standard

- 1 Mile Range
- 1/2 Watt Output, 14 Channels
- LCD Channel & Code Display
- 38 Selectable Channel Codes
- Back-Lit Display.
- No License Required!

$129.95 each or 2 for $250.00

Handheld Universal Counter

Features:
- 10-Digit LCD Display.
- 250MHz Direct Count.
- 16 Segment & RF Signal Strength Bargraph.
- NiCad Battery Included.

Model F-2800
1MHz - 2.8GHz

$99

B&K Spectrum Analyzers

500MHz Series BK2615A $1250, BK2620A $1675

- 150KHz to 500MHz
- Dynamic Range 80dB (113dB with attenuation)
- +20dBm maximum input
- 12.5 and 400KHz resolution bandwidth
- 150KHz/hour stability
- Built-in tracking generator (Model 2620A)

1.05GHz Series BK2625A $1925, BK2630A $2595

- 150KHz to 1,050MHz
- Dynamic Range 80dB (113dB with attenuation)
- AM & FM demod included
- 20 and 400KHz resolution bandwidth
- 150KHz/hour stability
- Built-intracking generator (Model 2630A)

Simm Module Tester
B&K Precision Model 898

- Tests 72 and 30 pin SIMMs to 36 bits.
- Stands alone and portable. No other equipment required.
- Automatically identifies width, depth and speed of SIMMs.
- 10 built-in tests identify mosts memory defects Pre-heat cycle prior to tests.

$625

Model XP-581

4 Fully Regulated DC Power Supplies in One Unit
4 DC voltages: 3 fixed -+5V @ 3A, +12V @ 1A, -12V @ 1A
1 Variable - 2.5 - 20V @ 2A

$89.95

Portable Semiconductor Tester
B&K Precision Model 510

- In or out-of-order circuit tests for transistor, FETs, SCRs and darlingtons.

$199

Satellite Finder
Model SF-01

- Aligns Satelite Dishes
- Range 950-2050MHz
- Compact Size
- Self Power Check

$39.95

Dual-Display LCR Meter w/ Stat Functions
B&K Model 878

$219.95

Auto/manual range
Many features with Q factor
High Accuracy

Digital Audio Generator
SG-9300

$175

- 10Hz - 1MHz
- Low Distortion
- Sine/Square waves
- Built-in 150MHz Frequency Counter

Guaranteed Lowest Prices

UPS SHIPPING: 48 STATES 5%
OTHERS CALL FOR DETAILS
IL Residents add 8.25% Sales Tax

C&S SALES, INC.

150 W. CARPENTER AVENUE
WHEELING, IL 60090
FAX: (847) 541-9904 (847) 541-0710
http://www.elenco.com/cs_sales/

VISA MasterCard

15 DAY MONEY BACK GUARANTEE

FULL FACTORY WARRANTY

PRICES SUBJECT TO CHANGE WITHOUT NOTICE

Write in 74 on Reader Service Card.

dealer directory dealer directory dealer directory

Events

CALENDAR

The Events Calendar is a free service for publicizing electronic events such as amateur radio hamfests, flea markets, etc. If your organization is sponsoring an event and would like a free listing, contact us at least 60 days in advance. Include your flyer, estimated attendance, name of the person to contact, and phone number.

Complimentary issues are available upon request for distribution to your attendees. A street address for UPS is required.

While we strive for accuracy in our calendar, we can not be responsible for errors or cancellations. The information contained in this column is for the use of the readers of *Nuts & Volts* and may not be republished in any form without the written permission of T & L Publications, Inc.

All listing information should be sent to:
Nuts & Volts Magazine
Events Calendar
430 Princeland Court
Corona, CA 91719
Phone 909-371-8497
Fax 909-371-3052
E-mail events@nutsvolts.com

OCTOBER 1998

OCTOBER 2-3

MS - BILOXI - Hamfest. Point Cadet Plaza, Hwy. 90. Fri: 5-9pm, Sat: 8am-3pm. Talk-in: 146.730. VE Exams. MS Coast ARA, Larry Kiser KC5QFR, 228-463-0407. Doris Miller, 228-539-9929

OCTOBER 3

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052

FL - ORLANDO - Hamfest. Bahia Shrine AR Unit, Phillip Stewart KD4CJK, 407-380-2902

IN - PERU - Hamfest. Miami Co. & Cass Co. ARCs, Gary Donaldson N9KQG, 219-382-2203. E-Mail: ccarc@netusa1.net Web: http://www.netusa1.net/~ccarc

KS - WICHITA - State Convention. Cotillion Ballroom, 11128 W. Kellogg (Hwy. 54). 8am-4pm. VE Exams. Stan Weir, 316-524-2568. E-Mail: kb0shb@juno.com Web: http://www.feist.com/~warc

MO - WARRENSBURG - Hamfest. Warrensburg Area ARC, Jim Callon KB8DQB, 660-563-6168

NY - SYRACUSE - Hamfest. Pompey Hills Fire Dept., off Rt. 20. 8am-2pm. VE Exams. Talk-in: 147.90/30. RAGS, Vivian Douglas WA2PUU, 315-469-0590. Web: www.pagesz.net/~rags

PA - WARRINGTON - Mid-Atlantic States VHF Conference. Hampton Inn, 1500 Easton Rd. 9am-9pm. Mt. Airy VHF Radio Club (Packrats), John Sortor KB3XG, 610-878-5674. E-Mail: johnkb3xg@aol.com

SC - FT. MILL - Rock Hill Hamfest & Computer Fair. Knights Stadium, I-77 Exit 88. Talk-in: 147.03 -600. Pete Krenn KC4ZJ 803-366-5932. E-Mail: pete@cetlink.net

TX - BELTON - Ham Expo. Bell Co. Expo Center. Mike LeFan WA5EQQ, 254-773-3590. E-Mail: hamexpo@tarc.org Web: http://www.tarc.org

OCTOBER 4

CA - LIVERMORE - Hamfest. Livermore ARK, Cliff Kibbe KF6EII, 209-835-6715. E-Mail: larkswap@hotmail.com

IN - LAWRENCE COUNTY - Hamfest. Hoosier Hills Ham Club, John Scheiwe KB9LTI, 812-279-0050. E-Mail: jscheiwe@dmrtc.net Web: http://dmrtc.net/~jscheiwe/hamfest.html

MD - FRIENDSHIP - Hamfest. Columbia ARA, Richard Frank W9RZ, 410-531-2933 or 301-314-7806

NY - QUEENS - Hamfest. NY Hall of Science Parking Lot, Flushing Meadow Corona Park, 47-01 111th St. Stephen Greenbaum WB2KDG, 718-898-5599 night only. E-Mail: WB2KDG@bigfoot.com

PA - WARRINGTON - Hamarama. Bucks Co. Drive In, Rt. 611. Talk-in: 146.52 simplex. Mt. Airy VHF Radio Club (Packrats), Mark Schreiner NK8Q, 215-497-1414. E-Mail: nk8q@amsat.org Web: http://www.ij.net/packrats

OCTOBER 9-10

NH - ROCHESTER - Hamfest. HOSSTRADERS, Joe Demaso K1RQG, 207-469-3492. E-Mail: klrgg@aol.com

OCTOBER 10

AR - MOUNTAIN HOME - Hamfest. Twin Lakes ARC, Paul Rasmussen KA6VAN, 870-491-5350. E-Mail: rasmussen@centuryinter.net

CA - FONTANA - Inland Empire ARC Amateur Radio & Electronics Swapmeet. A B Miller High School. Bill 909-822-4138 eves

FL - STARKE - Hamfest. Bradford Area ARC, Lev Francis K4SRA, 352-473-3511. E-Mail: afn22489@afn.org

GA - AUGUSTA - Hamfest. Evans Middle School, 4318 Washington Rd. 9am-4pm. VE Exams. Talk-in: W4DV repeater, 145.490-. Terry Brown KE4MHN, 706-796-7635, E-Mail: cricket@gabn.net. Frank Scoggins KS4OC, 706-560-9600, E-Mail: ks4oc@bellsouth.net

GA - BLAIRSVILLE - Hamfest. GA Mountain ARC, Tom Lourigan WA4RBM, 706-745-1282. Web: http://www.stc.net/~jrv/

IN - VINCENNES - Hamfest. Old Post ARS, Doug Herrold KB9ONI, 812-882-4828. E-Mail: dherrold@abcs.com

MI - ALPENA - Hamfest. Thunder Bay ARC, Tom Twite K8CHS, 517-354-2469

NJ - TEANECK - Hamfest. Bergen ARA, Jim Joyce K2ZO, 201-664-6725. E-Mail: jjjoyce@cybernex.net Web: http://www.bara.org

WA - BREMERTON - Hamfest. North Kitsap ARC, Susan Johnson AB7MD, 360-697-9379. E-Mail: sujohnso@linknet.kitsap.lib.wa.us Web: http://www.silverlink.net/nkarc

OCTOBER 10-11

FL - TAMPA - Hamfest. 4050 Dana Shores Dr., Unit Bldg. 8:30am-3pm. VE Exams. Talk-in: 147.105. Egypt Shrine Temple ARA, Jay Strom K9BSL, 813-822-9107

TN - MEMPHIS - MemFest '98. 2585 N. Hollywood @ I-240. Sat: 8:30am-4pm, Sun: 8:30-2pm. VE Exams. Talk-in: 146.22/146.82. Greater Memphis Amateur Radio Operators, Lee Bowers KA4KVW, 901-867-3461; Ben Troughton KU4AW, 901-372-8031. E-Mail: lbowers@netten.net

OCTOBER 11

CT - WALLINGFORD - Nutmeg Hamfest & Computer Show. Mountainside Special Event Facility. 9am-3pm. Gordon Barker K1BIY, 860-342-3258. E-Mail: nutmeghamfest@qsl.net Web: www.qsl.net/nutmeghamfest

MI - MASON - Hamfair. Ingham Co. Fairgrounds. 8am-1pm. Don Tillitson WB8NUS, 517-321-2004

NC - MAYSVILLE - Hamfest. Jo Ann Taylor WD4JYR, 252-393-2120

OH - LIMA - Hamfest. Northwest OH ARC, Greg Schwark N8WBD, 419-647-6321

OCTOBER 16-17-18

CA - CONCORD - Hamfest. Pacific Division Convention. Concord Airport Sheraton Hotel. Fri: 8am-7pm, Sat: 6am-7pm, Sun: 6am-12pm. VE Exams. Talk-in: 147.06+. Dick Schulze AA6DL, 510-932-6125. E-Mail: PACIFICON@designlink.com Web: http://www.mdarc.org

OCTOBER 17

AZ - TUCSON - Hamfest. Old Pueblo RC, John Kalmes KC7LIB, 520-296-4182

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052

IL - GODFREY - Hamfest. Lewis & Clark RC, Larry Roberts W9MXC, 618-466-0041. E-Mail: helmore@piasanet.com Web: http://www.ezl.com/~lmiller/lcrc.html

MT - BOZEMAN - Hamfest. Gallatin Ham RC, Steve Longacre AB7MV. E-Mail: longacre@montana.campus.mci.net

PA - LEWISBURG - Hamfest. Susquehanna Valley ARC, Bob Stahl WY3M, 717-473-7050. E-Mail: wy3m@amsat.org Web: http://loveland.dynip.com/svarc

PA - PLEASANT HILL - Hamfest. Hanover Area Hamming Assn., Wayne Leister N3MTR, 410-857-0989

TN - GRAY - Hamfest. Kingsport, Bristol, Johnson City RCs. Wendell Messimer K4ZHK, 423-928-4407

OCTOBER 17-18

FL - WEST PALM BEACH - Hamfest. Palm Beach RA, Wayne Cunningham AD4AK, 407-697-4231

OCTOBER 18

MA - CAMBRIDGE - Flea Market. Kendall Square area. MIT. Nick Alternbernd KA1MQX, 617-253-3776. Web: http://web.mit.edu/w1mx/www/swapfest.html

MI - KALAMAZOO - Hamfest. County Fairgrounds. Talk-in: 147.040 K8KZO repeater. Kalamazoo ARC & S.W. MI AR Team, Gary Hazelton N8GH, 75075 M-40, Lawton, MI 49065. E-Mail: ka8blo@net-link.net Web: http://www.net-link.net/wmat

OH - ASHLAND - Hamfest. County Fairgrounds. 8am-2pm. Talk-in: 147.105. Ashland Area ARC, David Fike N8UCA, 419-289-1082

PA - GREENSBURG - Hamfest. Foothills ARC, Al Compton N3LQX, 724-523-3727. Web: http://www.geocities.com/Heartland/Acres/7896/

PA - SELLERSVILLE - Hamfest. Sellersville Fire House, Rt. 152. Linda Erdman KA3TJZ, 215-679-5764. Web: HTTP://WWW.RFHILL.AMPR.ORG

WA - CHEHALIS - Hamfest. Chehalis Valley ARS, James Kruger KK7AB, 360-748-1930

OCTOBER 23-24-25

OK - KINGSTON - Hamfest. Texoma Hamarama, Herb Sleeper WB5PHM, 940-855-5820. E-Mail: retmarine@cst.net Web: http://www.qsl.net/KC5SIG/HAMARAMA

OCTOBER 24

CANADA - QUEBEC - MONTREAL - Hamfest. Montreal South ARC, Francois Drien VE2FDA, 514-672-9994. E-Mail: ve2fda@amsat.org

NC - HICKORY - Hamfest & Computer Show. Catawba Valley Community College, 2550 Hwy 70 S.E. 8am-5pm. William B. Walker W4ZCV, 828-322-6180. E-Mail: N1PD@TWAVE.NET

OR - RICKREALL - Swap-Toberfest, Amateur Radio Emergency Services Convention. Polk County Fairgrounds. 9am-3:30pm. Talk-in 146.86 repeater. Mid-Valley ARES, Bob Boswell W7LOU, 503-623-2513. E-Mail: w7lou@goldcom.com Web: http://www.teleport.com/~n7ifj/swaptobe.htm

OR - SALEM - Hamfest. Mid-Valley ARES, Tami Burroughs KB7HEK, 503-585-5924. E-Mail: w7lou@goldcom.com Web: http://www.teleport.com/~n7ifj/swaptobe.htm

PA - DANVILLE - Swapmeet & Show. Cloverleaf Barn Antique & Gift Village, 120 McCracken Rd., Rt. 80, Exit 33. Central PA Radio Collectors Club, Frank Hagenbuch, 717-326-0932

SC - SUMTER - Hamfest. Sumter County Exhibition Center, 700 W. Liberty St. 8am-3:30pm. Talk-in: 147.015. VE Exams. Sumter ARA, Steve Heriot KC4ZLB, 803-773-2282 or 803-428-5424. E-Mail: sheriot@ftc-i.net

WA - FERNDALE - Hamfest. Mount Baker ARC, Al Norton K7IEY, 360-354-4622

OCTOBER 24-25

TX - EL PASO - Hamfest. Sat: 8am-5pm, Sun: 8am-2pm. Int'l Hamfiesta Assn. Clay Emert K5TRW, 915-859-5502. E-Mail: cemert@dzn.com Web: http://www.dzn.com/hamfiesta

OCTOBER 25

IN - LEBANON - Boon/Clinton Co. Hamfest. Don Lecklitner K9DFK, 765-249-2020. E-Mail: nella@iquest.net

MD - WESTMINSTER - Mason-Dixon Hamfest & Computer Show. Carroll County Ag Center. Talk-in: CCARC repeater 145.410. VE Exams. Penn-Mar RC & Carroll Co. ARC, George Johns N3JKY, 717-633-6641. E-Mail: gjohns@sun-link.com Web: http://www.qis.net/~k3pzn

MI - WARREN - Hamfest. The Italian American Cultural Society, 28111 Imperial Dr. 8am-2pm. VE Exams. Talk-in: 147.180+ PL 100.00. Chris W8ZNT, 248-541-4623

NY - LINDENHURST - Hamfest. Knights of Columbus, 400 S. Broadway. VE Exams. Talk-in: W2GSB repeater 146.685 -600 136.5 PL. Great South Bay ARC, Peter Portanova WB2OQQ, 516-541-4886. E-Mail: info@gsbarc.org Web: http://www.gsbarc.org

OH - MARION - HamFiesta & Computer Show. Marion County Fairgrounds Coliseum. 8am-3pm. Talk-in: 147.90/30 repeater. Marion ARC, Karen Eckard N8KE, 614-499-3565; Betty Krist N8UDT, 614-387-3533 after 5pm

OCTOBER 31

MN - ST. PAUL - Hamfest & Computer Expo. The new St. Paul Rivercentre (adjacent to the former St. Paul Civic Center). 8am-4pm. VE Exams Fri @ St. Paul Civic Center 6pm. Twin City FM Club, Dale Reak KB0VCV, 612-687-9535

MO - ST. LOUIS - Hamfest. Kirkwood Community Center, 111 S. Geyer. 8am-1:30pm. Talk-in: 146.91 repeater. SLARC & GARA, Dennis McCarthy AA0A, 314-351-3568 or 314-533-0321 xt. 12. E-Mail: mccartdj@slu.edu. Steve Welton 314-638-4959, E-Mail: SLW@surface.com

TN - EAST RIDGE - Hamfest. Camp Jordon. 8am-4:30pm. Talk-in: 146.790- & 444.100+. Chattanooga ARC, Lou Carter KE4DGW, 423-821-4043. E-Mail: LCarter264@aol.com

NOVEMBER 1998

NOVEMBER 1

CA - LIVERMORE - Hamfest. Livermore ARK, Cliff Kibbe KF6EII, 209-835-6715. E-Mail: larkswap@hotmail.com

IA - DES MOINES - Hamfest. Tikva Tracers ARC, Randall Lees N0LMS, 515-279-4241. E-Mail: rclees@raccoon.com

IL - MACOMB - Hamfest. National Guard Armory. 8am-1pm. VE Exams. Talk-in: 147.060/147.660, 444.300/449.300. Lamoine Emergency ARC, Don Johnson KA9SQB, 309-833-4626

Continued on page 51

COMPUTER SHOWS

Blue Star Productions
612-788-1901
http://www.supercomputersale.com

Computers And You, 734-283-1754.
www.a1-supercomputersales.com

Computer Central Shows
847-412-1900 & 1-888-296-6066.
E-Mail: compcent@megsinet.net
www.computercentralshows.com

Five Star Productions
810-890-0988 E-Mail: jeff@fivestar
www.fivestarshows.com

Georgia Mountain Productions
706-838-4827.
E-Mail: gamtnpro@blrg.tds.net
georgiamountain.com

Gibraltar Trade Center, Inc.
734-287-2000. Taylor, MI.
Gibraltar Trade Center, Inc.
810-465-6440. Mt. Clemens, MI.

MarketPro, Inc., 201-825-2229
http://www.marketpro.com

MarketPro, Inc., 301-984-0880.
E-Mail: md@marketpro.com
http://marketpro.com

Northern Computer Shows
978-744-8440
E-Mail: inquiries@ncshows.com
Web: ncshows.com

Peter Trapp Computer Shows, 603-272-5008. Web: www.petertrapp.com

AGI Shows, 317-299-8827.
E-Mail: info@agishows.com
http://www.agishows.com

Greenleaf ELECTRONICS

For all your cable needs
Call us first!

SIX-MONTH GUARANTEE
(30-DAY MONEY BACK)

Phone 630-616-8050 or Fax 630-616-8094

For orders only: 1-800-742-2567

HOURS: MON.-FRI. 8-6 CST • SAT. 10-2 CST

Greenleaf Electronics • P.O. Box 538 • Bensenville, IL 60106

TONY TALLI'S ORIGINAL

WHERE OUR VALUED CUSTOMERS' BUSINESS IS HONESTLY APPRECIATED

TELEVIEW DISTRIBUTORS

FREE 1 YEAR SUBSCRIPTION TO NUTS & VOLTS WITH $500.00 MIN. ORDER

1•800•847•3773

Not affiliated with NCCA.

Vega One **ORDERS ALSO ACCEPTED**

1•800•525•0428 P.M. SALES

Orders called in by 1:00 pm shipped same day. $15 shipping.
NO NEVADA SALES • Hours: M-F 9-4 PST

MasterCard VISA

YES! WE HAVE COUPONS!

Call for this month's Nuts & Volts Specials

GIVE TELEVIEW TONY A CALL TODAY!

1-702-253-1852 • FAX 1-702-253-1854

SERVING YOUR CABLE NEEDS SINCE 1984

P.O. BOX 71465 • LAS VEGAS, NV 89170-1465



A Sonar Sensor for Amateur Robotic Platforms

by Lawrence Foltzer

Introduction

Two of the things I enjoy doing in my precious spare time are kayaking and building robots, so it was quite natural for me to want to combine the two activities. So, I decided I would build an autonomous boat whose sole purpose in life would be to follow me wherever I paddled, but would not run into me if I stopped to take in the view.

The boat tracks me by homing in on a water-born sonic beacon emanating from my kayak, and to avoid colliding with me or other objects, the boat uses a set of three atmospheric Sonar sensors for obstacle detection.

I initially looked into buying a commercially available Polaroid Sonar sensor, but was discouraged from that approach because of some of that device's characteristics; most noteable being its high voltage and power requirements, larger size, and cost. I felt I could do better!

So, armed with a handful of Microchip PIC processors to be used as programmable signal sources, I began investigating transducers ranging from small surplus PC speaker elements, piezoelectric ceramic discs, and ultrasonic transducers used in remote control applications.

The first two categories of devices worked surprisingly well, but had resonances in the audio frequency band, a few Kilohertz typically, and fairly high mechanical Qs. These characteristics meant that the transducer would "ring" long after excitiation was removed, causing receiver overload, creating a "dead-zone" proportional to Q/Fo, wherein near-field echoes would be impossible to detect.

There are basically two ways of reducing the dead-zone. One is to reduce transducer Q, the other is to increase the operating frequency. Reducing the mechanical Q of a transducer can be accomplished by loading the element.

However, this is a bad thing to do since it spoils the overall sensitivity of the transducer in both transmit and receive mode. The only load the transducer should have is the medium it drives. This leaves but one degree of freedom ... that of high-frequency operation. So, I turned my attention exclusively toward the 40-KHz ultrasonic sensors I found at reasonable cost in the Mouser Electronics catalog.

As it turned out, the Q of these ultrasonic transducers actually turned out to be somewhat higher than the Qs of the other low-frequency transducers I investigated, but Q/Fo (the ring-down time) was about half that of the other transducer elements I had examined. And, as it also turns out, the high Q of these transducers also translates to higher transmit and receive sensitivity, while providing excellent rejection of out-of-band frequencies.

As indicated earlier, one of the things that turned me away from commercially available sensors was their high-power requirements. So, I initially expected that I would need some sort of power amplifier to generate sufficient drive for the transducer to meet my range requirements. But not knowing exactly what was required, I continued my investigations of the transducer, driving it directly from a PIC microprocessor port that I could put in the high-Z state after transmission to unload it for echo detection.

Much to my total astonishment, I discovered I could detect echoes off walls 50 feet away, and relatively small objects at distances from a few feet, to 20 feet away. I was on the right track!

During the next phase of development, I added time dependent gain (TDG) to the receiver to flatten the receiver's echo amplitude from a "standard target," more or less independent of target range. And to prevent the receiver from going into hard saturation from the transmit pulse which also contributes to receiver recovery time, I added a resistor, diode combination (half a BAV70) at the receive front-end to limit/attenuate the signal level during the transmission sequence. This feature reduced the dead-zone from about three milliseconds to roughly one millisecond.

Other features of the sensor include:

- All surface mount construc-



FIGURE 1

tion (less transducer and crystal).

• 1.5" by 3.3" single-PCB construction.

• 9 to 12 volt operation @ 30 milliamperes.

Receiver stays active after ping sequence (until PING command goes low). This allows multiple sensors to act as echo detectors for accurate bearing determination using the method of triangulation.

Circuit Operation

A block diagram of the sensor is shown in Figure 1. Soundings are initiated by a "ping command" issued by the host processor. The sensor is then driven directly by the PIC processor with a 0.5 millisecond long, 40-KHz pulse train.

During the transmit sequence, the sensor's microprocessor mutes the receiver to reduce large signal recovery time ... then gates the received signal to the receiver, starts the time-dependent gain control ramp, and outputs an echo timing clock (2220 Hz) lasting 50 mS.

The 2217-Hz clock period is equivalent to the round-trip propagation time — in air — corresponding to a target distance of six inches. Echo range resolution can be reduced to three inches by observing both edges of the range clock. (Sound travels one inch in air in about 75 microseconds.)

The schematic for the Sonar sensor is shown in Figure 2. The 4.433-MHz crystal is used to generate a symmetrical square-wave near the 40-KHz resonant response peak of the transducer. During the sounding, the RX Mute line is held low causing D1 to clamp the input to the receiver, minimizing overload, receiver recovery time, and short range detection distance.



FIGURE 2

Figure 2 is the schematic of the sensor. The 4.433-MHz crystal is used to generate a symmetrical square-wave near the 40-KHz resonant response peak of the transducer. During the sounding, the RX Mute line is held low causing D1 to clamp the input to the receiver, minimizing overload, receiver recovery time, and short range detection distance.

After initiating a sounding (PING), the driver port is placed in a high-impedance state, unloading the transducer in preparation to receive returning echoes. After a millisecond, the RX Mute line is raised, opening the receiver gate and, at the same time, starting the TDG voltage ramp.

The receiver consists of a two-stage amplifier (Q1 & Q2), with DC feedback used to stabilize collector voltage. As the TDG voltage is increased, collector current and gain increase also. Q3 is a high sensitivity active detector of a type called an infinite impedance detector.

This transistor is biased very near cut-off so that input signals cause a downward modulation of the collector voltage (DC operating point) rectifying the signal. The long time constant of Q3's collector load removes the 40-KHz component of the signal, leaving the echo envelope for subsequent processing.



FIGURE 3

**Echogram of ten objects spaced at 1 foot intervals.
First object placed 1 foot from sensor.
First six objects are 1.7" diameter cylinders, 1.7" tall.
Last four objects are 1.7" cubes.
Objects sitting on carpeted floor, < 8" from center of beam axis.
SONAR sensor head was 3.5" above floor.**

Figure 3 shows the output of the detector for two values of the detector integrating capacitor, Ci. Note the improved signal-to-noise ratio of the top trace, and the better temporal resolution of the lower trace. You can get the best of both worlds by capturing and averaging several of the high speed traces, but at the expense of effective echo sampling interval. This is no free lunch!

The above traces were captured using a Tektronix TDS 220 oscilloscope as binary files and converted to bit mapped images using a QBASIC program. MS Paint was then used for editing and inclusion in this document.

The output of the detector circuit (Q3) is then turned into a digital representation by the LM311 comparator. The TDG voltage is used here to shift the zero crossing (detection level) point for enhanced sensitivity for more distant targets. The signal slicing level — overlayed on Figure 3 — starts roughly at the mid-amplitude point, and tapers upward toward the 75% amplitude level.

The threshold detected signal, the echo timing clock, and the ping command line make up



FIGURE 4

AST GLOBAL ELECTRONICS

24529 STATE HWY. 408, CAMBRIDGE SPRINGS, PA 16403
VOICE 814-398-8080 · 1-888-216-7159 · FAX 814-398-1176

VIEW COMPLETE LISTING AT: http://www.astglobal.com

IF WE DON'T CARRY IT ... WE'LL FIND IT QUICKLY ... AT REASONABLE PRICES.

B&K 3020, Sweep/Function Generator, 2MHz (Sine, Square, Triangle) ... $175
Boonton 42BD, Microwatt Meter w/o Cable/Sensor ... $150
Dranetz PA6001, Plug-in Line Analyzer ... $175
Dranetz PA6011, Plug-in Time Monitor ... $175
Dranetz PA6024A, Plug-in Harmonic Analyzer ... $275
Dranetz PA6024B, Plug-in Harmonic Analyzer ... $300
Dranetz 626, Universal Disturbance Analyzer, Frame only w/Power Supply & Communication Plug-in ... $375
ESI DP1311, Variable Resistor, 100K max 1K/Step ... $100
Fluke 332B, DC Voltage Standard ... $475
Fluke 335A, DC Voltage Standard ... $475
Fluke 382A, Voltage/Current Calibrator ... $525
Fluke 540B, Transfer Standard w/A54-2 Voltage Plug-in ... $625
Fluke 721A, Lead Compensator ... $275
Fluke 760A, Meter Calibrator ... $450
Fluke 845AB, Null Detector/Micro Voltmeter 1uV-1000VDC ... $375
Fluke 845AR, Null Detector/Micro Voltmeter 1uV-1000VDC ... $375
Fluke 893A, AC/DC Differential Voltmeter 0 to 1100 Volts, AC/DC, .01%DC, .05%AC, 1uV Resolution ... $100
Fluke 3330B, Constant Current/Voltage Calibrator ... $675
Fluke 5100B, Multifunction Calibrator, Opt. 03/05 ... $3,250
Fluke 5100B, Multifunction Calibrator ... $2,700
Fluke 5200A, Programmable AC Calibrator ... $1,250
Fluke 5215A, Precision Power Amp ... $950
Fluke 6011A, Synthesized Signal Generator, 10Hz-11MHz (7-digit) ... $825
Fluke 6070A, Synthesized RF Signal Generator 200KHz-520MHz ... $1,500
Fluke 8000A, DMM 3-1/2 Digit ... $75

TURN IDLE TEST EQUIPMENT — INTO *CASH* —
CALL OR FAX FOR QUOTATION

Fluke 8050A, DMM 4-1/2 Digit w/Battery Pack ... $145
Fluke 8050A, DMM 4-1/2 Digit w/o Battery Pack ... $145
Fluke 8520A, DMM 5-1/2 Digit ... $325
Fluke 8600A, DMM 4-1/2 Digit w/o Battery Pack ... $125
Fluke 8800A, DMM 5-1/2 Digit ... $175
General Radio 1390-B, Random Noise Generator ... $150
General Radio 1346, Audio Frequency Micro Voltmeter ... $125
Gould K105-D, Logic Analyzer w/4 Probe Pods ... $650
Guildline 9770B, Constant Current Source ... $125
HP 141T, Spectrum Analyzer Mainframe ... $475
HP 141T, Spectrum Analyzer w/8552A/8553B, 1KHz-110MHz ... $1,000
HP 141T, Spectrum Analyzer w/8552B/8553B, 1KHz-110MHz ... $1,200
HP 141T, Spectrum Analyzer w/8552B/8556A, 20Hz-300KHz ... $1,100
HP 141T, Spectrum Analyzer w/8552B/8554B, 1KHz-1.2GHz ... $1,700
HP 141T, Spectrum Analyzer w/8552B/8555A, 10MHz-18GHz ... $1,900
HP 180TR, Scope Mainframe ... $250
HP 214A, Pulse Generator, .08V-100V ... $250
HP 334A, Distortion Analyzer ... $275
HP 350D, Attenuator ... $75
HP 400EL, AC Voltmeter, 10Hz-10MHz ... $150
HP 400FL, RMS Voltmeter, 20Hz-4MHz, 100uV-300V ... $175
HP 403B, AC Voltmeter Battery Operated, 5Hz-2MHz, 1mV-300V ... $175
HP 415E, SWR Meter ... $100
HP 427A, Multi-function Meter (AC, DC & Resistance 10Hz-1MHz) ... $100
HP 432A, Power Meter w/Cable/8478, .01-18GHz Sensor ... $350
HP 432A, Power Meter w/o Cable/Sensor ... $250
HP 435A, Power Meter w/o Sensor/Cable ... $175
HP 651B, Test Oscillator, 10Hz-10MHz ... $150
HP 652B, Test Oscillator, 10Hz-10MHz ... $150
HP 654A, Oscillator, 10Hz-10MHz, 90dB Attenuator ... $225
HP 1630D, Logic Analyzer w/pods ... $550
HP 1980B, Scope Measurement System w/1965A Gated Universal Timer (like new) ... $550
HP 3312A, Function Generator, .1Hz-13MHz ... $490
HP 3325A, Programmable Frequency Synthesizer 1Hz-32MHz ... $1,650
HP 3330B, Automatic Synthesizer, 20Hz-13MHz ... $325
HP 3400A, True RMS Voltmeter, 10Hz-10MHz, 1mV-300V ... $200
HP 3403C, True RMS Meter, AC/DC/dB 100MHz ... $325
HP 3406A, RF Voltmeter, 50uV-3V, 1.2GHz ... $350
HP 3455A, DMM 5-1/2 Digit ... $250
HP 3456A, DMM 6-1/2 Digit ... $525
HP 3466A, DMM 4-1/2 Digit, AC/Battery, 5 Function ... $225
HP 3467A, Logging Voltmeter ... $225
HP 3580A, Spectrum Analyzer, 5Hz-50KHz, LED Readout ... $850
HP 3581A, Wave Analyzer, 15Hz-50KHz ... $475
HP 3762A, Data Generator, 30-150MHz ... $450
HP 3770A, Amplitude/Delay Distortion Analyzer ... $425
HP 3779B, Primary MPX Analyzer ... $625
HP 3781B, Pattern Generator ... $300
HP 5314A, Counter/Timer, 100MHz (unused) ... $175
HP 5328A, Counter, 100MHz w/DVM/Opt. 021 ... $250
HP 5328A, Counter, 500MHz ... $350
HP 5345A, Counter, 500MHz, HP-IB ... $450
HP 6104A, Precision Power Supply, 20V @ 3A, 20-40V @ 1A (metered) ... $175
HP 6112A, Power Supply, 40V @ .5A (metered) ... $175
HP 6116A, Power Supply, 0-100V @ 200mA (metered) ... $125
HP 6202B, Power Supply, 40V @ .75A (metered) ... $175
HP 6203B, Power Supply, 7.5V @ 3A (metered) ... $175
HP 6205B, Power Supply (dual), 0-40V @ .3A, 0-20V @ 8A (metered) ... $225
HP 6206B, Power Supply, 0-60V @ 1A (metered) ... $250
HP 6253A, Power Supply (dual), 0-25V @ 3A (metered) ... $225
HP 6260B, Power Supply, 10V @ 100A (metered) ... $400
HP 6265B, Power Supply, 40V @ 3A (metered) ... $250
HP 6266A, Power Supply, 40V @ 6A (metered) ... $250
HP 6289A, Power Supply, 0-40V @ 1.5A (metered) ... $225
HP 6294A, Power Supply, 0-60V @ 1A (metered) ... $275
HP 8011A, Pulse Generator, .1Hz-20MHz ... $175
HP 8013B, Pulse Generator, 1Hz-50MHz ... $275
HP 8015A, Pulse Generator, .1Hz-50MHz 30V ... $425
HP 8081A, Rate Generator (300MHz) w/8084A Word Generator (300MHz) w/8083A Output Amp (300MHz) ... $950
HP 8091A, Rate Generator (1GHz) w/8092A Delay Generator (1GHz) w/8093A Output Amp w/15401A & 15400A ... $3,000
HP 8165A, Programmable Sig Source, 1milliHz-50MHz ... $950
HP 8180A, Data Generator ... $425
HP 8182A, Data Analyzer ... $650
HP 8410B, Network Analyzer Mainframe ... $275
HP 8414A, Polar Display ... $225
HP 8443A, Tracking Generator w/Cables, 1KHz-110MHz ... $475
HP 8444A, Tracking Generator for 141T System, .5-1300MHz ... $750
HP 8553B, RF Plug-in (for 140 Series Mainframes), 1KHz-110MHz ... $425
HP 8553L, RF Plug-in (for 140 Mainframes), use with 8552A, 1KHz-110MHz ... $125
HP 8601A, Sweeper Generator, .1-110MHz ... $425
HP 8614A, Signal Generator, 800-2400MHz, AM/FM Leveled ... $475
HP 8616A, Signal Generator UHF, 1.8-4.5GHz, +10-126dB, AM/FM ... $475
HP 86242D, RF Plug-in, 5.9-9.0GHz ... $350
HP 8640B, Signal Generator, .5-1050MHz, Opt. 002/001 or 003. $1,800
HP 8640B, Signal Generator, .5-512MHz, Opt 001 or 003 ... $950
HP 8743A, Retlection Test Set, 2-12.4GHz ... $475
HP 8901A, Modulation Analyzer ... $2,400
HP 59303A, D/A Converter ... $175
HP 59501A, HP-IB Isolated D/A Converter ... $125
Huntsville 80-D, Micro Systems Troubleshooter ... $225
Huntsville 180P, Micro Systems Troubleshooter ... $350
Kepco ATE15-50M, Power Supply, 0-15V @ 50A (metered) ... $650
Kepco ATE55-5M, Power Supply, 55V @ 5A ... $425
Kepco BVP100-4M, Bi-Polar Power Supply, 0-100V @ 4A (metered) ... $520
Kepco JQE 36-15MVPT, Power Supply, 0-36 @ 15A (metered) ... $275
Kepco JQE 36-3MVPT, Power Supply, 0-36 @ 3A (metered) ... $175
Krohn-Hite 3202R, Dual Channel Tunable Filter, 20Hz-2MHz, High Pass, Low Pass Band Reject ... $275
Polorad SPNH, Signal Generator, 20Hz-20KHz ... $450
Polorad SPNL, Signal Generator, 1Hz-600KHz ... $350
Racal Dana 9303, True RMS RF Level Meter ... $550
Rockland 1022F, Dual Hi/Lo Filter ... $150
Rockland 5100, Synthesizer, DC-2MHz, .001 Hz Resolution ... $325
Sencore SC61, Scope (100MHz) w/New Probes, Dual Trace ... $750
Sencore SC61, Scope (100MHz) w/o Probes, Dual Trace ... $500
Sencore TVA92, TV Video Analyzer ... $1,100
Sencore VC63, VCR Test Accessory ... $100
Sencore VG91, Universal Video Generator ... $1,200
Sorenson DCR-80-5A, Power Supply, 80V @ 5A (metered) ... $475
Sorenson DCS-300-3.5, Power Supply, 0-300V @ 3.5A (digital readout) ... $375
SRL 112B, PLO/PRF Synthesizer ... $125
Tek DC503, Plug-in Counter Universal, 100MHz ... $150
Tek DM501A, Plug-in DMM, 4-1/2 Digit ... $175
Tek DM502, Plug-in DMM, 4-1/2 Digit ... $150
Tek FG501, Plug-in Function Generator, .001Hz-1MHz ... $175
Tek FG504, Plug-in Function Generator, .001Hz-40MHz ... $450
Tek PG501, Plug-in Pulse Generator, 5Hz-50MHz ... $175
Tek PS503A, Plug-in Power Supply Triple ... $175
Tek TM503, Power Module, 3 Slot ... $125
Tek TM504, Power Module, 4 Slot ... $150
Tek TM506, Power Module, 6 Slot ... $200
Tek OIG-502, Plug-in Optical Impulse Generator (unused) ... $950
Tek PS501-1, Plug-in Power Supply ... $150
Tek T922, Scope (15MHz), Dual Trace, nice ... $175
Tek 7A16A, Plug-in (225MHz), Single Trace Amp ... $100
Tek 7A18, Plug-in (75MHz), Dual Trace Amp ... $75
Tek 7A19, Plug-in (600MHz), Single Trace Amp ... $150
Tek 7A26, Plug-in (200MHz), Dual Trace Amp ... $150
Tek 7B50A, Plug-in (150MHz), Time Base ... $100
Tek 7B53A, Plug-in (100MHz), Dual Time Base ... $125
Tek 7B70, Plug-in (200MHz), Time Base ... $75
Tek 7B80, Plug-in (400MHz), Delayed Time Base ... $150
Tek 7B92A, Plug-in (500MHz), Dual Time Base ... $200
Tek 7D11, Plug-in Digital Delay ... $175
Tek 7D13, Plug-in DMM 3-1/2 Digit ... $125
Tek 7D15, Plug-in Counter/Timer, DC-225MHz ... $225
Tek 7S11, Plug-in Sampling Unit ... $175
Tek 134, Current Probe Amp ... $100
Tek 453, Scope (60MHz), Dual Trace ... $175
Tek 465, Scope (100MHz), Dual Trace ... $425
Tek 465B, Scope (100MHz), Dual Trace ... $475
Tek 466, Scope (100MHz storage), Dual Trace ... $575
Tek 475, Scope (200MHz), Dual Trace ... $475
Tek 475A, Scope (250MHz), Dual Trace ... $625
Tek 475/DM44, Scope (200MHz), Dual Trace w/DMM ... $575
Tek 485, Scope (350MHz), Dual Trace ... $850
Tek 520A, NTSC Vectorscope ... $575
Tek 576, Curve Tracer ... $1,500
Tek 2213, Scope (60MHz), Dual Trace ... $375
Tek 2236, Scope (100MHz) w/Counter/Timer/DMM ... $800
Tek 2445, Scope (150MHz), 4-Channel Cursor Readout ... $1,700
Tek 2465, Scope (300MHz), 4-Channel Cursor Readout ... $2,400
Tek 7104, Scope (1GHz), Dual Trace ... $1,750
Tek 7603, Scope Mainframe (100MHz) ... $200
Tek 7704A, Scope Mainframe (250MHz) ... $325
Tek 7854, Scope (400MHz), Dual Beam w/Waveform Calculator ... $625
Tek 7904, Scope Mainframe (500MHz) ... $350
Wavetek 145, Pulse/Function Generator, .0001-20MHz ... $350
Wavetek 185, Lin Log Sweep Generator, .0001Hz-5MHz ... $425
Wavetek 288, Synthesized Function Generator, 20Hz-20MHz (unused) ... $950
Wavetek 751A, Brickwall Filter ... $450
Wavetek 2002, Sweep/Signal Generator, 1-4000MHz ... $950
Wavetek 3000, Signal Generator, 1-520MHz ... $525
Wilcom, T222C, Signaling Test Set (unused) ... $825
Wilcom T-105B, Rev. Level Test Set ... $600
Wilcom 1504, Artificial Line T240 ... $700

VISA · MasterCard · DISCOVER NOVUS · AMERICAN EXPRESS

- 60-DAY WARRANTY
- 10-DAY RIGHT OF RETURN
- SATISFACTION GUARANTEED



FIGURE 5

the interface to the host processor. Connection to these signals and power are provided by header P1.

Interface to the Host Processor

There are two different ways to use this sensor, both requiring a three-signal interface consisting of the ping command line, the echo detection line, and the echo clock timing line. In both cases, a sounding is initiated by asserting (pulling low) the ping command line.

In the first method, the echo clock signal connects to the host processor's timer/counter interface port, while the echo signal goes to one of the hosts interrupt lines. Target range is determined by reading the counter after receiving the echo signal interrupt.

In the second method, the host processor's interrupt line is driven by the echo clock, causing the host to examine the echo line for a return signal and to update a software range counter. This arrangement is suitable for hosts that do not have an available hardware counter port.

Implementation

Figure 4 is a photograph of the prototype sensor, showing the component side of the board. In the prototype, only the component side of the board was etched, the other side forming a continous ground plane, and wires used in place of vias to the circuit to the plane. One-to-one artwork for the component side of the double-sided sensor circuit board is shown in Figure 5.

The traces on the back side of the PCB (not shown) are for power distribution only. All of the components are surface-mount type, with the exception of the ultrasonic sensor and the processor's crystal.

Conclusion

The boat isn't quite finished yet. I still have some work to do to increase the sensitivity of my home-made in-hull beacon sensor. But, with a little luck, I'll have a reliable boating companion before the summer is out. NV

Continental US orders only
Add $5.00 for S&H
Checks or Postal Money Orders Only

Make checks Payable to:
Lawrence Foltzer
P.O. Box 488
Occidental, CA 95465

Double-sided circuit boards with plated through holes: ..... **$20.00 each**
Programmed PIC12C508: ..... **$10.00 each**
Sonar Transducer: ..... **$15.00 each**
Complete assembled and tested unit: ..... **$69.95 each**
Three or more completed assemblies: ..... **$59.95 each**

Write in 73 on Reader Service Card.

You Win with Nuts & Volts

Subscribe today and be automatically entered in our *new* MONTHLY PRIZE DRAWING!!!

OCTOBER PRIZE

BASIC Stamp II Professional Package

A custom-built package consisting of the following parts:

- (1) BASIC Stamp II Starter Kit (includes BS2-IC module, carrier board, cable, software, manual)
- (1) Additional BS2-IC Module
- (1)BASIC Stamp Activity Board
- (1) DS1620 Digital Thermometer AppKit
- (1) LTC1298 A/D AppKit
- (1) Standard Servo

Provided compliments of **PARALLAX, Inc.**



A $350 Value

NOVEMBER PRIZE

HARD DRIVE DUPE-IT! PRO from CORPORATE SYSTEMS CENTER

Pro model loaded with IDE and SCSI interfaces, translator, drive mechanic, and drive diagnostic test software with printer port.

A $995 Value

To Subscribe –
Just fill in and mail the enclosed subscription card or call our toll free orderline at (800) 783-4624 with a Visa or MasterCard.

ATTENTION CURRENT NUTS & VOLTS SUBSCRIBERS:

If you have a current, paid subscription to Nuts & Volts, you are automatically entered each month in our drawing!!

We now offer a three-year subscription for only $51.00!! *(USA delivery only)*

If you do not wish to order a subscription, but would like to be entered in our drawing, simply ***send or E-Mail*** your name, address, and telephone number, to NUTS & VOLTS, 430 Princeland Court, Corona, CA 91719, drawing@nutsvolts.com. *No phone entries accepted.* All orders/entries must be *received* by October 31st to be included in the October drawing. November entries must be *received* by November 30th.

Check us out on the web!
http://www.nutsvolts.com

AUDIO TEST SETS



HEWLETT-PACKARD 3581A WAVE ANALYZER, separates and measures frequency and amplitude spectral components over 15 Hz to 50 KHz with 1 Hz resolution. Uses 5-digit LED freq-readout & analog meter for amplitude analysis. Meter scales: Volts (30 V - 100 nV linear), 90 dB or 10 dB display (+30 dB to -150 dB log). Sweep scan width adjustable 50 Hz to 50 KHz. Requires 100-120/200-240 VAC 48-440 Hz. Option 003 rackmount: 10.5x19.3x16.3, 30 lbs sh. USED-CHECKED, $595.00

MARCONI TF2005 DUAL AUDIO TEST SET, low distortion unit (de-signed <0.05%) consists of two 20 Hz-20 KHz oscillators, 0.1-111 dB T-attenuator and voltmeter. Output 15 dBm into 600 ohms. Attenuator balanced 75, 150, 600 ohms 1 W max; unbalanced 600 ohms. Voltmeter ranges 1.5, 5, 15, 25 V; dB ranges +10, +20, +24. Requires 115 VAC 50-60 Hz; 7x17x11, 32 lbs sh. USED-REPARABLE with output, $215.00



400 MHZ RADIOSONDE



VAISALA RS80 RADIOSONDE, ultra-light disposable transmitter (400 MHz approx) is designed to be carried aloft by weather balloon and transmit data for air temperature, barometric pressure and humidity to a ground station. Consists of circuit board, dipole antenna, and trailing wire. Requires 9 V battery. "Cute" experimenter item! 12.5"H as shown; 3 lbs sh. NEW, $9.95 ea; 5/ $44.

ELECTRON TUBES, "unused" military-boxed:

4D32 Raytheon, ~~$35~~. $28 ea. 10/$240. 6336B Cetron, ~~$40~~. $30 ea. 10/$250.
5755 Raytheon or 6922 ECG, $3.50 ea; 10 for $28 (one type). 100/$200.
7308 Amperex (not gold-pin, look Russian) $3.50; 10 for $28. 100/$200.

Prices F.O.B. Lima, Ohio. VISA, MASTERCARD accepted.
Allow for shipping charges. Write for latest Catalog.
Address Dept. NV + Phone 419/227-6573 + FAX 419/227-1313
E-mail: fairadio@wcoil.com Home: http://www2.wcoil.com/ ~fairadio

FAIR RADIO SALES CO.

1016 E. Eureka + Box 1105 + Lima, Ohio 45802

Write in 90 on Reader Service Card.

Celebrating our 16th Year Of Service !!

COLLIMATING LENS

This economical collimating lens assembly consists of a black anodized aluminum barrel that acts as a heat sink, and a glass lens with a focal point of 7.5mm. Designed to fit standard 9mm laser diodes. Simply place diode in the lens assembly, adjust beam to desired focus, then set with adhesive.

STOCK#	1-9	10-24	25+
LSLENS Lens Assembly	24.99	23.74	21.37

DIODE/TRANSISTOR TESTER KIT

This dynamic tester allows checking of transistors & diodes in circuit. Identifies NPN or PNP transistors. Checks all types, small or large power. Identifies anode or cathode of diodes.

STOCK#	1-9	10-24	25+
DT100K	24.99	23.74	21.37

ANTI-STATIC FOAM CLEANER

A thick, foaming cleaner for use in static sensitive applications. Safe for plastics and fiberglass. Use on computer cases and all office equipment. Also cleans soft fabrics. 5 oz. aerosol can.

STOCK#	1-9	10-24	25+
SB1102	1.99	1.89	1.70

EPROMS

STOCK#	1-24	25-99	100+
2716	2.99	2.84	2.56
2732	4.49	4.27	3.84
2732A-20	5.39	5.12	4.61
2764-20	5.39	5.12	4.61
2764-25	4.49	4.27	3.84
2764A-20	3.49	3.32	2.99
2764A-25	2.99	2.84	2.56
27C64-15	2.99	2.84	2.56
27256-15	4.79	4.55	4.10
27C256-15	2.99	2.84	2.56
27512-25	3.09	2.94	2.65
27C512-25	2.99	2.84	2.56
27C010-15	3.79	3.60	3.24
27C020-15	4.49	4.27	3.84
27C040-12	6.29	5.98	5.38
27C080-12	12.99	12.34	11.11

7400 SERIES I.C.'s

STOCK#	1-24	25-99	100+
7400	.29	.28	.25
7402	.19	.18	.16
7404	.29	.28	.25
7406	.27	.26	.23
7407	.33	.31	.28
7408	.33	.31	.28
7410	.19	.18	.16
7411	.55	.52	.47
7414	.27	.26	.23
7420	.24	.23	.21
7432	.33	.31	.28
7447	.89	.85	.77
7473	.79	.75	.68
7474	.33	.31	.28

FM MICROPHONE KIT

Transmit your voice on any FM radio. Range up to 1000'. Case included

STOCK#	1-9	10-24	25+
K30	11.99	11.39	10.25

What Do We Have ?

- I.C.'s
- Oscillators
- Crystals
- Diodes
- Tools
- Laser Diodes
- Vises
- Resistors
- Capacitors
- Connectors
- Trimpots
- Kits
- Vises
- LED's
- Transistors
- And more!

GADGETEER'S GOLDINE

This exciting collection of electronic projects features experiments ranging from magnetic levitation and lasers to high-tech surveillance and digital communications.

- By Gordon McComb

STOCK#	1-9	10-24	25+
TB3360	21.99	20.89	18.80

- Order Line — (800) 824-3432 • International — (724) 495-1230 • Fax Orders — (724) 495-7882
- Technical Support — (724) 495-1231 • No Minimum Order – (Orders under $20 subject to $ 5 charge) • UPS 3 day, Blue, Red, & Fed. Ex. Shipping Available (Call for charges) • PA Res. Add 7 % Sales Tax • Open Mon-Fri 9:00 AM - 5:00 PM (EST) • Corporate Accounts / Quantity Discounts Available • We accept M/C, VISA, Discover & American Express with no surcharge • Call For FREE Catalog ($2.00 Outside U.S.)
- We Carry A Complete Line Of Electronic Components • Email - unielect @ aol.com

FREE SHIPPING!!
on pre-paid orders

Unicorn Electronics
1142 State Route 18
Aliquippa, PA 15001

Write in 89 on Reader Service Card.

Turn Your Multimedia PC into a Powerful Real-Time Audio Spectrum Analyzer

Features

- 20 kHz real-time bandwith
- Fast 32 bit executable
- Dual channel analysis
- High Resolution FFT
- Octave Analysis
- Distortion measurements
- Signal Generation
- Triggering, Decimation
- Transfer Functions, Coherence
- Time Series, Spectrum Phase, and 3-D Surface plots
- Real-Time Recording and Post-Processing modes



Applications

- Distortion Analysis
- Frequency Response Testing
- Acoustic Research

System Requirements

- 486 CPU or greater
- 8 MB RAM minimum
- Win. 95, NT, or Win. 3.1 + Win.32s
- Mouse and Math coprocessor

Priced from $495

(U.S. sales only – not for export/resale)

DOWNLOAD FREE 30 DAY TRIAL!

www.spectraplus.com

PHS Pioneer Hill Software
24460 Mason Rd.
Poulsbo, WA 98370
a subsidiary of Sound Technology, Inc.

Spectra Plus
FFT Spectral Analysis System

Sales: (360) 697-3472 *Fax: (360) 697-7717* *e-mail: pioneer@telebyte.com*

Write in 72 on Reader Service Card.

RF Data Modules



AM TRANSMITTER

- Small size: 17.78 x 11.43mm
- CMOS/TTL input
- No adjustable components
- Low Current. 4mA typical.
- 418MHz or 433.92MHz OOK
- Simple to integrate -simply add antenna, data and power
- Range up to 250ft.
- Wide supply range, 2-14Vdc
- SAW controlled - stability
- Also available in DIL package

AM-RT5 ..... $12.10



AM RECEIVER

- Compact size: 38.1 x 13.7mm
- On-board data recovery. CMOS
- Low current. 2.4mA typical
- 2kHz data rate. CMOS/TTL output
- 5Vdc operation
- On 418MHz or 433.92MHz (4xx)
- No adjustable components
- Patented Laser Trimmed component
- High stability
- Sensitivity: -105dBm
- Available also in 0.8mA version

AM-HRR3-4xx $10.95

FM TRANSCEIVER

- Only 23 x 33 x 11mm
- Up to 40k bps data rate
- 19200 baud with ASCII
- Up to 500ft. range
- 5v operation
- 0.25mW into 50
- 418 or 433MHz FM
- Fast 1ms enable
- Direct interface to 5V CMOS
- Auto TX/RX changeover

BIM-4xx-F $87.36

RS232 TRANSCEIVER MODULES



- 4,800 to 38,400 bps half duplex
- 3-wire RS232 interface
- µController with user EEPROM
- RS232 interface protected to ±15kV
- Data packetizing performed by user
- Auto TX/RX changeover
- 418 MHz and 433MHz versions
- Range up to 500ft. (0.25mW ver.)
- 0.25mW & 10mW versions
- Reset switch and status LED's
- 7.5-15V dc via DB9 connector, 20mA

BIM-4xx-RS232 .... $139.30

70 x 65 x 15mm

- Up to 19,200 bps half duplex
- 3 wire RS232 interface
- Range up to 500ft
- Transparent data packetizing
- Supports 8 or 9 bit protocols
- Self test function
- Reset Switch & Staus LED's
- 1/4 wave wire antenna on board
- Available in a Simplex Tx/Rx pair.(RTcomTX & RTcomRx)
- 7.5V-15Vdc operation

Transceiver..... **RTcom-4xx..... $247.90**
Transmitter..... **RTcomTx-4xx..... $ 87.15**
Receiver..... **RTcomRx-4xx..... $105.52**

ABACOM TECHNOLOGIES

Free Catalog

Tel: (416)236-3858
Fax: (416)236-8866
www.abacom-tech.com
abacomtech@compuserve.com

BUILD THIS STEPPER MOTOR CONTROLLER

by David Williams

If you're interested in robotics, motion control, or just want to learn about stepper motors, then you should try building this versatile stepper motor controller.

This project allows you to control the speed, direction, and step size of a unipolar four-phase stepper motor. The controller is capable of handling motor winding currents of up to 1.25 amps per phase and it operates from a single supply voltage of 6-30 volts DC.

A unique feature of this project is that the circuit can operate in either remote mode or stand-alone mode. In the stand-alone mode, an on-board pulse generator and a four-position DIP switch allows you to demonstrate all of the functions without any additional connections. This mode is perfect for demonstrating basic stepper motor control principles. The circuit even has LEDs that show the energized phases for each step.

In remote mode, all motor functions can be interfaced to external logic or a microcontroller. This allows the controller to be incorporated into a robot, an X-Y plotter, or any motion control project you have in mind!

Pin Assignments -

LM555N Timer IC

Pin Assignments -



UCN5804B STEPPER MOTOR TRANSLATOR/DRIVER

CIRCUIT DESCRIPTION

Refer to the schematic of the stepper driver shown in Figure 1. Power is supplied by a DC wall transformer or DC power supply at P1.

The voltage can be anything from 6 to 30 volts, depending upon the rating of the stepper motor. The stepper motor uses most of the current in this circuit, so it is powered directly from the transformer output through resistors R1 & R2.

These resistors limit the current to the motor and allow the motor to be operated with a power supply voltage greater than the voltage rating of the motor for improved performance.

Stable voltage for the rest of the circuit is obtained by regulating the input voltage down to 5V with U4, a LM78L05 voltage regulator IC. Capacitors C7, C1, and C5 provide additional voltage filtering. U1 is capable of supplying up to 100 mA of current.

The heart of the stepper controller is U1, a UCN5804B stepper-motor translator/driver IC. It contains a CMOS logic section for the sequencing logic and a high-voltage bipolar output section to directly drive a unipolar stepper motor. U1 can generate waveforms for three different sequence modes: (1) FULL-STEP with two phases energized, (2) FULL-STEP WAVE and (3) HALF-STEP. The waveforms for these three sequence modes are shown in Figure 5.

Diodes D1-4 are clamps to prevent damage to U1 if the outputs swing below ground when driving the inductive load of the motor.

Each of the LEDs L1-4 light when the corresponding output goes LOW and are useful for observing the output waveforms. Resistor R3 provides current limiting to the LEDs.

Pins 9, 10, 14, and 15 of U1 are control inputs for phase, half-step, direction, and output-enable. These signals are pulled-down to a logic LOW level by resistors R7-11.

The control signals go to both con-



FIGURE 1

nector P3 and the four-position DIP switch (S1-4). Switches 1-4 allow for manual control of each function, or alternatively, connector P3 allows the functions to be controlled by external logic or a microcontroller chip.

The UCN5804B requires an external pulse input on pin 11 to advance the stepper motor. This signal can be supplied by external logic via connector P3 or can be provided by U2 or U3. U2 and U3 are LM555N timer ICs and are used to provide single-step or continuous pulses to U1.

U2 is configured as an astable oscillator that delivers continuous pulses. The pulse rate is controlled by potentiometer R13 and capacitor C2. Jumper J2 connects C6 in parallel with C2 to give a LOW SPEED range. U3 is configured in a monostable mode to produce a single pulse when S5 is pressed. Jumper J1 selects between the single-step or continuous mode.

ASSEMBLY INSTRUCTIONS

The easiest way to build the stepper motor controller is to use an etched circuit board as shown in Figure 2. If you don't want to fabricate your own board, a pre-etched and drilled board can be purchased from the source shown in the parts list.

Locate all the components shown in the parts list and use Figure 3 to determine component placement on the PC board. Begin by using three pieces of solid wire for J1, J2, and J3. Next install and solder the four diodes in place, noting their polarity. Then move on to the resistors and ceramic capacitors.

When installing the 5-watt resistors R1 and R2, leave a small space between the resistors and the PC board to allow for air circulation. Be sure to observe proper polarities when installing the electrolytic and tantalum capacitors and the voltage regulator. Note that it may be necessary to bend the leads of the U4 to fit the PC board.

Now solder IC sockets for U1, U2, and U3 to the board. If you use the switch specified in the parts list for S5, it can be soldered directly on the printed circuit board. Then install the four LEDs as shown in Figure 3.

It is recommended that you use screw-terminal connectors for P1 and P2. Potentiometer R13 can be either PC mount style or panel mount style. To use a panel mount potentiometer, cut three pieces of stranded wire to connect R3 to the PC board. If you plan to use the controller in stand-alone mode, solder a four-position DIP witch for S1-4. You may omit the DIP switch if you plan to use the P3 connector for remote interfacing.

Next, locate the UCN5804B integrated circuit (U1). Since U1 is a CMOS device, it can be easily damaged by static electricity. Take proper anti-static precautions when handling the chip. Refer again to Figure 3 before installing U1 to make sure of the proper orientation of pin 1, then press the IC firmly into the 16-pin socket. Repeat the procedure with ICs U2 and U3.



FIGURE 2



FIGURE 3

FINAL ASSEMBLY

Before continuing, clean the foil side of the PC board with alcohol or flux remover. Then refer to Figure 4 for details on connecting the stepper motor and DC power supply. Note that the wire colors for the stepper motor shown in Figure 4 apply only to the PF-42 motor that is included in the purchased kit. If you use a different motor, you will need to determine the appropriate wire connections to P2. Also note that the circuit is designed to drive six-wire UNIPOLAR motors only. Next, attach the wires from the DC power source to the PC board, observing the polarity show in Figure 4.

OPERATION

To run the stepper controller using the on-board oscillator, install jumper J1 in the "A" position and leave J2 open.

On the four-position DIP switch, set S1, S2, S3, and S4 all to the "OFF" position. Switch the DC power source ON and the stepper motor should start to turn. The speed can be regulated with potentiometer R13. Installing jumper J2 will switch to a low-speed range. If you try to drive a stepper motor too fast or with too large of a load, it can stall (see the note listed at the end of the article).

With the motor turning properly, you can switch S2, S3, and S4 to change the direction, step size, or phasing (see Figure 6). Note that S1 is

FUNCTION	S4- PIN 9	S3- PIN 10	FUNCTION	S2- PIN 14	S1- PIN 15
FULL-STEP 2-PHASE	L	L	FORWARD	L	
FULL-STEP WAVE DRIVE	H	L	REVERSE	H	
HALF-STEP	L	H	OUTPUT ENABLED		L
STEP INHIBIT	H	H	OUTPUT DISABLED		H

FIGURE 6

the output enable and will stop the motor when the switch is in the "ON" position. To control the stepper functions remotely, set all of the DIP switches to the "OFF" position and then use P3 to connect the control signals to an external microcontroller or toggle switches.

To operate the stepper controller in the single-step mode, install jumper J1 in the "B" position. Each time you press switch S5, the LN555 (U3) will produce a single pulse and will cause the UCN5804 to advance the motor one sequence position. The motor sequence will still be determined by the settings of S2, S3, and S4.

For single-step to work properly, you must release S5 before U3 completes its output pulse or else the LM555 will automatically re-trigger. The single-step mode is a great educational tool because you can actually observe the various step sequences in the LEDs (L1-4).

This controller is a robot builder's dream come true! The kit also makes a great educational project for demonstrating basic stepper motor control principles. **NV**

NOTE:

All stepper motors exhibit an inverse speed-torque relationship. As the stepping rate increases, the back EMF produced by the motor causes the current to decrease, which leads to a decrease in torque. If the stepping rate continues to increase, at some point the torque of the motor will drop below the inertial load and the motor will "STALL." The speed-torque curve can be greatly improved by using a higher input voltage with series resistors (R1 and R2). Higher input voltages will continue to improve the performance until practical power dissipation limits are reached or the voltage/current ratings of the UCN5804B are exceeded.



FULL-STEP (TWO PHASE)



HALF-STEP



FULL-STEP (WAVE DRIVE)

FIGURE 5

FIGURE 4



Parts List For The Stepper Motor Controller

Resistors (Except where noted, resistors are 5%, 1/4 Watt)
R1,2 ..... 50 Ohm, 5 Watt
R3 ..... 330 Ohm (Orange, Orange, Brown, Gold)
R4 ..... 10 K Ohm (Brown, Black, Orange, Gold)
R5 ..... 22 K Ohm (Red, Red, Orange, Gold)
R6 ..... 220 K Ohm (Red, Red, Yellow, Gold)
R7-12 ..... 100 K Ohm (Brown, Black, Yellow, Gold)
R13 ..... 100 K Ohm Potentiometer
Capacitors
C1-3 ..... 0.1 uF, Ceramic, marked: [104]
C4-6 ..... 1.0 uF, 16V Tantalum or Electrolytic
C7 ..... 470 uF, 35V Electrolytic
Semiconductors
U1 ..... UCN5804B, Stepper Controller IC
U2,3 ..... LM555N, Timer IC
U4 ..... LM78L05, 5 Volt DC Regulator (TO-92)
D1-4..... 1N4001 (or 1N4004), Rectifier Diode
L1-4 ..... RED Light Emitting Diode
Miscellaneous Items
JP1 — Wire Jumper, 0.4 inches long
JP2 — Wire Jumper, 0.5 inches long
JP3 — Wire Jumper, 0.6 inches long
J1 — 3-pin Jumper Post & Shorting Blocks
J2 — 2-pin Jumper Post & Shorting Blocks
P1 — 2-pos Terminal Block
P2 — 6-pos Terminal Block
P3 — 7-pin Jumper Post
S1-4 — 4-position DIP Switch
S5 — Miniature Pushbutton Switch
U1 — 16-Pin IC Socket
U2,3 — 8-Pin IC Socket
PCB — Etched Printed Circuit Board (STP0297)
MOT — Unipolar (6-wire) Stepper Motor
TXFMR — 12-14V DC, 500mA Wall Transformer or DC power supply
Misc: Hook-up Wire, Hardware, Solder, Etc.

The following items are available from: **LNS Technologies,** P.O. Box 67243, Scotts Valley, CA 95067, Phone: **(831) 768-9155**.

STEPPER-KIT: Complete kit of parts for the Stepper Motor Controller including etched and drilled printed circuit board, stepper motor, DC wall transformer, ICs, and all other components listed above $39.00. UCN5804B: Stepper Motor Driver IC (U1) $5.00. STEPPER-PCB: PC Board for Stepper Controller Kit $10.00.

Please add $5.00 Shipping/Handling. California residents add 8% sales tax. MC/VISA orders accepted. No COD orders.

The UCN5804B IC is also available from:
Alltronics, 2300 Zanker Rd., San Jose, CA 95131, **(408) 934-9773**.
931002: Stepper Motor Driver IC $4.50.

Events CALENDAR

Continued from page 42

OH - MASSILLON - Hamfest. Stark County Fairgrounds, 305 Wertz Ave. N.W. Talk-in: 147.18+ repeater. MARC, Don Wade W8DEA, 330-497-7232; Terry Russ, 330-837-3091 before 10pm. E-Mail: MARC.HAMCLUB@JUNO.COM

NOVEMBER 7

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052

FL - SORRENTO - Hamfest. Lake ARA, Chuck Crittendon KA4EXM, 352-669-2075

KY - HAZARD - Swapfest. Hazard High School, south end of Rt. 15, Hazard Bypass. 8am-2pm. VEC Exams. Talk-in: 146.07/.67. KY Mountains ARC, John Farler K4AVX, 606-436-5354. E-Mail: jfarler@mis.net Web: http://www.geocities.com/SiliconValley/2564/kmarc.html

NH - LONDONDERRY - Ham Radio Flea Market. Lions Club, Mammoth Rd. (Rt. 128). 8am-1pm. The Interstate Repeater Society ARC, Paul Gifford, 603-432-1538. E-Mail: k1llx@juno.com

NM - SOCORRO - Hamfest. SARA, TARA, & City of Socorro, Al Braun AC5BX, 505-835-3456 days or 505-835-1061 eves. E-Mail: AC5BX@juno.com Web: http://www.ees.nmt.edu/

OK - ENID - Hamfest. Garfield County Fairgrounds, Hoover Bldg., Oxford & 4th Sts. 8am-5pm. VE Exams. Talk-in: 147.15+ 444.400+. Tom Worth N5LWT, 580-233-8473, E-Mail: N5LWT@HOTMAIL.COM. Fred Selfridge N5QJX, 580-242-3551, E-Mail: FREDNNEL@IONET.NET

SC - MYRTLE BEACH - Beachfest '98. Myrtle Beach High School, 38th Ave. N. VE Exams. Talk-in: 147.12. GSARC, Jim Wood KF4CJE, 843-238-0800. E-Mail: kf4cje@juno.com Web: www.w4gs.org, http://www.qsl.net/kf4hav/hamfest.htm

WI - WAUKESHA - Hamfest. Milwaukee Repeater Club, Mike KB9PHA, 414-258-4435. Web: http://execpc.com/~mrc/friendlyfest.htm

NOVEMBER 7-8

GA - LAWRENCEVILLE - Hamfest. Gwinnett County Fairgrounds. Sat: 9am-5pm, Sun: 9am-3pm. VE Exams. Talk-in: 145.45, PL 107.2 if necessary. Alford Memorial RC, Randy Bassett KR4NQ, 770-410-3989. E-Mail: Hamfest@totr.radio.org

TX - ODESSA - Hamfest. Ector County Coliseum, Exhibit Bldg. D., 42nd & Andrews Hwy. Sat: 8am-5pm, Sun: 9am-1pm. VE Exams. Talk-in: 145.470. West TX ARC, Robert Jordan N5RKN, 915-335-7980. E-Mail: n5rkn@apex2000.net Web: http://www.apex2000.net/personal/wd5cwj/main2.htm

NOVEMBER 8

WI - KAUKAUNA - Hamfest. Starlite Club, Corners of Hwy. 55 & CR JJ. VE Exams. Talk-in: 146.52 simplex. Fox Cities ARC, Chad Pennings N9PRC, 920-993-0485. Web: http://www.w9zl.ampr.org

NOVEMBER 14

AL - MONTGOMERY - Hamfest & Computer Show. Garrett Coliseum, S. AL State Fairgrounds. 9am-3pm. Phil 334-272-7980 after 5pm CST. E-Mail: wb4ozn@worldnet.att.net E-Mail: kf4ilp.arthur@worldnet.att.net Web: http://jschool.troyst.edu/~w4ap/

CA - FONTANA - Inland Empire ARC Amateur Radio & Electronics Swapmeet. A B Miller High School. Bill 909-822-4138 eves

FL - PORT ST. LUCIE - Hamfest. Port St. Lucie ARA, Paul Harrison KI4MG, 561-878-2475. E-Mail: julian@ecqual.net

FL - TITUSVILLE - Hamfest. Titusville ARC, Bud Hughes K4CWG, 407-267-3450. E-Mail: bud@expedient.com

LA - WEST MONROE - Hamfest. Twin City Ham Club, Mark Ketchell N5MYH, 318-323-6621. E-Mail: TCHC@iAmerica.net Web: http://cust.iamerica.net/TCHC

NOVEMBER 14-15

IN - FT. WAYNE - Hamfest & Computer Expo. Allen County War Memorial Coliseum Expo Center. Sat: 9am-4pm, Sun: 9am-3pm. VE Exams. Talk-in: 146.88(-). Doug Jones N9NNT, 219-484-3317. E-Mail: djones2233@aol.com Web: http://www.pipeline.com/~dagagnon/

NOVEMBER 15

NC - BENSON - Jarsfest. American Legion Complex, Hwy. 301, N. 8am-4pm. Talk-in: 147.270 + 600. VE Exams. Johnston ARS, Paul Dunn KD4BJD, 919-894-3100 Web: http://www.jars.net

NOVEMBER 18

FL - ST. PETERSBURG - Hamfest. Pelican Chapter #128 QCWA, Jay Strom K9BSL, 813-822-9107

NOVEMBER 20-21

MS - OCEAN SPRINGS - Hamfest/Swapfest. Latimer Community Center, N. of I-10, Exit 50. Fri: 5-9pm, Sat: 8am-2pm. Talk-in: 145.110 N5OS (-600). West Jackson County ARC, Phil Hunsberger W9NZ, 228-872-1499; Harry McLemore KD4AK, 228-872-0732

NOVEMBER 21

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052

IL - LITCHFIELD - Hamfest. Central IL/St. Louis Area ATV Club, Scott Millick K9SM, 217-532-3837

NOVEMBER 21-22

FL - TAMPA - Suncoast Amateur Radio & Computer Convention. State Fairgrounds, Expo Hall. Ed Pellenz N4HRN, 813-685-7115 or 813-272-7021 xt. 3320. E-Mail: epellenz@cftnet.com

NOVEMBER 22

IL - WHEATON - Radio Fest, Electronics Flea Market. DuPage County Fairgrounds, Manchester Rd. GMRS of Illinois, Inc., 815-756-3933 or 630-393-3937

NOVEMBER 28

IN - EVANSVILLE - Winter Hamfest. Vanderburgh County Fairgrounds, Exposition Center. 8am-2pm. 145.150- Evansville, 146.925- & 443.925+ Vincennes. EARS, Neil WB9VPG 812-479-5741. E-Mail: EARSHAM@aol.com Web: http://members.aol.com/earsam/

NOVEMBER 29

CA - SANTA ANA - Swapmeet. ACP parking lot. Mary Russo 714-558-8813

DECEMBER 1998

DECEMBER 5

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052

GA - CLAXTON - Hamfest. Veterans Community Center, Hwy. 280 W. VE Exams. Talk-in: 147.075+. Claxton AR Emergency Service, Mr. Ellie Waters WB4CJB, 912-653-4939. E-Mail: ellie@premierweb.net. Wes Kennedy KU4SR, 912-739-2047, E-Mail: ku4sr@mci2000.com

LA - MINDEN - Christmas Hamfest. Civic Center, 520 Broadway. 8:30am-3pm. VEC Exams. MARA repeater 147.300+. MARA, Inc., Dusty Collins KB5WFE, 318-371-0636. E-Mail: dustyc@prysm.net Web: http://www.norwesla.com/mara.htm

NC - GREENSBORO - Hamfest. Coliseum Special Events Center. 9am-3pm. 76 Group, 336-851-1676. http://www.sabwc.com/gsohamfest

DECEMBER 6

CA - LIVERMORE - Hamfest. Livermore ARK, Cliff Kibbe KF6EII, 209-835-6715. E-Mail: larkswap@hotmail.com

DECEMBER 12

CA - FONTANA - Inland Empire ARC Amateur Radio & Electronics Swapmeet. A B Miller High School. Bill 909-822-4138 eves

FL - LAKE CITY - Hamfest & Computer Show. Columbia County Fairgrounds, SR 247, Gateway to FL #4. Columbia ARS, 904-935-2405 6-10pm, 904-755-7969 9am-4pm. E-Mail: wd4eoj@isgroup.net or wa5rkr@isgroup.net

DECEMBER 19

CA - SANTEE - ARC of El Cajon Ham, Computer & Electronic Swapmeet. Santee Drive-in. 619-561-0052

JANUARY 1999

JANUARY 9

SC - GREENWOOD - Hamfest & Computer Show. Greenwood Civic Center, 1610 Hwy. 72 E. 9am-5pm. FCC exams. Talk-in: 147.165+ (open) alternate: 146.52 simplex. Greenwood ARS, Frank Kolar WA9FWO, 864-229-5639

JANUARY 23

NC - WINSTON-SALEM - FirstFest. Dixie Classic Fairgrounds, Home & Garden Bldg. Forsyth ARC, Inc., 336-723-7388. Web: http://www.rbdc.com/~kq4lo/farc.htm

MICRO VIDEO CAMERAS

MB-750U & MB750P Video Cameras your Choice $89.95

- 1.25" sq.
- .1 LUX
- 420 TV Line

The Best, Smallest, Micro Cameras on the Market Today!
Call and Compare! We Match or Beat All Prices!

AFFORDABLE LIPSTICK CAMERAS

These cameras are supplied with a PCM-1 Video/Power cable. The RCA female connection is for standard video connection to a Monitor or VCR, Video signal -75 ohms at 1 volt peak to peak NTSC. The power is supplied to the camera by a 2.1mm barrel connector, 12 VDC center positive.

LP-850i -$119.95 LP-850p -$129.95

NIGHT VISION

Night Vision Scope w/ Illuminator
Fun to use, Low cost.
3.6 x 85mm f1.6
MI-PR100 - $399.95

WIRELESS VIDEO CAMERAS



Transmits Over 1000 ft.

GFT-1001 $189.95
Gives any camera the ability to be Wireless.
Transmits Over 1000 ft.

FREE Polaris Product Catalogs

Wireless Observations System's
GFS-1001 (900MHz) -$499.95
GFS-1001c (900MHz) -$599.95
(1.2 Ghz system's available)

Wireless 4-Channel B/W & COLOR Cameras Available!
Plug and Play Readiness

MICRO COLOR CAMERAS

Size: 1.25 x 1.25 sq. w/ Footprint

Micro Color MB-950C: $299.95
- Wide Voltage Range, 5-14 Volts!
- Small Footprint!
- Self contained ultra small package design for various applications.
- MCM PCB design for minimizing the size and improve durability.

Size: 1.7 x 1.7 sq. x 2 PC Board

Micro Color MB-960c: $199.95
- Lens: 3.6mm F=2
- Full Digital Process of BLC
- Auto Tracing White Balance
- 2H Mode of H.V. Aperture correction
- Digital process of color matrix
- Electronic Shutter up to 1/ 10,000
- Dip Switch Adjustment settings: 6)-BLC, 5)-Auto Shutter, 4)-AGC/On, 3)-Flickless, 2)-AWB/On, 1)-N/A

MB-1281 Color Camera
- Color module of 290,00 pixels 1/4" CCD
- 320 Horizontal Res. TV Lines
- DSP (Digital Signal Processing)
- Built -in Functions
  - Auto Gain Control
  - Auto White Balance
  - Electronic Shutter
  - Back Light Compensation
- Power - 12VDC @160mA
- Low Power Consumption

American Express DISCOVER MasterCard VISA

1-800-752-3571 Visit Polaris Ind. Web Site at: http://www.polarisusa.com

Polaris Industries 470 Armour Drive NE • Atlanta GA 30324 • Tech Info: 404-872-0722 • FAX 404-872-1038 Prices, availability and specifications are subject to change without notice. Shipping and Handling are not included with price.

A/D CONVERTERS with SERIAL OUTPUT

Tiny (1.75"x1.41") fully assembled and tested printed circuit board includes two 8-bit A/D converters and one digital input. Up to 16 units addressable (DIP switch setting) totalling 32 converters on a single serial port. Output is ASCII encoded bit count (0 to 255) at 2400 BPS via RJ-11 interface. Fully programmed PIC16C71 installed in IC socket. Sample software in BASIC included. Requires 8-28Vdc At 1-2mA. *$49.95*. Optional DC adapter $19.95. Add $5.00 shipping.

GLENTECH

Tele: 847-891-2584
Fax: 847-891-2587
www.glentech-rf.com

SURPLUS SALE

1,000,000 WALL TRANSFORMERS

3VDC/100MA	CX099	$0.75
6VDC/100MA	CS039	$1.45
9VDC/100MA	CR314	$1.45
12VDC/200MA	CS033	$0.99
13.5VAC/400MA	CR574	$1.29
24VDC/500MA	CR174	$3.40

Min 1000/type -- Call for other types

SURPLUS TRADERS
PO Box 276,
Alburg, VT 05440
Tel: (01) 514-739-9328
Fax: (01) 514-345-8303
http://www.73.com/w

FREE CATALOG!

PROGRAMMERS OVER 50 MODELS

ADVANTECH EETOOLS NEEDHAMS DATA I/O ICE TECHNOLOGY HILO SYSTEM GENERAL CHROMA MODULAR CIRCUIT TECHNOLOGY XELTEK

PROMAX EMP-20 MEGAMAX MEGAMAX4 SIMM/SIP TESTER EMUPA

CALL ADVANTECH LABTOOL	599 EETOOLS SIMMAX
629 ICE TECH MICROLV	795 CHROMA SIMM/SIP
650 EETOOLS ALLMAX +	359 MOD-MCT-EMUPA/R
409 EETOOLS MEGAMAX	279 MOD-MCT-EMUP/R
509 EETOOLS MEGAMAX4	49 EPROM 1G TO 512K
369 XELTEK SUPERPRO II	69 EPROM 1G TO 1MEG
409 XELTEK SUPERPRO II P	99 EPROM 4G TO 1MEG
249 XELTEX SUPERPRO L	199 EPROM 16G TO 1 MEG
165 XELTEK ROMMASTER II	89 EPROM 1G TO 8MEG
479 MOD-MCT-EMUPA	129 EPROM 4G TO 8MEG
739 STAG ORBIT-32	250 EPROM 8G TO 8MEG

LABTOOL48 MICROMASTER SUPERPRO ALLMAX PLUS ROMMASTER2

General Device Instruments
Sales 916-393-1655 Fax 916-392-4949
Web www.generaldevice.com E-Mail icdevice@best.com

BATTERY — YUASA

Sealed Lead-Acid/Gel-Cell
12V: 7AH $19, 2.3/4AH $16
18AH $39, 1.2AH $13
6V: 4AH $9, 10AH $13

Quantity Discounts Available
Call for other models

Aventrade
4518 Temple City Blvd.
Temple City, CA 91780
Tel. 626-286-0118 Fax 626-287-9618
E-Mail: aventrade@aol.com

Serial Problems???

Use your PC compatible desktop or laptop computer to debug serial communications problems with **Serial,** our test tool for serial communications.

Serial works with the standard data rates and asynchronous serial formats commonly found in modern office and industrial environments. Suitable for development, service work, and end-user problem diagnosis.

- Easy to Use
- Menu and Windows
- Highly Configurable
- Contextual Help
- Autobaud Detect
- Time Stamping
- Custom font editor for EGA/VGA Screens
- Saves Configurations
- Extensive Manual
- Block transmit ability
- CRC/LRC generation

Serial, with manual $99.95
Cable for full duplex monitoring $49.95

For Orders and Inquiries Call: 1-800-980-9806
Allison Technology Corporation
8343 Carvel, Houston, TX 77036
FAX and BBS 1-713-777-4746

GET IT UP BEFORE WINTER!

MARCONI ANTENNA 700W 50 Ω
THE BEST "LITTLE" LOW BAND ANTENNA

EASY TO INSTALL.

– 160M –
130' OVERALL
$53.95 PP

– 80M –
67' OVERALL
$46.95 PP

THE OCR, AN OPTICALLY COUPLED REGEN, IS AN **EXCEPTIONAL** REGEN RECEIVER KIT EASY TO ASSEMBLE. (SEE QST JUNE 98) ..... $ 91 95 PP

SEND FOR FREE CATALOG:
- **SMART BATTERY CONTROLLER KITS**
- **CODE PRACTICE OSCILLATOR.... $23.45 PP**
- **CURTIS KEYER KIT ..... $46.95 PP**

1-800 JADE PRO (523-3776)
www.jadeprod.com/
email: jadepro@jadeprod.com
JADE PRODUCTS INC. E. HAMPSTEAD NH 03826-0368

PCB's in Minutes From LaserPrint!*

8 1/2" x 11" Sheets

* Or Photocopier Use household iron to apply.

PnP BLUE or **PnP WET**

PnP BLUE — For High Precision Professional PCB Layouts	PnP WET — Easy Hobby Quality PCB's
1. LaserPrint	1. LaserPrint
2. Iron-On	2. Iron-On
3. Peel-Off	3. Soak-Off w/ Water
4. Etch	4. Etch
Adds an Extra Layer of Resist for Super Fine Lines on Std Clad Bds	Transfers Laser Printer or Copier Toner as Resist to Std Clad Bds

20Sh$30/40Sh$50/100Sh$100 Blue/Wet (No Mix)
Sample Pack 5 Shts Blue + 5 Shts Wet $20
VISA/MC/PO/CH/MO $4 S&H -- 2nd Day Mail
Techniks Inc. P.O. Box 463 Ringoes NJ 08551
(908)788-8249
100% Money Back Guarantee!-Dealer Inquiries Invited

Convert RS-232 to RS-485 or TTL/CMOS for Only $49.00

Communicate up to 4,000 feet, at up to 1 MEGA--BPS, full or half duplex. up to 32 units on one serial link, with 31 jumper options for flexible configuration. LED indicators.



COMMUNICATIONS CONVERTER

- **FULL SCHEMATIC AND DOCUMENTATION**
- **FULL FAMILY OF MODULAR DESIGNS**
- **RS-485/RS-422 REMOTE I/O MODULE KITS**
- **NETWORK SOFTWARE AND SOURCE CODE**
- **AUTOMATIC OR RTS UNITS AVAILABLE**
- **RJ-11/12 CONNECTORS OR TERMINAL STRIP**
- **TURN YOUR PC INTO A DISTRIBUTED DATA ACQUISITION AND CONTROL SYSTEM**

R.E. SMITH
(513) 874-4796
4311 TYLERSVILLE RD. ■ HAMILTON, OHIO 45011
www.rs485.com

TV 85 PJ & TV 86 CABLE CONVERTERS VOLUME & NON-VOLUME CONTROL

SALES/SERVICE
VOICE 1-800-473-0506
FAX 1-800-488-0525

FOSS WAREHOUSE DISTRIBUTORS
285 Schenck St.
N. Tonawanda, NY 14120
www.fossw.com

PCBs PER SQIN 9¢

$100.00 SETUP
WE SPECIALIZE IN SINGLE SIDED, 1 OZ, PC75

PCB LAYOUT 59¢

PER COMPONENT PIN $100.00 MINIMUM

ENGINEERING DIAGRAMS 39¢

PER COMPONENT PIN $100.00 MINIMUM

V&V MACH. & EQUIP., INC. (HOUSTON, TX OFFICE)
PH (281) 397-8101 FAX (281) 397-6220
MARKETING TECH. S.A. (MEXICO/PLANT)
PH 011 (525) 361-3351 FAX 011 (525) 361-5996

Peltier Junction

While They Last!

1 3/16 "x 1 3/16" cooling area

Quantity Pricing Available

WITH HEATSINK AND LEADS
$10 EACH
OR THREE FOR $25

COMREX RGB Composite Display



*refurbished
**90-day warranty

ONLY $99!!
Great for studio or lab monitors!!
640x480 resolution

Shreve Systems
318-424-9777
Ask for Jake

Returns subject to a 15% restocking fee. Prices are subject to change without notice.
WE ACCEPT VISA, MASTERCARD, AMEX, DISCOVER
http://www.shrevesystems.com

Telecom Hardware/Software Developers

STOP using your phone lines to test and demonstrate your telecom devices. Our affordable telephone line simulators offer authentic USA dial tone, busy signals, ringing, and exceptional speech quality.

RING-IT! TELCO SIMULATOR
- Single Line (two RJ-11 Jacks)
- LED Display
- DTMF Operation
- Automatic Ring-up Mode
- **$325** ($149 kit available)

PARTY-LINE TELCO SIMULATOR
- Six Extensions
- Caller-ID (Name/Nbr)
- Distinctive Ringing
- **$425** ($199.95 kit avail)

Digital Products
COMPANY
134 Windstar Circle
Folsom, CA 95630 USA
Tel: 916-985-7219
Fax: 916-985-8460
http://www.digitalproductsco.com

ADAPT-11 & ADAPT-12

Low-cost modules for HC11 & HC12 plug into solderless breadboards

- Evaluate your idea instantly!
- Breadboard it, for quick hardware changes
- Program it in-circuit, for quick software changes
- Debug your application– not the basics!

ADAPT-11 Modules feature three 8-bit I/O ports, SPI, SCI, eight 8-bit analog input channels, hardware timers/counters, & interrupts. All Starter Packages include PC serial download cable, documentation, & disk of utilities & examples. Bundle ImageCraft C for Windows (ICC11) with any Starter Package for an additional US$120 + $5 S&H.

HC11 Starter Package Configurations:

AD11-SP	2K EE/256 bytes RAM	US$ 74.95 + $5 S&H
AD11C75-SP	8K EE/512 bytes RAM	US$ 87.00 + $5 S&H
AD11C75DX-SP	8K EE/32K bytes RAM	US$120.00 + $5 S&H
AD11-SP64K	ADAPT-11 w/ 32K EE/32K RAM memory expansion card & dual slot adapter (2 I/O ports lost)	US$123.00 + $5 S&H

ADAPT-812 features 68HC812A4, (4K EE, 1K RAM, 85 I/O lines, eight high speed 8-bit analog inputs), memory expansion connector, RS232 & RS485, convenient firmware bootloader, plus support for all BDM pods. All this on a compact 2.25" x 3.25" board. Starter Package (AD812-SP) US$99+ $5 S&H. Add US$125 for ICC12WIN.
AVAILABLE SOON! ADAPT-912 features 68HC912B32 (32K Flash, 768 EE, 1K RAM, 56 I/O lines, 8 chan. analog), RS232 and RS485. All this and more on a compact 2.25" x 3.25" board! Starter Package (AD912-SP) US$99+ $5 S&H. Add US$125 for ICC12WIN.

TECHNOLOGICAL ARTS
voice/fax: (416) 963-8996
www.interlog.com/~techart

HIGH PERFORMANCE ULTRA-MINIATURE *PINHOLE LENS CAMERA W/ CASE*

The "NEW" SpyCam1 (in a metal case) is the smallest pinhole camera in the industry! Its actually smaller than the board cameras currently on the market. Comes w/mounting bracket, 50 ft cable & power supply for easy installation •High resolution—more than 400 lines, 0.1 lux •Ultra miniature - lightweight & measures only 29mm x 29mm x 12mm, •Pinhole lens offers sharp image w/ hightened sensitivity •Can be easily mounted behind a 1/16" hole for any custom/covert applications. *ONLY...$89.00*

Surveillance Catalog $5.00

SPY OUTLET
2468 Niagara Falls Blvd • Tonawanda NY 14150
(716) 695-8660 Fax 695-7380 www.spyoutlet.com

3-Axis Machine



Full function 3-axis machine kit based on Parallax's BASIC Stamp 2.
- 3 Stepper motor drive with 4 thou resolution
- Approx 12"x12"x18" when assembled
- Kits from $299
- Includes PCB Drilling software and Stamp code

Milford Instruments - England
Tel: 011-44-1977-683665 Fax: -1977-681 465
www.milinst.demon.co.uk

PC Board
Layout Software



www.expresspcb.com

ATTENTION DEALERS

WHOLESALE ONLY!

• ANY CABLE MFGR CONVERTERS & ACC

• BEST PRICING & SERVICE

• SHOP US *NOW*

PANASONIC • NOVA, ETC.

800-777-7731

ATOMIC TIME
FOR ANY COMPUTER

WWVB based time code receiver and real time clock with RS232 interface

FEATURES

- Sensitive receiver
- Direct UTC readout in ASCII
- Y2K compatible calendar
- 0.1 second accuracy
- RS232 powered
- Low cost

APPLICATIONS

- Remote data acquisition
- Embedded systems
- Automatic sequencers
- Tamperproof time stamping

ULTRALINK

702 782 9758 www.ulio.com

EPS

EPROMS AS LOW AS **25¢**

27C256	27C040	27C1024	87C51
27C512	27C400	28F010	8751
2732A	27C4096	28F020	8755
27C32	574000	28F040	68705
27C128	574200	8749H	2564
27C64	27C402	8748H	2516
2716	27C020	8741	
2708	27C210	8742	
27C512-90	27C010	8744	

PROCESSOR: 8255, 8254, 80C31

STATIC RAM / MEMORY: 62256 & 6264 & 6116, GAL16V8 & GAL22V10, PIC16C54 & PIC16C56

SPECIAL 2764

TEL: (818) 774-9444 · FAX: (818) 774-0822

WE BUY EXCESS INVENTORY



FREE SAMPLE COPY!

ANTIQUE RADIO CLASSIFIED

Antique Radio's Leading Monthly Magazine

Articles – Classifieds – Ads for Parts & Services. Also: Ham Equip. – Books – Telegraph – 40's, 50's & 60's Radios – Early TV – Auction Reports & more...

1-Year: $40.95 ($57.95 by 1st Class)
6-Month Trial - $20.95. Foreign - Write.

A.R.C., P.O. Box 802-G21
Carlisle, MA 01741

Call: 978-371-0512 — Fax: 978-371-7129
Web: www.antiqueradio.com

EQUIPMENT FOR SALE

ELECTRONIC TEST

Tektronix	EXT 330
Hewlett-Packard	EXT 331
Other Manufacturers	EXT 332
MEASURE & INSPECT	EXT 333
VIDEO PRODUCTS	EXT 370
SCIENTIFIC & LAB	EXT 335
LASERS	EXT 340
POWER SUPPLIES	EXT 334
COBWEB CORNER	EXT 380
MFG COMPLETE INDEX	EXT 300

To obtain information via FAX: A) Have your fax number ready. B) Dial 1-800-547-4636. C) Request above Extension Numbers.

DEXIS CORPORATION
(612) 944-7670 FAX (612) 942-9712
9749 HAMILTON ROAD
EDEN PRARIE, MN 55344

CUT MANUFACTURING COST!

CUSTOM METAL BOXES
WE ACCEPT SMALL ORDERS TOO

SHEET METAL
20 GAUGE
SILK SCREEN
PRINTED
WITH YOUR CO. NAME



ALSO PCB, SMT, PROTOTYPES, ASSEMBLY. PLASTIC MOLDS. INJECTION MOLDING.

USA Office: **V&V Mach. & Equipment, Inc.**
Ph: (281) 397-8101, Fax: (281) 397-6220.
Mexico Plant: **Marketing Tech.**
Ph: 011 (525) 361-3351, Fax: 011 (525) 361-5996.

Get PIC'n!

Everything you need to get started with the exciting **PIC microcontrollers** today!

PIC-n-GO Package includes:

ITU PIC-1+ Programmer

- Programs ALL PIC16C55x/6x/7x/8x/9x, PIC16F8x, and PIC12C devices!
- 5 pin expansion header for In-System Programming and adapters
- Power Supply, Cable, Software, Manuals and Example Programs

Options: 18 pin ZIF - add $15
40/28 pin ZIF adapter - $39

PLUS: a PIC16F84-10/P Electrically-Erasable Microcontroller **Only $75!** *Kit only $45*

See our Web Page for more PIC products!

Order Toll Free! (888) 4-ITU-TEC Visa, MC and AE Accepted

ITU Technologies
3704 Chevrot Ave. Ste. 3, Cincinnati, OH 45211
Phone: (513) 661-7523 Fax: (513) 661-7534
E-mail: sales@itutech.com

ASSEMBLY & ENGINEERING

Producible designs since 1970

Contract Engineering
- Embedded Microprocessors
- PCB Layout and Packaging Design
- Analog Including RF to 1 GHz
- Instrumentation
- A/D and D/A

Contract Assembly
- High-Speed Fuji Surface Mount
- Through hole
- Turn-key or Kit
- Run sizes one through thousands
- Test and burn-in available

Bilocon Corp.
800-736-5927
425-353-2276
www.bilocon.com

ST241A
Stereo microscope
$240.00
New – 1 year warranty

Seabird Technical
3580 Haven Avenue
Redwood City, CA 94063-4603

650/367-8320
Fax – 365-5845

Email-jlittle @ netwizards.net

CONTROL · MEASURE · INPUT

MODEL 40–$109
- RS-232 interface
- 28 lines digital I/O
- Eight analog inputs
- PWM output
- Three stepper ports

MODEL 100–$279
- 12-bit 100KHz A/D · Four analog outputs
- Three timer counters · 24 digital I/O

PRAIRIE DIGITAL, INC.
920 SEVENTEENTH ST., INDUSTRIAL PARK
PRAIRIE DU SAC, WI 53578
TEL: (608) 643-8599 · FAX: (608) 643-6754

Javalin Computer Systems

Pentium II P300MMX 3D Multimedia System

SYSTEMS INCLUDE:

MID TW. CASE, MB W/P II CHIPS 512 CACHE, 64MB EDO RAM, 5.1 GB HARD DRIVE, 24X CD ROM, 4MB 64 BIT 3D VIDEO CARD, 3.5" 1.44MB FD, 16 BIT 3D SOUND CARD, 33.6 FAX MODEM WITH VOICE, WIN 95 MOUSE, WIN 95 104 KEYBOARD, 80 WATT SPEAKERS, WIN 95 REL. 2, 17" SVGA MONITOR INCLUDED

$1499

800-804-6552

SURVEILLANCE
FREE CATALOG

Color Cameras Starting at $149 | IR Flashlights Starting at $35 | Night Vision Starting at $169

FULL ONLINE CATALOG
www.mscelectronics.com

MSC Electronics
PO BOX 461 Jessup, MD 20794
(301) 497-1600
FAX (301) 497-1925

---

1 MB cache, AMD 300

System featuring: 9/10/98

Mini+ Tower, **VIA** chipset, 100 MHz operation, **2 USB** ports, **64 MB PC-100** compatible memory, **8.4 GB IBM** UDMA33 drive, 32X CD-Rom with audio button, **8 MB** video card, ATI chipset, 1.44 floppy, **56Kflex/V.90** Diamond **PCI** faxmodem, 3D sound card, full-size speaker set, **17"** digital monitor, Windows 98 on CD $1179

tech-specialities, Inc.
(800)864-5391, fax: (713)307-0314
email: sales@ts.nu, web: www.ts.nu

Detailed Quote on other configurations (PII 300/400, single/dual CPU or **low cost**, 233 MHz/32 $570 w. monitor) by email, fax or phone. Ask for **Free Shipping** and **Catalog!**

TURNER TECHNOLOGIES, INC.
300 EUGENE ST. S.E., GRAND RAPIDS, MI 49507
616-475-8531 · 616-475-8534 FAX

LIST PRICE $275

THE REVOLUTIONARY **SMART PHONE**



- Advanced Caller ID with Call Waiting
- Personal Directory with 500 Name, Number, Address & Speed Dialing
- 1500 Name Speed Dialing
- Calendar, Date & Time Display
- Flash, Mute, Hold & Speaker Buttons
- Voice Mail with Local Phone Company
- And much, much more ...

OUR PRICE
$49.95

HF TO GO

The World's Smallest Full-Featured HF-SSB Radio

The SG-2020 is the perfect choice for base, backpacks or business trips. • Weighing in at just 4.5 pounds, the SG-2020 features fully adjustable output power from 0 to 20 watts PEP. • Low current requirements in receive mode allow practical battery pack operation. • A bullet-proof front end provides third order intercept at better than +18dB, virtually eliminating adjacent channel interference. • Designed with the portable user in mind, it comes complete with built-in, fully adjustable mode 'B' lambic keyer, VOGAD baseband speech processing and RF clipping. • All this plus legendary SGC quality and reliability at an incredibly low price.

SG-2020

For complete details on the SG-2020, see your SGC dealer, or check out our website.

SGC 1-800-259-7331 www.sgcworld.com

MADE IN USA

P.O. Box 3526 Bellevue, WA 98009 USA
Phone: (425) 746-6310 Fax: (425) 746-6384 Email: sgc@sgcworld.com

Write in 29 on Reader Service Card.

Equipment Management Technology
From Acquisition to Disposition

BUY * RENT * SELL
Quality
Test and Measurement Equipment

We inventory HP, Tektronix, Fluke, Anritsu, Wiltron, Iwatsu, Wavetek, GenRad and many other manufacturers. Our product lines include RF & microwave, oscilloscopes, generators, supplies, communications, voltage and frequency standards. Call us now for a quote!

Tel 650-631-1700 * Fax 650-631-1200 * email sales@emt1.com

Write in 30 on Reader Service Card.

HAM GEAR FOR SALE

MOTOROLA GP-68 VHF (136-174MHz) or UHF (430-470MHz) commercial handhelds 20 ch., DTMF keypad, PL/DPL, rapid 3 hours desktop charger 1200mAh battery, user programmable only $295 ea. E-Mail: info@nsiradio.com Tel 253-946-2426 Fax 253-946-8311. NSI Communications, Inc.

THE ALC245M AUTOMATIC VOLUME CONTROLLER will keep your transceiver or scanner's volume constant from a whisper to a scream. $22.95 S&H $5. Other models also available. **FREE BROCHURE**. C&S Electronics, PO Box 2142, Norwalk, CT 06852-2142. Phone: 203-866-3208 Fax: 203-854-5036. E-Mail: CANDSELECT@worldnet.att.net Visa, MasterCard, AMEX.

1998 CATALOG: big selection of inductors, ferrites, micrometals toroids, mica capacitors, components, semiconductors, more. Two stamps please. Johnson Shop Products, Box 2843, Cupertino, CA 95015.

MILITARY COMPONENTS wanted. Capacitors, resistors, diodes, transistors, semiconductors, ICs. Electronic Material Industries, 818-769-1002, FAX: 818-769-1084.

MIKEMASTER: A microphone preamplifier with noise gating & compression. Created by Marv Gonsior W6FR, March 1998 QST. Got noise get MikeMaster! For kit order #210-KIT at $69.95. Assembled & tested (specify Kenwood, ICOM, or Yaesu wiring) order #210-ASY at $89.95. Shipping for US & Canada is $6.50, others add 15%. CA residents add 7.75% sales tax. For info send legal size SASE to A&A Engineering, 2521 W. LaPalma #K, Anaheim, CA 92801. P 714-952-2114, Fax 714-952-3280.



CELLWAVE 4 channel cavity, ferrite transmitter combiners. 870MHz combiners will tune down to 860MHz. Cellwave model no. 505980. Dimensions: 13x18x13 inches. Weight: 50 lbs. $475. Cellwave power monitor ZRB101 with DSG-2 sensor $275. Test Equipment, 1412 S. Central Park Ave. #D, Anaheim, CA 92802. 714-778-5151. Fax 714-778-0312.

LML RADIO 2 meter mobile amp by Motorola 60 watt $30; Motorola Moster VHF 16 ch. 45 watt programmable $30; Motorola MT500 40-50MHz PL w/ant. $35; UHF repeater 15W programmable 256 channels $120. Free catalog 909-873-1319. Fax on demand 24 hr. 909-820-1885. Web catalog Http://members.aol.com/hrh6/LMLinc Write 424 E. Shamrock, Rialto, CA 92376.

WANTED: ROCKWELL-Collins HF-80 equipment, 851S-1, 237B-3 log periodic, Collins literature. Jim Stitzinger 805-259-2011, 805-259-3830 (fax), bfl-jfs@smartlink.net

SPECTRUM ANALYZERS, test equipment. Closing R&D/manufacturing company. Must sell lots of equipment. Call 1-800-869-7827 or visit www.starcom.com

---

ALFA ELECTRONICS

HIGH QUALITY TEST EQUIPMENT

Visit www.alfaelectronics.com for complete info
Call 1-800-526-2532 for Order and Free Catalog

DMM

DMM-89S ($179.00): true rms, AC/DC (V,A), Ω, bar graph, freq, capac., dBm, logic, diode
DMM-23T ($99.95): 4½ digit, true rms, high resol. (10µV, 10nA, 10mΩ), hFE, diode, contin.
DMM-20 ($74.95): AC/DC (V, A), Freq, cont., Capac, Induct., Ω, hFE, diode, duty cycle
DMM-122 ($59.95): DC/AC(V,A), Ω, hFE, diode, capacitance, freq, logic, continuity
DMM-123 ($44.95): DMM + capacitance, DC/AC(V,A), Ω, hFE, diode, continuity
DMM-10 ($19.95): 3½ digit, DC/AC V, Ω, hFE, diode, signal output(+3V,-0.5Vsq.,50%duty)

LCR/COUNTER

CAP-15 *($49.95)*: 3½ digit, 0.1pF-20mF, 9 Ranges, 0.1pF resolution, zero adjustment.
LCR-24 *($119.95)*: 0.1µH-200H, 0.1pF-2000µF, 0.01Ω-20MΩ, diode test. *New Model.*
LCR-131D *($219.95)*: autorange, 0.1µH-10kH, 0.1pF-10mF, 1mΩ-10MΩ, Q Factor, serial/parallel, 120Hz/1kHz testing mode.
FC-1200 *($129.95)*: 1.25GHz Handheld, 8 digits display, 10ppm accuracy, sensitivity 5mV (130-350MHz), 30mV (440MHz)

FLUKE

12B	$ 94.95
70-III	$ 99.00
73-III	$125.00
75-III	$155.00
77-III	$173.00
79-III	$195.00
87-III	$325.00
92B-III	$1,445
96B-II	$1,695
99B-III	$2,095
105B	$2,495
123-III	$1,130
863E	$555
867B	$740

SPECIALTY

• AC Current Probe	$34.95
• DC/AC Current Probe	$79.95
• Mini AC Clamp	$59.95
• AC Clamp w/temp	$89.95
• DC/AC Clamp	$109.95
• Thermometer	$69.95-$89.95
• IR Thermometer	$189.95
• Sound Level Meter	$169.95
• Tachometer	$169.95-$219.95
• EMF Tester	$69.95
• Pressure Meter	$299.95
• Watt Meter	$129.95
• High Voltgae Probe	$59.95
• pH Meter	$79.95
• Light Meter	$79.95-$89.95



Single Output DC Power Supplies

• Constant current, constant voltage mode
• Short Circuit and overload protected

Analog Meters Display	*Digital Volt, Analog Current*
PS-303 ($159.00) 30V/3A	PS-8200 ($179.95) 30V/3A
PS-305 ($219.95) 30V/5A	PS-8201 ($239.95) 30V/5A
PS-8112 ($399.95) 60V/5A	*Digital Volt & Current Display*
PS-1610 ($289.00) 16V/10A	PS-8300 ($199.95) 30V/3A
PS-8107 ($399.95) 30V/10A	PS-8301 ($259.95) 30V/5A

Triple Output

• independence or Tracking operation
• Parallel to double current output (PS-8102 & PS-8103 only)

Triple Output (Analog displays)
PS-8102 ($399.95) 30V/3A/30V/3A
PS-8103 ($489.95) 30V/5A/30V/5A

Digital Displays
PS-8202 ($499.95) 30V/3A/30V/3A
PS-8203 ($549.95) 30V/5A/30V/5A

AUDIO/RF/FUNCT. GEN.

RF Generator • SG-4160 ($124.95) 100kHz-150MHz sinewaves in 8 ranges
• **SG-4162AD**($229.95) with 6 digit counter
Audio Generator • AG-2601 ($124.95) 10Hz-1MHz, 0-8Vpp sine, 0-10Vpp squarewave
• **AG-2603AD** ($229.95) with 6 digit counter
Function Generator • FG-2100A ($154.95) 0.2Hz-2MHz,5mV-20V_{pp}
• **FG-2103** ($329.95) *Sweep* 0.5Hz-5MHz

GW/INSTEK®

20 MHz Scope

• **OS-620 $324.95**
• Most economical scope
• Dual CH/X-Y operation
• 1 mV/div sensitivity
• Z-axis input,CH1 output
• TV syn, ALT trigger
• 2 probes (x1, x10)

Cursor Readout

• **OS-626G $599.95**
• **Readout & Cursor meas**
• Dual CH / Delay sweep
• Built-in delay line
• ALT trigger, Hold-Off
• Z-axis input,CH1 output
• 2 probes (x1, x10)

DC POWER SUPPLIES

Triple Output

• 2 variable out 0-30V,0-3A
• One fixed 5V,3A output
• Auto track, serial, parallel
• Const. volt, current mode
• 4 analog or 2 digital display
PC-3030 ($499.95)
PC-3030D ($549.95) digital

Single Output

• Const voltage. current mode
• Voltage regulation ≤0.01%
• Current regulation ≤0.2%
PS-1830 ($198.95) 18V/3A
PS-1850 ($214.95) 18V/5A
PS-1830D($214.95)18V/3A
PS-1850D($244.95)18V/5A

Programmable

• Auto serial/parall.(PPT ser)
• Auto track (PPT series), IEEE-488.2 and SCPI compatible command set
PPS-1860G($1,149.95)18V/6A
PPS-3635G($1,149.95)36V/3.5A
PPT-1830G($1,499.95)18V/3A
PPT-3615G($1,499.95)36V1.5A

FUNCTION GENERATOR

FG-8020G ($209.95)
• 0.02Hz-2MHz w/counter
• Sine/Squ/Tri/pulse/Ramp
FG-8020G ($209.95)
• 0.02Hz-2MHz w/counter
FG-8050 ($449.95) Sweep
• 0.05Hz-5MHz w/counter
• INT/EXT AM/FM mod

BENCHTOP DMM

DM-8034($179.95) 3½ dgt
• AC/DV(V,A),C,Ω,diode
DM-8040($339.95) 3¾ dgt
• ACV to 50kHz, true rms
DM-8055G($889.95)5½dgt
• 0.006% accuracy, GPIB
• dBm,auto,REL, min/max

ALFA ELECTRONICS
P.O. BOX 8089
PRINCETON, NJ 08543-8089

TEL: (800)526-2532 / (609) 897-1135
FAX: 609-897-0206
E-mail: sales@alfaelectronics.com

Call / Write / Fax / Email for FREE CATALOG
Visa, MC, AMEX, COD, PO Accepted. OEM Welcome.
1 Year Warranty (2 Years for GW/Instek)

Write in 31 on Reader Service Card.

HAM EQUIPMENT repair or overhaul Collins, Drake, Swan, Astro, Yaesu, Kenwood, etc. 20 years experience with former Slep Electronics Co. Same excellent service, reasonable rates, satisfaction guaranteed. Brooks Electronics, 828-349-3503. E-Mail: rwbrooks@dnet.net

HAM GEAR WANTED

MILITARY COMPONENTS wanted. Capacitors, resistors, diodes, transistors, semiconductors, ICs. Electronic Material Industries, 818-769-1002, FAX: 818-769-1084.

CB – SCANNERS

ANTTRON ANTENNAS for CB, ham and scanners. Anttron 305 base antennas in stock. We stock all Anttron antennas. Send $3.50 for full line Anttron catalog, refundable on first order. Twin-Tronics, Inc., PO Box 2571, Youngstown, OH 44507, phone 330-788-9693.

BLACK BOOK CB LINEARS. Theory, 60 schematics. $25. KEN's, 2825 Lake, Kalamazoo, MI 49001 616-345-4609. www.kenselectronics.com

SALES, SERVICE: CB equipment, radios, modifications, power mice, echo-reverb boxes, kits, meters, filters, antennas, noise toys, mounts, hard-to-find items. Partial list $1, complete list $4. D&R Electronics, 10 Park St., Thomaston, CT 06787. 860-283-9492.

RED BOOK CB MODIFICATION. Audio, modulation, PLL/VCO, sliders, $25. Ken's 2825 Lake, Kalamazoo, MI 49001. 616-345-4609. www.kenselectronics.com

ORANGE BOOK SCANNER REPAIR. 500 models, modifications, $25. KEN's, 2825 Lake, Kalamazoo, MI 49001 616-345-4609. www.kenselectronics.com

CB MODIFICATIONS! Frequencies, books, kits, high-performance accessories, plans, repairs, amplifiers, 10-meter conversions. The. best since 1976! Catalog $3. CBCI, Box 1898NV, Monterey, CA 93942.

WANTED: AOR8000 schematics, EEPROM program mods, etc. Paul, fax 248-738-9291.

Motron Electronics 310 Garfield St Suite 4, PO Box 2748, Eugene, Oregon 97402
http://www.motron.com

DTMF Remote Controller Only $99.00 Plus S/H



The Auto-Kall® AK-16 DTMF Controller Board features 16 relay driver outputs and DTMF to X-10 house control capability! Control the relay driver outputs, X-10 modules, or both with your radio keypad! X-10 operation requires the PL-513 Power Line Interface ($20). The **AK-16** mates readily with our **RB-8/10** ($99) or **RB-16/10** ($149) relay boards. The 0-12 digit security code is user programable using your DTMF keypad. Additional features include re-programable CW ID, CW response, and several modes of operation including Pan-Tilt Camera Control. The **AK-16** is a fully assembled and tested printed circuit board.

Visa, MasterCard, American Express, Discover. S/H: $8 USA; $11 Canada; $16 Foreign.

Se Habla Español. Pida Por Don Moser.

Price and Specifications are subject to change without notice

Info: (541) 687-2118 **Orders: (800) 338-9058** Fax: (541) 687-2492

SUPERSTAR, GALAXY, Mirage, Uniden, Cobra, microphones, power supplies, scanners hard-to-find products, picture price sheets. $1 to cover postage (REFUNDABLE). Galaxy, Box 1202, Akron, OH 44309. Over 10 yrs. in business.

240+ CHANNEL CB/HAM/COMMERCIAL radios: AM/FM/SSB/CW export/domestic: RCI, Motorola, Uniden, Cobra, Alinco, Kenwood. Mics, antennas, linears, meters, books, night scopes, and tons more stuff! Catalog $3. MAXTECH, Box 8086, New York, NY 10150. 718-547-8244.

ULTIMATE MODIFICATION BIBLE. Mind boggling is the way to decide this 220 page book. Modification of CBs, channels, power, sliders, talk back and more. 10 meter radios, HAM RADIO, scanners, toys, meters, and more. Only $29.95 + $3.25 shipping. Phone orders 1-800-256-9895 (MC-Disc-Visa) No CODs.

CB RADIO EQUIPMENT: Selling all kinds of equipment! For details E-Mail: **rushead1@juno.com**

KONNEX DISTRIBUTING. Call 1-888-777-7874. PO Box 451372, Los Angeles, CA 90045. CBs, antennas, meters, transistors. Best prices. Credit card acceptable.

SCANNING USA: monthly magazine 100% scanning. All the news and product reviews from the writers you trust. Get more from your scanner. Subscriptions $24.95, samples $3. Call 1-800-651-0922 your Visa or MasterCard, or write 2054 Hawthorne, Joliet, IL 60435

"CB MODIFICATION SECRETS," new 200-page guide by author of "CB Radio Hacker's Guide." More easy AM/SSB CB upgrades & enhancements: Cobra, Realistic, Uniden, President, etc. Freq. expansion, VFO, clarifier unlock, VOX, Roger Beep, anti-theft device, receive preamp, more. Only $21.95, plus $5 S/H ($7 to Canada). CRB Research, Box 56, Commack, NY 11725. NYS res. add $2.22 tax. Visa/MC orders call: 516-543-9169.

WANTED TO BUY: Radio Shack PRO-2006 VHF scanner. New, used unmodified or modified. Please state condition and price. Pete Haas, PO Box 702, Kent, OH 44240-0013.

FOR SALE: Complete set Sams CB manuals, plus Midland, Cobra, Uniden, etc., into the 90s. B&K 2040/1040, modified for extras. Chips and transistors, sorted in cabinet. LOTS of PLL technical data. Days and weekends, 972-991-5328 (Texas).

NEW BOOKS!

Build, Upgrade, Repair YOUR COMPUTER!
2nd Edition
Mike Harris
180pp, large format, $24.95
Exactly what you need to know to save a ton of money, and get precisely what you need and want from a computer. This illustrated book has it all: parts sources, construction details, troubleshooting, and much more. *Now Includes Pentium II coverage!*

CREDIT POWER
John Q. Newman.
164pp, large format, $19.95

Information never before available to the public, including some techniques that might be *illegal* but work! You'll get all the tools you need to manage the image of your credit that the world sees. **A super credit repair guide!**

RADIO MONITORING
Skip Arey, N2EI
334pp, $19.95
This terrific new book will teach you how to capture radio signals from down the street, across town, around the world, and even from space. The most comprehensive book on radio monitoring from DC to Daylight — *for experts and beginners alike.*

Index Publishing Group
3368 Governor Dr, #273N
San Diego, CA 92122-2936

s/h $4.75 1st book, then $2.50 each

Credit Card Orders
1-800-546-6707
Call for our free catalog!

Write in 34 on Reader Service Card.

❖ ATTENTION CABLE VIEWERS ❖

CABLE VIEWERS . . . get back to your BASIC Cable Needs

Call 1-800-577-8775
For information regarding all of your **BASIC** cable needs.

5 GOOD REASONS TO BUY OUR FAR SUPERIOR PRODUCT
- ❖ PRICE
- ❖ EFFICIENT SALES AND SERVICE
- ❖ WE SPECIALIZE IN 5, 10 LOT PRICING
- ❖ ALL FUNCTIONS (COMPATIBLE WITH ALL MAJOR BRANDS)
- ❖ **ANY SIZE** ORDER FILLED WITH SAME DAY SHIPPING

We handle NEW equipment ONLY – Don't trust last years OBSOLETE and UNSOLD stock!
COMPETITIVE PRICING – DEALERS WELCOME

It is not the intent of B.E.S.W. to defraud any pay television operator and we will not assist any company or individual in doing the same.
*Refer to sales personnel for specifications.

BASIC ELECTRICAL SUPPLY & WAREHOUSING CORPORATION

P.O. BOX 8180 · BARTLETT, IL 60103-8180 · 847-584-2099

Write in 32 on Reader Service Card.

ViewStar Converter Sale !!

Best Quality, Reliability & Performance
DOC, FCC, UL, Approved with 1 Yr. Warranty

Including Such Features And More:
- Double PLL Synthesized 550 Mhz Tuner
- On Screen Display
- Closed Caption Decoder
- Unlimited favorite Channel Recalls
- Full Text Fields
- Rapid Channel Scanning
- Parental Control
- Remote Control Included

	1-9	10-49	50+
85 Channel Converter	56	53	51
W/ Volume Control	69	66	63
W/ Closed Caption Decoder (With Text & On Screen Display)	98	90	85

(Freight included)

Call 1-888-603-4439

Write in 33 on Reader Service Card.

WHOLESALE TO THE PUBLIC!

THE INDUSTRIES
LEADING DISTRIBUTOR OF
CABLE ELECTRONICS IS NOW OPEN TO THE PUBLIC

- WE WILL BEAT ALL COMPETITOR'S PRICING
- 30 DAY MONEY BACK GUARANTEE
- ALL NEW LIFETIME WARRANTY (CALL FOR DETAILS)
- STATE OF THE ART EQUIPMENT

A WHOLE NEW DIMENSION
IN CABLE ELECTRONICS

1 800.474.2343

QUALIFIED PROFESSIONAL SALES & SERVICE REPRESENTITIVES ARE WAITING FOR YOUR CALL.

NO NEW YORK SALES. ANYONE IMPLYING THEFT OF SERVICE WILL BE DENIED OF ALL SALES ASSISTANCE

PRINTED CIRCUIT BOARDS

QUALITY PRODUCT
FAST DELEVERY
COMPETIVE PRICING

PROTOTYPE THROUGH PRODUCTION

- UL approved
- Single & Double sided
- Multilayers to 8 layer
- SMOBC
- LPI mask
- Through hole or SMT
- Nickel & Gold Plating
- Routing or scoring
- Electrial Testing
- Artwork or CAD data
- *Fast* quotes

PULSAR, INC
9901 W. Pacific Ave.
Franklin Park, IL 60131
Phone 847.233.0012
Fax 847.233.0013
Modem 847.233.0014
www.pulsar-inc.com

Write in 35 on Reader Service Card.

MUSIC & ACCESSORIES

MODULAR ANALOG SYNTHESIZER KITS. Build your own studio-quality music synthesizer. Complete with all parts, double-sided PCB, front panel and solder. Includes 20+ page instruction/tutorial manual, full schematics. New kits added every month! Synthesis Technology. Phone/fax 817-498-3782. More information on our website: **www.synthtech.com** E-Mail: synth1@airmail.net

COMPUTER HARDWARE

EVERYTHING NEW w/warranty! Motherboards w/CPU + 512K cache, P300MHz MMX $195, 1.2 gigabyte $75. 15"/17" SVGA monitors $145/235. Pentium Class systems from $395. Also multimedia kits, hard drives, scanners, printers, SCSI adapters $25. Memory, cases, etc. Call for monthly specials. CCI 714-778-0450. E-Mail: cci@net999.com

LIQUIDATION! STOREROOM cleanout, obsolescent computer stuff, cheap! For list, E-Mail: <armanmik@n-jcenter.com> or SASE to Box 785, Ormond Beach, FL 32175.

THE SMALLEST AND COOLEST, FULL IBM PC EVER MADE! Yours for $649! Cost was $4,000. People are amazed when they see it! Extremely well made. Weighs only 2 pounds! Measures 9"x5.5"x1.37"! Take it wherever you go! Runs any application for DOS or Windows 3.1. Windows for pen computing has animated icons & sound annotation with a cool female personality. Only a few available, so don't wait a single day. Built-in handwriting recognition and on-screen or external keyboard. Electronic pen acts as a mouse and doesn't need to touch the glass screen to move the cursor! 486/25 with 4 meg RAM and 80 megabyte capacity. Razor sharp 6" mono screen 640x480/1 meg VGA touch screen, built-in speaker, parallel/serial/ext. monitor, outputs. Includes: electronic pen, battery, glove leather case, AC supply, compact external keyboard is the same size as the computer. Small external half inch high 1.4 floppy. Books and software. Netcom 1-800-733-3733 ext. 6300.

COLOR LASER PRINTERS: Hewlett Packard Color Laserjet (3100A) $1,490; QMS Colorscript 210 (postscript) $995; QMS Colorscript 230 (postscript) $1,395; QMS Magicolor CS1000 (11x17") $1,695; Tektronix Phaser (4693PX) $595; Tektronix Phaser 200I (postscript) $895; Tektronix Phaser III PXI (11x17") $995; Tektronix Phaser 300I (11x17") $1,695. Accept VISA, MasterCard, AMEX. 60 day warranty. Call MAPLE DATA: 908-964-7070. E-Mail: Maplesales@aol.com

CNC SYSTEMS! Write: motivity, Attn. Pam, PO Box 428, Rocklin, CA 95677. Call: 916-349-8757. Info/pictures at **www.motivityusa.com** A great place to buy CNC.



WANTED: EXCESS ELECTRONIC INVENTORIES, ICs, MEMORY, EPROMs, PALs, LEDs, CIRCUIT BOARDS, DIODES, AND TRANSISTORS. CALL ACTIVE MICRO, 562-494-4851 OR FAX 562-494-4913.

Network Service Tool Set

Popular installation and service tools for networks, modems and telephones. All hand tools are professional heavy duty type.

Use the compact tester on 10BASE-T (UTP & STP), thin Ethernet (BNC), 8-position Token Ring, AT&T 258A and EIA/TIA 568A/B. Automatically scans cables for continuity, wiring sequence and polarization. Tests STP cable ground. Testing installed cables is easy with Remote Terminator and gender changers (UTP and BNC). 9V battery included.

- Coax Stripping Tool, RG-58 & RG-59
- BNC Crimping Tool, RG-58 & RG-59
- Modular Cutting/Stripping/Crimping Tool (4, 6 & 8-Position)
- Multi-Network Cable Tester
- AC Receptacle Tester
- Cable Cutter

Order No. 55625 $197.00



PC Diagnostic Tool Set

- AMI Diagnostic Software
- POST Card

Order No. 55555 $89.00

Network Installation Tool Set

- Network Tool Set 55625 without the Multi-Network Cable Tester.

Order No. 55600 $99.00

PC Service Tool Set

Contains all tools needed to troubleshoot & service IBM-compatible PCs. Set includes:

- AMI Diagnostic Software
- POST Card
- Logic Probe
- Digital Multi-Meter
- AC Receptacle Tester
- Serial Adapter
- Serial & Parallel Loopback Connectors
- DIP IC Puller
- PLCC IC Puller
- Grounding Wrist Strap
- Key Top Puller

Order No. 55000 $198.00

Call for your FREE Catalog

Graymark®

P.O. Box 2015 Tustin, CA 92781
http://www.labvolt.com

CALL TODAY!

800-854-7393

VISA MasterCard AMERICAN EXPRESS Cards DISCOVER NOVUS

Write in 36 on Reader Service Card.

1-800-380-9530

LARGE QUANTITIES – RAW, UNMODIFIED
SCIENTIFIC ATLANTA SA-8590-757
GUARANTEED WORKING

SPECIALIZING IN LARGE QUANTITIES

Plus other Models & Manufacturers

http://www.newworldtec.com

CALL TODAY FOR INCREDIBLE QUANTITY PRICING

Write in 37 on Reader Service Card.

PENTIUM MOTHERBOARDS, VIA chipset, 1MB, AGP, 100MHz operation, 3 ISA/3 PCI, $99. **CPUs:** Celeron 128K 300/333 @ $199/239. Pentium **II**: 300/333/350/400 @ $269/329/439/589; **IBM/Cyrix** 233/266/300 $68/89/109; **AMD** K6 **MMX** 233/266/300/300-2/333-2 @ $89/109/129/169/259; 32X **CD-ROM,** audio button $49, 32/64MB SDRAM 10ns DIMM $45/96, 64/128MB PC-100 DIMM $104/191. S3 **Virge** DX 4MB video card $32. Call for current pricing, other parts and illustrated catalog, faxback catalog pages, 1-year warranty or better. tech-specialties, Inc., 5703 Heffernan, Houston, TX 77087-4113, 1-800-864-5391 for orders and tech support, fax: 713-307-0314, Internet: www.ts.nu



19" RACKMOUNT PC chassis: Heavy duty, 4U, 8 slots expandable to 12 or 14, four (three hidden) 3.5"/two 5.25" drive bays, front panel fan, mini tower power supply not included, $179 ($199 if ATX) with this ad! Monitor chassis $269, keyboard chassis $139. 8255-8253 I/O card with prototyping area $69, 12-bit ADDA card $89, both with software. **Computronics Technology,** 972-242-8087.

NEC 386SL 25MHz color notebook computers 4MB RAM 120 HD $100. John 973-591-0523.

DEC EQUIPMENT WANTED!!! We are buying DEC systems, boards, terminals, drives and peripherals. Also Scientific Micro Systems (SMS), DSD, Datability, Dilog, other DEC compatibles, and Computer Output Microfilm (COM) units. Please call for a quote or fax us your equipment list. We buy, sell, and trade. **KEYWAYS, INC.,** 937-847-2300 OR fax 937-847-2350.

START YOUR OWN TECHNICAL VENTURE! Don Lancaster's newly updated **INCREDIBLE SECRET MONEY MACHINE II** tells how. We now have autographed copies of the Guru's underground classic for $18.50. Synergetics Press, Box 809-K, Thatcher, AZ 85552. 520-428-4073. VISA/MC.

WE CARRY a variety of cables, switch boxes, accessories, and adapters to connect PCs, printers, Mac's, networks, telecommunications, and audio/video equipment. We offer: custom cables, free catalogs, and same day shipping on most orders. Visit our website at www.rogerssystems.com or call 1-800-366-0579.

CRTs CHEAP. Buy direct from the manufacturer. Save money. Mfg. all CRT types since 1950. **3 year warranty**. Reg-Res 19" tubes $75; 25" $100; hi-res 13" tubes from $80. We specialize in **hi-resolution** video/computer CRTs. **T.M.C.** 215-226-0749/215-223-0388.

PENTIUM II 300 FROM $899. PENTIUM 233MMX SYSTEM from $599. Complete line of parts, systems, and supplies at wholesale prices. Call Monday-Friday 8am to 6pm Eastern Time, for details & price list. Phone toll free 877-465-1614. COMPUTER CONCEPTS.

Low Cost PICmicro Programming Tools

EPIC Plus Pocket PIC Programmer

Programs PIC12C50x, 67x, 16C55x, 6xx, 7xx, 8x. Optional ZIF adapters for DIP, SOIC, PLCC. Runs off two 9-volt batts or optional AC adapter. Includes programming software and assembler. $59.95

PICProto Prototyping Boards

Get it wired quicker! High-quality blank prototyping boards for PICmicros. Holds 5V reg, caps, osc, DB9-25, large proto area. $8.95 - $17.95

Your first PicBasic Pro program:

```
LCDOUT "Hello World!"
END
```

***New!* PicBasic Pro Compiler**

Now it's even easier to program the fast and powerful Microchip PICmicros. PicBasic Pro converts your English-like BASIC programs into files that can be put directly into a PICmicro. BS1/2 library. True compiler for faster and longer programs. Direct and library access to any pin. Built-in LCD support. Interrupts in BASIC. For mid-range PIC12C67x, 16C55x, 6xx, 7xx, 8x. $249.95 (Standard PicBasic Compiler $99.95)

microEngineering Labs, Inc.

Box 7532 Colorado Springs CO 80933 http://www.melabs.com
(719) 520-5323 (719) 520-1867 fax email: info@melabs.com

Write in 38 on Reader Service Card.

ELECTRONIC TEST EQUIPMENT BOUGHT & SOLD

90 DAY WARRANTY PARTS & LABOR • 10 DAY RIGHT OF RETURN, OPEN ACCOUNTS

Ailtech 360D11, Frequency Syn. .01-2GHz	$800	HP 8559A/853A, Spectrum Analyzer, Digital, .01-21GHz	$4,500
Ailtech Type 32, Precision Attenuator, 0-100dB	$300	HP 8565A, Spectrum Analyzer, .01-22GHz	$3,500
Argosystems AS210, Frequency Calibration System	$2,000	HP 8566A, Spectrum Analyzer, as new	$25,000
Ball Efratom PC-10, Rubidium Standard	$800	HP 86222B/H69, RF Plug-in, .01-4GHz	$1,000
Bird 4381, RF Power Analyst, Opt. 832	$200	HP 86241A, RF Plug-in, 3.2-6.5GHz	$400
Boonton 102B, Signal Generator, .45-520MHz	$500	HP 86260A, RF Plug-in, 12.4-18GHz	$400
Boonton 518-A4, Q Standard	$250	HP 86290A, RF Plug-In, 2-18GHz	$1,200
Boonton 82AD, Modulation Meter	$650	HP 86290B, RF Plug-in, 2-18GHz	$1,400
Boonton 92BD, Digital RF Millivolt Meter	$250	HP 8640B, Signal Gen., .5-512MHz AM/FM	$1,000
Boonton 4200/4E, Power Meter, 18GHz	$800	HP 8656B, Signal Generator, .1-990MHz, AM/FM	$3,000
Boonton 4220/51013, Power Meter, 18GHz	$800	HP 8660C, Freq Syn w/86603A & 86635A, 2.6GHz	$2,500
Boonton 4300, Power Meter w/2-51013 Detectors, Calibrated	$2,500	HP 8743A, Reflection Transmission Test Set	$200
Boonton 4300, RF Power Meter, 2 Sensors	$2,500	HP 8743A/018, Reflection Transmission Test Set, 18GHz	$300
Bruel & Kjaer 1612, Bandpass Filter	$250	HP 8748A/H26, S-Parameter Test Set, 4-2600MHz	$2,000
Calif. Inst. 101T, AC Power Source	$400	HP 8750A, Storage Normalizer, Includes Cable	$400
Datron 1062, Digital Multimeter	$300	HP 8754A/H26, Network Analyzer, 4-2600MHz	$4,000
DR Thiedig MILLI-TO2, Ohmmeter, 1 Milliohm-2 Terraohms	$400	HP 8755C, Network Analyzer Plug-In	$500
Eaton 380K11, Frequency Synthesizer, 1-2000MHz	$2,000	HP 8757A/001, Network Analyzer, Opt. 001	$4,000
EIP 371, Source Locking Microwave Counter, 18GHz	$1,000	HP 8901A/02/03/010, Modulation Analyzer	$1,200
ESI 250DE, LCR Bridge	$200	HP 8903A, Audio Analyzer	$2,000
ESI 296, Auto LCR Meter	$800	Keithley 192, Programmable DMM, 6.5 Digits, HPIB	$600
Fluke 3330B, DC Voltage, Current Calibrator	$200	Keithley 199, System DMM	$400
Fluke 335A, DC Voltage Standard, 0-1100VDC	$400	Keithley 614, Electrometer	$700
Fluke 515A, Portable Calibrator	$800	Krohn-Hite 3202, Filter, LP, HP, BP, Unused	$350
Fluke 5200A, Programmable AC Standard, HPIB	$1,000	Leeds & North 1091, Capacitor Decade, .001uF-1uF	$150
Fluke 6010A, Frequency Synthesizer, 10Hz-11MHz	$500	Marconi 6960, Power Meter with 6920 Sensor	$800
Fluke 6071A, Frequency Synthesizer, .2-1040MHz	$2,500	Narda 5082, High Directivity Bridge, 2-18GHz	$300
Fluke 6080A/AN Frequency Syn., .5-1024MHz	$5,000	Narda 5292 Directional Coupler, 1-18GHz	$200
Fluke 731B, DC Transfer Standard	$150	PMI 1018B, Peak Power Meter	$350
Fluke 8922A, True RMSVoltmeter	$250	Polarad 1105 E-L, Sig. Gen., 1020A Mod., .8-2.4GHz	$300
Fluke 9010A, Micro-System Troubleshooter Opt. 001	$200	Polarad 1207, Signal Source 3.8-8.2GHz	$200
Fluke A55, Thermal Converter	$200	Racal Dana 1515, Delay Pulse Generator	$500
General Microwave 478A, Peak Power Meter	$700	Racal Dana 1992, Frequency Counter, High Stab.	$500
General Radio 1433G, Decade Resistor	$350	Racal Dana 9082P, Signal Gen. 1.5-520MHz	$600
General Radio 1433G, Decade Resistor, 1.111111m.	$300	Racal Dana 9303, True RMS RF Level Meter	$500
General Radio 1531, Strobetac	$150	Racal Dana 9515, Universal Counter, HPIB, Opt. 41	$200
General Radio 1538-P4, High Intensity Flash Capacitor	$50	Rohde & Schwarz SPN, Audio Generator	$300
General Radio 1633-A, Incremental Inductance Bridge	$500	Sanders 5440C, Noise Figure Mtr., 10KHz-40GHz	$400
General Radio 1650A, Impedance Bridge	$200	Sencore TF30, Super Cricket Transistor Tester	$200
Gigatronics 600/6-12, Synthesized Source	$1,000	Tek 1241A, Logic Analyzer, with Accessories	$650
Gigatronics 600/10-18, Signal Generator, 10-18GHz	$1,500	Tek 1410, Sync Generator SPG2, Color Bars TSG7	$650
Guildline 9154C, Transvolt Standard Cell	$300	Tek 1420, NTSC Vectorscope	$500
Guildline 9577, Precision DMM, 7.5 Digits	$300	Tek 1470, NTSC Color Sync & Test Sig. Generator	$500
Hitachi V-212, Scope, 20MHz, Dual Trace	$200	Tek 1502, TDR, Opt. 4, Chart Recorder	$1,000
HP 1124A, 100MHz Active Divider Probe, Unused	$100	Tek 1503/01/05, TDR, Scale in Meters	$1,200
HP 11590A, Bias Network	$250	Tek 178, Linear IC Test Fixture, For 577	$300
HP 11604A, Universal Extension	$300	Tek 2230, Digital Scope, 100MHz, Dual Trace	$1,500
HP 11605A, Flexible Arm	$200	Tek 2235, Scope, 100MHz Dual Trace	$750
HP 11638A, Calibration Kit, Type N	$600	Tek 2336, Scope, 100MHz, Dual Trace	$800
HP 11664A/01, Detectors, .01-18GHz	$200	Tek 2432, Scope, Digital, 300MHz, 4 Channel	$3,000
HP 11665B, Modulator	$250	Tek 2465, Scope, 300MHz, 4 Channel	$2,000
HP 11712A, Service Kit for 8670 Series Inst.	$500	Tek 305DMM, Scope, 10MHz, Dual Trace, DMM, battery	$800
HP 11869A, Adaptor for Plug-In 8350A/B	$350	Tek 464, Scope, 100MHz Dual Trace, Storage	$400
HP 15453A, Pod Set for 8170A	$200	Tek 465, Scope, 100MHz Dual Trace	$400
HP 1630G, Logic Analyzer, 65 Ch. 100MHz	$600	Tek 465M, Scope, 100MHz Dual Trace	$400
HP 16500A, Mainframe, 16510A, 16530A, 16531A, 16520A, 16521A	$3,000	Tek 492/02, Spectrum Analyzer	$4,000
HP 16510B, Logic Analyzer Card, 16500A System.	$500	Tek 496P, Programmable Spectrum Analyzer	$4,000
HP 16530A/16531A, Digital Scope Card, 16500A System	$500	Tek 5003, Power Module	$300
HP 1742A, Scope, 100MHz Dual Trace, DMM	$200	Tek 5A13N, Differential Comparator	$250
HP 214B, Pulse Generator	$1,000	Tek 5A20N, Differential Amp	$100
HP 3312A, Function Generator, .1-13MHz, Sweep	$400	Tek 604, XY Monitor	$100
HP 3325A, Function Generator	$1,200	Tek 7CT1N, Curve Tracer	$200
HP 3325A/01/02, Function Gen. Opt. 01/02	$2,000	Tek 7D20, Programmable Digitizer PI	$600
HP 3400A, RMS Voltmeter, 10Hz-10MHz	$200	Tek AM502, Differential Amp	$100
HP 3455A, Digital Multimeter	$300	Tek AM503/A6302, Current Probe Amp	$600
HP 3456A, Digital Voltmeter, 6.5 Digits	$600	Tek DC503, Universal Counter Timer TM500	$150
HP 3468A, Multimeter, 5.5 Digits	$400	Tek DC504, Counter/Timer TM500	$100
HP 3580A, Spectrum Analyzer, Opt. 02	$800	Tek DM502A, Autoranging DMM	$150
HP 4270A, Automatic Capacitance Bridge	$200	Tek FG502, Function Generator, .1Hz-11MHz	$250
HP 436A/022, Power Meter, HPIB	$800	Tek FG504, Function Generator, .001Hz-40MHz	$500
HP 438A, Power Meter w/2 8481A Sensors.	$3,500	Tek MR501, XY Monitor Scope	$200
HP 5004A, Signature Analyzer	$100	Tek P6046, Differential Probe	$300
HP 5006A, Signature Analyzer	$300	Tek PG508, Pulse Generator, 50MHz	$300
HP 5182A, Waveform Recorder, Generator	$500	Tek PS503A, Dual Power Supply	$150
HP 5316A, Universal Counter	$200	Tek SC502, Scope, 15MHz, Dual Trace	$250
HP 5328A/021/040, Frequency Counter, DMM	$250	Tek SC503, Scope, 10MHz Storage	$400
HP 5334A/020, Universal Counter w/DVM	$800	Tek SC504, Scope, 80MHz Dual Trace	$500
HP 5335A/010, Frequency Counter	$800	Tek SG502, Sig. Gen. 5Hz-50KHz TM500 Sys.	$200
HP 5335A/030, Frequency Counter, 1300MHz	$1,000	Tek TG501, Time Mark Generator	$400
HP 5340A, Frequency Counter, 18GHz	$800	Tek TM503, Mainframe 3 Slot, TM500	$100
HP 5340A/011, Frequency Counter, LEDs, HPIB	$1,200	Texscan SSG2000, Freq. Syn., 100KHz-2GHz, AM, FM	$1,800
HP 54100D, Digital Scope, 1GHz	$2,000	Valhalla 2000, Auto Digital Watt-Ammeter	$200
HP 54200A, Digital Storage Scope, Dual Trace, 200/MG/S	$1,000	Vu-Data 5110, Semiconductor Tester, In/out Circuit	$150
HP 6112A, Power Supply, 0-40V, 0.5A	$200	Wavetek 1045/14139, Power Meter 1MHz-18GHz Opt. 01, 05	$800
HP 8015A, Pulse Generator, .1Hz-50MHz, 30V	$500	Wavetek 1084, Signal Gen. Sweeper, 3.5-4.5GHz	$300
HP 8165A, Programmable Signal Source, .0001-50MHz	$1,600	Wavetek 185, Sweep Function Gen. .0001-5MHz	$400
HP 8350A/86290B, Sweep Oscillator, 2-18GHz	$4,000	Wavetek 1910, XY Monitor, Dual Trace	$400
HP 8350B, Sweep Oscillator Mainframe	$3,000	Wavetek 452, Filter, Dual Hi/Lo, 1Hz-10KHz	$450
HP 8410C/8412B, Network Analyzer w/8411A/Opt. 18, 18GHz	$800	Wavetek 7530A, FFT Spectrum Analyzer 0-100KHz	$500
HP 8411A, Frequency Converters	$250	Wavetek 907, Signal Generator, 7-11GHz	$600
HP 8414A, Polar Display	$300	Wavetek 955, Micro Source, 7.5-12.4GHz, AM, FM, Sweep	$1,000
HP 8445B, Spectrum Anyz., Automatic Pre-Selector	$300	Wiltron 560A, Network Analyzer	$800
HP 8445B/02/03, Preselector, Digital Readout	$600	Wiltron 560-97A50, SWR Autotester, .01-18GHz	$500
HP 8553B, Spectrum Anyz., RF Plug-in, 1KC-110MHz	$200	Wiltron 610D, Sweeper Mainframe	$250
HP 8554B/8552B, Spectrum Analyzer 141T, 1.2GHz	$1,500	Wiltron 610D/6237D, Sweep Generator, 2-18GHz	$800
HP 8556A, Plug-In, Spectrum Analyzer, 20Hz-300KHz	$300	Wiltron 6213D, RF Plug-In, 10MHz-4.2GHz	$400
HP 8557A/180TR, Spectrum Analyzer, .01-350MHz	$1,000	Wiltron 6219D, RF Plug-In, 2-8GHz	$200
HP 8558B/180TR, Spectrum Analyzer, .1-1500MHz	$1,800	Wiltron 6223D, RF Plug-In, 4-12.4GHz	$250
HP 8559A/182T, Spectrum Analyzer, .01-21GHz	$3,000	Wiltron 6229D, RF Plug-In, 7.9-18.5GHz	$300
		Wiltron 62FF75, VSWR Bridge, 10-1000MHz	$150
		Wiltron 6NF50, Autotester, 1-1500MHz, for 640	$100
		Wiltron 7B50, Detector, 1-1500MHz, for 640	$100

INVENTORY CLEARANCE SALE
SAVINGS UP TO 50%

PHELPS INSTRUMENTS
2631 Hillside Ave., Norco, CA 91760
909-279-7347 • FAX 909-279-7347

MasterCard VISA AMERICAN EXPRESS

Write in 39 on Reader Service Card.

Pacific Test Equipment

PACIFIC TEST EQUIPMENT

BLOWOUT SALE

	HP 8657A Synthesized Signal Generator 0.1 - 1040 MHz with 10 Hz Resolution, +12 to -143.5 dBm 50W Reverse power protection, internal AM/FM Modulation Note: RF Connectors on rear panel (opt. 002)	Retail $9,995 Regular $5,900 **Sale $2,375**
	**HP 8656B Synthesized Signal Generator** 0.1 - 990 MHz with 10 Hz Resolution, +13 to -127 dBm 25W Reverse power protection, internal AM/FM Modulation Note: RF Connectors on rear panel (opt. 002)	Retail $7,900 Regular $4,250 **Sale $1,875**
	HP 8656A Synthesized Signal Generator	**Sale $1,050**
	HP 5334B Universal Counter 0 to 100MHz, 9 digit per second resolution, rise/fall time, pulse-width, ac/dc voltage measurement. Frequency, period, ratio and time interval. Front and rear inputs in parallel. HP-IB	Retail $2,305 Regular $1,000 **Sale $195**
	HP 3457A Digital Multimeter 3-1/2 to 6-1/2Digit with extended resolution to 7-1/2 digits. dcV, acV, dcI, acI, Ohms, frequency and period.1350 readings/sec. at 3-/2 digits. HP-IB	Retail $3,260 Regular $2,495 **Sale $1,380**
	Tektronix 2445A 150MHz Oscilloscope Auto-setup, 4 channel, 1M and 50 Ohm input impedance, dual time base, CRT readout with cursors. 2mV sensitivity.	Regular $3,200 **Sale $1,895**

Above items come with a 90 Day warranty, standard accessories, and FREE UPS Ground shipping within the continental U.S.
We accept VISA, MC and prepayment in advance. Sorry no C.O.D.'s. Quantities are limited to stock on-hand. 20% restocking fee on returns.

We Buy Late Model Test and Measurement Equipment

by HP, Tektronix, Fluke, R&S, Wavetek, Anritsu, and others.

(408) 441-7341 or fax (408) 441-8049

We also carry Brand New Iwatsu/LeCroy - Topward - LG Precision

Iwatsu/LeCroy
LA314/SS-7840
400 MHz, 4 Channel
Cursor, High-Speed Auto Setup,
TV Trigger
$7,200

Topward

Single Output

Model	Meter	Output	Price
3603D	Digital	60V/3A	$495

Triple Output

Model	Meter	Output	Price
6603D	Digital	60V/3A X 2 5V/5A Fixed	$875

Others Available - Call

LG Precision
OS-5100RB
100 MHz, 4 Channel
Cursor, Auto Setup
CRT Readout
$1,595

PACIFIC TEST EQUIPMENT

Pacific Test Equipment Corp.
1450 Koll Cir. #111 • San Jose, CA 95112
(408) 441-7341 • Fax (408)441-8049
For a free catalogue
or inquires on other equipment call
(408) 441-7341 M-F 9-6 (PST)
Ask for Erwin Talavera

Write in 75 on Reader Service Card.

Lowest Dealer Price Available

	5+	10+	20+
Refurb. Panasonic 145	$45	$40	$35
Panasonic 175	$70	$68	$65
Regal w/Remote	$38	$35	$30
BC4535 86 Channel	$30	$28	$25
Oak Sigma 99 Channel	$45	$40	$35
75 Channel Converter	$18	$18	$18
Zenith ST1600 w/Remote	$75	$70	$65

Call us today to satisfy all your cable equipment needs!

SAM'S ELECTRONICS

1-405-631-1856

All Cable Equipment is unmodified.

CD DUPLICATOR MediaFORM Genesis 2601. Duplicate or master up to 25 CDs at a time. Accepts most CD formats. $4,200 or best offer. GearHead Electronics, PO Box 413, Williamsville, NY 14231-0413, 716-636-4370, http://www2.pcom.net/gearhead

FIXED FREQUENCY MONITOR SUPPORT. The MING graphics accelerator card will run a fixed frequency monitor just like an SVGA monitor on a standard PC with virtually all DOS TEXT, and graphics up to 1280x1024 resolution. 909-738-1416. http://www.riverside.quik.com/ming E-MAIL: ming@mail.quik.com

MONITOR ADAPTERS. Convert OEM. (incl. PGA) 31.5KHz & above monitors with BNC connectors to PC use. Model VA10 VGA to RGB+ Sync $45. Model VA11 VGA to R G/Sync B $55. VA12 VGA to PGA (DB9) $45. Pikul & Assoc., 101 Glenfield Dr., Festus, MO 63028. 314-937-0335.

NEW "All-In-One" 486 mainboard with Intel DX2 66MHz CPU (with heatsink and fan) 128K cache 1Meg Video (Video 7) and IDE I/O (and all the cables) for $60. (Also available without CPU for $40). Fits in a standard PC case. 16 30 pin SIMM sockets. Call Under The Wire Electronics (UTWE) 626-930-1121 (10am-5pm Pacific Time) or fax 626-930-1123. UTWE, 235 E. Colorado Blvd. #211, Pasadena, CA 91101. E-Mail: sales@utwe.com

LOOKING FOR cheap clone PC parts that actually work? Call UTWE for CD-ROMs, hard drives, disk controllers, video cards, mainboards CPUs, etc. For example, NEW Clone-o-matic mainboard with 4 PCI, 3 ISA, 256K cache, I/O built on board with 200MHz AMD $110, 2 meg PCI S3 video board $28. Remember, today we have, tomorrow we don't! For all the latest deal sheets E-Mail: dealsheets@utwe.com Call 626-930-1121 (10am-5pm Pacific) or fax 626-930-1123. E-Mail: sales@utwe.com

UTWE KNOWS what YOU want on the web! Pictures of the private parts collection of UTWE (yea, and cheap prices). See all those SCSI cases, the mainboards, the network cards, the disk drive controllers, video cards, network hubs, cables (you did realize I meant computer parts right?), keyboards, drives, sound cards, and some other new and used oddball stuff by stopping by www.utwe.com If you just want text deal sheets sent to you then E-Mail: dealsheets@utwe.com And of course, we still have a voice phone 626-930-1121 (10am-5pm PST) and fax 626-930-1123. E-Mail: sales@utwe.com

DIGITIZERS: SummaSketch III Pros (12"x18") used, with 4- or 16-button cursor (state choice, no stylus pens in stock), serial interface cable, power supply, manual, support files for DOS, WIN3.x, 95, NT, ground UPS for **$185** (money order or after cleared check), 90 days replacement warranty. Support at Calcomp website. Also microchannel, PS/2 parts available, send SASE or E-Mail address. MEMORIES, 1251 South Reynolds Rd., Suite 240, Toledo, OH 43615. 419-389-8240.

HITACHI HANDHELD PC HPW-10E4MB Windows CE w/28.8 modem and touch panel LCD screen $175. 714-843-6476.

P233 MHz Multimedia systems, fully loaded, liquidation price $495. AT&T Pentiums $650, 486 systems $95. Laser printers $275, Color Inkjets $95, Notebooks $350, Closeout prices on Software. Call 714-778-0450.

ATT OPEN to buyer items listed here; voice & data, computer cables, adaptors & wire, D, subminiature, connectors & hardware, communications, antennas photo electric sensors, phone system that does it all for all types of business. Ohio Service Supply Company, PO Box 8802, Canton, OH 44711-8802.

LOWEST COST LCD'S ON EARTH

VIDEO LCD

4 Inch Video NTSC $150
Sharp P/N 4LU4E
Composite NTSC & RGB Input
12:00 OR 6:00 Viewing Angle
Integrated Backlight & Inverter
Extended Temp: -10 to + 60 C
Brightness: 260 nits
Power Consumption: 4.3 Watts
Contrast: 50 to 1



CHARACTER LCD

OPTREX DMF-5005SN-EW
240 x 64 Graphic EL Backlit STN $30
OPTREX DMF-5005N
240 x 64 Graphic Reflective STN $30
SANYO DM2023-7G1
2 x 20 Character Reflective STN $8
SHARP LM20A21
2 x 20 Character Reflective STN $8
VIKAY 2035TNLD NOTW-D
2 X 16 Character LED Backlit STN $8

LCD MONITOR

10.4" DSTN or 12.1" TFT
Analog SVGA Input
Autosync
Auto Sizeing
Automatic Expansion of VGA images to SVGA (On 12.1")
Very Aggressive Pricing Starting under $500!

TOUCH MONITOR

EarthVue 10.4
10.4" VGA TFT
Analog VGA Input
105 Nit Brightness
RS-232 Touch Screen Option
Only 9.9"W x 7.7"H x 1.5"D
Ideal For Factory Automation
Fully Articulating Ball Mount
Only $1095 With Touch

LCD DISPLAYS

6.3" Mono STN	$60
9.4" Mono Reflective	$60
8.4" TFT	$250
9.4" DSTN	$150
10.4" TFT	$350
10.4" DSTN	$240

NoteBook Screens
340 Models in Stock
Obsolete Screens Stocked
Hard To Find LCD? Call!



CONTROLLERS

ISA
PCI
PC/104
NTSC
Analog VGA
Complete LCD Kits with LCD, Controller & Cable Starting under $200

EARTH Computer Technologies

"The World Leader In LCD Recycling"

Ph: (949) 361-2333 Fax: (949) 361-2121
http://www.flat-panel.com

Write in 39 on Reader Service Card.

AMAZING PRODUCTS! INFORMATION UNLIMITED

VISIT OUR "ACTION" WEB SITE@ http://www.amazing1.com
DEPT NV 0498
BOX 716 AMHERST, N.H. 03031

ATTENTION!! RAILGUN EXPERIMENTERS

HIGH ENERGY PULSER EXPERIMENTORS AND RESEARCHERS

RAIL GUN, COIL GUN, EXPLODING WATER, ANTIGRAVITY, MASS WARPING ,LEVITATION, PLASMA PROPULSION, LATTICE SNAPPING, EMP etc

- Lossless Energy Charging
- Programmable Voltage to 2 KV and Energy Control to 3 KJ
- Triggered Spark Switch [1KJ]
- Universal 12 VDC or 115 VAC
- 7.5 X 7.5 X 7" Light weight

HOTSHOT

HEP3 Plans High Energy Pulser/Ignitor.....$15.00
HEP3K Kit/ Plans (With 500 Joules Energy Storage).....$49.50
HEP30 Assembled (With 500 Joules Energy Storage).....$449.50
All Individual Parts and Subassemblies Available

BURNING LASER RAY GUN

BLASTS THRU THE HARDEST OF METALS!

All Parts Available
A FUTURISTIC CONCEPT!!
LAGUN2 Plans.....$20.00

BURNING CO2 BENCH LASER

HOTTER THAN MOST TORCHES!
All Parts Available

LC7 Plans.....$20.00

ELECTRONIC HYPNOSIS AND MIND CONTROL

Generates Highly Effective Audible and Visual Stimuli With Bio-Feedback That Can Induce Hypnotic as Well as ALPHA Relaxed States of the Mind. Place Subjects "Under" Your Control. Enhances Hidden PSYCHIC Ability in Many People!

MIND Plans.....$15.00
MIND2K Kit and Plans.....$49.50
MIND20 Assembled.....$89.50

TELEPHONE TAPING SYSTEM

EXTENDED X4 PLAY
Tapes Phone Conversation
20 Megs Input 2! Check Laws!

TAP30X Ready to Use.....$84.50
BEEP10 Beeper Alert.....$29.95

JACOBS LADDER

Observe a pyrotechnical display of "traveling" fiery plasma. Starts off as 1/2" arc and expands to over 3" before evaporating into space. This is an excellent attention getting display as well as a winning science project!! With arc control.

JACK1 Plans.....$8.00
JACK1K Kit Minus Case.....$129.50
JACK10 Ready to Use.....$249.50

12KVGEN20 Pwr Supply Only.....$99.50
12KVGEN2K Kit of Pwr Supply.....$79.50

3Mi FM VOICE TRANSMITTER

Safety Product Allows Listening to Children or Invalids In Hazardous Areas, Pools, Ponds etc. Great Security Intrusion Alert! Uses FM Table Top Radio.

FMV1K Kit/Plans.....$39.50

ATTENTION!

ANTI GRAVITY,

We Can Supply Low Cost HIGH VOLTAGE Current Producing Generators from 50 to 500 KV. Contact Factory For Details or Call 603 673 6493

MICRO MINI MITE TESLA COIL

LIGHTS UP A 4 FT FLOURESCENT TUBE WITHOUT CONTACT!!! YET ONLY 3" TALL!
Super Magic Trick
Low Cost Science Project
12 VDC/115 VAC Operation

MTC1K Kit/Plans.....$19.50
MTC10 Ready to Use.....$34.50

PHASOR BLAST WAVE PISTOL

130 db of Directional Sonic Shock Waves Energy Handheld and Battery Operated

PPP1 Plans.....$8.00
PPP1K Kit/Plans.....$49.50
PPP10 Ready to Use.....$79.50

HOVERBOARD PLANS

Kit Soon to be Available

28 Pages of "how to" build a magnetic force field capable of containing a column of ionized air up to several psi! Proven theory may require additional experiment

HOVER Plans.....$25.00

TRANSISTORIZED TESLA COIL

TURNS A LIGHT BULB INTO A SPECTACULAR PLASMA DISPLAY

Transmits Wireless Energy
Noiseless Operation
Pyrotechnic Effect
12 VDC/5 Amps or Battery
115 VAC Optional Converter
Adjustable Frequency Control For Effect

TCL5 Plans.....$8.00
TCL5K Kit/Plans.....$59.50
TCL50 Ready to Use.....$109.50
12DC/7 12VDC@7Amps.....$39.50

1 800 221 1705 ORDERS ONLY! **FAX 1 603 672 5406** **INFO 9-5pm 1 603 673 4730** **FREE CATALOG ON REQUEST**

Pay by MC, VISA, Cash, Chk, MO, COD. Please Add $5.00 S&H plus $5.00 if COD. Overseas Please Contact for PROFORMA

Write in 40 on Reader Service Card.

WE BUY & SELL!

C and H SALES COMPANY

50 YEARS IN BUSINESS

2176 E. Colorado Blvd.
Pasadena, CA 91107

Take advantage of our special purchase on TEST EQUIPMENT

HIGH PRECISION DIGITAL MULTIMETER
FLUKE, Model 8810A. LED readout. 5-1/2 digit autoaranging multimeter. Has ohms converter and true rms options. Accuracy AC volts 0.1% to 0.5%, AC rms 0.2% to 0.4%, DC volts 0.01%, ohms 0.02% to 0.2%. Max input voltage 1000 VDC or peak AC. Input impedance to 1 to 1000 meg ohms depending on range. Power input voltage 115 VAC 50/60 Hz. Has built-in carrying handle that can be used as a tilting base. Dimensions: 9-1/4" wide x 14-1/2" deep (including carrying handle) x 3-1/4" high.
Stock #TE9805 **$295.00**

MILLIOHMETER
HEWLETT PACKARD, Model 4328A. Designed to measure very low resistances. Measurement range 1m ohm to 100 ohms. Resolution 20 u ohms. Analog meter readout. Ideal for measuring contact resistance of switches or relays. This unit is also useful for measuring the resistivity of semiconductor devices. (Requires special 4 terminal probes which are not supplied, but probably are available from Hewlett Packard.) Power input: 115–230 VAC 48–66 Hz, 5 VA max. Dimensions: 5-1/8" wide x 11-1/2" deep x 6-1/2" high.
Stock #TE9812 **$200.00**

3-1/2 DIGIT DIGITAL MULTIMETER
FLUKE, Model 8000A. LED readout. Classic digital multimeter. Ideal companion to our Stock #TE9800 counter. Measures AC/DC volts/milliamps plus ohms. Input range 0–200 mV to 1200 volts, 0–200 UA to 2000 mA. 0 to 2000 K ohms. Portable unit with carrying handle which also can be used as a tilt stand. Input impedance 10 meg ohms. Max. input voltage 1200 VDC or rms. Accuracy DC volts 0.1% of input +1 digit. AC volts 0.5% of input +2 digits 45 Hz to 10 KHz. Input power 115 VAC 50 to 400 Hz 5 watts. Dimen.: 8-1/2" wide x 12" deep (including carrying handle) x 2-1/2" high.
Stock #TE9801 **$75.00**

200,000 COUNT DIGITAL MULTIMETER, FLUKE, Model 8800A. LED readout. 6-digit, autoranging multimeter. Basic accuracy ±.005%. 15 ranges DC volts: ±200 mv to ±1200 in 5 ranges accuracy ±.008% or better. AC volts: 2 VAC to 1200 VAC in 4 ranges. Accuracy ±1% or better depending on frequency and range. Resistance 200 ohm to 20 meg ohms in 6 ranges. Accuracy ±.02 or better. Input impedance: 1000 meg ohms or more on DC ranges, 2 meg ohms on AC ranges. Has complete overload protection and isolated inputs. Power input 110/230 VAC 50/60 Hz 8 watts. Built-in carrying handle that also acts as a tilt-up base. Dimensions: 3-1/2" high x 9" wide x 12-1/2" deep.
Stock #TE9815 **$100.00**

3600 RPM DC MOTOR WITH OPTICAL ENCODER PACIFIC SCIENTIFIC, #4VM82-004-4. 30 volts nom. input voltage. Permanent magnet, reversible servo motor. Has Hewlett Packard optical encoder. Ball bearings. No load speed at 30 VDC input is 4600 rpm. No load current 0.75 amp at 60 oz-in load rpm is 3600, current is approx. 6.6 amps. Torque constant is 9.1 oz-in per amp. Rotor inertia 0.0007 oz-in-sec^2. Terminal resistance 0.89 ohm. Optical encoder is similar to "HEDS 6000" series. Encoder has 1024 counts per revolution, two channel quadrature output. Outputs are TTL compatible. Encoder requires 5 VDC input at less than 50 mA input current. Dual shafts: front shaft is 3/8" dia. x 3/4" long. This shaft is tapped on the end 8X32 tpi. Rear shaft is 1/4" dia. x 7/16" long. This shaft has dual flats that measure approx 3/16" across. Motor has four 8X32 tpi tapped mounting holes on front. A 3-3/16" dia. centering pilot is also provided on the front face. Dimensions: 4" dia. x 5-1/2" long (excluding shafts.)
Stock #DCME9850 **$79.50**

Call us first if you have surplus inventories of electronic, optical, or mechanical items for disposal

☑ *Master Charge* ☑ *Visa* ☑ *American Express* ☑ *Discover*

TOLL FREE: 1-800-325-9465

Write in 42 on Reader Service Card.

CABLE PLUS, INC.

- **Basic converter boxes**
- **Volume-86 Channels and 125 Channels**
- **Can use in any cable system**

COMPETITIVE PRICING

Genuine, Unmodified

CFT, ZENITH, S.A., JERROLD, DPB7, TOCOM, PANASONIC, PIONEER and more With Remote Control

- **PARTS FOR ANY CABLE BOXES**
- **REMOTE CONTROL FOR ALL BRANDS OF CABLE BOXES**

No Florida Sales

CALL 1-877-269-6600
FAX 305-269-7102
http://www.cable-converter.com

FREE SHIPPING w/Visa. Internet mouse $6.95, SVGA Monitors $145, Flatbed Scanners $75, 56K Modems 45, 386SX40 $25, 1.2/1.44 Floppy $20, Adaptec SCSI controllers $45, memory 1.25/megabyte. 714-778-0450.

SONY/AMIGA/MAC/IND. MULTISCANS 15" 0.26 DP 15.7-37KHz TTL/Analog, sync on green, &150 **Blem 15" SVSA's $85.** Expert Sony repair.Refurbished. Pikul & Assoc., 101 Glenfield Dr., Festus, MO 63028. 314-937-0335.

SCSI JAZ drive w/2 disks, rarely used $200. HP laser jet 5P needs repair $50. Datasouth XL400 printer new $650. Zebra S533 Barcode printer (stripe 500) new $700. Epson DFX500 printer EC $600. Bob 847-394-1656 or teslacoil@aol.com

http://www.pccables.com PC CABLES and PARTS. 100s of hard-to-find new cables and parts, free technical information, low prices, fast online ordering & browsing.

4 MB, 72 Pin SIMMs $4 ea. Pikul & Associates, 314-937-0335.

BUILD YOUR own IBM COMPUTER from available parts with the help of an easy 79 minute video tape. This award winning VHS shows you how to save money or start a small business by assembling any compatible 386 to Pentium MMX computer in a step-by-step, easy-to-follow procedure. It's **easy** when you know how! Order your tape today, while supplies last, only $29 (reg $59.95) plus $2.95 P&H. Send check to: **EVP, PO Box 2201, Northlake, IL 60164-0201** or call 1-800-754-5096 now!



CLOSE-OUT SALE, MONITOR ARM SETS. New, robust, commercial quality, made in USA, Ergo, brand model MA-28 arm, CM desktop clamp with adjustable 13" wide x 12" deep metal platform. Swivel 270 wrist joint, platform 360 & base 360. Shipping weight 36lbs., $89 a set, FOB Las Vegas. Call for quantity discounts. Less Busters Electronics 702-642-0325. Catalog: www.lessbusters.com

SYSTEMS, PERIPHERALS. UPS. Closing R&D/manufacturing company. Must sell lots of equipment. Call for list 1-800-869-7827 or visit www.starcom.com for list

COMPUTER SOFTWARE

FREE IBM DISK CATALOG of quality Shareware and CD-ROMs. **MOM 'N' POP'S SOFTWARE** <ASP>, PO Box 15003-N, Springhill, FL 34609-0111. 352-688-9108. momnpop@gate.net

LINUX & FREEBSD & LINUX & FREEBSD Linux and FreeBSD distributions on CD-ROM for as low as $1.99. See our full range of Linux products and books at **incredible prices.** Use our secured shopping cart system at **www.cheapbytes.com** Visa and MasterCard gladly accepted. E-Mail: sales@cheapbytes.com fax: 209-367-8518. CheapBytes, PO Box 2714, Lodi, CA 95241.

MOD CHIPS for Sony PlayStation. Now your backups will work. Only $9.95 ea. + $3 shipping. Call 1-888-467-6150, all major credit cards accepted. Computers & components at wholesale prices. www.cconusa.com

DISKETTE & CDR DUPLICATION. Turnkey packaging, quick turnaround, guarantee blank disks available, formatted diskettes 11 cents. **Neil Duplication 510-226-0171.**

When Visiting Disney World And Sea World.
Come To The World Of Electronic Surplus!

SKYCRAFT

PARTS & SURPLUS, INC.
ORLANDO, FLORIDA

Located At The Intersection Of I-4 And Fairbanks Avenue.

A Self-Service Retail Outlet Featuring Commercial And Government Electronic Surplus Including:

- ★ WIRE
- ★ SWITCHES
- ★ RESISTORS
- ★ TRANSISTORS
- ★ TRANSFORMERS
- ★ TEST EQUIPMENT
- ★ NI-CAD BATTERIES
- ★ COAX
- ★ RELAYS
- ★ HARDWARE
- ★ CAPACITORS
- ★ PANEL METERS
- ★ CIRCUIT BOARDS
- ★ INTEGRATED CIRCUITS

★ ★ ★ ★ ★ ★ ★ ★ ★

We Buy Surplus Electronic Parts — *FAX your list.*

FAX 407/647-4831
PH 407/628-5634
P.O. BOX 536186
ORLANDO, FLA. 32853-6186

HOURS:
Monday - Friday 8:30-6:00
Saturday 8:30-5:00

Honey, I shrunk the COMPUTER!



PicStics are like BASIC Stamps® on steroids. They have more speed, more parallel I/O, more code and data space, and more neat features like a real-time clock, 12-bit ADC, and 12-bit DAC.

As low as $29

Call for a catalog or visit our Web site today.

www.micromint.com

(800) 635-3355
(860) 871-6170

4 Park St. • Vernon, CT 06066

BASIC Stamp is a registered trademark of Parallax, Inc.

Write in 41 on Reader Service Card.

FREE HACKING/phreaking/trubbleware diskette catalogue. Incredible subject matter. No commercial programming and NO SHAREWARE here! Peregrine Dynamics, 720 Portage Trail, Cuyahoga Falls, OH 44221.

FLOPPY DISKS formatted, excellent pricing, call 510-226-0171.

CAM & MOTION SW/HW: Z-trace, PCB toolpath. Plotcam motion control, step drivers. cmheater@juno.com MSG/FAX 407-452-7197, 407-459-2729. **www.megabits.net/ddt**

LIQUIDATION WINDOWS 95/98, Office97, WindowsNT, 1,000 games, Encarta 10 CDs $25, DOS $25, Wordperfect Suite $35. Antivirus $5. Call 714-778-0450.

SONY PLAYSTATION mod chips allow you to play CDR backups & imports. $10 ea. + $3 shipping. 619-590-9320.

MAKE $$$ giving away our software! Business kit $10 (refundable). RASCOM, 685-A Del Amo Blvd. #151, Carson, CA 90746-3308.

CD DUPLICATING service. Back-up copy, $25 includes shipping. You are allowed 1 copy by law. Call for quantity price for your own software. Check or M/O to Wizard Eng., 1782 Arlington, Toledo, OH 43609. 419-385-3100.

MICROSOFT OFFICE 97 PROFESSIONAL EDITION, $79. That's right, $79. Includes Word 97, Excel 97, Access 97, PowerPoint 97, and Outlook 97. Brand new, unopened, and shrink-wrapped. Easy fulfillment. No manuals. Visa/MC accepted. Call Gulf Professional Services toll-free 1-888-208-9797, or order online at www.gulfpro.com E-Mail: sales@gulfpro.com

SERVICE REPAIR TIPS for **FREE! PROFESSIONAL BOARD LEVEL & COMPONENT LEVEL REPAIRS for TVs, VCRs, projection TVs, CAMCORDERs,** CD players, audio and other repairs on computer disk. **ADD** your repairs. **PRINT** out repairs. **BACKUP** & save **your** repairs. Want to share your repair tips? If you do, we'll send you **FREE** updates! Ask about our TIP EXCHANGE policy. For IBM compatible computers with a hard drive. Get your **FREE Stage 1 SERVICE TIPS Now! FREE CALL. CALL NOW 1-800-215-5081**.

GCODE95 for Windows 95, 98 & NT. Reads AutoCAD DXF files and converts data to Gcode Mcode Rs274. For milling, turning flamecutting Etc. Easy to customize for almost any machine. Download a free trial copy. http://members.aol.com/gcodemcode/index.htm http://www.tarheel.net/andrewc119/index.htm E-Mail: andrewc119@aol.com

APPLE DUAL 200 MHz 604e PPC Card for 8600, 9500, or 9600MP $275; **Powerbook Duo 280C** 32/330/14.4 with **Duo Dock II** $700; **Powerbook 280C Duo with Duo Dock** 24/330 $625; **280/2300** 16 meg memory $75; **8 meg** $50; AC adapter 500 series **ADP-4888** $85; **M3050** $85; **POWERMAC 6100/66** 24/500 $350. 650-842-3268.

MICROSOFT OFFICE 97 SR-1 CDs $145. Valid serial number sealed full OEM version! While they last WOW! COMPARE Academic $249. Retail $539. Cashier's cheque or M/O. Document Control, 103 South Court, Cleveland, MS 39530. 601-843-0152. docctrl@tecinfo.com

COMPUTER EQUIPMENT WANTED

WANTED: TERMINALS + PRINTERS: DEC, Wyse, IBM, ADDS, Okidata, Data South, Epson, C.ITOH, etc. Call for quote on any surplus computer equipment. Call Jeremy, 603-673-8077.

The Pocket Programmer



The portable programmer that uses the printer port of your PC instead of a internal card. Easy to use software that programs E(E)prom, Flash & Dallas Ram. 27(C)/28(C)/28F/ 29F/29CXXXX & 25XX series from 16K to 8 Megabit with a 32 pin socket. Adapters available for Pic, MCU's 874X, 875X, 40-Pin X 16 & Serial Eprom's, PLCC, 5-Gang, 82/74 Prom's and Eprom Emulator to 32K X 8.
Only $129.95

Same Name, Address & Phone Number for 16 Years.... Now isn't that Amazing ?

Intronics, Inc.
Box 13723 / 612 Newton St.
Edwardsville, KS 66113 **Add $5.00 COD**
Tel. (913) 422-2094 **Add $4.00 Shipping**
Fax (913) 441-1623 Visa / Master Charge / Amex

TONER CARTRIDGE RECHARGE

& Laser Printer Supplies

CALL NOW FOR YOUR FREE CATALOG #13 !

Instruction Manual Free with starter kit
Video Training Tapes choose from our library
Catalog #13 100 pages FREE!
Marketing Flyers with customized pricing
Printer/Copier/Fax Cross Reference 68 pgs-Free with any order

- Black, Color & MICR Toners
- Tools and Accessories
- Technical Support
- Cartridge Parts
- Video Training Tapes
- OPC Drums and Belts
- InkJet Refill Supplies
- Graphic Black Toner Kits
- MICR Toner Kits

- Fast, Same Day Shipping
- Mail-in Cartridge Service
- Export Orders
- Monthly Sales Specials
- Marketing Flyers

Visit our website at www.chenesko.com for all the free tech documents; Sales Specials and the latest industry news!

CP CHENESKO PRODUCTS
Chenesko Products Inc.
2221 Fifth Ave., Suite 4,
Rankonkoma, NY 11779
Fax: 516-467-3223
E-Mail: chenesko@aol.com
http://www.chenesko.com
800-221-3516

Write in 43 on Reader Service Card.

FOR THE BEST PRICES ON PROFESSIONAL TOOLS, CALL ELECTRO-TOOL

platt – Case – Deluxe Polypropylene. Chemical Resistant. Tools by CooperTools and others. 800T Case, complete with tools . . . **$419.95**
800T Case Only . . . **$121.80**



platt – Case – Cordura Exterior. Two exterior pockets & one literature pocket. 660ZT Case, complete with tools . . . **$223.00**
660ZT Case Only . . . **$59.45**
Optional Sperry meter #DM6510 as shown . . . **$65.00**



Weller WCC100- Electronically controlled station, temperature adjustable from 350°F-850°F, Zero voltage circuit-safe for sensitive components, 40 Watt pencil . . . **$97.90**

OptiVISOR – Superior magnification, Optical Glass Prismatic lenses (not plastic). Select any one of (6) magnifications . . . **$24.00**



GoldStar – 20 MHz Dual Trace Oscilloscope OS-9020A-Large 6" rectangular, high sensitivity: 1mV/div,.high accuracy: ±3%, stable, low-drift design, 8 divisions of displayed dynamic range and accurate, distortion-free waveform measurements . . . **$372.00**

Electro Tool, Inc.
9103 Gillman, Livonia, MI 48150
Customer Service: (734) 422-1221
ORDERS ONLY: 1 (800) 772-3455
FAX: (734) 422-3432
"Tools American Made."

WANTED: FOR historical museum, pre-1980 microcomputers, magazines, and sales literature. Floyd, VA 24091-0341 (540-763-3311/540-382-2935).

HP CALCULATORS wanted: models 10, 70, calculator watch, others for private collection. Cash paid. Bob Morrow, 765-855-2348, rkmorrow@aol.com

COMPUTER EQUIPMENT WANTED: Epson Action 1100 Laser Printer cartridge. New or used (working). Part #So51023.3. Don 714-730-6015.

Closing Date For Next Issue – October 5th!

DEC EQUIPMENT WANTED!!! We are buying DEC systems, boards, terminals, drives and peripherals. Also Scientific Micro Systems (SMS), DSD, Datability, Dilog, other DEC compatibles, and Computer Output Microfilm (COM) units. Please call for a quote or fax us your equipment list. We buy, sell, and trade. **KEYWAYS, INC.,** 937-847-2300 OR fax 937-847-2350.

TEST EQUIPMENT

SPECTRUM ANALYZER in a probe. $249. View thru your inexpensive scope. WWW.spectrumprobe.com

DEC EQUIPMENT WANTED!!! We are buying DEC systems, boards, terminals, drives and peripherals. Also Scientific Micro Systems (SMS), DSD, Datability, Dilog, other DEC compatibles, and Computer Output Microfilm (COM) units. Please call for a quote or fax us your equipment list. We buy, sell, and trade. **KEYWAYS, INC.,** 937-847-2300 OR fax 937-847-2350.

FEITEK PROVIDES repair, calibration and traceable certifications of test equipment. Free estimates. We buy, sell and trade all makes of test equipment. Visa and MasterCard accepted. Check out our inventory and specials at WWW.FEITEK.COM 2752 Walton Road, St. Louis, MO 63114, 314-423-1770.

SURPLUS TEST EQUIPMENT

HEWLETT PACKARD

11713A, Attenuator/Switch Driver $800
11729B, Carrier Noise Test Set $4500
11975A, Amplifier, 2-8GHz $2000
16500A, Logic Analysis System w/16510A/16520A 16521A/16531A $6000
1652B, Logic Analyzer w/Oscilloscope $4000
3310A, Function Generator $250
3312A, Function Generator, .1Hz-13MHz $700
3314A, Function Generator, .001Hz-19.99MHz $2250
3325A, Synthesizer/Function Generator $1000
3325A/01/02, Synthesizer/Function Generator $1500
3335A, Frequency Synthesizer, 200Hz-81MHz w/Opt. 01 ..... $5500
334A, Distortion Analyzer $250
339A, Distortion Analyzer $1200
3456A, Digital Multimeter, 6.5 Digits $800
3478A, Digital Multimeter $700
3488A, Switch Control $800
3551A, Transmission Test Set $950
3562A, Dynamic Signal Analyzer $7000
3562A, Dynamic Analyzer w/Opt. 063 ..... $8000
35677A, S-Parameter Test Set $2700
3575A, Phase Gain Meter 1Hz-13MHz $1000
3581C, Selective Voltmeter $800
3585A, Spectrum Analyzer, 20Hz-40.1MHz $7000
3586B, Selective Level Meter $750
4192A, LF Impedance Analyzer w/16097A Kit $12,000
4193A, Vector Impedance Meter $7500
4342A, Q-Meter $1800
435B, Power Meter $500
436A, Power Meter w/Opt. 022 ..... $1200
4935A, Transmission Impairment Test Set w/Opt. 001 ..... $1500
5314A/01/02, Universal Counter $225
5316B, Universal Counter $1000
5328B, Universal Counter $1000
5334A, 100MHz Universal Frequency Counter $1000
5334B, Universal Counter $1000
5335A, Frequency Counter, Opt. 10/20 ..... $850
5340A, Frequency Counter, 10Hz-18GHz $800
5340A, Frequency Counter w/Opt. 01/02/011 ..... $1350
5342A, Microwave Frequency Counter, 10Hz-18GHz $1100
5355A, Frequency Converter $1000
5386A, Frequency Counter, 10Hz-3GHz $2350
54100A, Digitizing Oscilloscope $2500
54110D, 1GHz Color Digitizing Oscilloscope $3000
54120A, Digitizing Oscilloscope Mainframe $5750
54121A, Four Channel Test Set $8250
54201D, Digitizing Oscilloscope $2650
8011A, Pulse Generator $400
8011A, Pulse Generator w/Opt. 001 ..... $500
8012B, Pulse Generator $750
8013B, Pulse Generator $750
8116A, 50MHz Pulse/Function Generator, Opt. 001 ..... $4500
8165A/002, Programmable Signal Source w/AM $2200
8347A, RF Amplifier, 100KHz-3GHz $3000
8350A, Sweep Oscillator Mainframe $1500
8350B, Sweep Oscillator Mainframe $2350
83522A, Sweeper Plug-in, .01-2.4GHz, w/Opt. 02 ..... $4500
83540A, RF Plug-in, 2.0-8.4GHz $2000
83540A/002, RF Plug-in, 2-8.4GHz $2500
83545A, Oscillator Plug-in, 5.9-12.4GHz $1750
83570A, Sweep Oscillator Plug-in, 18-26.5GHz $4750
8411A/018, Frequency Converter .11 to 18GHz $500
8494H, Programmable Attenuator (unused) $800
8495H, Programmable Attenuator (unused) $600
8501A, Storage Normalizer $1000
8511A, Harmonic Frequency Counter $7000
853A/8558B, Spectrum Analyzer, 100KHz-1500MHz $3850
853A/8559A, Spectrum Analyzer, 10MHz-21GHz $4750
8554B, RF Spectrum Analyzer Plug-in, 500KHz-1250MHz $800
8559A, Spectrum Analyzer Plug-in, .01-21GHz $2650
8566A/B, Spectrum Analyzer, 100Hz-22GHz $25,000
8568A/B, Spectrum Analyzer, 100Hz-1500MHz $11,000
8569B, Spectrum Analyzer, 10MHz-22GHz $7000
86290B, Sweep Oscillator Plug-in, 2-18.6GHz $1100
8640A, Signal Generator, 0.5-512MHz $700
8640B, Signal Generator, Opt. 002, .5-1024MHz $2100
8640B, Signal Generator, Opt. 1, 2 ..... $2200
8654A, Signal Generator, 10-520MHz $450
8656A, Signal Generator, 100KHz-990MHz $2000
8660D, Synthesized Signal Generator $7000
8672A, Synth. Signal Gen., 2.0-18.0GHz $8000
8746B, S-Parameter Test Set, 5-12.4GHz $700
8753A, Network Analyzer w/85046 Test Set $13,500
8757A, Scalar Network Analyzer, 10MHz-60GHz $5000
8901B, Modulation Analyzer $4000
8903B/001, Audio Analyzer $2500
8904A, Multifunction Synthesizer w/Opt. 002 ..... $2500
8970A, Noise Figure Meter $5000

TEKTRONIX

1502, TDR Cable Tester w/Opt. 04 Recorder $1700
1503, TDR Cable Tester w/Opt. 04 Recorder $1550
2236, 100MHz Oscilloscope w/Counter/Timer/DMM $1550
2247A, 100MHz Oscilloscope w/Counter/Timer/ Voltmeter $2500
2337, 100MHz Oscilloscope w/DMM $1650
2432A, 300MHz Digital Storage Oscilloscope $3000
2445, Four Channel 150MHz Oscilloscope $1500
2465, Four Channel 300MHz Oscilloscope $2500
466, 100MHz Storage Oscilloscope w/DM44 ..... $800
475, 200MHz Oscilloscope $650
475A, 250MHz Oscilloscope $800
485, Oscilloscope, 350MHz $900
576, Curve Tracer $2750
577/D2, Curve Tracer, Non-storage w/177 Fixture $1750
7A42, Four Channel Amplifier Plug-in $650
7D20, Programmable Digitizer $400
7L5/L3, Spectrum Analyzer, 20Hz-5MHz, w/Opt. 025 Tracking Generator $1850
7L12, Spectrum Analyzer, 100KHz-1.8GHz $1500
7L13, Spectrum Analyzer, 1KHz-1.8GHz $1800
7L18, Spectrum Analyzer Plug-in, 1.5-18GHz Capable of 60GHz with Mixers $2500
7S12, TDR/Sampler $450
AA5001, Programmable Distortion Analyzer $1700
AFG5101, Arbitrary Function Generator $1500
CG5001, Programmable Calibration Generator $4000
CSA907R, Error Detector, 1-700MHz $6500
PG506, Calibration Generator Plug-in $600
R2246, 4 Channel Oscilloscope, 150MHz $1650
SG5010, Programmable Oscillator $3000
SG504, Leveled Sinewave Generator $2200
TM5003, Three Slot Power Mainframe $450
TM5006, Six Slot Power Mainframe $550
TR503, Tracking Generator for 492/4/5/6 ..... $850

VISIT OUR WEBPAGE AT WWW.RSSURPLUS.COM

MISCELLANEOUS

Acme Elect. PS2L1000, Electronic Load $850
California Inst. 4500L/M3, AC Power Source $4500
California Inst. 4503L, AC Power Source $4500
Eaton 2052B, Amplifier, 100-512MHz $800
EIP 545A, Microwave Frequency Counter $1250
EIP 548A, Frequency Counter, 10Hz-26.5GHz $2700
EIP 548B, Frequency Counter, 10Hz-26.5GHz $3900
EIP 578, Source Locking Frequency Counter $3000
ENI 1140LA, Power Amplifier, 9KHz-250KHz $3500
ENI 310L, RF Amplifier, 50dB, 250KHz-110MHz $2000
ENI 325LA, Power Amplifier, 250KHz-150MHz 25 Watts $1850
ENI 503L, RF Amplifier, 40dB, 2-510MHz $800
ENI 5100L, RF Amplifier, 100 Watt, 1.5-400MHz $8000
Fluke 5100B/03/05, Multifunction Calibrator $3000
Fluke 5101B/03, Calibrator $3000
Fluke 5200A, AC Voltage Calibrator $2000
Fluke 5440B, Direct Voltage Calibrator $3000
Fluke 732A, DC Standard $1850
Fluke 752A, Reference Divider $2500
Fluke 8520A, Digital Multimeter $700
Gigatronics 910, Frequency Synthesizer, .05-26GHz $9500
Kikusui PAD16-10L, Power Supply, 16V, 10A $300
Kikusui PLZ700W, Electronic Load $850
Krohn-Hite 3202/R3202, Tunable Filter/ Rack Version ..... $500/$350
Marconi 2019A, Signal Gen., 80KHz-1040MHz $2750
Phillips 6652C, Prog. High Res. Counter/Timer, 8 Digit, 120MHz $1300
Sorensen DCR300-33T, DC Power Supply 300V/33A $2750
Sorensen DCS40-25, DC Power Supply, 40V/25A $750
Trans. Devices DLR400 15 3500A, Dynamic Load $1500
Trans. Devices DLP 50-60-1000A, Electronic Load $800
Trans. Devices DLVP 130-110-1000 Electronic Load $950
Trans. Devices DLVP 50-120-1000 Electronic Load $1000
Valhalla 2703, AC Voltage Standard $2350
Varian VZL6942G5JM, Amplifier, 1-2GHz, 100 Watt $8000
Wandell Golterman SPM19, Level Meter, 50Hz-25MHz $2000
Wavetek 178, Automatic Synthesizer $1850
Wavetek 23/01, 12MHz Synthesized Signal Generator $1000
Wavetek 3000, Signal Generator, 1-520MHz $900
Wavetek 3000-200, Signal Generator $900
Wavetek 3001, Signal Generator 1-520MHz $1000
Wavetek 801, Pulse Generator, 5Hz-50MHz $800
Wavetek 8502A, Two Channel Microwave Power Meter $3750

MasterCard VISA

R & S Surplus
1050 E. CYPRESS STREET, COVINA, CA 91724
(626) 967-0846 · FAX (626) 967-1999

A & S WHOLESALE

Cable Boxes • Accessories

DEALERS ONLY

	5 LOT	10 LOT
PANASONIC w/volume	$160	$145
DIGI w/volume (125 ch.)	$165	$150
DIGI one-piece (83 ch.)	$105	$99
PANASONIC 1003	$55	$49

CALL FOR PRICING ON ITEMS NOT LISTED
Buy Directly From The Wholesaler And Save $
1-800-370-0801
Mon. - Fri. 9am - 6pm • CST
30-Day Money Back Guarantee • 6 Month Warranty
Anyone implying theft of cable service will be denied assistance.
WE WILL MEET OR BEAT OUR COMPETITOR'S PRICING

EFRATOM FRK-L rubidium **oscillators!** 10MHz sinewave output at 0.5Vrms. Long term stability: <1 x 10^{-10}/month. Includes optional Mdl EEK-10 heatsink and I/O connector. **Used, calibrated, with fresh NIST traceable certificates only $500 ea.** Requires 23VDC to 32VDC at 1.7A max. Full specifications and picture at our website. (Quantities available) **Handheld LCR/DMM/frequency counter, BelMerit DX460L**, all standard DMM functions plus frequency to 20MHz, TTL and CMOS logic, capacitance meter and inductance meter and more! Comes with holster, battery, test leads and manual. Three-year warranty! Special price $95. **Sencore SC61 waveform analyzer**, DC 60MHz, oscilloscope plus digital readout of frequency, P-P volts, Delta volts, Delta time, etc. Comes with 2 brand new Sencore probes! Fully checked out and guaranteed $750. **Lehman Scientific 1-800-784-8680 Visa/MC. www.lehmanscientific.com**

KENTRONIX TEST EQUIPMENT SPECIALS. Check our WEB site at **http://www.kentronix.com** for monthly specials. We are also looking to buy test equipment, coaxial and waveguide components, manuals, etc. Contact Brian at 732-681-3229 or FAX 732-681-3312. E-Mail: brian@kentronix.com

WANTED: WESTERN electric test equipment. Tube-type only please. Freq. measurment sets, oscillators, amplifiers, coils, transformers, parts, tubes. **Free offer, Great Wireless Museum** 1-800-653-6427.

TERRIFIC VALUES: Tek 222A handheld digital storage scope with readout $995; **Tek AM 503, A6302** current probe, amplifier $825; **HP 54100D** 1GHz digitizing oscilloscope $3,100; **HP 83522A** .01 to 2.4GHz plug-in $4,100; **HP 83570A** 18 to 26.5GHz plug-in $5,400; **HP 3488A** mainframe $650 (cards available); **HP 8161A/020** 100MHz dual channel pulse generator $2,750; **HP 339A** distortion analyzer $1,150; **Stanford Research SR 510** lock-in amplifier $975; **HP 8410C, 8410B, 8410A** network analyzer mainframes $625, 450, 250; **HP 8411A/018, 8411A** harmonic frequency converters $425, 300; **HP 8743B/018, 8743A** test sets $575, 325. All in excellent condition with warranty. Pepper Systems (home.earthlink.net/~peppersys) 214-353-0257 (Fax 214-902-9511). E-Mail: peppersys@earthlink.net

TEST EQUIPMENT Sale: HP 8620C w/sweeper plug-in (various) $900; Tek 485 $500; Tek 466 $500; Tek 468 $500; Tek 7104 w/plugs $900; Wavetek/135 $200; Wavetek/188 $200; Tek 7854 $900; Fluke 2175A $50; GR 1390B $75; HP 37900D $2,500; HP 5370A $275; HP 5383A $200; HP 54201A $900; HP 54501A $1,500; HP 64700A $500; HP 8018A $200; HP 8444A $250; HP 141T w/plug-ins $1,000; Boonton 92B $250; DIO 29B w/Unipak IIB $350; HP 86633B $500; HP 3310A $200 HP 3310B $200; HP491C $450; HP 1741A $350; HP 1745A $350. All with warranty, more next month! Visa, MasterCard, Discover are accepted. Tru Cal International, Phone 1-800-681-5540, Fax 630-238-8101.

WHOLESALE CABLE

COMPLETE LINE OF CABLE PRODUCTS

☑ Quality merchandise by brand name manufacturers
☑ Satisfaction guaranteed ☑ Free gift on first order
☑ Technical support
☑ 2 year warranty on new converters
☑ COD shipping & overnight shipping by request
☑ Experience where it counts ☑ Volume pricing

Tell us the best price you were offered, where you got it from, and let us try to beat it.

PLAIN CONVERTERS: ZENITH, OAK, PANASONIC, PIONEER, EAGLE, HAMLIN, STARGATE, PLUS MORE.

REMOTE CONTROLS: ALL MAJOR BRANDS, INCLUDING 2-4 FUNCTION UNIVERSAL REMOTES

WHOLESALE CABLE M-F 11am-6pm EST **(800) 909-4333**
(718) 262-0900 · FAX (718) 657-4015 · (718) 297-9221

No NY sales. Federal and local laws provide criminal and civil penalties for unauthorized use. Check with your cable providers for permission to use equipment. Must be paying for all services you receive. Order by model number only. Some equipment refurbished as new.

Low Cost Serial to LCD Interface IC



ZERO Pin Interface!

Ideal For Prototype or Production – Easy to Use yet Extremely Powerful!

Designed to provide a cost-effective LCD control solution for both prototype & production designs, the EDE702™ LCD Interface IC controls nearly any character-based LCD module via a simple one-wire serial link. A serially-controlled digital output pin (ideal for a piezo beeper or LED) on the EDE702™ makes the connection to any microcontroller or Stamp™ effectively a zero-pin interface. Both RS-232 and TTL compatible, this IC offers full control over all LCD module features such as custom character generation, scrolling, etc. Operation at 2400 or 9600 Baud N-8-1 ensures compatibility with nearly all microcontroller systems via either a serial transmit pin or via a 'software UART' (a simple bit-shifting method used to send serial data to an output pin). Available in 18 pin DIP or SOIC packages, the EDE702™ is ideally suited for both one-offs and production runs. Priced at $9.00 single unit, $4.50 1K pricing. For additional details download the EDE702™ Datasheet or contact us directly.

ē·lab Digital Engineering, Inc.
E-Lab Digital Engineering, Inc.
1600 N. 291 Hwy Ste. 330
P.O. Box 520436
Independence, MO 64052
(816) 257-9954
FAX: (816) 257-9945
www.elabinc.com

Also popular are our EDE300 PC Interface IC, EDE1200 Stepper Motor Controller, and EDE1400 Serial to Parallel Printer IC.
Engineers: call about our Component-Reduction™ Service: we create custom IC's for use in your embedded designs, reducing component count, increasing functionality, and lowering per-board price. Economical even in low volumes.

VISA & MASTERCARD gladly accepted. All prices are subject to change without notice. Seeking Committed Distributors for EDExx IC Family.

Write in 44 on Reader Service Card.

EQUIPMENT MANUALS we have 1000's of service and operators manuals for all types of test and measurement equipment from 1950 to present. All test equipment manufacturers are represented. Call, write, or fax your want list. Please include mfg.'s manual P/N unit serial numbers if known. **Manuals Plus**, Box 549, TAD #601, Tooele, UT 84074. 435-882-7188, FAX 435-882-7195.

LOWEST PRICES! HP 3551A transmission test set $500; HP 5316A universal counter $400; HP 141T display mainframe $300; HP 5005B signature multimeter $300; HP 5345A electric counter with channal C plug-in, option 011 and 012 $500; HP 8750A storage normalizer $300; HP 5004A signature analyzer $200; HP 5150A thermal printer w/opt 002 $200. All items come with a manual and 10 day right of return. **WALL SURPLUS**, phone/fax 732-681-2032 anytime.

TEKTRONIX OSCILLOSCOPES: 475 200MHz with opt 93 $325; 466 storage 100MHz $325; 464 storage with DM44 $325; 454 scope $250; 434 storage $250; **7623A** with 7A14, 7A18, 7B53A plug-ins $275; 7613 with 7A18 + 7B53A plug-ins $200; **7603, 7613, 7623A** mainframes $125. Each with manuals and 10 day right of return. **WALL SURPLUS**, phone/fax 732-681-2032.

STRAINSERT TN8C 8 channel transducer strain indicator, $150; Tektronix TM504, with PS503A dual power supply, DM501A, 4.5 dig DVM, and FG503 3 MHz function generator, $700; Wavetek 1034 portable power meter 1MHz-18GHz power meter, $400; HP 428B current meter and probe, $300; Tektronix 2235 100MHz dual channel scope, $600; Tektronix, DM501A, $200; PS-503A dual power supply, $150; FG503 3MHz function gen., $200; HP 204C audio osc., $150. A-Comm Electronics, 11891 East 33rd Avenue, Unit C, Aurora, CO 80010. Phone 303-341-2283, fax 303-341-2293. Web site: http://www.a-comm.com

WANTED: RADIO service monitors, IFR, Motorola, HP, Marconi, also late model HP equipment. 716-763-9104 or Fax 716-763-0371. http://www.amtronix.com

AFFORDABLE HP power sensor repair! Most 8481As repaired for $235 or less. We also handle 478As and many others. Call or fax for more information. Willamette RF, Inc., 541-754-7226, FAX 541-753-4629.

MICRODYNE 1100, 1200, 1400 series receivers all bands, FM and PM demods, SDU, IF filters. Aydin, Schlumberger, monitor systems bit syncs. 805-934-2058.

HP 8672A synthesizer signal generator (2 to 18GHz) good working condition $5,300. 714-778-5151.

SCOPE SALE: New Tek isolator A6902B $350; 475A DM44 $700; 7904 frame w/7A24, 7A26, 7B85, 7B92A, $600; Philips PM3217, $200; Kikisui 50MHz 4 channel 5042, $200; Tek 466, $400; 7A13, $100 LED; 7A18, $45; 7A19, $100; 7A26, $60; 7B53A, $60; 7B80/7B85, $75 ea.; 7B92A, $125; 7D15, $175; 7F10 optical to electrical converter $225; DC504, $175; PG-508, $350; S-2 sampling head $150; SC-501 scope $125; $200 w/TM-501; SI-5010 as new $200, Tektronix 1502 opt. 4 $1,100; CALL FOR OTHERS. All with 30-day warranty. Call **Psitech Plus**, phone 707-745-4804, fax 707-747-5277. E-Mail: apeas@ix.netcom.com

TEST EQUIPMENT for sale! HP 331A distortion analyzer $175; HP 353A patch panel, 110dB attenuator, combining case $55; Eico 324 RF generator 150KHz-450MHz $29; Heath IM11 VTVM $45; Heath IM5210 40KV probe $39; Knight G30 Grid Dip Meter 1.5-300MC $35; Lafayette TE19 CRT rejuvenator $45; 3M/MinCom 8155A flutter meter $79; Micronta 22-012 tube tester $25; NRI Mod 33 signal tracer, RF generator $39; RCA Senior VoltOhmyst, model WV98C $29; Scaler rate meter radiation counter $25; REM CRT rejuvenator $55. Call Tom 609-222-0636. FAX 609-222-0638.

EQUIPMENT SALE: HP 8640B opt. 003 $475; HP 59501A D/A power supply $50; HP 1630G logic analyzer, with all pods $450; Anritsu 645A, both the sending & receiving unit for $250; Siecor M42 optical time domain reflectometer, $200; Leader LPS-151 DC tracking supply $200. Psitech Plus, 707-745-4804, fax 707-747-5277. E-Mail: apeas@ix.netcom.com

HP 54602B 4 ch. 150MHz DSO, opt 5 (enhanced video trigger), 7512 terminator, benchlink module and software (scope to computer via RS232), training kit pouch, probes, transferable HP warranty, new cond. $2,800. Sorenson DCR-115B DC power supply, CVCC, 0-20V, 0-115A, dual meter 220V new cond. $800. Call 201-796-1405.

WANTED: WESTERN electric test equipment. Tube-type only please. Freq. measuring sets, oscillators, amplifiers, parts, tubes, etc. 1-800-251-5454.

BRUEL & KJAER BUY, SELL, BEST PRICES. EXCALIBUR ENGINEERING, 3198-C AIRPORT LOOP DRIVE, COSTA MESA, CA 92626. 714-540-0169, FAX 714-540-5417.

TEST EQUIPMENT repair or overhaul Tektronix, HP, Wavetek, Boonton, etc. 20 years experience with former Slep Electronics Co., same excellent service same reasonable rates, satisfaction guaranteed. Brooks Electronics 828-349-3503. E-Mail: rwbrooks@dnet.net

Source Code:810NV — Sale Ends: 12/15/98

www.spysite.com

COVERT SURVEILLANCE: Protect Your Assets

MC-985 $350 | CL-985 $350 | SD-985 $295 | VL-985 $350

EXIT SIGN CAMERA EX-985 $295

EMERGENCY LIGHT CAMERA EL-985 $325

All "985" Series Color Cameras Feature:

- Sensor: 1/3" Sharp® Color CCD
- Resolution: Over 380 TV lines
- Sensitivity: Super Low, 2 Lux
- Built-In Backlight Compensation
- Lens: 3.7 mm Pinhole
- Viewing Angle: 92 FOV
- Video Output: Female RCA
- Power: 5V DC (included)

CLOSEOUT

Color Camera Kit:
- 1/2" Sony Color CCD
- 400 TV line Res.
- 2 lux Sensitivity
- Backlight Compensation
- 4 mm Standard Lens
- Wall Mounting Kit
- 5V Power Transformer

SONY-1002 $175

Counter Surveillance: Protect Your Privacy

Protect Yourself From:
- Telephone Taps
- Room Transmitters
- Body Wires

Built-In White Noise Generator

AI-5500 $380

Detects Concealed:

- Tape Recorders
- Video Cameras
- Body Transmitters
- Room Transmitters

LED and Vibration Alert

TRVD-900 $450

Your Payment Options: Credit Card, Cashier's Check, or Money Order

AMERICAN INNOVATIONS, Inc.
119 ROCKLAND CENTER ~ Suite 315 NANUET, NY 10954
Voice: (1) 914-735-6127 Fax: (1) 914-735-3560

Write in 45 on Reader Service Card.

CHECK CAPACITORS IN-CIRCUIT WITH 100% ACCURACY

CapAnalyzer 88 $179
- Automatically discharges cap; Checks for low **DCR** and shorts; Checks high-frequency **ESR** and displays on 20-segment LED meter
- 3-color chart shows typical values.
- Includes gold-plated tweezer probe
- Portable... Batteries included!

LOCATE ANY SHORTED or LEAKY COMPONENT TO THE EXACT SPOT



LeakSeeker 82A $179

Locates shorted & leaky parts to the exact spot on the PCB without cutting up the board or unsoldering any parts!

- *60 DAY MONEY-BACK GUARANTEE ON ALL EDS TEST EQUIPMENT*
- *AVAILIABLE AT YOUR FAVORITE DISTRIBUTOR*

ELECTRONIC DESIGN SPECIALISTS

4647 Appalachian St, Boca Raton, FL 33428 561-487-6103 www.eds-inc.com

VISA MasterCard DISCOVER

we make test equipment designed to make you money.

Write in 46 on Reader Service Card.

COMPUTER CIRCULATION CENTER, Inc.

dba: Alltech Electronics

2618 Temple Heights Drive.
Oceanside, CA 92056
Phone Order Hours 9AM - 5:30PM Mon-Fri

Phone Orders
760/724-2404
$25 -Min. Order -

9350 Clairemont Mesa, San Diego - 619/573-0411
1401 El Camino Real. Oceanside - 760/721-0093
1300 E. Edinger. Santa Ana - 714/543-5011
2018 W. Lomita BLVD. Lomita - 310/539-2260
We buy surplus & excess computer inventory as well as scrap electronics related inventory.

Refurbished Computer Systems

486DX2/66
16 MB • 200 MB New SVGA Monitor • $249.00
Systems Include Keyboard and 1.44 MB Floppy
You supply software & go!

$249!

Be sure to check our Web Site for more information on these and other products!

www.allelec.com

Fujitsu Cash Drawer

With Metal Till. Triggers from any 24VDC source. RJ45 connector.
$79.00



Fujitsu Cash Drawer, Metal Till, 9" Monochrome VGA Monitor, & Star SP200 Parallel Printer $299.00

NEC Mini 486



Mini footprint 3.5" x 11.5 x 13
486 SX 25 CPU
4MB On board
2 ISA Slots
IDE, FD, 2 COM, 1 LPT & 512K VGA
UPGRADABLE to DX2/66

Need a Linux Box?
$29.00

$14.95

Pulls from working systems. Non PnP Version. Works with any* OS. No Plug n Pray Hassle!

USR Sportster 14.4

8 Port 10 BaseT Hub Home Network?

$49.00

Cable Modem?

Used/Tested 8 Port Hub. 8 10BT and 1 BNC.

Epson Reciept Printer

EPSON TM300PD Parallel Interface With drawer trigger

$89.00



Slimline Case
8MB RAM
1.44 Floppy
DX266 Add $10

$39.00

486 DX33 Barebones

10" Open Frame NEW Color SVGA!

Up to 1024 x 768 pixels
110V AC operation.
CD-1035EM

$159.00

Refurb: $119.00

Great for servers, small places, POS systems..
Low profile case with swivel stand

$79.00

9" Mono NEW VGA

External SCSI Cases

$29.00 & Up



5.25" Closed HH $29.
5.25" Open HH .$35.
5.25" Open FH . .$45.
3.5" Open for Zip., Syquest., etc . . . . .$29.
3.5" Lunchbox . .$19.
All cases have two 50 pin centronics connectors.

Mac ADB Trackpad

$9.95

Powerbook like trackpad.
ALPS Glidepoint
2 1/8" x 1 1/2"
ADB Cable.
Works with any ADB Mac.

Floppy & Zip SCSI Drives

3.5" NEW 720K $5.00
3.5" NEW 1.44MB $16.00
SCSI Zip Drive External
Refurb **$89.00**

PC Keyboard / Mouse

AT 101 Keyboard $9.95
9 Pin Serial Mouse $6.95

Black External 28.8 Modem/Fax with Mac Cable. No Software Included.

Originally from: "Pippin @world"

$29.00

Motorola Macintosh ModemSURFr 28.8

Metal Box 'Cube' case
Security Monitor with front mount controls.
Black cabinet.
75Ω input

$39.00

9" B&W Security Monitor

CPUs

486SX 25/33	.$3.00	.$5.00
486SX2-66		.$8.00
486DX25/33	.$5.00	.$8.00
486DX2-50/2-66	.$18.00	.$29.00
486DX4-100		.$49.00
Pentium 75/90	.$39.00	.$49.00
Pentium 100 / 133	.$65.00	.$75.00
Pentium 166		.$99.00

Upgrade Your System

EPROMs

2716 /2732	75¢
2764 /27128	$1.50
27256 /27512	$2.00
1Meg	$2.50
2 Meg	$3.50

RAM Chips

4Meg x 9-80	$15.00
1x32-70	$9.00
2x32-70	$19.00
4x32-70	$35.00
1 meg x9-10	$2.00
1 meg x9-80	$3.00
1 meg x9-70	$4.00

IDE Hard Drives

420 Meg	$59.00
320 Meg	$49.00
270 Meg	$40.00
120 Meg	$35.00
80 Meg	$25.00
40 Meg	$15.00

PC Oldies but Goodies

EGA/CGA Card -or- ISA Super I/O	$14.95
2 Meg AT Memory Card - or - Parallel/Mono Card	$9.00
Floppy Controller -or- Serial / Parallel Card	$6.95
VLB 1 Meg VGA Card - or - 386 Motherboard w/2 Meg.	$19.95
16 Bit (ISA) VGA w 256/512/1 Meg	$9.00 / $12.00 / $14.95
VLB Super I/O	$12.95
8 Bit VGA Card - or - XT Motherboard w/640K	$9.95

Modems

External or Internal PC 2400	$9.95
Internal PC 9600	$12.95
Internal PC 14.4/Fax	$15.95
External Practical Peripherals 14.4 (Pacakged for Mac, but works with anything	$19.00
PCMCIA 14.4 Modem (Various)	$29.00
External 28.8 Modem (New/Bulk)	$39.00

CD ROM & Sound Cards

4x IDE Internal	$29.00
8x IDE Internal	$39.00
24x IDE Internal	$59.00
4x SCSI Internal	$39.00
4x SCSI External	$69.00
Ensoniq SoundScape w/on board CPU	$49.00
Universal Audio Cable (CD ROM to Soundcard)	$4.95

HTTP://WWW.ALLELEC.COM

VISIT OUR WEB PAGE DAILY FOR SPECIALS & MORE INFO. ON THESE ITEMS

CA Residents please add 7.25% Sales tax.• Minimum shipping & handling charges $8.50. • Warranty: Used/Refurbished products have a 90 day warranty • ALL Returns must have an RMA #, call before shipping back to us. • No Returns without an invoice. Shipping & Handling charges are non-refundable • 20% Restocking charge, applies to products purchased in error & incompatibility problems. School & University Purchase Orders accepted, others on AOC only. • Prices and availability subject to change at anytime without any notification whatsoever..

EFRATOM FRK-L rubidium oscillators! 10MHz sinewave output, 0.5Vrms. Long term stability: <1 x 10 $^{-10}$/month. Includes optional Mdl EEK-10 heatsink and I/O connector. Used, with fresh NIST traceable calibration certificate only $500 ea. 6 month guarantee! Full specifications and picture at our website. Lehman Scientific 1-800-784-8680. Visa/MC. www.lehmanscientific.com

CAPANALYZER 88 finds bad caps in-circuit with 100% accuracy. Checks both ESR and DCR, auto-discharge feature. Money back guarantee. www.eds-inc.com 561-487-6103.

LEAKSEEKER 82A tracks a shorted or leaky component to the EXACT location on the PCB. Range: zero to 150 ohms. Money back guarantee. www.eds-inc.com 561-487-6103.

HEWLETT PACKARD 141T spectrum analyzer with 8552, 8553, and 8554 plug-ins $1,000; 141T mainframes $250; HP 7035 X-Y recorder $50. All plus shipping, send SASE for list. John Bartholomew, 519 Lower Terrace, Huntington, WV 25705. Phone 304-525-8793.

TEST EQUIPMENT for sale/wanted: RF, Microwave, video and fiber optic. Cable TV, Broadcast TV, satellite and related industries. Wavetek, Tektronix, Hewlett Packard and other manufacturers. Spectrum analyzers, signal level meters, sweep systems, TDRs, OTDRs, and much more. PTL Test Equipment, Inc. Phone 561-747-3647 FAX 561-575-4635.

POOR MAN'S Spectrum Analyzer/Monitor Receiver Kit. 2 to 1,700 MHz. Basic kit only $78. Now available with switched resolution filters, tracking generator and direct digital frequency readout. Works with ANY scope or IBM compatible computer. Send stamped envelope for details. Science Workshop, Box 310B, Bethpage, NY 11714. http://www.science-workshop.com

LOWEST PRICES! Check out Metric's "Current Specials" at **http://www.metricsales.com** Great deals on top quality refurbished test equipment. Call 1-800-432-3424 for a free catalog.

SUCH A DEAL! Check out Metric's "Current Specials" at **http://www.metricsales.com** Great deals on top quality reconditioned test equipment. Call 1-800-432-3424 for a free catalog.

WANTED! ELECTRONIC test equipment. We pay top dollar for used scopes, generators, analyzers from HP, Tektronix, and others. Call Charles at Metric for immediate quotation. **1-800-432-3424** Fax: 510-264-0886.

TEST EQUIPMENT for sale: HP 83557A millimeter wave 50-75GHz as new boxed $6,000; HP 83558A 75-110GHz $6,000; HP 8508A with 85081A $3,900; EIP 931 microwave sweeper .01-18GHz $3,900; Fluke 3384B DSO 100MHz NEW $3,000 and much more. **WE BUY TEST EQUIPMENT,** FAX your list to: HTB Elektronik; ATTN: "Tom" FAX 01149 4706 7049 or E-Mail: htb@bremerhaven-net.de

WANTED! ELECTRONIC test equipment. We pay top dollar for used scopes, generators, analyzers from HP, Tektronix, and others. Call Charles at Metric for immediate quotation. **1-800-432-3424** Fax: 510-264-0886.

WANTED! ELECTRONIC test equipment. We pay top dollar for used scopes, generators, analyzers from HP, Tektronix, and others. Call Charles at Metric for immediate quotation. **1-800-432-3424** Fax: 510-264-0886.

WANTED: ELECTRONIC estates. Ham, broadcasting, military, test, public address, tubes, transformers, telex equipment. The bigger the pile, the more worthwhile. We fly anywhere. Sumner McDanel 1-800-251-5454.

NEW: POCKET TESTBENCH, tiny, portable, RS-232 instrument. Scope, logic, spectrum, counter, generator modes. Oricom Technologies, 303-444-9776 (www.sni.net/~oricom).

FACTORY BOXED new 30 HSM 2GHz high-speed module $450; Fluke 8920A true RMS voltmeter $300; Psitech Plus, 707-745-4804, fax 707-747-5277. E-Mail: apeas@ix.netcom.com

WE WANT to buy your excess test equipment. We will pick up and pay at time of pick up. Metrowest Technologies, phone 508-478-7613, fax 508-634-3806, WWW.metrowesttech.com

TEKTRONIX EQUIPMENT: Curve tracers, logic analyzers, scopes, spectrum analyzers, etc. Metrowest Technologies, phone 508-478-7613, fax 508-634-3806, WWW.metrowesttech.com

METROWEST TECHNOLOGIES: Boston's Equipment Supersource. Call us for a quote on your next equipment purchase. Metrowest Technologies, phone 508-478-7613, fax 508-634-3806, WWW.metrowesttech.com

HP 6268B power supply 0-40V@0-30A, manual $475; **HP 4342A** Q-Meter $595; **HP 8640B** 001,002,003, manual $1,195; **TEK** 465M $349; **Wavetek** 1001A $149; **HP 334A** $100; **Fluke** 540B $295; **TEK** AM 502 $100; **HP 6006A** $149; **HP 8620C** 5.9-9GHz $295; **TEK** TM 503 $75, **TEK** 7844, opt. 3,22,78 $149. Technologies West, 541-267-6064.

NEW WORLD TECHNOLOGIES, INC. and EWIG U.S.A.

Remote Control Manufacturer Selling Directly to YOU!

Offering Remotes:

- **For all Converters & TVs**
- **Universal Remotes**
- **Hotel/Motel Remotes**
- **Manufactured to your specs, if desired**
- **More competitive pricing (less expensive)**

Plus FREE BATTERIES
BLANKET ORDERS WILL BE SHIPPED FREE-OF-CHARGE
CONTACT US TODAY FOR DETAILS!!!

1-800-380-9530 Home Office
1-800-322-5286 Southeastern Division

BECOME AN EWIG U.S.A. DISTRIBUTOR
FAX# 904-721-5013 **WEBSITE http://www.newworldtec.com**

Write in 37 on Reader Service Card.

The Filter Company

Positive Notch Filters

Internet: www.gofilters.com

Large STOCK on all Available Channels
2 thru 30*, 95 thru 99
0,1,57,58,59,60,61,A1,A2,A3,A4,A5
ORDER BY SINGLE CHANNELS

We Specialize in Large Quantities on every Channel
Prices as low as $6.00ea

NOBODY BEATS OUR PRICES

Monday - Friday (8am to 5pm) Central Time
QUALITY METAL CYLINDER TYPE NON-TUNABLE
ABSOLUTELY NO DRIFTING PROBLEMS

Standard Positive Filters

1pc-$16.00 5pcs-$14.00 10pcs-$12.00
25pcs-$10.00 50pcs-$8.00

*Standard Positive Filters, Channels 26-30 add $3.00 more each.

Positive "G and S" Series Filters

1pc-$30.00 5pcs-$28.00 10pcs-$25.00

Tom G. - FL ***Excellent Service, fast and quick. The only bad thing about this company is they don't sell Cable Boxes. We hope someday they will.....***

David P. - CA ***We called around for help on filters and nobody had any answers except one, call the "THE FILTER COMPANY" we did and had an answer in a matter of seconds.....***

John B. - IL ***Our company buys in the 100 quantities and needs a large selection of different channels. "The Filter Company" was the only one who was able to supply.....***

PHONE ORDERS:

1-800-235-8080

Visa, Mastercard and Discover
(UPS COD for established customers)

Anyone implying theft of Cable Service will be denied assistance
We do not sell Data Blockers, Bullets or FM Traps !!!!

A "TFC" Company

Give our 800 line a howl for the best service in the Country.....!!!!

TEKTRONIX PLUG-INS: We have them for 7000 series scopes, TM500 mainframes, TM5000 mainframes. Metrowest Technologies, phone 508-478-7613, fax 508-634-3806, WWW.metrowesttech.com

FREE CALIBRATION? We offer free calibration for most equipment when you purchase test equipment from us. Metrowest Technologies, phone 508-478-7613, fax 508-634-3806, WWW.metrowesttech.com

LOWEST PRICES! HP 7585B drafting plotter $1,000; HP 7596A Draft Master II plotter $1,000; HP 7475A, 7550A plotters with **HPIB** $500 each. All items come with manuals and 10 day right of return. **WALL SURPLUS,** phone/fax 732-681-2032.

KENTRONIX TEST EQUIPMENT SPECIALS. Check our WEB site at **http://www.kentronix.com** for monthly specials. We are also looking to buy test equipment, coaxial and waveguide components, manuals, etc. Contact Brian at 732-681-3229 or FAX 732-681-3312. E-Mail: brian@kentronix.com

HP 141T/8552/8554 spectrum analyzer, excellent condition w/bright CRT and manuals, $1,000 + shipping. 925-455-9514 voice; 925-455-1760 FAX; E-Mail: jdhymer@ricochet.net

ENI MRI 2000 2KW linear pulse power amp 15-65MHz, unused $1,600; Esterline Angus S-22906-1 three phase power recording system with current probes 50A and 1KA, A-Comm Electronics, 303-341-2283.

DUKANE ULTRASONIC welder 1600 watt, several transducers, many horns, RF generator, monitor, manual $2,500. 937-429-5403.

HP 7475A, 6 pen plotter, RS-232, $100; HP 10601A scintillation detector, 2" crystal $300; Jim Triplett, Box 101, Ames, IA 50010. 515-233-1770.

HP 8566 bottom section for parts, HP 8445B preselector, EICO tube tester, HP 5343A-001-011 counter, EIP 548B counter, EIP 585 pulse counter. PH/FAX 706-653-2511.

CUSHMAN CE3 $175; Heathkit Frequency Counter SM2420 0-512MHz $29; Simpson 260 multimeter $20; Tek 465 & DM 40 $125. Call for list. 909-873-1319.

TEST EQUIP. GenRad 1316 osc. $700, 1308 osc./amp $850, 1424A DecCap $250, 142551 DecCap $450, 1666 res/brig $500, 1863 megohmmeter $525. 978-251-3855.

LOWEST PRICES! Tektronix PLUG-INS: 7A16A, 7A18, 7B53A, 5B85, 5B42 $50 each; 7A13, 7A19, 7A26, 7B92, 7B92A, 7D11, DM501, PG505 $100 each; 7A24, FG501, 7S11 $150 each; DC508 $350 each. **WALL SURPLUS** phone/fax 732-681-2032.

HP 8620C sweep oscillator opt 011 with 862 42A RF plug-in $500; **HP** 8444A tracking generator $350; **Tek** 7912 AD programmable digitizer $400; **Tek** 7CT1N curve tracer $250; **Tek** SC 502 15MHz scope $250. Each with manual and 10 day right of return. **WALL SURPLUS**, phone/fax 732-681-2032 anytime.

BEST PRICES on guaranteed test equipment. Oscilloscopes, Tektronix 305, 454, 475, SC 504, 2225, 2246, & others. Huntron Tracker 2000, Fluke, HP and other fine used test equipment. Check us out at: **www.lonemtn.com**

DIGITAL, ANALOG, & RF test equipment. Closing R&D/manufacturing company. Must sell lots of equipment. Call 1-800-869-7827 or visit www.starcom.com for list.

TEKTRONIX RACK Mount 496P Spectrum Analyzer $4,350. 510-226-7783.

HP 1722B 275 MHz oscilloscope excellent condition with manual $575; **HP 334A distortion analyzer** $275; **HP 5326B** universal counter/DVM $120. 650-842-3268.

HP 3581C selective voltmeter, complete, $125; HP 5246L 18GHz counter $50. Both need work. Ray, 541-267-6064.

GOOD STUFF: HP 5383A $100; 7475A $50; TEK P6015A $125; P6451 $30; P6455 $30; P6460 $35; 7A24 $100; 7A26 $45; 7B92A $90; 130 LC meter $40; DAS9100 cards $40; DATA-IO 29B w/Unipak 2B programmer $115; Wavetek 3001 signal generator $400. Call Jeff for list. 508-533-5944.

TEK 2445, 2465 attenuator problems? We can repair most Tek 2445, 2465 attenuators. Call for details. Metrowest Technologies. Phone 508-478-7613, Fax 508-634-3806, WWW.metrowesttech.com

Roger's Systems Specialist

800-366-0579

"We Have Great Connections"

Computer -Communication
Network - Audio - Video

Best Prices! Best Service!

Call today for a FREE full-product catalog.

Helping Hands



Holds projects in place for easy soldering. Comes with attached magnifying lens.

#TM-HLP....$5.00 ea

Order On-line! www.rogerssystems.com

20' Audio Cable

Stereo extension cables, for speakers and headphones 3.5mm, gold plated male to female, shielded, 20 ft.

#AC-560.....$4.50 each

CD Jewel Case

Replacement for original case. durable plastic.

#TM-CD-1....3/$1.00

USB Cable

Male to male "A" to "A", shielded, 6 ft.



#CC-USB-6.....$5.00 each

Microphone

Stick-on monitor or clip on shirt, 6 ft. cord, condenser mic.

#TM-MIC-2....$1.00 each

Mouse Pad

Sponge rubber backing to prevent sliding, many colors available, call for details.

#TM-PAD.....$1.00 each

USB Ports

USB(2) to 10 pin motherboard w/ bracket

#TM-USB-9.....$7.00 each

Network Cable Tester

Test the correct pin configuration of 10Base-T/ 10Base-2 Thin Ethernet cable, RJ45/RJ11 modular cables 356A, TIA-568A/568B

Easy to verify cable continuity, open, short and miss-wire

With remote kit, it can remotely test cable up to 1000 ft away either on wall plate or patch panel

#TM-147.....$75.00 each

Computer Toolkit

Ideal for standard user maintenance repairs and general servicing of computers peripherals, includes: 14 in. nut driver, 1/8 in. slotted screwdriver, 3/16 in. slotted screwdriver, IC extractor for 8.40 pin ICs assembly tweezers, heat sink clamp, tri claw parts holder, spare parts tube: diameter 3/4 in., length 6 in. durable black vinyl padded case with individuals straps for all tools listed above.

#TM-TK1....$10.00 each

Specifications **Keyboard, Monitor, Mouse Auto Switch**





Serial and PS/2 Mouse emulation and keyboard emulation for automatic PC boot up
Supports SVGA, VGA and Multisync monitors
Built-in buzzer for switching confirmation
keyboard LED status recorded and restored while switching among computers
Auto Scan for monitoring PC periodically
Provides PC/AT keyboard ports
Built-in PS/2 mouse and serial mouse ports
Built-in PS/2 keyboard ports

Features
- Access four computers with a single console
- AT and PS/2 compatible
- Select between computers easily
- Great for testing or server control
- Daisy Chainable

#DS-104-KMM.....$299.00 ea

Local 805-295-5577 **Remember, We Have Great Connections...For You!** **FAX 805-295-8777**

$10.00 minimum order required • Add $4.50 shipping for pre-paid orders
California residents add 8.25% tax • eMail sales@rogerssystems.com

Call for quantity discounts • No out of state checks accepted • Most orders shipped same day!

24895 Avenue Rockefeller, Valencia, CA 91355

SECURITY



FACTORY SALE! QVS 104: 4 BNC/RCA inputs, 1 BNC/RCA quad output, 512x512 pixels, 256 scale. 8.5" (W) x 2" (H) x 5.5" (L). $169 @ 5 pcs., $149 @10 pcs. Also available: 8-1 video autoswitcher, $65 @ 5 pcs., $58 @10 pcs. Distributors welcome. Matco, Inc., 1-800-440-0299 Fax: 630-350-9546. E-Mail: sales@mat-co.com



FACTORY SALE! PS 102: Built-in pin hole CCD, lens size: 1.2mm. 5-1/2" (D) x 1.7" (H). $69 @ 5 pcs., $65 @ 10 pcs. Distributors welcome. Matco, Inc., 1-800-440-0299 Fax: 630-350-9546. E-Mail: sales@mat-co.com

Write in 47 on Reader Service Card.

UNDETECTABLE PHONE TAP

- SOPHISTICATED ULTRA HIGH IMPEDANCE CIRCUITRY AS USED BY CIA AND KGB
- NOT DETECTABLE BY EVEN THE MOST ADVANCED TAP SWEEPING EQUIPMENT
- MONITOR CONVERSATIONS, FAXES AND DATA WITHOUT FEAR OF DETECTION
- PLUG INTO ANY TELEPHONE LINE WITH NO CLICK, HUM, NOISE OR VOLTAGE CHANGE
- UNIVERSAL DESIGN ALLOWS MONITORING WITH HEADPHONES, TELEPHONE OR TAPE RECORDER
- VOICE ACTIVATED TAPE RECORDER CONTROL
- DISGUISED AS " TELEPHONE LINE TESTER "
- COMPACT SIZE - BATTERY POWERED

$109.95 VISA MC COD

Ar² Communications Products

Box 1242 Burlington CT 06013

(203) 485-0310

Write In 49 on Reader Service Card.

SURVEILLANCE EQUIPMENT wanted. Audio, video, RF, telephonic, countersurveillance, communications, any other professional equipment. Please describe completely in first communication. No junk or CCTV. Fax or E-Mail to Sales@swssec.com fax 410-836-1190. www.swssec.com/used.html

FACTORY SALE! CNL100, CNP101: 1/3" CCD, 430 line horiz., 12V/100mA, lens and pin hole types, lens 3.6mm/F2.0, 1.27" (W) x 1.27" (L) x 1" (H). $43 @ 5 pcs., $38 @ 10 pcs. Distributors welcome. Matco, Inc., 1-800-440-0299 Fax: 630-350-9546. E-Mail: sales@mat-co.com

FACTORY SALE! PC 103: Built-in pin hole CCD, lens size: 1.2mm. 11" (W) x 11" (H). $79 @ 5 pcs., $75 @ 10 pcs. Distributors welcome. Matco, Inc., 1-800-440-0299 Fax: 630-350-9546. E-Mail: sales@mat-co.com

ALARM CATALOG of Ademco, Moose, Napco, CCTV, phones & more. 44 pages of equipment that only the professionals can buy. Send $2 to HES Electronics, POB 183, Brick, NJ 08723. Mention this ad and get a $10 off certificate! Visit www.heselectronics.com

COUNTER-SURVEILLANCE=$250 HR! Electronic eavesdropping is unbelievably widespread! Are you sure you're safe? Learn how others (without prior experience) earn **$250 HR** in the fascinating field of COUNTER-SURVEILLANCE! For FREE catalog call: **1-800-732-5000.**

MILITARY COMPONENTS wanted. Capacitors, resistors, diodes, transistors, semiconductors, ICs. Electronic Material Industries, 818-769-1002, FAX: 818-769-1084.

SATELLITE EQUIPMENT

USED SATELLITE EQUIPMENT. You name it, we have it. LNAs, downconverters, drives, receivers. Working condition guaranteed. Call 765-385-2305.

FREE SATELLITE TV CATALOG. Tech books, installation videos, analysis software **1-800-843-2425** or **www.baylin.com**

SATELLITE RADIO BOOK AND GUIDE. New book covers all Audio Services, SCPC, Subcarriers, FM Squared, Facsimile, Press Services, Weather Services. Simple how-to-receive instructions. $16.95 plus $3 Priority Mail. UNIVERSAL ELECTRONICS, 4555 GROVES ROAD, #12, COLUMBUS, OH 43232. 614-866-4605.

SATELLITE EQUIPMENT available: Receivers $25 and up; 20-25 LNB $30; C-KU feed horns $65. Call 757-599-4408.

SATELLITE INTERNET! 400 KPS streaking to you from the sky above. The fastest Internet available nationwide. You must experience it to believe it! Visit our web sites: www.ultimate-internet.com www.invents.net E-Mail: mail@invents.net Inventive Solutions, PO Box 8, Stratford, NY 13470, 1-888-346-4925.

FREE BIG dish catalog. Low prices! Systems, upgrades, parts, and "4DTV." Skyvision, 1010 Frontier Dr., Fergus Falls, MN 56537. www.skyvision.com **Call 1-800-543-3025.**

BEST PRICING on 18" satellite TV systems for home and RV. DSS, DISH Network programming, multi-room viewing options, accessories. www.skyvision.com **Call 1-800-543-3025.**

ANA Instruments

Phone: 1-800-944-0495
Fax: (540) 775-9638
E-Mail: anainstr@crosslink.net

Specials

HP 141T CRTs, New in Box.....$195.00
HP 8657A Signal Generator.....$4,500.00
100 KHz-1040 MHz
HP 8640B Signal Generator.....$2,100.00
Opt. 001, 002, 003
Gigatronics 600 .01-8 GHz.....$2,400.00
HP 86222A .01-2.4 GHz.....$1,100.00
HP 8903B Audio Analyzer.....$2,700.00
HP 8901B Modulation Analyzer.....$3,700.00
HP 8902A Measuring Receiver.....$17,500.00
HP 436A Power Meter w/Cable.....$1,400.00
Tek 492 Opt 1,2,3 Spec. Analyzer..$6,200.00
Sanders 5440C Noise Figure Meter...$400.00
(new)

Wanted

RF & Microwave Test and Measurement Equipment & Components

Electronic Test Equipment Bought and Sold
Visa and MasterCard Accepted

ALL CABLE NEEDS

KDE

SE HABLAN ESPAÑOL

CONVERTERS

ALL BRANDS WITH REMOTE

TOLL FREE ORDER LINE:
1-800-361-4586
ALSO
HOOK-UP HELP LINE:
1-630-889-0281

COMPETITIVE PRICING

PARENTAL LOCKOUT AVAILABLE

NO ILLINOIS SALES

VISA MasterCard COD ACCEPTED

HOURS: Mon. thru Fri. 9-6, Sat. 10-2
30-DAY MONEY BACK GUARANTEE
1 YEAR WARRANTY

KDE ELECTRONICS CORP.
P.O. BOX 1494, ADDISON, IL 60101

Write In 48 on Reader Service Card.

TIMELESS PRODUCTS

The Best Prices and Service • In Business over 15 years!

Phone 218-346-6660 Fax 218-346-6664

CABLE TV CONVERTERS

WILL NOT DECODE

New! "TP 125 V"
128 Channel Converter with Volume

Special Prices for TP1550PC Call for Details

Panasonic still available!

- REFURBISHED CONVERTERS ALSO AVAILABLE •
- QUALITY REPAIR DEPARTMENT FOR ALL YOUR TUNER REPAIRS •
- REMOTES AVAILABLE FOR MOST CABLE BOXES •

DEALERS ONLY • GREAT QUANTITY PRICES • NO DECODER SALES

Write in 51 on Reader Service Card.

SUMMER SPECIALS

MOTHERBOARDS WITH CPU:

K6 233 Mhz MMX w/ CPU	$159
K6 266 MHz MMX w/ CPU	$169
K6 300 MHz MMX w/ CPU	$189
K6- 2 300 MHz MMX w/ CPU	$239
K6- 2 333 MHz MMX w/ CPU	$279
K6-2 350 Mhz MMX w/ CPU	$369
Pentium II 266 MMX w/ CPU	$319
Pentium II 300 MMX w/ CPU	$379
Pentium II 333 MMX w/ CPU	$399
Pentium II 350 MMX w/CPU	$529
Pentium II 400 MMX w/CPU	$729
Pentium II 450 MMX w/CPU	$895

32MB MEM $39.95

24X CD ROM..$42

32/36ROM..$52/59

Orders & Price
Tel:(800) 899 6430
Fax:(209) 549 8576

32X Bundle
$79
32X Speed CD
16 Bit Sound Card with Wavetable.
Amplified Speakers 80W

Buy with confidence
Risk Free
30 Days
Money Back

For ALL kinds of Drives, Sound Cards Speakers and CD Titles: $Call

CASES WITH POWER SUPPLIES

DESKTOP CASE PREMIUM	$35
MED TOWER CASE PREMIUM	$35
FULL TOWER CASE PREMIUM	$75
ATX MED TOWER CASE PREMI.	$59

WE ALSO CARRY COMPLETE SYSTEMS

Printer Memory

FLOPPY DRIVES

1.44 Mitsumi	$18
1.44 Teac	$21

MONITORS

14" .28 108 N-I, Low Radiation	$125
15" .28 1024x768 N-I, Low Rad	$135
17" .28 1280x1024 N-I, Low Rad	$239

KEYBOARDS

104 Keyboard	$10.95
Keytronic	$23
Focus 2000	$call

HARD DRIVES SPECIALS

2.1GB..$119 3.5GB..$129 4.3GB..$145
6.4GB..$165 8.4GB..$219 11GB..$CALL

VGA CARDS

SVGA 1MB ISA	$32
PCI 1MB/2MB/4MB	$25/35/59
PCI OR AGP 4MB...TV OUT. OPTI	$35
PCI 0R AGP VGA 8MB	$99
MATROX, ATI, DIAMOND	$CALL
SVGA CARDS WITH VRAM	$CALL
ANY OTHER VGA CARDS	$CALL

CONTROLLER CARDS

I/O 2S, 1P & 1G	$12

MODEM/ FAX MODEM

33.6K Voice Modem/ Fax Modem	$37
56K Voice Modem\ Fax Modem.V90	$54
US ROBOTIC 56K Modem....V90	$99
ISDN	$CALL

IBM 6X86 300 MMX
Motherboard CPU,VGA SOUND
$199

Simm Memory LOW $$$
Will beat any price
Resellers Dealers Welcome

AMD K6 300 MMX
Motherboard CPU,VGA & SOUND
$209

All Systems carry 3 years Parts & 5 years Labour Warranty. Lifetime Tech Support

CREDIT CARDS OK

*Govt. P.O. * C.O.D.

Terms: No Minimum Charge. No Hidden Charge. Prices subject to change without notice. 15% Restocking fee for Non Defective Items. Orders of $950 or more, ground shipping free, except for Cases, Monitors, Keyboards and F.Drives.

CALL FOR OUR EVERYDAY LOW PRICES

www.bisme.com

BISME COMPUTERS OUTLET 906 N Carpenter Rd. Suite A. Modesto. CA 95351

Write in 50 on Reader Service Card.

DSS TEST CARD information. Call toll free, 1-888-416-7296.

MILITARY TRANSISTORS & DIODES & INTEGRATED CIRCUITS WANTED. ELECTRONIC MATERIAL INDUSTRIES 818-769-1002, FAX 818-769-1084.

L BAND quadrifilar T/R antenna, 55 dB LNA, 20 watt HPA, works great for remote GPS. Info at afstar.com

KU UPLINK. 5.6 meter antenna, modulators, upconverters, TWT HPAs, exciter, test equipment, 26KVA generator. Closing company. Must sell lots of equipment. Call 1-800-869-7827 or visit www.starcom.com for list.

1998 DSS SOFTWARE COOKBOOK 700+ CD-ROM COLLECTION CLONING REVERSE-ENGINEERING, PPV, ADULT, EMULATORS, DIAGRAMS, SCHEMATICS, PATCHES, PLANS, MUCH MORE. (SPECIAL: 1ST 500 ORDERS GET 500+ ADDITIONAL PROGRAMS!) WHOLESALE ONLY $22 (BUY 2, GET 1 FREE!!!). DSS TESTCARD INFO SOURCE MANUAL $10. VISA/MC/AMEX/COD/CHECKS/MO. BRINKER ENGINEERING LABS, USA. CALL NOW 352-429-5496.

MILITARY SURPLUS ELECTRONICS

MILLIONS $$$ in "scrap gold" from old computers and electronics junk. Message: 603-645-4776 or www.tiac.net/users/quiksand/goldtek.htm

AUDIO – VIDEO – LASERS

START YOUR OWN TECHNICAL VENTURE! Don Lancaster's newly updated **INCREDIBLE SECRET MONEY MACHINE II** tells how. We now have autographed copies of the Guru's underground classic for $18.50. Synergetics Press, Box 809-K, Thatcher, AZ 85552. 520-428-4073. VISA/MC.

MOD CHIPS for Sony PlayStation. Now your backups will work. Only $9.95 ea. + $3 shipping. Call 1-888-467-6150, all major credit cards accepted. Computers & components at wholesale prices. www.cconusa.com

ANTIQUE VIDEO TRANSFER SERVICE: transfer of any 2" quadruplex video tapes. Quad TV spots, features, medical, corporate, military, government, and university tape libraries TRANSFERRED TO VHS. Affordable. Phone/fax 415-821-7500. If no answer call 415-821-3359 or pager 415-245-8700.

SYNC-A-LINK UNIVERSAL VIDEO SYNC GENERATOR restores all horizontal & vertical sync lines, DC level, compensates for inverted video, color phase, from standard or distorted analogue video-type formats. Comes complete with operations manual & 90-day warranty. $160. 918-479-6451 or write to Sync-A-link Communications, PO Box 4, Locust Grove, OK 74352.

BROADCAST VIDEO equipment wanted: all types, new or old. Please call, Jon with info. 1-800-539-2859.

WANTED: PRO video equipment, VCRs, switchers, cameras, etc. Advanced Media 702-874-1911.

UNIQUE VIDEO PRODUCTS: Pattern generators with char. ID, color black, switchers, reference osc., distribution amps, video conversion, etc., kits also available. FREE catalog, GEKCO Labs, PO Box 642, Issaquah, WA 98027-6730, 425-392-0638, www.gekco.com

Mr. NiCd — OCTOBER SUPER SPECIALS!

THE BEST BATTERIES IN AMERICA!

Packs & Charger for YAESU FT-50R / 40R / 10R:

FNB-40xh	Slm-NiMH	7.2v	650mAh	$41.95
FNB-47xh	(NiMH)	7.2v	1800mAh	$49.95
FNB-41xh	(5w NiMH)	9.6v	1000mAh	$49.95

For YAESU FT-51R / 41R / 11R:

FNB-38	pack (5W)	9.6v	700mAh	$39.95

For YAESU FT-530 / 416 / 816 / 76 / 26:

FNB-26	pack (NiMH)	7.2v	1500mAh	$32.95
FNB-27s	(5w NiMH)	12.0v	1000mAh	$45.95

For YAESU FT-411 / 470 / 73 / 33 / 23:

FNB-11	pack (5w)	12.0v	600mAh	$24.95
FBA-10	6-Cell AA case			$14.95

Packs for ALINCO DJ-580 / 582 / 180 radios:

EBP-20ns	pack	7.2v	1500mAh	$29.95
EBP-22nh	pk.(5w)	12.0v	1000mAh	$36.95
EDH-11	6-Cell AA case			$14.95

For ICOM IC-Z1A / T22-42A / W31- 32A / T7A:

BP-180xh	pk. (NiMH)	7.2v	1000mAh	$39.95
BP-173	pack (5w)	9.6v	700mAh	$49.95

For ICOM IC-W21A / 2GXAT / V21AT: (Black or Gray)

BP-132s	(5w NiMH)	12.0v	1500mAh	$49.95

For ICOM IC-2SAT / W2A / 3SAT / 4SAT etc:

BP-83	pack	7.2v	600mAh	$23.95

For ICOM 02AT etc & Radio Shack HTX-202 / 404:

BP-8h	pack	8.4v	1400mAh	$32.95
BP-202s	pack (HTX-202)	7.2v	1400mAh	$29.95

For KENWOOD TH-79A / 42A / 22A:

PB-32xh	pack (NiMH)	6.0v	1000mAh	$29.95
PB-34xh	pack (5w NiMH)	9.6v	1000mAh	$39.95

For KENWOOD TH-78 / 48 / 28 / 27:

PB-13	(original size!)	7.2v	700mAh	$26.95

For KENWOOD TH-77, 75, 55, 46, 45, 26, 25:

PB-6x	(NiMH, w/chg plug!)	7.2v	1200mAh	$34.95

Mail, phone, & Fax orders welcome! Pay with Mastercard / VISA / DISCOVER / American Express

Call 608-831-3443 / Fax 608-831-1082

Mr. NiCd - *E. H. Yost & Company*
2211-D Parview Road, Middleton, WI 53562

CALL OR WRITE FOR OUR FREE CATALOG!

Cellular / Laptop / Videocam / Commercial & Aviation packs too!

E-mail: ehyost@midplains.net

Write in 50 on Reader Service Card.

Serving Southeastern USA

NEW COMPANY

FOR ALL YOUR CABLE REQUIREMENTS

1-800-322-5286

SPECIALIZING IN QUANTITY PRICING

Guaranteed Lowest Prices

Will match or beat Competitors

RAW UNMODIFIED SCIENTIFIC ATLANTA • JERROLD • PIONEER • ZENITH • TOCOM & MORE

CALL TODAY FOR OUR INCREDIBLE OFFERS

Se Hablan Espanol

http://www.newworldtec.com

Write In 37 on Reader Service Card.

PROFESSIONAL RECORDERS 1/4" 2 track 15IPS 10" with consoles: Ampex 440B $450; Scully 280 $675; Studer A80 with monitor speaker, shuttle edit & electric counter $1,500 to $2,200; 7.5IPS/7" decks: Akai X150D $85; Ampex 950, tube recorder $150; Lafayette tube deck, as-is $85; Roberts 450 $55; Roberts 721, tube as-is $115. Call Tom 609-222-0636. FAX 609-222-0638



TFT COLOR LCD monitor: 12VDC power, NTSC video input. Display for car, boat, navigation, instrument, security. 4" panel $199. 5.6" monitor $499. TV tuner and 6.4" display, remote control, audio/video switching $699. Also whole line of CCD CAMERA, SECURITY products. Rearview black/white camera and 4" display set for RV, truck, bus safety $339. 1-800-266-5706 PCT. Website: mobil-e-tech.com

SONY PLAYSTATION mod chips allow you to play CDR backups & imports. $10 ea. + $3 shipping. 619-590-9320.

FOR SALE: 30 milliwatt Helium-Neon laser and power supply $900 obo. 400 milliwatt Argon laser with partial power supply $1,200 obo. 208-895-6723.

SONY/TEK-RTD 710 real time digitizer, $2,000. Great for video engineering. Call Roger @ GS&E, 716-338-7001. VISA/MC.

CABLE TV

DEALERS: NEW VM8000 cable converter. Sharp tuner, 800MHz. 125 channels. Call for lot pricing. NTS 1-888-355-6687.



NOTCH FILTERS 110, 108.5, 106.5, 97.5 75dB deep notch. $19.95 ea., 1-5 qty. $15.95 ea., 6-10 qty. $11.95 ea., 11-20 qty. $9.95 ea., 21 or more qty. Call 24 hr. order and information hot line 516-389-3536.

UNMODIFIED JERROLD-212 converter $50. 97.5, 106.5, 108.5, AB filters $12 ea. All PIC 16C series, 68HC series wholesale only! Good price 1-888-561-4796 8am-5pm CST. E-Mail: KOGEN-ELECTRONICS@JUNO.COM

ADEAL4U WHOLESALES BIG SAVINGS $$$ BEST QUALITY - NO CHEAP CLONES 888-387-1248 www.adeal4u.com

NEW! CABLE converter electronic service equipment and supplies for most cable converter boxes. Highest service, lowest prices. Call Ken Erny Electronics. 24 hr. order and information hot line 516-389-3536.

I WANT to buy any quantity in any condition: CFT 2254, CFT 2024, CFT 2014, Jer BB7, DPV 7, Pioneer 5135, 6100, 6300, and SA 8590, 8600. Call 702-79C-TECH Mon-Fri 9-6.

CABLE CONVERTERS: unmodified, Jerrold, Scientific Atlanta, Zenith, Pioneer, Tocom, Panasonic, quality units at great dealer prices. Call now for specials 702-270-4351.

REFILL INKS FOR INKJET PRINTERS

Refill your old cartridge and save. All refill kits come with instructions and needed materials for refilling inkjet cartridges. Success guaranteed. Available for the following:

CANON BC-01, BC-02 CANON BJ10e, APPLE STYLEWRITER, BJ-200 Single Black Refill $8.00; Triple Refill $19.00. **CANON BJC-600** (BC-201) Single Black or Single Colors (3 refills) $8.00. **CANON BJ-130/300/330 & IBM Exec Jet** (Cart #BJI-481 & BJI-642) Black - 3-bottle kit $22.00. **CANON BJC-210/240** (BC-05 Cart) 3-color kit (3 refills each color for BC-05) $24.00. **CANON BJC-4000** and Apple Stylewriter 2400 Black 3-bottle kit (3 refills BC-20, 9 refills BCI-21 black, 30 refills BCI-11 black, 10 refills BCI-10) $19.00. **CANON BJC-4000/BJC70** and **Apple Stylewriter 2400** Tri-color kit - 6 refills each color for BCI-21 or 15 refills each color for BCI-11 $24.00. **CANON BJC-800/820/880** 3-bottle kit (for BJI-643B) $19.00. **CANON BJC-800/820/880** 3-bottle tri-color kit (Cart #BJI-643CMY) $24.00. **EPSON STYLUS COLOR PRINTER** - (Cart S020034) Single Triple black $19.00; Tri-color kit (Cart S020036) 2 refills each color $24.00. **EPSON STYLUS COLOR II** - (S020047) Triple Black $19.00 (S020049). Tri-color (2 refills each color) $24.00. **EPSON STYLUS COLOR 400, 500, & 600** (S020093) Triple black (7 refills total) $19.00; **EPSON STYLUS COLOR 200, 500** (S020097) Tri-color 3 refills each color $24.00. **EPSON STYLUS COLOR 400, 600, 800, 1520** Tri-color (S020089) 3 refills each color $24.00. **EPSON STYLUS 800/1000** (S020025) 3-refill kit, black, $19.00. **HP DESKJET 500/550/560** (51608A, 51633A, 51626A) Black single refills $8.00. **HP DESKJET 500/550/560.** Black 3-bottle kit $19.00. **HP DESKJET 500C/550C/560C .** Tri-color kit (5 refills each color) $24.00. **HP DESKJET 1200C, DESIGNJET 650** (Cart #HP 51640B) Black Three pack (3 refills) $19.00. **HP DESKJET 1200C/1600C, DESIGNJET 650** (Cart #HP 51640 C,M,Y). Tri-color kit (one refill each color) $24.00. **HP DESKJET 600/660** (HP 51629A) Black three pack $19.00. **HP DESKJET 600C/660C.** (HP 51649A) Tri-color (5 refills each color) $24.00. **HP DESKJET 855C/1600C** (HP 51645A) Black three pack $19.00. **HP DESKJET 855C** (HP 51641A) Tri-color kit (2 refills each color) $24.00. **HP DESKJET** 720, 722, 890, **OFFICE JET** 1170 & 1175 (C1823A) Tri-color kit (2 refills each color) $24.00. **HP PAINTJET** and **PAINTJET XL** (51606A) Black 3-bottle kit $19.00. **HP PAINTJET** and **PAINTJET XL** (51606C) Tri-color kit $24.00. **HP PAINTJET XL300** (C1645A & C1656A) Black 3-refill kit $19.00. **HP PAINTJET XL300** Tri-color kit (1 refill each color) HP 51639C,M,Y $24.00. **HP THINKJET, QUIETJET, KODAK DICONIX 150** (51604A or 92261A) black 5 refills $9.00. **IBM/Lexmark/Execjet/4076** (1380620) black 3-refill kit $19.00. **IBM/Lexmark ExecJet IIC, WinWriter 150 C** (Cart #1380619) 4 refills each color $24.00. **SNAP AND FILL SYSTEM** - Permits refilling HP 51626A (black for HP 500-series) and HP 51629A (black for HP 600-series) cartridges without making a hole in the cartridge. Consists of special cartridge holder, syringe, plastic tubing, and directions. **STARTER KIT** - with ink for 3 refills $28.00. **EXTRA INK FOR SNAP & FILL SYSTEM** (black only) 4-oz. bottle $18.00; 8-oz. bottle $34.00. Specify whether for HP 51626A or HP 51629A.

HARD-TO-GET PRINTER RIBBONS

Gorilla Banana, Commodore 1525 **$8.00**; Adam Coleco **$12.00**; TI-850/855 **$6.00**; Centronics 700 Zip Pack **$5.00**; C. Itoh Prowriter Jr., Riteman C+/F+ **$6.00**; Riteman Inforunner **$8.00**; Commodore MPS-801 **$5.00**; MPS-803 **$7.00**; Decwriter LA30/36 **$4.00**; Apple Scribe **$4.00**; Mannisman Tally Spirit 80, Commodore 1526 **$5.00**; Epson JX-80 4-Color **$14.00**. Printronix P-1013 **$11.00**; Star SJ144 color 3-pack **$29.00**.

ALSO HEAT & TRANSFER RIBBONS AND PAPER FOR PRINTING T-SHIRTS.

Over 300 different ribbons in stock. All ribbons new, not re-inked. Fully guaranteed. Order directly or send SASE for complete list.

Add $4.00 per order shipping. California residents add 7.75% sales tax.
On ribbon orders over $50.00 deduct 10% discount.

H.T. ORR Computer Supplies
249 Juanita Way, Placentia, CA 92870-2216
714-528-9822 · 800-377-2023 · FAX 714-993-6216
http://www.extremeplay.com/occomp/orr.htm

Write In 53 on Reader Service Card.

Subscribe to Nuts & Volts and be automatically entered in our monthly prize drawing!



CABLE CONVERTER ACCESSORIES

We only dedicate ourselves to one thing... HAPPY CUSTOMERS!!!

CALL US NOW! FOR OUR LATEST PRODUCT RELEASES

WE CARRY A COMPLETE LINE OF CABLE ACCESSORIES AND ELECTRONIC COMPONENTS

NOTICE: WE DO NOT SELL DESCRAMBLERS, CONVERTERS, SATELLITE EQUIPMENT OR ANY KIND OF DECODING DEVICES

BLOW OUT

Motorola 68HC705 Micro

$7.50 50 pc. min. order

MON-FRI 9-5PM EASTERN

SALES: (800)637-9936

Sorry, No Canada Sales

Write In 52 on Reader Service Card.

Metric
Equipment Sales, Inc.

800-432-3424
Fax: 510-264-0886
www.metricsales.com

RENT • BUY • SELL

Yes, we will buy your surplus equipment!

Scopes, Meters, Analyzers, Power Supplies, Signal Generators, Counters, Recorders and more

Hewlett-Packard, Tektronix, Fluke, Dranetz, TTC, Anritsu, Wavetek, Keithley, and more

Test & Measurement Instruments

Over 7000 Models • 6-Month Warranty
Save 30-90% • 5-Day Free Trial

Write in 56 on Reader Service Card.

PROGRAMMABLE POWER SUPPLY &DATA LOGGER



RKA SYSTEMS PRESENTS:

PROGRAMMABLE POWER SUPPLY

DATA LOGGER

WINDOWS ENVIRONMENT

EXCEL COMPATIBLE

- **Programmable Power Supply (+/- 10 V, +/- 100Ma)**
- **Virtual Digital Storage Scope(100 Samples Stored)**
- **Virtual Digital VOM (Volts,Current,Power,Resistance)**

Applications:

- *Lab Testing*
- *Voltage/Current Monitor*

NOW ONLY $159.95

VISIT OUR WEB SITE AT: http://www.rkasys.com

RKA

RKA Systems
484B Washington St. Unit #421
Monterey CA, 93940
Tel: 800 500 0449
EMail info@rkasys.com

Write in 55 on Reader Service Card.

ZENITH 73 ch. unmodified ST1622 complete as-is $35 each; refurbished $75. Also Pioneer 6110 field pull working $90. Also Zenith ST-1000 complete as-is $8. Also Zenith 16xx 99 ch. refurbished $95 . Limited quantities Call M-F 9-4 Gregg 702-270-4341 or pager 1-800-478-0334.

FREE CABLE DESCRAMBLER PLANS! For details write: Sierra Publishing, 909 E. Yorba Linda Blvd., Suite H-181, Dept. NVH, Placentia, CA 92870.

ATTN: CABLE converter repairer. We stock-up most converter parts like: Tocom, Pioneer. Call for Zenith transistor saw filters, converter cases, lens and all other parts. Minimum order $50. Call: 405-634-1535.

"TOP OF the line" Panasonic TZPC with volume refurbished only $69; Regal: CR-83V volume, STD/HRC parental lock, last channel recall, good for all Boss, $45; Panasonic TZPC-145, $45. Minimum 10-lot. 1 full year warranty. Call: 405-634-1535.

CBTV REPAIR. We specialize in all converters, including Zenith. Give us a call: 405-634-1535.

ONE STOP shop. We carry a full line of CBTV equipment for all your cable needs. Also a wide variety of converter parts and accessories. Call for free catalog: 405-631-5153, FAX: 405-631-4788.

UNMODIFIED CABLE CONVERTERS. Zenith ST1600, ST1086, ST300, Panasonic 175, 145 vol. & non-vol. Regal RR-92 & RC 83, DP5, DP7, DRZ, 5503 VIP, SA 8580. Guaranteed low prices. Please call for more converters 405-631-1856.

ATTENTION: YOU'VE tried the rest, now go with the best. **UNICORN ELECTRONICS** where our valued customers **ALWAYS** come first. **CABLE CONVERTERS AND ACCESSORIES.** We will beat all competitors prices **GUARANTEED.** All **UNITS** in **STOCK FOR IMMEDIATE SHIPMENT. FREE** batteries and coax cable. **FREE** bullet protection with every unit purchased. **FREE** shipping with a $500 purchase or more. **NO** COD charges. **ALL** products come with a 1 year warranty and a 30 day money back guarantee. Please give us a call TOLL FREE 1-888-738-8181 9am to 6:30pm EST. **VISA, M/CARD, DISCOVER, COD. UNICORN** Electronics does not advocate unauthorized use or theft of cable services.

CABLE CONVERTERS, remotes, etc., free flyer. Jake 1-800-879-9657.

CALL ALEN for all your cable needs or computer software. Programming service available. For info call 909-941-4858 or visit us at our web on site http://members.aol.com/**ALENCABLE**

UNBELIEVABLE PRICES. We carry a full line of cable tools and equipment for all your cable needs. Also a wide variety of electronic parts & accessories, tools, diagrams, converters, step-by-step instructions, no raw parts. **Full technical support.** 12pm-7:30pm EST. **1-800-562-8442.**

CABLE STOP, one stop for all your cable needs. What do you get for your money? Quality parts at a low price, 800 tech support, a company that will be there when you need them. **1-800-562-8442** 12pm-7:30pm EST



EXPLOSIVE CABLE TV GRAB! BRINKER ZAPPER/SNOOPER STOPPER combo module all in one! Buy wholesale factory-direct, no middleman. Let others get fined + zapped instead. 100% COMPATIBLE. Your order shipped NATIONWIDE immediately! LIFETIME GUARANTEE! VISA/MC/AMEX/COD/MO/CHECKS. ONLY $10 (SPECIAL: 3/$20 plus FREE DESCRAMBLER PLANS!). SUPER ZAPPER MODULES ONLY $16! (3/$33)! Use SUPER ZAPPERS if you have COX, TCI, WARNER in: CA, TX, FL, NY, PA, MI. DESCRAMBLER PLANS (4=$5, 20=$15) 130+ DESCRAMBLER SOURCES ($5). FREE SHIPPING. OPEN 24 HOURS! 352-429-5496. BRINKER ENGINEERING LABS, USA.

CABLE PARTS! Computer parts. Call for great prices or visit us on the Web: HTTP://WWW.CB-Electronics.com or call 1-800-436-8630.

WANTED PIONEER 6310 CONVERTERS, RAW, TOP CASH, LOTS 5 OR MORE. 702-642-0325.

PIONEER 6310s, READY TO GO, SATISFACTION GUARANTEED, SORRY NO NEVADA SALES, LESS BUSTERS ELECTRONICS, 702-642-0325, WEB: WWW.lessbuster.com

MOD CHIPS for Sony PlayStation. Now your backups will work. Only $9.95 ea. + $3 shipping. Call 1-888-467-6150, all major credit cards accepted. Computers & components at wholesale prices. www.cconusa.com

PLANS: DESCRAMBLE CABLE FOR UNDER $12. PLUS TWO FREE BONUSES. TOLL FREE 1-888-588-3715.

JERROLD UNMODIFIED CONVERTERS FOR SALE. CALL FOR BEST PRICES. **NO DESCRAMBLER SALES.** CALL BRLD ELECTRONICS 1-800-322-6316.

ALL.TV.INC.

"Our Name Says It All"

Call Us for ALL Your Cable Needs
Large Inventory of Major Brands
We will beat *ALL* competitor's prices

Also serving Puerto Rico

Se Habla Espanol

In Stock 85 Channel HRC ST – VIEWSTAR
In Stock 125 Channel HRC ST Volume
In Stock Panasonic TZ-PC175DG2

Same Day Shipping

E-Mail – alltv@icanect.net

TOLL FREE 1-800-510-1924

Write in 55 on Reader Service Card.

CABLE PARTS & EVERYTHING and more. Parts & accessories. Best prices & quantity discount. WE DON'T SELL BOXES. 1-800-MODULE-0.

UNMODIFIED ST 1000 and ST 4000, $20 ea. Bill 419-385-3100.

AS-IS converters Oak Sigma, $20; Zenith, $7; genuine unmodified DPV5, $10. Call John 419-243-7856.

CABLE TV. Panasonic TZPC 175DG2, brand new, $80 w/volume, 1 year warranty, minimum 10 pcs. any qty., plus all major brands available. Lowest price new/field pulls. E-Mail: OCALA@BELLSOUTH.NET phone: 1-800-929-1549 fax: 305-220-9396

CABLE MODIFICATION plans with detailed color photo, can be done with little or no parts. 330-963-4952.

PICS, GALS READ if you've lost your masters. Programming service available. Call for info. Network Sales, 616-683-0500.

125 CHANNEL Digital Pro converter with audio & video $82 each. Panasonic TZ-PC175DG2-7 converter with volume control $135 each. The best converters you can buy! Pleas call 1-888-561-4796.

CONVERTERS WHOLESALE. 550 MHz converters for you CATV needs, Panasonic, Regal, Timeless, RA550E. Gentry Communications. 507-332-2788.

PANASONIC 145 $45/10 lot. Regal CR-83 $40/10 lot. All fully warrantied/RAN and repacked! Gentry Communications. 507-332-2788.

BATTERIES WHOLESALE. AAA and AA available at 12¢ ea. Call for all quantity needs. Gentry Communications. 507-332-2788.

CATV EQUIPMENT visit us on our web at: www.mygale.com/05/gentry/ or call us at Gentry Communications. 507-332-2788.



ISOLATION-BUFFER AMPLIFIER. Specially manufactured unit **(1)** Blocks connected devices oscillator signals from being received or reflected on the incoming coax cable line. **(2)** Blocks-Protects connected devices against APPLIED LFAC-DC-surge voltages that may occur on or applied to it's incoming coax cable line. Frequency response 40-900MHz, Gain 8dB, 117V UL approved. Includes 6ft coax cable $19.95 PP set, 2 sets $35.95 PP. **(3) 1-4 Set TV-CABLE SPLITTER-DSS DIPLEXER**, Low loss, top quality, with 3ft coax cable, 3 ea. terminating resistors. $5.95 PP a set with isolation amplifier order. **PAYMENT: M/O ONLY. LESS BUSTERS ELECTRONICS**, 2039 Civic Center Dr. #176, N. Las Vegas, NV 89030. **WEB: lessbusters.com**

CABLE HACKER'S BIBLE Volume 3. 25+ Master files. Includes: binary files, installation instructions, disclaimers, and more! $79.95 Postpaid. 520-726-2833. **TELECODE,** Box 6426-NV, Yuma AZ 85366-6426.

GENUINE UNMODIFIED JERROLD DPBB7312 FOR SALE 10 LOT MIN. CALL 708-715-6118.

WANTED: GENUINE RAW UNMODIFIED CABLE TV CONVERTERS, TOP CASH PAID. CALL 708-715-6118.

PIONEER CONVERTERS. 619-667-9252.

Sell Nuts & Volts
in your store and earn $$$!
Contact us for details. 909-371-8497
E-Mail distributors@nutsvolts.com

TELEPHONE/FAX

BEEPER, TWO-WAY radio repairs, modifications, duplications, all models, test equipment. Call TJ 718-341-1849, Fax 718-978-4616.

TELEPHONE CATALOG of Panasonic, SWBell, VTEC and more, including alarm systems, parts, and all phone accessories. Send $2 to HES Electronics, POB 183, Brick, NJ 08723. Mention this ad and get a $10 certificate! Visit www.heselectronics.com

NEW: MEMORECS system, the most important feature your answering machine is missing. Oricom Technologies, 303-444-9776. www.sni.net/~oricom

BLUE BOOK PHONE REPAIR. 1000 models answering machines, cordless, $25. KEN's, 2825 Lake, Kalamazoo, MI 49001 616-345-4609. www.kenselectronics.com

PHONE SYSTEMS WANTED!!! We buy AT&T MERLIN, SYSTEM 25/75/85 and other AT&T phone systems. Please call for a quote or fax us your equipment list. **KEYWAYS, INC.**, 937-847-2300 or FAX 937-847-2350.

THE GSM BIBLE. Book on CD-ROM. Subjects include: Reverse engineering, cloning, smartcard simulator (source-code), emulators, differential fault analysis (DFA), DES hacking, A5 code and A3A8 algorithm (source code in C), reverse hacking, how PIC chips are hacked, GSM card reader schematic, security, standards, FAQs. Over 1,500 pages when printed out! Dozens of software programs, all executable program files in IBM format. CD-ROM is in HTML format and is viewed with Netscape or Internet Explorer Web Browser, Version 2.0 or higher. $39.95 postpaid USA. Telecode, PO Box 6426, Yuma, AZ 85366-6426. Order Tel: 520-726-2833. http://www.hackerscatalog.com/whatsnu.htm

RAINBOW KITS

CALL FOR OUR COMPLETE CATALOG

ACTIVE ANTENNA

Freq. 1MHz to 100MHz

- Replace a 60' long wire antenna with this small unit.
- Use it on short-wave, HF and VHF.
- Great for scanners, ham receivers, or general coverage receivers.
- Gain control

ACA-1 PCB size: 4.2" x 4.6" KIT $44.95
ACA-C Optional Cabinet available Size: 1.5"H x 5"W x 5.3"D $14.95

2 STATION INTERCOM

Great for kids room to the kitchen, put one out to your garage.

- Communicate up to 500' between units
- 2 intercom stations supplied in INT-2 kit
- Power requirements: 2 - 9v batteries
- 30' of hookup wire supplied

INT-2 PCB size 1" x 1.75" KIT $29.95
INT-2C Optional (2 cabinets) Size: 1.6"H x 2.5"W x 3"D $24.95

WATER ALARM

When the liquid level reaches the sensor it automatically turns the pump on or off. The Water Alarm supplies you with 100 mA of output that activates a relay (that you supply). This relay can turn on a sump pump, or in applications where you are filling an area with liquid it turns off the pump.

WA-2 Size 1.4" x 2" KIT $17.95

INTERNET PHONE

PHONE HOOK UP to INTERNET

- Use your telephone to talk on the internet instead of that little microphone and speakers that are attached to your computer.
- Gives you better clarity, even gives you privacy.
- With a cordless phone you have the freedom to walk around the room while on the internet.
- Uses any standard type phone.

INP-1 PCB size: 4.5" x 4.1" KIT $44.95
INP-C Optional Cabinet available Size: 1.5"H x 5"W x 5.3"D $12.95

SKILL MASTER

Fun for the whole family! 6 skill levels

- Tests your eye hand coordination.
- The more LEDs you light up, the better your skill.
- Push the button when its green and you advance up the skill level, push it when its red and you loose a step.
- Comes with 6 different game overlays
- Operating voltage 9v DC. **Case Included**

SLG-1 Size: 2.3" x 4.8" KIT $29.95

10 MINUTE COUNT DOWN GAME TIMER

- 10 Minute Timer
- 3 - seven segment LED displays.
- Counts down by seconds.
- In the last minute it sounds a short beep every 10 seconds.
- The last 10 seconds sound a beep every second.
- One long beep will sound when time is up.
- This kit is a good example of how a microprocessor works.

GT-10 PBC: 2.3" x 4.8" KIT $49.95
GT-C Cabinet size: 1.6"H x 2.5"W x 5"D $12.95

Amateur Radio "PERFECT CODE" Keyer

Measure the DOTS and DASHES perfectly every time.



Add this CW Keyer to your existing rig or use it as a code practice oscilator.

- INEXPENSIVE CW Keyer great for the beginner or the old timer alike.
- Speed and Volume control.
- Built in paddles.

APC-1 PCB size 2.25" x 2.75" KIT $39.95
APC-C Optional Cabinet available Size:1.5"H x 5"W x 5.3"D $14.95

NIGHT CRICKET

Sneak this little **NIGHT CRICKET** into someone's bedroom, when night falls the fun begins. The lights go out and the cricket starts chirping, turn the lights on to find the varmint and the chirping stops. Small enough to hide most anywhere.

NC-1 PCB size: 2.75" x 1.2" KIT $14.95

TV NOTCH FILTERS

FOR CHANNELS 2 thru 22 ONLY

Our TV filters eliminate unwanted TV channels or interference that alters both sound and video with a beep beep beep. Works on cable channels (2 thru 22) only.

NOTE: All TV Filter Kits are sold for educational purposes only. You must obtain permission from your local cable company before using these filters on your cable system.

DF-222 KIT $14.95

This Manual contains schematics, parts lists & P.C. board layouts for many of the Rainbow Kits. Use your own parts to construct our kits.

KIT BOOK $14.95

ELECTRONIC RAINBOW

We will accept telephone orders for Visa or Mastercard

SHIPPING COSTS:	U.S.A.	CANADA P.R. & MEXICO 8D
$1.00 - $50.00	ADD $5.50	$7.00
$50.01 - $100.00	ADD $6.50	$7.00
$100.01 - $150.00	ADD $7.50	$9.00
$150.01 - UP	ADD $8.50	$10.00

Electronic Rainbow Ind., Inc.
6227 Coffman Rd. Indianapolis, IN 46268
CALL 317-291-7262 FAX 317-291-7269
INTERNET: www.rainbowkits.com

MasterCard VISA

PREPAID PHONE cards. Up to 66% discount on 80 minute cards. Any size order filled. Gentry Communications. 507-332-2788.



MOTOROLA FLIP/POCKET PHONE DATA PORT INTERFACE CABLE SET. Motorola OEM molded 8 pin data plug with 8 lines (4ft.) connected to molded 8 pin mini DIN plug, also includes 1 each 8 pin mini DIN jack, DB-25 plastic housing, DB-25 Dsub solder plug and data sheet. 1 set $19.95, 2 sets $35 PP. Payment PMO only. No checks. **LESS BUSTERS ELECTRONICS, 2039 CIVIC CENTER DRIVE #176, N. LAS VEGAS, NV 89030.** Telephone 702-642-0325. **WWW.lessbusters.com**

Don't miss a single issue!
Have Nuts & Volts delivered right to your door every month for only $19 for 12 issues.
Call 1-800-783-4624 to order.

COMPONENTS

RESOLVER, BRUSHLESS 2 piece direct mount to motor. Harowe 2 1/16" OD 1/2" ID $50. 818-761-8594.

DON LANCASTER'S ACTIVE FILTER COOKBOOK is back in print. Autographed copies of the seventeenth(!) classic printing $28.50. **SYNERGETICS PRESS,** Box 809-N, Thatcher, AZ 85552. 520-428-4073. Visa/MC.

IC PULLOUTS, other components, sold cheap. Buying unused connectors, especially coaxial and "round plugs." www.ncci.net/millermetal



AMAZING! 15¢ ALL ICs. CD4001B, CD4011B, CD4013B, CD4017B, CD4028B, CD4050B, CD4066B, CD4069B, LM324, LM339, LM358, LM393, LM555, LM741, MC1488, MC1489, 74LS174, 74LS244, 74LS245, 74LS374. Brand new parts. 100pcs./package. Add $6 freight. Gateway Products Corporation, PO Box 936397, Margate, FL 33093, 954-974-6864. Fax 954-974-6818. VISA/MC, no CODs.

OLD ICs & TRANSISTORS WANTED: HIGHEST PRICES PAID please FAX your list with part number, quantity & condition of **any semiconductors** to Rick @ ESI, 5363 Broadway Ave., Cleveland, OH 44127. 216-441-8500 FAX 216-441-8503. Since 1946! www.electronicsurplus.com



AMAZING! 10¢ ALL REGUALTORS. All TO92 package: 78L05, 79L05, 78L12, TO220 package for 20¢: LM317T, 7808, 7812, 7815, 7818, 7908, 7912, 7915. Brand new parts. 100pcs./package. Add $6 freight. Gateway Products Corporation, PO Box 936397, Margate, FL 33093, 954-974-6864. Fax 954-974-6818. VISA/MC, no CODs.

WANT TO Buy: ICs, military & aircraft relays, diodes, transistors, Cannon, TRW, Amp, Burndy, Deutsch, Bendix connectors, electronic test equipment & most components. Hoffy Electronic Ent., 818-718-1165, FAX 818-341-5506.

MILLIONS $$$ in "scrap gold" from old computers and electronics junk. Message: 603-645-4776 or www.tiac.net/users/quiksand/goldtek.htm

COMPONENTS: MOTOROLA MC6802CP $.50, 74LS166AN 5¢, 74LS00B1 5¢, 74LS240 5¢, Z80 15¢, BOURNES 500 ohm 25¢, 74LS164P 5¢, 74LS165AN 5¢. All parts are unused in tubes, send check or money order to LLoyd's, 27315 Jefferson Ave. Ste. J-17, Temecula, CA 92590. $3 for postage and handling.

AMAZING! 35¢ ALL TOGGLE SWITCHES. Brand new. Rated 6A/125V. Hardware included. 1/4" panel hole. SPDT or DPDT on-on, or on-off-on. Minimum 100pcs./package. Add $6 freight. Gateway Products Corporation, PO Box 936397, Margate, FL 33093, 954-974-6864, Fax: 954-974-6818, VISA/MC, no COD.

MILITARY TRANSISTORS & DIODES & INTEGRATED CIRCUITS WANTED. ELECTRONIC MATERIAL INDUSTRIES 818-769-1002, FAX 818-769-1084.

PHOTOMULTIPLIER TUBES, radiosondes, electro-luminescent panels, electronic parts, test equipment. **www.lonemtn.com**

SEC *Sun Equipment Corporation*

LODESTAR *Lodestar Electronics Corp.* *Since 1979*

P. O. Box 97903, Raleigh, NC 27624 E-mail: sunequipco@ipass.net
To request FREE CATALOG, please call, fax, write, or e-mail us.

One Year Warranty. 15 Day Money Back Guarantee. OEM WELCOME.
School purchase order accepted. Bids accepted. **VISA, Mastercard**
SALES REP./DISTRIBUTORS/OEM WANTED. **Discover, AmrExpr**

Quality Test Equipment for Cost-Minded People **1-800-870-1955/(919)870-1955 Fax:(919)870-5720**

DC POWER SUPPLY (CC/CV)

All models: protection of short ckt, overload, reverse polarity, overvoltage; Constant Current & Voltage (CC/CV) fully adjustable. Regulation: ≤.01%+3mV (line)/≤.01%+3mV (load); ripple≤1mV.

SINGLE OUTPUT
Analog Displays
PS-303 $159.00, 30V/3A.
PS-305 $219.95, 30V/5A.
PS-1610S $289.00, 16V/10A.
PS-2243 $139.00, 12V/24V select, 3A.
PS-2245 $159.00, 12V/24V select, 5A.
8107 $399.95, 30V/10A.
8110 $289.95, 60V/3A.
8112 $399.95, 60V/5A.
Digital Voltmeter & Analog Ammeter
8200(8201) $179.95($239.95), 30V/3A(5A)
Digital Displays **8210/8300 $199.95,** 30V/3A.
8211/8301 $259.95, 30V/5A.

DUAL OUTPUTS
Independent/Tracking
Analog Displays
8108 $549.95, 60V/3A.
8109 $699.95, 60V/5A.
PS-303D $314.95, 30V/3A. **PS-305D $399.95,** 30V/5A.
TRIPLE OUTPUTS, a fixed 5V/3A output, Indep./Tracking
Digital Displays **8202(8203) $499.95($549.95),** 30V/3A(5A)x2.
Analog Displays **8102(8103) $399.95($489.95),** 30V/3A(5A) x2, with *Parallel* (30V/6A) and *Series* (60V/3A) Mode operation.

NTSC/PAL TV COLOR BAR GEN.

CPG-1366A $159.95, VHF NTSC;
Freq.: 45.75, 175.25, 187.25 MHz;
RF Output: 10mV; *Impedance:* 75Ω;
Video Output: BNC, $1V_{p-p}$;
Power: 9VDC; 9V AC adapter **($6).**
CPG-1367A $159.95, VHF PAL.

SWR/RF/mW POWER METER

310 $89.95, 1.8-150MHz; *RF Power:* 0-4W/20W/200W 3 ranges; *SWR Measurement.:*1.0-∞, 4W min. Accuracy: 5~10%; *Insert Loss:* .3dB *In/Output Imp.:* 50Ω; SO-239 plug.
320 $89.95, 130-520MHz. Spec. 310.
330 $119.95, 1.8-520MHz. Spec. see 310.

SWR-3P $26.95 1.7-150MHz;
RF Power: 0.5-10W, 0.5W-100W.
SWR-2P $22.95, 1.7-30MHz; *RF Power:* 0.5-10W.
mW RF Power Meter 340 $219.00, 1.8-500MHz; *RF Power:* 20mW/200mW/2W 3 ranges; *Imped.:* 50Ω; *Accuracy:* ±10% full scale; SWR <1.15; N-type connectr; BNC type output

FM STEREO MODULATOR

AG-2011A $549.00
RF SECTION:
Carrier: 98MHz ±2MHz;
Output: 10mV, 1mV & 0.1mV
COMPOSITE SIGNALS:
Pilot: 19KHz ±2Hz, 0.8Vrms
INT. MODULATION: 400KHz, 1KHz ±1%, 1Vrms, distortion < .5%; *L-R Separation:* >50dB.
EXT. MODULATION: *Freq.:* 50Hz-15KHz
L-R Separation: >45dB 100Hz-3KHz; >35dB 50Hz-15KHz.

WOW-FLUTTER METER

WF-3103A $699.95 *Freq. Range:* 3KHz±10% JIS/CCIR; 3.15KHz±10% DIN.
Measure: .03/.1/.3/1/3% full scale.
Accuracy: ±5% of full scall.
WF-3105A $799.95 digital display
*Function:*LIN/WOW/Flutter/WTD.
Freq Counter: 10Hz-9.99MHz.
Indication: CCIR/DIN/JIS.

TOOLKITS - ELECTRONIC/PC

9Z45 $29.99 U.S. Patented, 45-pcs. Contents: IC insert/extractor with securers & bows, 3-prong part retriever, #0 phillips screwdriver, 1/8" flat srewdriver, self-hold tweezers, metal tweezers, part tube, soldering iron, solder, crimping tool, long-nose plier, cuttng plier, zipper vinyl case. Bits include: *Phillips:* #0/#1/#2/#3; *Flat:* 1/8"/3/16"/1/4"/9/32"; PZ1/PZ2; T8/T9/T10/T15/T20/T25/T27/T30/T40/T45; *Hex:* 5/64"/3/32"/1/8"/5/32"/3/16"; *Sockets:* 3/16" (5mm)/7/32" (5.5mm)/1/4" (6mm)/9/32" (7mm)/5/16" (8mm).
8G23 $34.99 23-pcs *Contents:* IC inserter/extractor with securer & bows, 3-prong part retriever, 3/16"/1/4" nutdriver, 3/16"/ 1/8" sloted screwdriver, #0/#1 phillips, reversible T10/T15 bits, reversible #2 phillips/¼" slotted bits, tweezer, long-nose plier, cutter, 6" adj. wrench, soldering iron, solder, crimping tool, zipper case.
Various packages available, call/write/e-mail/fax for detail.

RF SIGNAL GENERATOR

SG-4160B $124.95, 100K-150MHz up to 450MHz on 3rd harmonics in 6 ranges; AM modulation; *Accy:* ±5% *RF Output:* 100mVrms to 35 MHz; *Modulation:* Int. 1KHz (AM); Ext. 50Hz-20KHz, at least $1V_{rms}$ input. *Audio Output:* 1KHz, $2V_{rms}$ min.
SG-4162AD (w/ Freq. Counter) $229.95, Spec. see SG-4160B.
COUNTER SECTION: 10Hz-150MHz; *Max. Input:* ≤3Veff; *Gate Time:* .1, 1sec. *Input Sensitivity: 35mV, 10Hz-200MHz. Input Impedance:* 1MΩ(HF), 50Ω(VHF). *Display:* 7-digit LEDs.

AM/FM STD SIGNAL GEN.

SG-4110A $1799.00, *Freq:* 0.1~110MHz; *Display:* 6-digit LED; Resolution: 100Hz (0.1~34.999MHz); 1KHz (35MHz~110MHz). *Accuracy:* <±($5x10^5$ ±1 count); *Output:* -19dBu~99dBu, 1dB steps. *Imped.:* 50Ω VSWR 1.2; 100 preset frequency, store funct.

AUDIO GENERATOR

AG-2601A $124.95, 10Hz~1MHz in 5 ranges; *Output:* sinewave 0~$8V_{rms}$; square $10V_{p-p}$. *Output Imped:* 600 Ω *Distortion:* <0.05% 500Hz~50KHz; <0.5% 50KHz~500KHz.
AG-2603AD $229.95, with 6-digit, Int/Ext. Freq Cntr, 10Hz~150MHz,
Output Control: 0/-20/-40dB & fine adjuster, spec. see AG-2601

FUNCTION GENERATOR

FG-2100A $169.95, 0.2Hz-2MHz in 7 ranges; sne, square, triangle, pulse & Ramp; *Output:* $5mV_{p-p}$-$20V_{p-p}$, 1% distortion. *VCF:* 0-10V/freq. to 1K:1
FG-2102AD $229.95 see FG-2100a; 4-digit counter display; CMOS & TTL Output, 30ppm ±1 cnt accuracy
FG-2020B $159.00 0.5Hz-500KHz; Sine, Square, Triangle.
FG-2103 $329.95, Digital sweep generator, 0.5Hz-5MHz in 7 ranges. *Operating Mode:* sweep, AM, gated burst, VCG. *Freq. Counter:* Int. 0.5Hz-5MHz; Ext. 5HZ-10MHz.
FG-513 $769.95, 13 MHz, Microprocessor embedded sweep; *Freq. Counter & TCXO:* 5Hz-100MHz, 6.5 digits. x1/x20 attenuation; Sine/Square/Triangle/Pulse/Ramp/TTL & DC; ±(.01%+1).

AC MILLIVOLT METER

MV-3100A $159.95 wide band 5Hz~1MHz; 3 scales, mV/dB/dBm; 300μv ~100V in 12 ranges, 10μv resolution; -70~40dB in 12 ranges, 0dB=1Vrms, 0dBm=0.755V; ±3% accuracy; Input impedance 10MΩ; Noise <2%.
MV-3201B $309.95 2 ch.; simultaneous measurement; spec see MV-3100

OSCILLOSCOPES

OS-7305B $249.00 DC~7MHz; 3" CRT; *Horz:* .25V/div; 10Hz~100KHz in 4 ranges; *Vert:* 10mV/div; Int./Ext. sync.; *Input:* 1MΩ/35pF.
OS-7010A $299.95 10MHz, 5" crt; *Horz:* .2V/div; *Vert:*10mv~10v /div
OS-622G $389.95 20MHz, 2 CH.; Alt trig., trig. lock, hold off, TVsyn. 8x10 div_{sq} 1mV/div., *Horz:* .2μs~.5s/div; *Vert:* 1mV~5V/div.
OS-653G $699.95 50MHz, 2 CH/delay sweep, Alt trig., TV syn.
OS-6101G $1499.95 100MHz, 4ch/8 traces, delay sweep, cursor readout. *2 years warranty for OS-620, 622G, 653G, 6101 &6102*

UHF ATTENUATORS

RT-8815U (50Ω) $299.00 / RT-8817U (75Ω) $299.00, 950MHz 81dB, 0.5W max.; *Steps:* 1/2/3/5/10/20/20/20, 8 switches.
085E-2 (50Ω) $399.00 / 087E-2 (75Ω) $399.00, 950MHz, 81dB, 0.5W max.; *Steps:* 10dB+7.1dBx10, Electronic adjustment knob.

MICROPROCESSOR TRAINER



BGC-8088 $699.00, learn computer theory. Excellent for school & individual who want to learn about ROM, RAM, I/O ports, programming, & run a 8088 Microprocessor. An easy to understand step-by-step manual guides you to achieve your goal. 56-key keyboard, LCD display, RS-232, UART...

GRID DIP METER

DM-4061 $89.95 1.5-250MHz, 6 bands; 6 plug-in coils, 2 transistor, and 1 diode. *Modulation:* = 2KHz Sinewave. *Crystal Oscillator:* 1-15MHz. Wave absorption meter. 9VDC battery.

FREQUENCY COUNTER

FC-5250C $119.95 10Hz-220MHz. HF:10Hz-20MHz;VHF:10-200MHz *GateTime:* .1, 1s; *Max. Input:* $10V_{p-p}$ *Sensitivity:* 35mV/10Hz-200MHz; *Input Imped.:* HF:1MΩ; VHF:50Ω; *Display:* 7-digit; 9V adapter **($6).**
FC-5260A $129.95 10Hz-600MHz; 7-digit LEDs. 9V AC adapter **($6).**
FC-5270 $149.95 10Hz-1.2GHz; 8-digit LEDs. 9V AC adapter **($6).**

FC-5600B $229.95 10Hz-600MHz; 10-digit LEDs; 110/220VAC.
FC-5700 $299.95 10Hz~1.3GHz; 10-digit LEDs; Period measure

SIGNAL TRACER/INJECTOR

SE-6100 $134.95
TRACER: Gain 60dB maximum. *Attenuation:* 0/20/40/60dB *Input Imped:* 100kΩ; *Meter:* Vu .1mA *Output Imped.:* 600Ω; *Speaker:* 8 Ω.
INJECTOR: =1KHz Squarewave; *Output Level:* Variable 0 ~ $4.5V_{p-p}$; 9V battery or adaptor **($6.00).**

LCR METERS

MIC-4070D $179.95, *L:* 0.1μ~200H, *C:* 0.1p~20mF, *R:* 1mΩ~20MΩ, 2Ω range, Dissipation factor measurement, Zero adjust; Surface mount device (SMD) test probe: **LT-06 $21.95**

DIGITAL MULTIMETER

DMM-120 $24.95, 3½ dig.; 600vDC, 2ADC 500vAC, 2MΩ, hFE/diode/continuity; 1.2%.
DMM-123+Cap. $44.95, 3½ digit; 600vDC, 600vAC, 10ADC/AC, 2GΩ, 20μF, hFE & diode test, continuity beeper; 0.8% accuracy.
DMM-124+Cap.+Temp.+Freq $69.95, 3½, 600vDC/500vAC, -58~752° F, 2GΩ, 20mF, 200KHz, 3-phase/diode/continuity test; 1.2%
DMM-125 $54.95, Auto /Bargraph, 32MΩ, 600vDC/AC, 10ADC/AC, diode/continuity.
MIC-35 $59.95, 3½ LCD, Autorange 20MΩ 1000vDC/750vAC, 20ADC/AC, data hold, diode/continuity test, free holster; 0.5% accy.
MIC-39 $129.95, Auto/Bargraph, True RMS, 3¾ LCD, 40MΩ, 40μF, 1000vDC/750vAC, 20ADC/AC, 600KHz freq. cntr, data hold, sleep mode, memory, read functions, holster; 0.3% accurcy.
POCKET ANALOG MULTIMETER AMM-9810P $14.95

DCV: *Range:* 10/50/250/500V; ±4%.
ACV: *Range:* 50/250/500V; ±4%.
DCA: *Range:* 25mA, 250mA; *Accuracy:* ±4% full scale; *Protection:* 0.5A/250V fuse.
Resistance: *Range:* **500kΩ (x 1k);** ±5%.
dB Test: +4 to +56 dB on ACV range; *Accuracy:* ±5% of full scale.
Battery Test: 1.5V and 9V.
Max. Input: 500VDC/AC, or 250mADC.

AUTO. CAPACITANCE METER

CM3300A $139.00 10 ranges, 99.9pF ~ 99.9mF, fully automatic. *Resolution:* 0.1pF lowest, 0.1% full scale. *Accuracy:* 0.5% of full scale ±1 digit to 99.9μF, 1% of full scale ±1 digit to 99.9μF. *Display:* 3 digit LED.

Unit: pF, nF, μF, mF, Overflow indicator.

AUTO DISTORTION METER

DM-3104A $799.95
DISTORTION MEASURE
Range: 0.01% to 30%, 0.1/0.3/1/3/10/30% 6 ranges.
Freq: 400Hz±10%, 1kHz±10%(HPF).
Input: 3mV~100V; Ratio meas. 20dB.
Auto. Freq. Switching Ranges:
Fundamental Freq. = (fo)±10%;
Fund. Rejection: >-80dB at (fo)±5%; >-70dB at (fo)±10%.
Harmonic Accuracy: ±0.5dB, 1.8(fo)-60KHz.
LEVEL MEASURE *Range:* 0~100V; .03/.1/.3/1/3/10/30/100V;
Freq Response: ±0.5dB/20~50kHz; ±1dB/20~100kHz.
DM-3204 $1,599.00 dual channels; Spec see DM-3104A.

1998 CATALOG: big selection of inductors, ferrites, micrometals toroids, mica capacitors, components, semiconductors, more. Two stamps please. Johnson Shop Products, Box 2843, Cupertino, CA 95015.



WANTED: EXCESS ELECTRONIC INVENTORIES, ICs, MEMORY, EPROMs, PALs, LEDs, CIRCUIT BOARDS, DIODES, AND TRANSISTORS. CALL ACTIVE MICRO, 562-494-4851 OR FAX 562-494-4913.

SMT COMPONENTS and complete SMT manufacturing system. Closing R&D/manufacturing company. Must sell lots of equipment. Call 1-800-869-7827 or visit www.starcom.com for list.



AMAZING! 4MHz CRYSTAL FOR 30¢. Brand new. 100pcs./package. Add $6 freight. Gateway Products Corporation, PO Box 936397, Margate, FL 33093, 954-974-6864. Fax 954-974-6818. VISA/MC, no CODs.

AMAZING! 10¢ ALL SCHOTTKY DIODES: 1N5817, 1N5819, 1N5820, 1N5821. 100pcs./package. Brand new parts. Add $6 freight. Gateway Products Corporation, PO Box 936397, Margate, FL 33093, 954-974-6864. Fax 954-974-6818. VISA/MC, no CODs.

MICROCONTROLLERS

RS485 TO BASIC STAMP 2! CONTROL 1 TO 32 BASIC STAMP 2 CHIPS at a distance of up to 4,000 feet. Board includes an interface to RS485, a slot for a BASIC STAMP 2, a 1 amp 5 volt power regulator, and robust screw terminals for easy connections to each STAMP 2 I/O pin. Manual provides a full explanation of how to use the board and RS485, as well as a tutorial with a software example to help you create your own controller/slave system. JD Richards. 530-823-5210. **www.jdrichards.com**

ANTIQUE ELECTRONICS

ANTIQUE RADIO CLASSIFIED. Free sample copy! Antique radio's largest-circulation monthly magazine. Old radios, TVs, ham equip., 40s & 50s radios, telegraph, books & more. Ads & articles. Free 20-word ad monthly. Subscribe today. Six-month trial: $20.95. Yearly rates: $40.95 ($57.95 by 1st Class). Foreign: write. ARC, PO Box 802-G22, Carlisle, MA 01741. Phone: 978-371-0512; Fax: 978-371-7129; Web: www.antique radio.com

WESTERN ELECTRIC WANTED: 1920's-1960's. Amplifiers, mixers, preamps, speakers, tubes, etc. FREE OFFER 1-800-251-5454.

WANTED: FOR historical museum, pre-1980 microcomputers, magazines, and sales literature. Floyd, VA 24091-0341 (540-763-3311/540-382-2935).

WESTERN ELECTRIC audio equipment wanted. 1926-1960s amplifiers, speakers, pre-amps, tube, transformers, etc. 1-800-old-mics 1-800-653-6427 Great Wireless Museum.

WE'LL MEET OR BEAT ANY COMPETITOR'S PRICE!

ALL PRODUCTS
1 Year Warranty

BRAND NEW
Wavemaster 99 Channel
• Sleep Timer • Std./HRC Switch • Parental Control
AS LOW AS $45.00 COMPLETE
CHECK US OUT!

JAMES' ELECTRONIC SERVICES, LTD.
Formerly JES, Inc.
BEST PRICES!
FAST SERVICE
SAME DAY SHIPPING

Panasonic 145 & 175's
WE STOCK
EVERY MODEL USED.
CALL NOW FOR
WHOLESALE PRICING

TOLL FREE: 800-322-9690 VISA MasterCard *FAX: 516-246-5634*

CRYSTAL SETS. Parts, plans, books, kits. Largest source in the world. Catalog $2. MIDCO, PO Box 222288, Hollywood, FL 33022.

WESTERN ELECTRIC WANTED: 1927-1960S. Amplifiers, speakers, tubes, etc. Free offer. 1-800-251-5454.

MILITARY TRANSISTORS & DIODES & INTEGRATED CIRCUITS WANTED. ELECTRONIC MATERIAL INDUSTRIES 818-769-1002, FAX 818-769-1084.

RADIO TUBES and phono. needles. 870-347-2281.

AVIATION ELECTRONICS

MILITARY TRANSISTORS & DIODES & INTEGRATED CIRCUITS WANTED. ELECTRONIC MATERIAL INDUSTRIES 818-769-1002, FAX 818-769-1084.

SYNCHRO RESOLVER test sets, system analyzers, test equipment. **www.lonemtn.com**

BUY, SELL, trade, avionics equipment, Collins, King, Sperry: test equipment, IFR, Litton LTN series INUs. 941-625-3222 P, 941-625-0494 F, E-Mail: avionics@afcon.net

PUBLICATIONS

THE CASE AGAINST PATENTS. Don Lancaster's tested and proven alternatives that work in the real world. $28.50, Synergetics Press, 3860 West First Street, Box 809, Thatcher, AZ 85552. 520-428-4073. synergetics@tinaja.com VISA/MC.

NEW SURVIVAL COMMUNICATIONS BOOK. How to build complete home communications systems. Covers all needs: shortwave radio, amateur radio, citizens band, scanners, federal, weather, alternate news, satellite radio, equipment sources. How to build and use alternate emergency power sources, solar, generators, backup batteries. 200 pages. $24 Fast delivery Priority Mail. MC or Visa. Call Universal Electronics 1-800-241-8171.

MILITARY COMPONENTS wanted. Capacitors, resistors, diodes, transistors, semiconductors, ICs. Electronic Material Industries, 818-769-1002, FAX: 818-769-1084.

ELECTRONIC EAVESDROPPING EQUIPMENT DESIGN by Winston Arrington. This revised edition contains 117 schematics and text of our production equipment. 29 crystal transmitters, 35 room, 32 telephone, 15 subcarrier, countermeasures and much more. Request a free detailed explanation sheet of contents. **PRICE:** $65 + S&H $6. **SHEFFIELD ELECTRONICS CO.,** PO Box 377940-E, Chicago, IL 60637-7940. Tel: 773-324-2196. http://www.adnetmk.com/sheffield

MONICA PROBABLY doesn't have a copy of "Tormet's Electronics Bench Reference" but you should. It has over 100 pages of circuits, design information, parts sources, large radio section, etc. See details at www.ohio.net/~rtormet/index.htm or send check or money order for $19.95+ $2.50 postage and handling to: RMT Engineering, 6863 Buffham Rd., Seville, OH 44273.

ADDRESSABLE STEPPER MOTOR CONTROLLER

The PARAMAX stepper motor controller is a PC parallel port based addressable controller capable of simultaneous operation of 4 uni-polar stepper motors ranging in voltages from 5 to 12 volts at up to 2 amps per phase. The PARAMAX stepper motor controller includes 8 digital inputs with a data through put rate of 500k bytes per second. Using the unique PARAMAX addressing method, up to 256 controllers can simultaneously function from a single parrallel port. The programming package includeslibraries that allow you to create applications both under Windows and DOS. Included libraries are: C++, Pascal, Delphi, Basic and utilities for DOS and Windows.

Also available at:
FORD ELECTRONICS, INC
(714) 521 - 8080

Part Number: JWP1X-1A
$199.95



PARAMAX INC.
(800) 473 - 8080
Come and visit us on the internet at:
www.paramax.net

HOW TO PLACE A CLASSIFIED AD

TYPE or PRINT your **ELECTRONICALLY RELATED** ad copy **CLEARLY (not all caps)** on a separate piece of paper. Spell out words when submitting hand-written copy. Calculate the number of words and multiply it by the appropriate rate (see RATE PER WORD section). Include any charges for **bold** and/or CAPPED words, any artwork costs that would be applicable, and/or costs for boxing your ad (explained below). Choose the appropriate classification for your ad(s) to appear in (see below). If no classification is indicated, it will be placed in Misc. Electronics or wherever we deem most suitable. **Enclose your name, address, phone number, and *Nuts & Volts* account number from your mailing label** (if available) for identification purposes. Include full payment — **CLASSIFIEDS RUN ON A PRE-PAID BASIS ONLY** — and mail your completed order to:

NUTS & VOLTS MAGAZINE, 430 Princeland Ct., Corona, CA 91719.

RATE PER WORD

The ad rate for **current PAID subscribers** is **60¢** per word. All others pay **$1.20** per word. There is a **$9.00 minimum** charge per ad per insertion.

WORDS IN BOLD AND/OR ALL CAPS

Words to be set in **bold** or CAPS are each 10¢ extra PER WORD. **BOLD CAPS** are 20¢ extra per word. The first two words of each ad are bold capped at no charge. Indicate bold words by underlining. Words normally written in caps (e.g., IBM) and accepted abbreviations such as VAC or MHz are NOT charged as all cap words. Use a two-letter abbreviation for states.

PHOTOS, DRAWINGS, AND BOXES

A photo or drawing may be run at the top of your classified ad for an additional **$10.00** (1" depth max.) for camera-ready art. No wording is allowed in this area. Add a one-time charge of **$5.00** to enlarge, reduce, or duplicate line art, or **$8.00** for halftone of photographs. To **BOX** your ad, include an additional **$50.00** for copy-only ads, or **$75.00** for ads with art or photos.

FAXING IN AD COPY

You may fax in ad copy or changes before the closing date (5:00pm on the **5th**) at 909-371-3052 using MasterCard or Visa. Include credit card expiration date, the name that appears on the card, a daytime phone number, and your *Nuts & Volts* account number. Ads without credit card information will not be listed as received until payment is received in full. **WE DO NOT CALL OR FAX BACK VERIFICATION OR QUOTES OF FAXED-IN ADS.** For verification of faxed-in ads, please call 909-371-8497.

DEADLINE

Prepaid ads received by 5:00pm on the **closing date (5th of the month)** will appear in the following month's issue. Ads postmarked through the **5th**, but received after the closing date, will be placed in the next available issue. No cancellations or changes after the 5th. Cancellations and changes must be submitted in writing.

IMPORTANT INFORMATION

All classified ads are running copy only. No special positioning, centering, dot leaders, extra space, etc. is allowed. All advertising in *Nuts & Volts* is limited to **electronically related items ONLY**. All ads are subject to approval by the publisher. We reserve the right to reject or edit any ad submitted. We do not take ad copy or changes over the phone. We do not bill for classified ads. Repeat ads or ads run in multiple classifications within the same issue are allowed. Paid subscribers may run ads at the 60¢ rate only through their subscription expiration date. **NO REFUNDS**. Credit only. No credit for typesetting errors will be issued unless you *clearly* print or type your ad copy.

Choose a category for your ad from the classifications listed below.

10. Ham Gear For Sale
20. Ham Gear Wanted
30. CB/Scanners
40. Music & Accessories
50. Computer Hardware
60. Computer Software
70. Computer Equipment Wanted
80. Test Equipment
85. Security
90. Satellite Equipment
95. Military Surplus Electronics
100. Audio/Video/Lasers
110. Cable TV
115. Telephone/Fax
120. Components
125. Microcontrollers
130. Antique Electronics
135. Aviation Electronics
140. Publications
145. Robotics
150. Plans/Kits/Schematics
155. Manuals/Schematics Wanted
160. Misc. Electronics For Sale
170. Misc. Electronics Wanted
175. BBS & Online Services
180. Education
190. Business Opportunities
200. Repairs/Service

ADVERTISER'S INDEX

A & S Wholesale 62
Abacom Technologies 48
ABC Electronics 77
Ace Computers 85
ACP Super Store 77
Advanced Educational Systems 7
Alfa Electronics 54
All Electronics Corporation 88
Allison Technology Corporation 39, 52
Alltech Electronics 64
Alltronics 19
All TV, Inc. 70
American Innovations, Inc. 63
American Technologies Network Corp. 20
AM Research, Inc. 21
ANA Instruments 67
Andromeda Research 15
Antique Radio Classified 53
Ar2 Communications Products 67
AST Global Electronics 46
Aventrade 52
Basic Electrical Supply & Warehousing Corporation 55
Baylin Publications 25
Bell Electronics 76
Bilocon Corp. 53
Bisme Computers Outlet 68
Brick Wall Div., Price Wheeler Corp. 14
C & S Sales, Inc. 40, 90
C and H Sales Company 60
Cable Plus, Inc. 60
Chenesko Products, Inc. 61
Communications Surplus 83
Comtrad Industries 101
Consumertronics 28
Corporate Systems Center 2, 102
Cruising Equipment 21
Cunard Associates 20
Danbar Sales Company 87
Davilyn Corp. 29
Dexis 24, 53
Digital Products Co. 52
Dimension 56
Earth Computer Technologies 59
E.H. Yost & Co. 68
E-Lab Digital Engineering, Inc. 63
ELECTRO MAVIN 76
Electro Tool, Inc. 61
Electronic Design Specialists, Inc. 63
Electronic Goldmine 32
Electronic Rainbow Ind., Inc. 71
Electronix Express 78
EMAC, Inc. 22
EPS 53
Equipment Management Technology 54
Ewig USA 65
ExpressPCB 53
Fair Radio Sales 47
Foss Warehouse Distributors 52
Gateway Electronics, Inc. 86
General Device Instruments 52
General Science & Engineering 99
Glentech, Inc. 52
Graymark 56
Greenleaf Electronics 43
Halted Specialties Co. 3
H.T. Orr Computer Supplies 69
Index Publishing Group 55
IndustroLogic 35
Information Unlimited 59
Inkjet Southwest 79
Interactive Image Technologies, Ltd. 5
Intersoft 82
Intronics, Inc. 61
ITU Technologies 53
Jade Products, Inc. 52
James' Electronic Services, Ltd. 73
J-Works, Inc. 24
KDE Electronics Corp. 67
Kimtronix 78
La Paz Electronics Int'l. 77
Lemos International Co., Inc. 39
Linear Systems 17
LLH Technology Publishing 93
Lynxmotion, Inc. 80
M2L Electronics 78
Metric Equipment Sales, Inc. 70
microEngineering Labs 57
Micromint 60
Milford Instruments-England 52
Modern Electronics 22
Motron Electronics 55
MSC Electronics 53
Netcom 15
New World Technologies, Inc. 65
Optoelectronics 103
Pacific Test Equipment Corp. 58
Parallax, Inc. .... Back Cover
PARAMAX, INC. 73
PCW, Inc. 80
Phelps Instruments 57
Pioneer Hill Software 48
Polaris Industries 57
Prairie Digital, Inc. 53
Pulsar, Inc. 56
R & S Surplus 62
Ramsey Electronics, Inc. 89
Resources Un-Ltd. 34
R.E. Smith 52
RKA Systems 70
Roger's Systems Specialist 66
Sam's Electronics 59
Scott Edwards Electronics 94
Seabird Technical 53
SGC 54
Shreve Systems 52
SIMCO 33
Skycraft Parts & Surplus, Inc. 60
Spy Outlet 52
Square 1 Electronics 23
Sun Equipment Corporation 72
Surplus Traders 52
Synergetics 91
Techniks, Inc. 52
Technological Arts 52
tech-specialities, Inc. 53
Teleview Distributors 43
Telulex, Inc. 76
Test Equipment Plus 30
The Filter Company 31, 65
The RF Connection 7
Timeless Products 68
Timeline, Inc. 33
Turner Technologies, Inc. 53
Ultra Link 53
Unicorn Electronics 47
USI Corp. 23
Utopia Tools 35
V&V Mach. & Equipment, Inc. 52, 53
VersaTech Electronics 17
Viewstar 55
Viking International 77
Visitect, Inc. 25
Voltex 99
Weeder Technologies 14
Western Test Systems 26-27
Wholesale Cable 62



AMATEUR RADIO & TV

Abacom Technologies 48
Alltronics 19
Communications Surplus 83
Gateway Electronics, Inc. 86
Intersoft 82
Jade Products, Inc. 52
Lemos International Co., Inc. 39
Ramsey Electronics, Inc. 89
SGC 54
The RF Connection 7

BATTERIES/CHARGERS

Aventrade 52
Cruising Equipment 21
Cunard Associates 20
E.H. Yost & Co. 68
Jade Products, Inc. 52

BUSINESS OPPORTUNITIES

Chenesko Products, Inc. 61

BUYING ELECTRONIC SURPLUS

ABC Electronics 77
Alltech Electronics 64
C and H Sales Company 60
Dexis 24, 53
Earth Computer Technologies 59
EPS 53
Equipment Management Technology 54
Metric Equipment Sales, Inc. 70
Roger's Systems Specialist 66
Skycraft Parts & Surplus, Inc. 60
Timeline, Inc. 33

CABLE TV

A & S Wholesale 62
All TV, Inc. 70
Basic Electrical Supply & Warehousing Corporation 55
Cable Plus, Inc. 60
Dimension 56
Ewig USA 65
Foss Warehouse Distributors 52
Greenleaf Electronics 43
James' Electronic Services, Ltd. 73
KDE Electronics Corp. 67
Kimtronix 78
Modern Electronics 22
New World Technologies, Inc. 65
PCW, Inc. 80
Sam's Electronics 59
Teleview Distributors 43
The Filter Company 31, 65
Timeless Products 68
Viewstar 55
Wholesale Cable 62

CB/SCANNERS

USI Corp. 23

CCD CAMERAS/VIDEO

American Innovations, Inc. 63
American Technologies Network Corp. 20
General Science & Engineering 99
MSC Electronics 53
Polaris Industries 57
Ramsey Electronics, Inc. 89
Resources Un-Ltd. 34
Seabird Technical 53
Spy Outlet 52
USI Corp. 23
Timeline, Inc. 33

COMPONENTS

Ace Computers 85
Communications Surplus 83
E-Lab Digital Engineering, Inc. 63
Electronic Goldmine 32
Electronix Express 78
EPS 53
La Paz Electronics Int'l. 77
Linear Systems 17
Pulsar, Inc. 56
Skycraft Parts & Surplus, Inc. 60
Unicorn Electronics 47
Visitect, Inc. 25

COMPUTER

Hardware

Ace Computers 85
ACP Super Store 77
Allison Technology Corp. 39, 52
Alltech Electronics 64
AM Research, Inc. 21
Bisme Computers Outlet 68
Brick Wall Div., Price Wheeler Corp. 14
Consumertronics 28
Corporate Systems Center 2, 102
Earth Computer Technologies 59
ELECTRO MAVIN 76
General Device Instruments 52
Halted Specialties Co. 3
La Paz Electronics Int'l. 77
Roger's Systems Specialist 66
Shreve Systems 52
Techniks, Inc. 52
tech-specialities, Inc. 53
Ultra Link 53
Voltex 99

Software

AM Research, Inc. 21
Bisme Computers Outlet 68
Comtrad Industries 101
Interactive Image Technologies, Ltd. 5
Pioneer Hill Software 48
Ultra Link 53

Microcontrollers / I/O Boards

Abacom Technologies 48
Advanced Educational Systems 7
AM Research, Inc. 21
Bisme Computer Outlet 68
EMAC, Inc. 22
IndustroLogic 35
Intersoft 82
ITU Technologies 53
La Paz Electronics Int'l. 77
Micromint 60
Motron Electronics 55
Parallax, Inc. ....Back Cover
PARAMAX, INC. 73
Prairie Digital, Inc. 53
R.E. Smith 52
Scott Edwards Electronics 94
Square 1 Electronics 23
Technological Arts 52
VersaTech Electronics 17

Printers/Printer Supplies

Chenesko Products, Inc. 61
H.T. Orr Computer Supplies 69
Inkjet Southwest 79

DESIGN/ENGINEERING SERVICES

E-Lab Digital Engineering, Inc. 63
ExpressPCB 53
Pulsar, Inc. 56
V&V Mach. & Equipment, Inc. 52, 53

EDUCATION

Advanced Educational Systems 7
EMAC, Inc. 22
Sun Equipment Corporation 72

EVENTS/SHOWS

ACP Super Store 77

KITS

Alltronics 19
C & S Sales, Inc. 40, 90
Digital Products, Inc. 52
Earth Computer Technologies. 59
Electronic Goldmine 32
Electronic Rainbow Ind., Inc. 71
EMAC, Inc 22
Gateway Electronics,Inc. 86
Information Unlimited 59
Inkjet Southwest 79
Jade Products, Inc. 52
Ramsey Electronics, Inc. 89
Scott Edwards Electronics 94
USI Corp. 23
Weeder Technologies 14

LASERS

Information Unlimited 59
Resources Un-Ltd. 34
Unicorn Electronics. 47

MISC./SURPLUS

All Electronics Corporation. 88
Alltech Electronics 64
C and H Sales Company 60
Communications Surplus 83
Consumertronics 28
Electronic Goldmine 32
Electronic Rainbow Ind., Inc. 71
EPS 53
Equipment Management Technology 54
Fair Radio Sales 47
Gateway Electronics, Inc. 86
Halted Specialties Co. 3
Resources Un-Ltd. 34
Shreve Systems 52
SIMCO 33
Skycraft Parts & Surplus, Inc. 60
Surplus Traders 52
Timeline, Inc. 33
Unicorn Electronics 47
Viking International 77
Visitect, Inc. 25
Weeder Technologies 14

PROGRAMMERS

Andromeda Research 15
General Device Instruments 52
Intronics, Inc. 61
M2L Electronics 78
microEngineering Labs 57

PUBLICATIONS

Antique Radio Classified 53
Consumertronics 28
Index Publishing Group 55
LLH Technology Publishing 93
Netcom 15
Square 1 Electronics 23
Synergetics 91

ROBOTICS

Abacom Technologies 48
Lemos International Co., Inc. 39
Lynxmotion, Inc. 80
PARAMAX, INC. 73
Milford Instruments-England 52

SATELLITE

Baylin Publications 25

SECURITY

American Innovations, Inc. 63
American Technologies Network Corp. 20
Information Unlimited 59
Intersoft 82
Lemos International Co., Inc. 39
MSC Electronics 53
Polaris Industries 57
USI Corp. 23
Visitect, Inc. 25

SOLAR EQUIPMENT

Cruising Equipment 21

STEPPER MOTORS

Alltronics 19
E-Lab Digital Engineering, Inc. 63
PARAMAX, INC. 73

TELEPHONE

Ar2 Communications Products 67
Bilocon Corp. 53
Digital Products, Inc. 52
Telulex, Inc. 76
Turner Technologies, Inc. 53
Weeder Technologies 14

TEST EQUIPMENT

ABC Electronics 77
Alfa Electronics 54
Allison Technology Corp. 39, 52
ANA Instruments 67
AST Global Electronics 46
Bell Electronics 76
C & S Sales, Inc. 40, 79
C and H Sales Company 60
Cruising Equipment 21
Danbar Sales Company 87
Davilyn Corp. 29
Dexis 24, 53
Digital Products, Inc. 52
Electronic Design Specialists 63
Equipment Management Technology 54
Electro Tool, Inc. 61
Glentech 52
Intronics, Inc. 61
J-Works, Inc. 24
Metric Equipment Sales, Inc. 70
Optoelectronics 103
Pacific Test Equipment Corp. 58
Phelps Instruments 57
Pioneer Hill Software 48
R & S Surplus 62
RKA Systems 70
Seabird Technical 53
Sun Equipment Corporation 72
Telulex, Inc. 76
Test Equipment Plus 30
Western Test Systems 26-27

TOOLS

C & S Sales, Inc. 40, 90
Electro Tool, Inc. 61
Electro Tool, Inc. 61
Graymark 56
Sun Equipment Corporation 72
The RF Connection 7
Utopia Tools 35

WIRE/CABLE & CONNECTORS

Roger's Systems Specialist 66
The RF Connection 7

Top Quality Reconditioned Electronic Test Equipment

Hewlett-Packard • Tektronix • Fluke • Wiltron

BOUGHT & SOLD

Test Equipment Wanted

Looking for Test Equipment Manuals?
Contact: Manuals Plus (801)882-7188 • Fax (801)882-7195

Corporate Offices
P.O. Box 1762
San Mateo, CA 94401

Seattle, WA 206-251-6653
285 S.W. 41st St.
Renton, WA 98055

415-579-1711 • Fax 415-579-5777
http://www.bellelect.com

BELL Electronics

Write in 60 on Reader Service Card.

♦**NEW HP IIcx COLOR SCANNERS $150.00**

♦SCANNER DOCUMENT FEEDER (FITS 2cx,3c,4c & 4p) $100.00

♦**USED HP DUPLEX LASER PRINTERS $375.00**

HEWLETT PACKARD IIID - MIO PORT TO NETWORK - 300 DPI - PRINT DOUBLE OR SINGLE SIDED - DUAL LETTER TRAYS - PRINTS LETTER OR LEGAL SIZE - 3 MEG OF RAM (EXPANDABLE) USES 95A CARTRIDGES - LEASE RETURNS, EACH WELL MAINTAINED UNDER SERVICE CONTRACT NO HASSLE 30 DAY WARRANTY

♦**ULTRA SCSI HARD DRIVES**

BRAND NEW, LESS THAN 5 CENTS A MEG

♦ **4 meg Diamond 4000 3D AGP Video Cards $50.00**

♦ *SLICK LOOKING AT STYLE TOWER CASES - FULL-TOWER (260W/PS) $35.00*
MID-TOWER (230W/PS) $23.00 - MINI-TOWER (230W/PS) $18.00

The List Grows Daily!! So Check the Web Site for More Low Prices

ELECTRO MAVIN

800-421-2442 OR FAX 310-632-3557
E-MAIL john@mavin.com OUR WEB ADDRESS IS
http://www.mavin.com/mavsales.htm

PUBLICATIONS *cont.*

START YOUR OWN TECHNICAL VENTURE! Don Lancaster's newly updated **INCREDIBLE SECRET MONEY MACHINE II** tells how. We now have autographed copies of the Guru's underground classic for $18.50. Synergetics Press, Box 809-K, Thatcher, AZ 85552. 520-428-4073. VISA/MC.

HACKERS GOLD CD-ROMs (2) 30,000 programs! The most complete underground collection of hacker's files ever assembled. 550+ megabytes on each! Published: February 1998. Either CD-ROM $34.95. Both $49.95. 520-726-2833. **TELECODE**, PO Box 6426-NV, Yuma, AZ 85366-6426. http://www.hackerscatalog.com/hackgold.htm

ROBOTICS

H-BRIDGE MOTOR controllers, 12VDC, 35A average, 50A peak PWM out. Forward, reverse, ramp-up and ramp-down on accelleration/decelleration. Current foldback when hot, reverse polarity protected, conformal coated, regenerative braking, compact, approx. 3.75"x5.5". $25 & S&H. 717-735-5053. http://members.tripod.com/~divelec

CNC SYSTEMS! Write: motivity, Attn. Pam, PO Box 428, Rocklin, CA 95677. Call: 916-349-8757. Info/pictures at **www.motivityusa.com** A great place to buy CNC.

PLANS – KITS – SCHEMATICS

HOBBY CATALOG: Broadcasting and microbroadcasting transmitters, amplifiers, antennas. **Start your own radio station books**. Audio, TV, ham, CB, surveillance, science projects, and more. **PAN-COM** International, Box 130-V, Paradise, CA 95967. **www.panaxis.com**

ELECTRONIC KITS, projects and supplies for prototyping, designing or hobby. Call 1-888-GO-4-KITS for catalogs or send $3 to Quality Kits, 49 McMichael St., Kingston, ON., K7M 1M8. **http://www.qkits.com**

TEST EQUIPMENT kits. If you liked Heathkit, you will love Technology Systems, 4 Prospect Pl., Torrington, CT 06790.

HEATHKIT COMPANY is selling photocopies of most Heathkit manuals. Only authorized source for copyright manuals. Phone: 616-925-5899, 8-4 ET.

MOD CHIPS for Sony PlayStation. Now your backups will work. Only $9.95 ea. + $3 shipping. Call 1-888-467-6150, all major credit cards accepted. Computers & components at wholesale prices. www.cconusa.com



BROADCAST FARTHER! 75-110MHz amplifier connects to stereo transmitters. Produces 2-15 watts. Requires 50-150mW drive. Complete plans with part source and antenna information only $14 + $2 S&H. **Progressive Concepts,** PO Box 586, Streamwood, IL 60107. 630-736-9822.

BUILD THE MENDOCINO MOTOR. This fascinating device is a solar powered, magnetically levitated motor. It will delight and amaze you and your friends. The 27 page plans book includes a list of parts suppliers. The motor uses readily available parts. Plans are $15 plus $2.50 S&H. Write to: St. Elmo's Fire, PO Box 141, Stow, MA 01775. E-Mail: tcv@genrad.com

SURVEILLANCE TRANSMITTER SCHEMATICS! FM band- 2 telephone and 3 room transmitters constructed using Radio Shack parts with their numbers given. One telephone and two room transmitters are tunable from 65 to 305MHz, and constructed with listed supply house parts. PC board patterns presented. **PRICE**: $25 + S&H $2. For immediate shipment, pay with money order. **SHEFFIELD ELECTRONICS CO.**, PO Box 377940-E, Chicago, IL 60637-7940. Tel: 773-324-2196. http://www.adnetmk.com/sheffield

BUILD A radar jammer out of your old radar detector. No electronic knowledge needed. Call 24 hr. for easy step-by-step plans. "GUARANTEED." New from "Image Master Publishing" 1-800-295-0953. Only $9.95, $2.50 S&H.

MILITARY COMPONENTS wanted. Capacitors, resistors, diodes, transistors, semiconductors, ICs. Electronic Material Industries, 818-769-1002, FAX: 818-769-1084.

Any waveform you want!

Telulex Inc. model SG-100A

$995 Quantity 1

Money back guarantee

● **Synthesized Signal Generator**
Clean sinewaves DC-20 MHz with .001% accuracy!
.1 Hz steps. DC Offset. RS232 remote control.

● **Arbitrary Waveform Generator**
40 Megasamples/Second. 32,768 points. 12 bit DAC

● **Function Generator**
Ramps, Triangles, Exponentials, Noise & more.
0 to 2 MHz in 1 Hz steps. Continuous or Triggered.

● **Pulse Generator**
Digital waveforms with adjustable duty cycle


DC to 20 MHz linear and log sweeps


Int/Ext AM, SSB, Dualtone Gen.


Int/Ext FM, PM, BPSK, Burst


Ramps, Triangles, Exponentials


Pulse Generator

Noise


Arbitrary Waveforms


Unlimited Possibilities!

Telulex Inc.

2455 Old Middlefield Way S
Mountain View, CA 94043

Tel (650) 938-0240
Fax (650) 938-0241

http://www.Telulex.com
Email: sales@Telulex.com

Write in 61 on Reader Service Card.

Professional **10 HOUR RECORDER** *Factory Direct*

"BUILT LIKE A BATTLESHIP"

- Heavy duty commercial recorder - NOT improvised from consumer models
- 12, 14, and 16 hour models also available
- BUILT-IN voice activation (add $30)
- Applications information included
- Dimensions: 11.5 x 7.0 x 2.75"

SPECIAL Nuts&Volts Price.. $159

FREE 40-PAGE SPECIAL EQUIPMENT CATALOG!

COD's OK. Sorry, no credit cards. Free catalog USA only; other countries $5. Price Includes UPS to 48 States on Pre-Paid Orders

Viking International 150 Executive Park Blvd. #4600 San Francisco, CA 94134
Phone: (415) 468-2066 • Fax: (415) 468-2067 • Web: www.vikingint.com

Write in 62 on Reader Service Card.

ABC ELECTRONICS 315 7TH AVE N. MPLS. MN. 55401
(612)332-2378 FAX (612)332-8481 E-MAILSURP1@VISI.COM
WE BUY TEST EQUIPMENT AND COMPONENTS.
VISIT US ON THE WEB AT WWW.ABCTEST.COM

HP 8901A MODULATION ANALYZER	$2100.00	TEK 2465A 350MHZ 4CH OSCILLOSCOPE	$3500.00
HP 8165A 50MHZ PROG. SIGNAL SOURCE	$1700.00	TEK TDS320 100MHZ DIGITAL O-SCOPE	$1700.00
HP 436A RF POWER METER NO CABLE OR SENSOR	$700.00	TEK 465 100MHZ OSCILLOSCOPE	$400.00
HP 8559A/853A .01-21GHZ SPECTRUM ANALYZER	$3500.00	TEK 475 200MHZ OSCILLOSCOPE	$500.00
HP 1740A 100MHZ OSCILLOSCOPE	$250.00	TEK 496P 1KHZ-1.8GHZ SPEC. ANALYZER	$4000.00
HP 8350B SWEEP OSCILLATOR MAINFRAME	$2900.00	TEK 576 CURVE TRACER	$2500.00
HP E3617A 0-60VDC 1AMP DIG. READOUT	$275.00	TEK CG5001 PROG.O-SCOPE CAL GEN.	$2000.00
HP 3325A SYNTHESIZER/FUNCTION GENERATOR	$1100.00	TEK PS5010 POWER SUPPLY	$450.00
HP 3325A OPT.01 HIGH STABILITY TIME BASE	$1350.00	TEK 7L12 SPECTRUM ANALYZER	$1350.00
HP 6034A 0-60V 10A DIG.DISPLAY	$900.00	TEK 485 350MHZ OSCILLOSCOPE	$650.00
HP 5335A 200MHZ COUNTER	$800.00	TEK 454 100MHZ OSCILLOSCOPE	$300.00
HP 3488A SWITCH/CONTROLLER	$550.00	TEK TM5006 POWER FRAME	$250.00
HP 2804A QUARTZ THERMOMETER	$300.00	TEK 11A32 400MHZ 2CH AMPLIFIER	$750.00
HP 4140B PICO-AMP METER/DC VOLTAGE SOURCE	$3500.00	TEK 11A34 300MHZ 4CH AMPLIFIER	$900.00
HP 54201A 300MHZ DIG.OSCILLOSCOPE	$1500.00	TEK 11A52 600MHZ 2CH AMPLIFIER	$400.00
HP 8011A PULSE GENERATOR	$250.00	TEK 11A71 1GHZ 1CH AMPLIFIER	$300.00
HP 3455A DMM	$250.00	TEK 11302A 500MHZ PROG O-SCOPE FRAME	$750.00
HP 3497A DATA ACQUISITION/CONTROL UNIT	$600.00	TEK 11401 500MHZ PROG. O-SCOPE FRAME	$750.00
HP 86290A RF PLUG IN 2-18GHZ	$1200.00	TEK 11402 1GHZ DIG.PROG. O-SCOPE FRAME	$1000.00
HP 86603A RF PLUG IN 1MHZ-2.6GHZ	$1700.00	TEK TM506 POWER FRAME	$100.00
HP 86601A RF PLUG IN .01MHZ-110MHZ	$400.00	TEK 7104 1GHZ OSCILLOSCOPE FRAME	$1250.00
HP 86632B AM/FM MODULATION PLUG IN	$750.00	TEK AM503 CURRENT PROBE AMPLIFIER	$350.00
HP 1631D LOGIC ANALYZER	$300.00	TEK 7B92A TIME BASE	$125.00
HP 8640B OPT.002 1GHZ AM/FM SIGNAL GEN.	$1400.00	TEK 7S12 SAMPLING PLUG IN	$350.00

Write in 63 on Reader Service Card.

ADVANCED TECHNOLOGY: Antigravity, free-energy, time-travel, alternative fuels, psionics, space-age weapons, lasers, ultrasonics, strange-science, bionics, high-voltage, robotics, surveillance, electronic test equipment, and more. Plans, schematics, kits. $3 for catalog: Future Horizons, Dept-N, PO Box 125, Marquette, MI 49855. http://www.futurehorizons.net/energy/



CIRCUIT BOARDS. Single sided. No minimum. No set-up fees. No hidden costs. No per hole charge, up to 1,000 holes per panel. Complete price list available. Circuit Design, PO Box 5415, Central Point, OR 97502, 541-664-7904. Phone or Fax. The Worldwide Circuit Design Network, http://www.circuitdesign.net

PROTOBOARDS FOR rapid project construction, PIC monitor, pocket testbench chips/kits. Oricom Technologies, 303-444-9776, www.sni.net/~oricom.

EXPERIMENTS WEAVING COMPOSITE PARTS for project builders without machine shops, high strength lightweight precision parts and structures you can make yourself. Plus gold recycling. Also used parts listing $5 booklet. Dale Trynor, Box 18, St. George, NB E0G-2Y0, gadget@nbnet.nb.ca

AWESOME KITS: voice changers, levitators, lasers, gas sensors, and more! Catalog $1. **LNS Technologies,** PO Box 67243, Scotts Valley, CA 95067. www.ccnet.com/~LNSTECH.

200+ ELECTRONICS PROJECTS. Build for pleasure or make 100% (or more) profits reselling printed plans. $1 (refundable) for catalog & dealer info. MATCO-A5, PO Box 509, ROSEVILLE, MI 48066-0509.

UNLIMITED UNDERGROUND ELECTRONICS. Electronic weapons, EMP, rail guns, plans, kits, parts, alt energy, more. SASE for free catalog or http://www.access1.net/ninteach & Visit http://www.info-labs.com. UUE, 1839-D West Vistaway #515, Vista, CA 92083.

MANUALS – SCHEMATICS WANTED

MILITARY COMPONENTS wanted. Capacitors, resistors, diodes, transistors, semiconductors, ICs. Electronic Material Industries, 818-769-1002, FAX: 818-769-1084.

CASH FOR your test equipment manulals in good condition for most Tektronix, HP, Fluke, and other test equipment. E-Mail your list and best price to: **manuals@lonemtn.com**

MISCELLANEOUS ELECTRONICS FOR SALE

MILITARY TRANSISTORS & DIODES & INTEGRATED CIRCUITS WANTED. ELECTRONIC MATERIAL INDUSTRIES 818-769-1002, FAX 818-769-1084.

SOLAR-POWERED FAN HAT. Baseball type hat with solar powered fan. Great for sports fans, golfers, etc. Available in red or blue. $19 plus $2.00 shipping. CA residents add 7.75% sales tax. Visa/MC/Disc/Amex OK. H.T. Orr Computer Supplies, 249 Juanita Way, Placentia, CA 92670. 714-528-9822, 1-800-377-2023, FAX 714-993-6216.

FREE FLYER on cable TV, phones, credit cards info, schematics, project boards, other misc. items. Bill 1-800-879-9657.

ELECTRONIC TECHNICIANS, hobbyists, and experimenters, stop paying high prices for electronic components. Send for free information to Short Circuit Electronics, PO Box 833, Mt. Clemens, MI 48046-0833.

ANAHEIM WIRE PRODUCTS. DISTRIBUTOR OF ELECTRICAL WIRE AND CABLE since 1973. Items available from our stock: Hook up wire, Automotive primary wire, GXL, SXL, Plenum cable, Teflon wire, Multi-conductor cable, Irradiated PVC, SO-CORD, Mil-Spec wire, Building wire, Welding cable, Battery cable, Telephone wire, Shrink tubing, Cable ties, Connectors. If interested, please call **1-800-626-7540**, FAX: 714-771-5043. Visa/MC/Amex. SEE US ON THE INTERNET: http://www.anaheimwire.com OR E-Mail: info@anaheimwire.com

NUCLEAR ELECTRONICS (NIM, CAMAC), PMTs, optics, high vacuum, and high voltage components and equipment. Guaranteed quality at reasonable cost. OE Technologies, Box 703, La Madera, NM 87539. Ph: 505-583-2482, Fax: 505-583-9190, E-Mail: oetech@newmexico.com http://www.oetech.com

Z64 GAME recorder: self-contain computer with 32meg RAM, ZIP. Plug into N64 station. Unlimited game storage, saving $375. N64 is a Nintendo trademark. 1-800-266-5706 PCT. Website: mobil-e-tech.com

NEW, USED, and "as is" Radio Shack items. Software, printers, computers, books, parts for R/C cars, etc. Free list. B and B Enterprises, 208 S. Pulaski St., Baltimore, MD 21223. 410-566-5388.

ACP's 88th GIANT COMPUTER SWAP★MEET

Orange County's Original!

Be a Seller ...for your space Call Mary

All Day Sunday 8am-2pm

Nov 29th

FREE Admission & Parking Shop 100's of Sellers

in ACP's Giant Parking Lot !!!

Advanced Computer Products, Inc.

ACP SUPER★STORE Since 1976

1310 E. Edinger Santa Ana, CA
714-558-8813

COMPUTER PARTS

www.lapazusa.com

MEMORY UPGRADES

1Mx9-70 SIMM	$10
4Mx9-70 SIMM	$19
1Mx32/36-70 72-pin SIMM (4MB)	$10/18
2Mx32/36-70 72-pin SIMM (8MB)	$19/28
4Mx32/36-70 72-pin SIMM (16MB)	$24/35
8Mx32/36 -60 72-pin SIMM (32MB)	$39/44
256Kx4 DIP DRAM	$3

VIDEO

256Kx16-70 VIDEO SOJ (2CAS)	$6
256Kx16-70 VIDEO ZIP (2CAS/2WE)	$18/20

CACHE

64Kx1-15ns 22-DIP	$5.50
32Kx8-25/20/15ns 28-DIP	$3/2.50
64Kx8-15ns 32-DIP	$6
128Kx8-15/20ns 32-DIP narrow	$12 & up
128Kx8-15/20/25ns 32-DIP wide	$12 & up

CPU

INTEL 486DX2-66 (5v) CPU	$30
INTEL 486DX4-100 (5v) CPU	$69
INTEL PENTIUM 133/166 CPU	$72/81
80387SX/DX CO-PROCESSOR	$19/32

MISC. MOTHERBOARD KITS

486 M/B 100Mhz, 256K, 16MB $89.00
PENTIUM M/B 133Mhz, 256K, 32MB $190.00
* 1-year warranty on these kits

MMX ADAPTOR allows your M/B to accept MMX CPU's $34.95

AMD 486DX4-100+5v ADAPTOR+CPU FAN
This kit will allow you to upgrade your old M/B to a faster CPU $65.00

LBA CARD upgrade your hard drive beyond 540MB without the expense of upgrading your present BIOS $29.95

PACKARD BELL
386/486 to Pentium motherboards

PRICES SUBJECT TO CHANGE WITHOUT NOTICE -- TERMS: COD(CASH), VISA/MC -- MINIMUM ORDER $20 -- SHIPPING & HANDLING: $7 MIN.
ORDER LINE: (800) 586-4199

LA PAZ ELECTRONICS INT'L
P.O. BOX 261095, San Diego CA 92196
TEL (619) 586-7610 FAX (619) 586-1482
e-mail: lapazusa@pobox.com

Write in 64 on Reader Service Card.

ATTENTION DEALERS

BUY DIRECT FROM THE WHOLESALER

GET THE BEST PRICES AND SERVICE

ALL UNITS ARE IN STOCK FOR IMMEDIATE SHIPMENT

CABLE CONVERTERS AND ACCESSORIES

CALL FOR PRICING ON ITEMS NOT LISTED

	QTY 5	QTY 10	QTY 25	QTY 50	QTY 100
NEW CONVERTERS					
CENTURY CT-3000	$64	$60	$55	$50	CALL
COMMERICIAL-11	$75	$70	$65	$62	CALL
VIEWSTAR-550 MHZ	$50	$45	$42	$38	CALL
DIGITECH-550 MHZ	$55	$49	$48	$46	CALL
EXPLORER CONVERTERS					
EXP-6600	$250	$225	$200	$175	CALL
PANASONIC CONVERTERS					
PAN-175/VOL	$165	$155	$145	$135	CALL

WE WILL MEET OR BEAT ANY ADVERTISED PRICE

1-800-800-0766

KIMTRONIX

30 day money back guarantee. All shipping and handling at customers expense. Anyone implying theft of cable service will be denied sale. NO FLORIDA SALES.

WE WILL MEET OR BEAT ALL COMPETITOR'S PRICES IN THIS MAGAZINE KIM-12

Write In 65 on Reader Service Card.

EZ-EP DEVICE PROGRAMMER - $169.95

Check Web!! -- *www.m2l.com*

Fast - Programs 27C010 in 23 seconds

Portable - Connects to PC Parallel Port

Versatile -Programs 2716-080 plus EE and flash (28, 29) to 32 pins

Inexpensive - Best for less than $200

- Correct implementation of manufacturer specified algorithms for fast, reliable programming.
- Easy to use menu based software has binary editor, read, verify, copy, etc. Free updates via bbs or web.
- Full over current detection on all device power supplies protects against bad chips and reverse insertion.
- Broad support for additional devices using adapters listed below.

Available Adapters

EP-PIC (16C5x,61,62x,71,84)	$49.95
EP-PIC64 (16C62-5,72-4)	$39.95
EP-PIC12 (12C50x)	$39.95
EP-PIC17 (17C4x)	$49.95
EP-51 (8751,C51)	$39.95
EP-11E (68HC11 E/A)	$59.95
EP-11D (68HC711D3)	$39.95
EP-16 (16bit EPROMS)	$49.95
EP-Z8 (Z86E02,3.4,6,7,8)	$39.95
EP-SEE2 (93x,24x,25x,85x)	$39.95
EP-750 (87C750,1,2)	$59.95
EP-PEEL (ICT22v10,18v8)	$59.95
EP-1051 (89C1051,2051)	$39.95
EP-PLCC (PLCC EPROMs)	$49.95
EP-SOIC (SOIC EPROMs)	$49.95
EP-TSOP (TSOP EPROMs)	$59.95

Many Other Adapters Available

M²L Electronics

970/259-0555
Fax:970/259-0777
361 S Camino Del Rio #119
Durango, CO 81301
CO orders please add 7% sales tax.
http:/www.m2l.com



Write In 66 on Reader Service Card.

HIGH QUALITY TOOLS AND STAINLESS STEEL HARDWARE. European and American screwdrivers, nutdrivers, pliers, hex- keys, balldrivers, and more! Wiha, Bondhus, and Knipex. Stainless cap screws, machine screws, nuts, washers, U-bolts, and eyes. Free catalog. Robert Mink Import-Export, Box 6437V, Fair Haven, NJ 07704. Telephone or fax 732-758-8388. E-Mail: w2tv@csi.com



THIN FILM solar cells - flexible to 1" radius. Only 0.010" thick. 100mA @6V 2-7/8"x10" 0.15oz. $24.95, 2 for $39.95. 200mA @ 6V 5-3/4"x10" 0.30oz. $49.95. Delta Tek, Inc., 1201 Airport Rd., Suite #5, Ames, IA 50010. 515-232-2352. fax: 515-233-6895. **Visa & MasterCard.** www.deltatekinc.com

DUKANE ULTRASONIC welder 1600 watt, several transducers, many horns, RF generator, monitor, manual $2,500. 937-429-5403.

CALL FOR a **free electronics catalog** or visit our web site at **www.bgmicro.com/ B.G. Micro,** PO Box 280298, Dallas, TX 75228. Order line **1-800-276-2206.**

http://www.pccables.com PC CABLES and PARTS. 100s of hard-to-find new cables and parts, Free technical information, low prices, fast online ordering & browsing.

L BAND quadrifilar T/R antenna, 55 dB LNA, 20 watt HPA, works great for remote GPS. Info at afstar.com.

HIGHEND SURPLUS 203-744-4101. OK INDUSTRIES DEMO BLOWOUT. If it is not listed just give us a call, chances are we have it! **SOLDER STATIONS**: total rework, forced convection, hot air. MTR5000 (retail $4,595) sell $2,350; MTR4000 (retail $3,995) sell $1,750; MTR3000 (retail $2,495) sell $1,250; BTR2000 (retail $1,595) sell $775; FCR2000 (retail $1,850) sell $950; BTR1000 (retail $825) sell $400; SMT1160 (retail $1,000) sell $450; SA2000 (retail $395) sell $185; SA1000 (retail $295) sell $150; SA500 (retail $225) sell $75. **PUR-AIR**: Fume exactors. EP101 (retail $1,695) sell $475; EP051 (retail $595) sell $225. **JEM**: Batch ovens JEM310 (retail $7,995) sell $3,600; JEM210 (retail $4,995) sell $2,200. **PICK & PLACE**: Chip placers, vacuum pencils, fluid dispensers. SMT8001 (retail $4,000) sell $1,750; SMT880 (retail $2,200) sell $950; FD1000 (retail $395) sell $175; VP100 (retail $395) sell $175. **BOARD ETCHER**: SSP-75A (retail $995) sell $400. **ALWAYS BUYING: VIDEO, RADIO, PHONE SYSTEMS, COMPUTERS, STEREO, AND BROADCAST EQUIPMENT.**

ELECTRONICS PARTS: LOW PRICES! Phone, fax, E-Mail for free catalogs. Hoffman Industries, 853 Dundee Ave., Elgin, IL 60120. Ph: 847-622-8201, Fax: 847-622-8202, toll free: 1-888-311-4248, E-Mail: hoffind@aol.com Visit our web site & on-line catalog: http://hoffind.com

SMT MANUFACTURING equipment. components, digital, analog, & RF test equipment. 26 KVA generator. Closing R&D/manufacturing company. Must sell lots of equipment. Call 1-800-869-7827 or visit www.starcom.com for list.

NEW ITEMS: Telephone-coupling transformers for interconnecting data/voice modem terminals to telephone lines meet FCC. Part 68 modular plugs, modular jacks, shielded modular plugs and jacks. SMT jacks with Sof-Lok post, Harmonica jacks, cable ready jacks, compu shield plugs, compu shield jacks, die sets and modular plugs. New products and cable assemblies. Power application tooling and cable tester: Send for schematic and connection diagrams, phone and fax mach. Ohio Service Supply Co., PO Box 8802, Canton, OH 44711-8802.

ELECTRONIX EXPRESS

WELLER SOLDERING STATION – *MODEL WLC 100*
- Variable power control (5 to 40 watts)
- Replaceable heating element
- Quality light-weight pencil iron

$36.95

DUAL-TRACE OSCILLOSCOPE
W/HIGH RESOLUTION, BLUE CRT
INCLUDES PROBES, POWER CORD
2 YEAR WARRANTY
Goldstar 5020
20MHZ **$349.00**

INSTEK FUNCTION GEN.
WITH INT/EXT FREQ. COUNTER
MODEL 8016 **$215.00**

SCOPE PROBE 60 MHZ **$12.95**
SWITCHABLE X1, X10

ALLIGATOR LEADS
SET OF 10 **$2.10**

DIGITAL MULTIMETER
WITH CAP/FREQUENCY/ TRANSISTOR TESTER
Model DM645 **$34.95**

SWITCHES
8 POS DIP ..... 60¢ ea.
Mini Toggle SPDT ..... 50¢ ea. ON-ON

PAD-234
DIGITAL/ANALOG TRAINER
Complete portable workstation. Variable and fixed power supplies, function generator, digital I/O, rugged design, high impact case.

Assembled	Kit
$150.00	$110.00

HIGH QUALITY TOOLS
With Cushion Grips and Return Spring

Needle Nose Pliers	Wire Stripper	Diagonal Cutter
$2.95	$1.50	$2.95

POWER SUPPLIES
0–30 VDC, 0–3 Amp. Built-in current limiting, overload protected, constant voltage and current operation.

01PSGP4303A	Analog Display	$165.00
01PSGP4303D	Digital Display	189.00

SOLDERLESS BREADBOARD
830 tie points. MB102PLT model features 3 binding posts and aluminum backplate.

Part No.	1-9	10+
MB102	5.95	5.00
MB102PLT	8.95	8.00

HELPING HAND WITH MAGNIFIER #060836 **$3.50**

RESISTOR KIT
1/4W 5% film. 5 pieces each of 73 values. 365 pieces total. **$3.95**

MOTION DETECTOR
$2 ea. – 10 For $15

LM555 10 Min.	22¢ ea.
LM741 10 Min.	27¢ ea.
74LS00 10 Min.	18¢ ea.
7805 Regulator 10 Min.	30¢ ea.
2N3904 10 Min.	6¢ ea.
PN2222 10 Min.	6¢ ea.
Red LED T 1¾ 10 Min.	6¢ ea.
Green LED T 1¾ 10 Min.	7¢ ea.
Yellow LED T 1¾ 10 Min.	8¢ ea.
Photo Cell 10 Min.	65¢ ea.
100K Pot., 1" Shaft PC Mt. 10 Min.	15¢ ea.

SOLDERING IRON 3-WIRE
HIGH PERFORMANCE #060501 **$5.25**

SOLDERING IRON STAND
W/SPONGE #060842 **$3.50**

1 LB. 60/40 Solder Roll .031" **$5.95**

DESOLDER PUMP W/TIP #060820 **$3.50**

15 TURN POT
69¢ ea.
Bourns 3006P series. All standard values available.

7 SEG. DISPLAY
60¢ ea.
MAN72 C.A Red 0.3"
MAN74 C.C Red 0.3"

FREE CATALOG
MORE Low-Priced Items In Our **FREE** *216-Page Catalog*

TERMS: Min. $20 + shipping. School Purchase Orders, VISA/ MC, Money Order, Prepaid. NO PERSONAL CHECKS, NO COD. NJ Residents: Add 6% Sales Tax.

In NJ: 732-381-8020
FAX: 732-381-1572

365 Blair Road • Avenel, NJ 07001-2293
800-972-2225

http://www.elexp.com
email: electron@elexp.com

Write In 67 on Reader Service Card.

3 MATURE Hi-tech precision electronics calibration product lines. Inquiry at 619-268-2976.

CONTENTS OF 10 x 20 storage unit for sale. CCTV, security systems, 300 cable filters, 300 PS-2 keyboard extention cables, 100 electronic stud finders, VHF marine radios, CBs, 500 beta tapes and three recorders, 300 tubes of ICs, 2,000 tennis dice games etc. and etc. Please send your want list and SASE to T. Schur, 2850 Sunrise Lakes Dr. W #110, Sunrise, FL 33322. 954-749-9419.

MISCELLANEOUS ELECTRONICS WANTED

DEC EQUIPMENT WANTED!!! We are buying DEC systems, boards, terminals, drives and peripherals. Also Scientific Micro Systems (SMS), DSD, Datability, Dilog, other DEC compatibles, and Computer Output Microfilm (COM) units. Please call for a quote or fax us your equipment list. We buy, sell, and trade. **KEYWAYS, INC.,** 937-847-2300 OR fax 937-847-2350.

MILITARY TRANSISTORS & DIODES & INTEGRATED CIRCUITS WANTED. ELECTRONIC MATERIAL INDUSTRIES 818-769-1002, FAX 818-769-1084.

WANTED: BALANCING machines & vibration analyzing equipment manufactured by the following: Spectral Dynamics, Hofmann, Bentley Nevada, Schenck, IRD Mechanalysis, Gishott. Contact Mike Park at E.T. Balancing, 12823 Athens Way, Los Angeles, CA 90061. 310-538-9738, FAX: 310-538-8273.

TESTERS WANTED: Immediate offers made for Ultrasonic, Magnetic Particle, Eddy Current, X-Ray and Borescopes, 24hrs. Leave detailed message with make/model. 1-800-530-3371.

WANTED: ELECTRON tubes, ICs, semiconductors. Summit, PO Box 1850, Linden, NJ 07036. Call 1-800-526-4052.

RADAR/MICROWAVE equip: Aviation, marine, fire control. Like TPS 21, APS 10, 42 APG 30. Parts, TM's, etc. Radar, Box 10215, Pittsburgh, PA 15232.

WE BUY your electronic excess inventories. ICs, caps, transistors, LED, connectors, PCBs, computers and related products. Call Tom Freeman 714-558-8813, fax 714-558-1603.

WANTED: TUBE HiFi/commercial amps, preamps, corner/horn speakers. Altec, Marantz, McIntosh, Western Electric, etc. 405-737-3312 fax 405-737-3355.

WESTERN ELECTRIC audio equipment wanted. 1926-1960s amplifiers, speakers, pre-amps, tube, transformers, etc. 1-800-old-mics 1-800-653-6427 Great Wireless Museum.

WANTED: ELECTRONIC estates. Ham, broadcasting, military, test, public address, tubes, transformers, telex equipment. The bigger the pile, the more worthwhile. We fly anywhere. Sumner McDanel 1-800-251-5454.



WANTED: EXCESS ELECTRONIC INVENTORIES, ICs, MEMORY, EPROMs, PALs, LEDs, CIRCUIT BOARDS, DIODES, AND TRANSISTORS. CALL ACTIVE MICRO, 562-494-4851 OR FAX 562-494-4913.

WANTED: TUBES, radios, transmitters, receivers, gyros, bearings, connectors, relays, lamps, synchros. Hyness Company, 709B Delair Road, Cranbury, NJ 08512-4212. Phone: 609-395-1116, FAX 609-395-1117.

OLD ICs & TRANSISTORS WANTED: HIGHEST PRICES PAID please FAX your list with part number, quantity & condition of **any semiconductors** to Rick @ ESI, 5363 Broadway Ave., Cleveland, OH 44127. 216-441-8500 FAX 216-441-8503. Since 1946! www.electronicsurplus.com

WESTERN ELECTRIC WANTED: 1920's-1960's. Amplifiers, mixers, preamps, speakers, tubes, etc. FREE OFFER 1-800-251-5454.

ELECTRON TUBES, transistors-RF aircraft radar & comm. Sold or bought. ARS Electronics, 7110 De Celis Pl., Van Nuys, CA 91406. 1-800-422-4250, fax 818-997-6158.

WANTED: MOTOROLA EXPO handhelds and parts. Must be in excellent to mint condition. 301-428-9076.

CONNECTORS WANTED. Unused surplus Bendix, Cannon, other "round plugs." Also coax, others. Fax list. 812-665-3824.

WESTERN ELECTRIC audio equipment wanted. 1927-1960's. Amplifiers, "preamps," speakers, transformers, tubes, etc. 1-800-251-5454.

WANTED: SURPLUS, excess inventories. We buy your electronic excess inventories. Call 714-236-1776 or fax your list 714-236-1778 or E-Mail: blkfea@juno.com

WANTED: HEATHKIT ID-4001 digital weather computer (working). Also wanted: Heathkit: ID-1890, ID-1990, ID-2090. Telephone: 314-567-8751.



HIGHEST PRICES paid for Western Electric tubes, new and used. Call Don Singerhouse/Singerhouse Sound. Toll free 1-888-715-tube.

Tired of Expensive Inkjet Cartridges ?

Save 90% on Inkjet Inks !

Printer	# of Refills		Cost/Refill		Kit Price	
	Black	Color	Black	Color	Black	Color
HP 500 Series, 400, Officejet 300, 350, Fax	7	14	**4.71**	**2.85**	32.95	39.95
HP 600 Series, Officejet 500, 570, 600	7	14	**4.71**	**3.21**	32.95	44.95
HP 800 Series, 1000C, 1150C, Copier 120, 210	6	10	**6.67**	**4.00**	39.95	39.95
HP 720C, 722C, 890C, 1120C	6	10	**6.67**	**4.50**	39.95	44.95
Canon BJ-10, 200, 210, 240, 250 Apple SWriter 1200, 1500	14	20	**2.15**	**2.00**	29.95	39.95
Canon BJC-4000 Series, C2500, C3000, C3500, C5000	60	60	**0.50**	**0.67**	29.95	39.95
Apple StyleWriter 2400, 2500						
Canon BJC-600, 610, 620 Apple SWriter Pro	20	13	**1.50**	**3.07**	29.95	39.95
Epson Stylus Color, Color Pro, Pro XL	12	12	**2.50**	**3.33**	29.95	39.95
Epson Stylus Color II, IIs	15	15	**2.00**	**2.66**	29.95	39.95
Epson Stylus Color 500, 200	20	17	**1.50**	**2.35**	29.95	39.95
Epson Stylus Color 400, 600, 800, 850, Photo	20	17	**1.50**	**2.65**	29.95	44.95
Lexmark JP 1000, 1020, 1100, ExecJet II, IIc, Medley 4C	10	17	**3.00**	**2.35**	29.95	39.95
Lexmark JetPrinter 5700, 5000, 7000, 7200	10	17	**4.00**	**2.35**	39.95	39.95
Xerox Home Center 450C, XJ6C Inkjet	22	12	**1.36**	**3.33**	29.95	39.95

SAVE 30 - 50% on New Compatible Cartridges!

Printer	BLACK CARTRIDGE	COLOR CARTRIDGE
Canon BJC-4000 Series, C2500, C3000, C3500, C5000	$5.50	$12.95
Apple StyleWriter 2400, 2500	$5.50	$12.95
Canon BJC-600, 610, 620 Apple StyleWriter Pro	$4.95 (9cc)	$4.95 @ (9cc)
Hi-Capacity Canon BJC-600, 610, 620	**$5.95 (15cc)**	**$5.95 @ (12cc)**
Canon BJC-70, BJC-80	$9.95 (3-pak)	$14.95 (3-pak)
Epson Stylus Color, Color Pro, Pro XL	$12.00	$19.00
Epson Stylus Color II, IIs	$14.00	$19.00
Epson Stylus Color 500, 200	$14.00	$19.00
Epson Stylus Color 400, 600, 800, 850,1520, Photo	**$14.00**	**$19.00**

- **BULK Inks, Refill Accessories**
- **Glossy card stock & Coated Paper**
- **School & Government PO's Welcome**
- **2 - 3 Day Shipping**

Quality Inks for:
HP • Epson • Lexmark
Canon • Apple • DEC

Inkjet Southwest

VISA MasterCard Discover

Call or see us online!

Monday - Friday
7:30 - 4:30 PST 10:30 - 7:30 EST

www.inkjetsw.com
(602) 668-7334 Fax

1-800-447-3469
(602) 668-0959

AMATEUR ROBOTICS NOTEBOOK

by Robert Nansel

Sometimes, you just have to do really dumb, seemingly pointless things in order to make real progress in robotics. Anyway, that's what I kept telling myself this month when I set out to build a clone of the Parallax BS2-IC.

If you remember, last month, I swapped out the weeny BS1-IC in my original Breadbot for the more powerful BS2-IC. The brain surgery was a success, the patient survived, but it was only a couple days before I was itching to do more brain surgery.

This time I wanted to try out some of the spiffy SIMMStick boards I talked about a couple months ago in the August '98 edition of this column. Rather than dump everything I've built up to this point, I decided to try out the PIC.002, a single-height SIMMStick designed for the PIC16C55 and PIC16C57. The reason I chose this particular board is that the PIC16C57 is the chip used for the BS2-IC, and Parallax separately sells a PIC16C57 with the PBASIC2 firmware burned in. One version comes in a plastic DIP28 for $25.00. That was all I needed to know to get started.

A BS2 Clone on a Stick

You may well ask why I would want to build a BS2 on a SIMMStick. After all, the Parallax version, with its surface mount construction, is smaller and lighter. And it comes preassembled. Cost? Here the SIMMStick has the advantage: even using the fancy machined-pin IC sockets that I prefer, it still cost less than $40.00, whereas a BS2-IC is $49.00. Plus I got to spend five hours building and debugging it. What a bargain.

Okay, okay, so maybe tearing my beard out for five hours getting the thing to work cancels out saving 10 bucks, but I learned plenty in the process, so I consider it a fair deal. If you follow my instructions it should take you beginners out there about an hour to build and test (and you grizzled veterans might learn — or relearn — a thing or two).



Figure 1. BS-2 SIMMStick Schematic



Figure 2. Alternative BS2 SIMMStick Programming Cable

Options, Options ...

Part of my trouble stemmed from the fact that all SIMMStick designs to date offer a plethora of options. This is a good thing, something that makes the whole SIMMStick line very hacker-friendly. However, the documentation for the first two SIMMStick designs — the (now obsolete) PIC.001 and the PIC.002 — leave a lot to the imagination (you can download the relevant document at: http://www.wirz.com/pic/docs/ds0002a.pdf). I hasten to add that from the PIC.003 on, the documentation has made great strides, and all of the DonTronics designed SIMMStick products are copiously documented.

But back to the PIC.002. First of all, the board has no silkscreened parts placement diagram. This isn't so bad because the docs do have a drawing to show where everything goes. A larger failing, though, is that there isn't a complete schematic for any of the PIC.002 board's options, including the

5 Axis Robotic Arm Kit $195.00 *Plus S&H*

We make it easy!

Lynxmotion

You can build this Robotic Arm! Impressive, fast, accurate, and repeatable motion. Any computer capable of sending 2400 or 9600 baud serial data can control the arm, even a Basic Stamp. This arm makes a great foundation for AI and motion control experiments. Position the arm in an X, Y, Z, grid with a joystick or keyboard using the new RoboMotion for Windows. The kit includes the hardware, structural components, Hitec servos, pre-assembled SSC servo controller, DOS and Windows software, and an illustrated assembly manual. Camouflage paint not included.

We have many more cool robots, check out our web page or ask for our free catalog!

3 Axis Version $155.00 • Mobile Version $250.00 • Mobile Robots Book $48.00

Lynxmotion, Inc.
104 Partridge Road
Pekin, IL 61554-1403 USA
http://www.lynxmotion.com

Tel: 309-382-1816
Fax: 309-382-1254
sales@lynxmotion.com
tech@lynxmotion.com

Write in 110 on Reader Service Card.



Figure 3. BS-2 SIMMStick Breadbot Schematic

BS2 option. There are fragments of schematics which show, for instance, how the quirky half-duplex RS-232 interface functions and what SIMMStick bus (SSBus) pins the serial EEPROM connects to, but little else.

Compounding the problem, the parts placement diagram shows some parts that aren't in any of the schematic fragments, and some parts I would expect to see (such as a brownout reset IC), are absent. When you first power-up a PIC, it can take several milliseconds for the power supply to come to full voltage, and a PIC can do peculiar things when it doesn't have enough voltage, but the MCLR\ (the PIC's reset line) is high. To prevent this, MCLR\ needs to be pulled low until power stabilizes, whether accomplished with a purpose-designed brownout reset IC or a transistor and some RC time delay.

I traced through the PCB and found a place where perhaps a simple reset transistor or a three-pin brownout reset IC could go, but the parts placement diagram showed a simple pullup resistor there instead.

And there was something weird about the programming cable schematic: it showed an outboard resistor, transistor switch combination connected between the PC serial connector's DTR pin and the PIC.002 RESET, but with the BS2-IC, DTR connects directly to the BS2-IC ATN pin, not RESET. Then I noticed that there was no pin dedicated to ATN in the SSBus pinout.

Hmmm. Time to check with a "higher authority."



Figure 4. SIMMStick BS-2 Breadbot Wiring

Parallax to the Rescue

The higher authority I consulted was the bible of things BASIC Stampish, the *BASIC Stamp Programming Manual, Version 1.8.* This is available for free download from Parallax as a PDF file (ftp://ftp.parallaxinc.com/pub/acrobat/stamp_manual_v1.8.pdf).

There on page 207 in the BASIC Stamp II section were most of the answers I was looking for, namely a full schematic of a BS2 constructed from DIP package parts. That schematic, with modifications for the PIC.002, is shown here in Figure 1; all parts designations conform with the Parallax schematic, so read the PIC.002 documentation for the tidbits about other SIMMStick configurations, but ignore the BS-2 schematics and use this article instead, at least if you want to build the BS2 option.

Incidentally, there is another BS2 schematic in the Parallax manual on page 448, but that one is for the BS2-IC using surface mount parts and is much harder to read, too, because it's so tiny.

Anyway, the schematic on page 207 showed all the missing bits, and it cleared up the ATN vs. RESET conundrum: the ATN line is driven high by the PC serial cable's DTR line when the host PC software wants to reset the BS2. A +12V RS-232 level on ATN turns Q2 ON and forces Reset down to Vss (hereafter called "ground"), but, with a 0 to -12V level on ATN, Q2 remains OFF and Reset is pulled up to Vdd by R6.

This explains the odd programming cable (Figure 2) that the original PIC.002 docs showed. Since the SSBus doesn't have a dedicated ATN line as the BS2 does, it simply places the transistor switch circuit off the board; the transistor does double duty, translating the ±12 volt RS-232 line levels to logic

Cable Converters

NEW
860E, 135 channel converter with remote, ch-3 output, AFT/MFT(auto fine tuning & manual fine tuning), parental lock, HRC/STD and sleep timer

NEW
860V, 135 channel volume control converter, with remote, ch-3/4 output, AFT/MFT, parental lock, HRC/STD and sleep timer

550E, 85 channel converter with remote unit, ch-3 output, AFT(auto fine tuing), parental lock, HRC/STD, sleep timer

Refurbished 85 channel plain converter with remote,ch-3 output, auto fine tuning, HRC/STD and sleep timer ---------- from $25

Call or Fax us for free brochures and price list

PCW CO/ (310)515-5085, (310)538-3636(Fax)



Figure 5. Installed SIMMStick BS-2

levels swinging between Vdd and Ground, and inverting the active high ATN so it works with the active low Reset. Indeed, that is the function Q1 and Q3 perform for the Serout and Serin lines.

A Little Brownout

The brownout reset IC, U3, also connects to Reset; whenever the supply voltage wanders down into the range of 4.2 to 4.5 volts (a "brownout"), U3 pulls Reset low to keep the PIC from running off into the weeds. Antti Lukats, who designed the first SIMMSticks, provided space on the PIC.002 board to put a three-pin brownout chip, though he didn't allocate specific pads for a pullup resistor.

If you use a CMOS output chip, such as the MN1381-S shown in Figure 1, then you might not need R6 as a pullup, but if you use an Open-Drain output device, such as the MN13811-S, then R6 is required. I haven't tested this latter combination, but it should work fine.

With the mysteries of ATN and Reset explained, I pondered what to do about the lack of an ATN signal in the SIMMStick pinout. One option would be to build the special programming cable with the level translator transistor built in as shown in Figure 2. Or, I could put the transistor circuitry on the breadboard chassis of Breadbot. Neither of these appealed to me. What I wanted was to make the PIC.002 board fully BS2-compatible, and that got me looking at some of those left over pads at the top of the board, just right of center. The transistor level translation circuit would fit quite comfortably there. But where to put the ATN line?

All the SIMMStick boards I'm familiar with do not use the third pin, called A3. The docs mention that it could be used for a negative supply or some such, but none of the boards I've seen actually do this (indeed, the pin is left unconnected). Since it's adjacent to Serout and Serin it would be a natural place to put ATN, though it would need a wire jumper on the back of the board. But that's what hacking is all about, right?

In the upper right of Figure 1, all the circuitry surrounding Test Point 4 is stuff I added to the PIC.002 to make it more BS2-compatible. The only area where it isn't the same as a BS2 is how I treat the RTCC real-time clock/counter input. By the way, Microchip calls pin 1 on the PIC16C57 "TOCKI," but Parallax calls it "RTCC," which makes more sense to me, so that's what I'll call it.

The Parallax BS2-IC just ties RTCC to ground, whereas the PIC.002 connects it to SSBus pin 14, and it's no problem to just tie the pin to ground on the breadboard. However, Antti provided pads for a pullup resistor for that pin, so I chose to install it (R9); it doesn't seem to bother the PBASIC2 chip that RTCC is held high, just as long as it's tied to a logic level. With R9, if I ever swap out the PBASIC2 chip for a chip with my own firmware, then I don't have to modify the board if I want to use RTCC; external sources can drive the pin with no conflict.

For all the forgoing hassles, the board goes together quite easily. I've shown all the stages of assembly, as well as test points for tests you should



Step 1. Bare PIC002 PC Board



Step 2. Install 30-pin RA header & IC sockets.



Step 3. Voltage Regulator & Reset IC



Step 4. Decoupling Capacitors

Identify and Control with
RFID
Transponders, Antennas, Reader/Decoders
for access control, personnel identification, animal feeding, pet id, race timing, ticketing, inventory control, eas, pallet control, vehicle tolling, garment management, plant routing, equipment locator , ...
Development kit US$ 139.00
Radio Frequency IDentification
Since 1991
INTERSOFT
1840 Lockmiller Rd, Estill Springs TN 37330, USA
Ph 931-967-8643 Fx 931-967-5069 www.cafes.net/intersoft

Write in 111 on Reader Service Card.



Step 5. Transistors



Step 6a. Install resistors



Step 6b. Wire jumpers and modifications.

do along the way to ensure everything works the first time. If you faithfully follow these steps, the blue smoke will stay inside your chips where it belongs, and you won't get the dreaded "Hardware not found" message from the STAMP2 software.

Do You VROC?

In bringing any microcontroller system to life, many, many hours of debugging and hair tearing can be saved if you remember this simple mnemonic:

VROC = Voltage + Reset + Oscillator + Communication

These four things (along with functioning software) are essential for every microcontroller system; if any one item in the mnemonic is wonky you are in for a frustrating experience if you can't diagnose the trouble and cure it. In order:

VOLTAGE

The chips have got to have a reasonably clean DC input in the +4.5 to +5.5 V range. With all the versions of Breadbot so far, I've been cheating a little in that I feed raw +6V directly from the battery pack to Vdd, bypassing the 5V regulator. For this reason, you can omit the regulator (U4 in Figure 1) if you like, though I recommend you put it in anyway on the theory that you never know when you will need it. Just be aware that U4 needs a minimum of 7.5 volts to provide its rated output voltage and current, so Breadbot's 6V battery pack won't cut it. That's why I use the raw 6V. But isn't that living dangerously?

It says here in the PIC microcontroller databook from Microchip that Vdd at 6V is beyond "Standard Operating Conditions," but it also says that the absolute maximum Vdd is 7.5V. There's also all sorts of legalese that essentially says, "Go ahead and use higher than 5.5V, but we won't guarantee it'll work." I may yet pay for my perfidy with a blown chip, but with 1.5 volts headroom, the odds are very good that 6V will not damage the PIC.

Feeding the MCU unregulated battery voltage can be problematic from another point of view, though, when you start building robots larger than what can be driven by hobby servos. Servos are pretty well-behaved creatures; because they are meant to operate in conjunction with sensitive superhet radio receivers, they are designed so they don't inject much noise into the power supply they share with the receiver.

For larger robots with larger motors and higher currents, you will definitely want to use regulated voltage for your controller. The hash large motors can put out can force you to provide completely separate batteries for the motors and controller, with opto-isolation for all logic signals passing between the controller and the motor drive electronics.

With little robots, we don't have those headaches — usually. If you are in doubt about how clean your battery power is, take a look at it on an oscilloscope some time when the motors are running. Even with regulators, it's a good idea to check the output with a scope. It's truly weird to see a lowly voltage regulator trying to oscillate in the megahertz range, but they will do just that if not properly bypassed with capacitors on the input and output. One clue a regulator is oscillating is that it's too hot to touch and nothing in your system is working.

In summary: Your supply voltage is guilty until proven innocent. That's why the first Test Point in Figure 1 is on the output of the regulator.

RESET

Microcontrollers, no matter who designs them, always have an unintentional extra instruction in their instruction sets, the so-called BTTG instruction ("Branch To Tall Grass"). It is invariably executed when you least expect or desire it, especially when your processor's oscillator starts clocking before the chip is fully powered up. Brownout reset ICs were invented to defeat the BTTG instruction. A simple pullup resistor will work 99% of the time, but it's that other 1% that you wind up spending 99% of your debug time on. They cost less than a buck. Use them.

OSCILLATOR

Another killer is an oscillator that doesn't. With digital microcontrollers, it's easy to forget how quintessentially analog a beastie the crystal oscillator is. For this discussion, I lump ceramic resonators with quartz crystals. I ran into oscillator problems when building my PIC.002 board. I discovered that the ceramic resonator I'd chosen wouldn't function with the PIC. I was trying to use a 20 MHz, three-pin ceramic resonator, the kind with built-in load capacitors, only I neglected to look at what the values of those load caps were. As it turned out, they were 30 pF, and when I powered up the system, the OSC1 and OSC2 lines stuck at some DC voltage partway between Gnd and Vdd, a dead giveaway (DC is, after all, not an oscillation).

When I checked the Microchip databook, it said that 15 pF is the maximum load capacitance for crystals and resonators. I didn't have any other resonators on hand, but I did have a 20 MHz crystal and a couple 15 pF caps. And that was all it took. Lesson: Make sure you see high-frequency wiggly lines on the scope when you probe Test Point 5.

Trimble GPS 400

$59.95 w/Ant



• 6 Channel
• Active Button 3" Antenna
• Sold before in Nuts & Volts @ $129.95

4x4 POWER SUPPLY
• +5, +12 @ 1 amp
• 115/230V, 50/60 cyl.
• OEM Modular

$9.95 *Quantities Available*

• MX360R - 48 ch UHF Walkie 4W Programmable..... $50
• MCX1000 - 56 ch UHF 35W Mobile Programmable..... $175
• DataRadio Modem MDM 2400 baud $100

Communications Surplus
4212 Mt. Vernon
Houston, TX 77006
713-526-8000
877-878-6GPS (6477)

Write in 112 on Reader Service Card.

COMMUNICATION

This one isn't as direly and directly related to the operation of a microcontroller but, for most systems, it's just no fun if they don't talk to the outside world in some reliable fashion, whether it be a blinky light or an RS-232 connection. When I built my board, I somehow managed to solder Q3 in backwards, and STAMP2 absolutely refused to acknowledge that I was even close to right. "Hardware Not Found," again and again. Arghh!

For RS-232 you should see signals in the range of +3V to +15V for one logic level, and -3V to -12V for the other. Measure the levels your PC actually puts on TxD (pin 3) and DTR (pin 4) of your serial cable; if the voltages are between +3V and -3V, then you have trouble with your serial card or the cable or both.

Now to Breathe Solder Smoke

Now that you know everything that can go wrong, it's time to build the board. The diagrams show in what order to solder the components and what test points to be probing at each step.

Steps 1 & 2: Install the 30-pin header so you can plug the SIMMStick into Breadbot. Orient the board in front of you so the notch is on the left and the lettering "PIC002" is visible on the right; the side of the board with



Step 7. Oscillator Options



Step 8. ICs

the lettering is the component side, and you'll be mounting all of the components from this side. Press the header pins in a bit at a time. The holes proved to be a very tight fit, so work the header pins in as best you can with needle-nose pliers.

Once you get all the pins in a little way you can flip the board over and press the board down on a flat surface until the header seats, then solder. If you are using IC sockets (a good idea), use bits of masking tape on the component side to hold them in place temporarily while you solder.

Steps 3 & 4: Install U3 and U4. The flat of U3 should face the header connector. Bend the leads of U4 so its flat lies against the copper area in the upper left corner of the board. I soldered a loop of 24 gauge bare wire as a strap to hold the plastic case in firm contact with the copper.

Next install the decoupling capacitors C1 through C3. Make sure the positive lead of the tantalum capacitor C3 is oriented to the left. Look ahead to Step 7 for a moment. Decide which of the oscillator options shown in Step 7 you are going to use. If it is one that requires load capacitors C4 and C5, then solder them in now, as well. Be sure to leave enough lead on the component side so you can bend C4 and C5 outward a bit so you have more room for the crystal or resonator, whichever you use.

Apply +7.5 volts to pin 7 and ground to pin 9 on the header and check the voltage between TP1 and TP3. It should be 5V. If it isn't, check that you haven't put U4 or C3 in backwards.

If it passes the 5V test, check the voltage between TP2 and TP3. If you still see +5V, then the "V" part of "VROC" is mostly taken care of. You'll want to check these test points for proper voltage again when you have the whole board assembled with U1 and U2 plugged in just to make sure it still works when there's a load on the regulator.

Steps 5 & 6: Solder in the transistors. Q1 and Q2 are NPN, and Q3 is PNP. The flats of the plastic cases of Q1 and Q3 should face left. Q2 should have its flat facing toward the upper edge of the board. Leave the pins of Q2 unclipped after solder until the resistors are soldered in because you'll be using the resistor leads of R6, R7, and R8 to form the reset circuit.

Form one lead of each resistor (except R5) into a loop that brings that lead back parallel with the body of the resistor (see Figure 5). Bend the leads of R5 like a staple so it fits flat on the board. Solder the resistors in place. Leave the leads of R6 through R9 unclipped.

Following the diagram in Step 6b, on the solder side of the board at location(a), bend the lower lead (not the looped lead) of R8 over so it touches the emitter lead of Q2 and flow some solder into the joint, then clip those two leads flush.

Likewise, at (b), bend the lower lead of R7 so it makes contact with both the looped lead of R8 and the base lead of Q2 and solder these joints and clip the excess leads.

At (c) bend the lower lead of R6 to the left so it touches the collector lead of Q2, then solder and snip. Finally, at (d) bend the looped lead end of R6 to contact the lower lead of R9.

At (a) and (b), make sure that you leave gaps — a paper thickness at least — between the resistor leads and the solder side of the board so they don't short to the copper traces running between the pads. It's a good idea to use a meter to check for shorts between the resistor leads and any traces they come close to.

Using 30 gauge wire wrap wire, make jumpers JP1 through JP3 and solder in place. Check for proper continuity between the lower lead of R6 at (c) and pin 28 of U1 and pin 8 of the SSBus; ATN (the looped lead of R7) should be connected with pin 3 of the SSBus; (a) should be connected to ground, pin 9 of the SSBus; (d) should be connected to Vdd, pin 7 of the SSBus.

Power up the board again and measure the voltage at TP4. With nothing connected to either pins 3 or 8 of the SSBus, you should see something near +5V. If you apply -12V to ATN, you should see no change. Apply +12V and TP4 should drop to ground. Likewise, when you temporarily connect Reset (pin 8) to ground, TP4 should also go to ground.

Steps 7 & 8: Solder in the crystal or resonator you've chosen. With the crystal it's important to make sure the metal case doesn't short against either of the adjacent load cap leads. Leave a gap of about 1/8 inch between the crystal case and the PC board as shown in Step 7 and in Figure 5.

Item	Description	Vender	P/N
C1, C2	0.01 µF 50WV, 5%, polyester	Digi-Key	P4582-ND
C3	10 µF, 16 V tantalum	"	P2038-ND
C4, C5	15 pF 5% monolith ceramic cap	"	P4839-ND
J1	30-pin single row, RA header	"	S1111-30-ND
J2*	8-pin DIP IC socket, .3" rows	"	ED333308-ND
J3*	28-pin DIP IC socket, .6" rows	"	ED3628-ND
PCB	PIC15C57 SIMMStick board	Wirz Elex	PIC.002
Q1, Q2	2N3904 NPN, 40V, 100mA, TO-92 case	Digi-Key	2N3904DICT-ND
Q3	2N3906 PNP, " " "	"	2N3906DICT-ND
R1, R4, R6*	4.7K ohm, 1/4 watt, 5% carbon film	"	4.7KQBK-ND
R2, R3, R5	8.2K ohm, " " " " "	"	8.2KQBK-ND
R7, R8, R9	10K ohm, " " " " "	"	10KQBK-ND
U1	PIC16C57 with PBASIC2 firmware	Parallax	PBASIC2/P
U2	2k byte serial EEPROM	Digi-Key	24LP16B/P-ND
U3*	Reset voltage detector, 4.5V, CMOS	"	MN1381-S-ND
U4*	+5V positive regulator, TO-92	"	NJM78L05A-ND
XTAL*	20 MHz crystal, HC49/US case	"	X438-ND

*see text

As always, if you have suggestions for improving Breadbot, if you've built a Breadbot, or if you have questions or comments about amateur robotics topics, as usual you can reach me at:

Robert Nansel
69 S. Fremont Ave. #2
Pittsburgh, PA 15202
E-Mail: bnansel@nauticom.net

Finally, using precautions against static discharge, install U1 and U2 with their orientation notches facing left as shown in Step 8.

Ready or Not

Apply power to the finished board. If anything gets hot, begins to smoke, sparks, or otherwise behaves unexpectedly, remove power immediately. If everything is fine, recheck the voltages at all the test points. In particular, make sure you see oscillations at TP5.

If all these tests check out, you are ready to connect the BS2 programming cable. If you've diligently performed the "V," "R," and "O" tests of VROC, don't be surprised if the board works the first time (though if it doesn't, you still have the Q1 and Q3 RS-232 level-shifter circuits to check).

Once everything is working, try TESTBB3.BAS. First you'll need to rewire Breadbot as shown in Figures 4 and 5. Those of you who've followed this series so far know the drill — pull out a few old jumpers and add some new ones. The rest of you, where have you been? Read the Breadbot construction articles starting with June '98. If you don't have the back issues, get online and order some.

Next Time

I'm getting eager to explore other boards that really show the performance potential of SIMMSticks. PBASIC is fine for first experiments, but I want something that really screams, and for that we'll be looking at other languages, including — gasp — some assembly language. Until then, keep on VROCing. **NV**

Suppliers Mentioned:

Digi-Key Corp.
701 Brooks Ave. South
Thief River Falls, MN 56701-0677
1-800-344-4539
http://www.digikey.com

DonTronics:
http://dontronics.com

Parallax, Inc.
3805 Atherton Road #102
Rocklin, CA 95765
1-888-512-1024
http://www.parallaxinc.com

RadioShack
1-800-THE-SHACK
http://www.radioshack.com

Wirz Electronics SIMMSticks:
http://www.wirz.com

WANTED: AVIONICS test equipment, IFR, 600A, 401L, others, Collins, King, Sperry, North Atlantic, Litton INUs LTN series, rate and tilt tables, air data test sets, 941-625-3222 P, 941-625-0494 F, E-Mail: avionics@afcon.net

WANT USED or surplus DC motor controls or adjustable frequency AC drives, 1/2 HP and up. DC motors fractional to 3 HP. C. Woodruff, 5507 55th Ave. S., Seattle, WA 98118. Voice/Fax 206-723-8487.

BBS & ONLINE SERVICES

VISIT DON Lancaster's **GURU'S LAIR** website at **http://www.tinaja.com** PICs, pseudoscience, PostScript, patents, Tinaja quests, flutterwumpers, book-on-demand, magic sinewaves, money machines, Navicubes, tramways, wavelets, and Webmastering. Online reprints, consultants net, forums, annotated hot links, surplus bargains, great heaping bunches more.

MOD CHIPS for Sony PlayStation. Now your backups will work. Only $9.95 ea. + $3 shipping. Call 1-888-467-6150, all major credit cards accepted. Computers & components at wholesale prices. www.cconusa.com

EDUCATION

START YOUR OWN TECHNICAL VENTURE! Don Lancaster's newly updated **INCREDIBLE SECRET MONEY MACHINE II** tells how. We now have autographed copies of the Guru's underground classic for $18.50. Synergetics Press, Box 809-K, Thatcher, AZ 85552. 520-428-4073. VISA/MC.

DON LANCASTER'S ACTIVE FILTER COOKBOOK is back in print. Autographed copies of the seventeenth(!) classic printing $28.50. **SYNERGETICS PRESS**, Box 809-N, Thatcher, AZ 85552. 520-428-4073. Visa/MC.

GRAND UNIFIED THEORY MADE EASY. 110 page book explains a new theory linking gravity, electronics & magnetism. Explores universe mysteries, goes beyond relativity & quantum theory. **$9.95**. To order: send check or M/O to American Science Innovations, PO Box 155, Clarington, OH 43915.

WANTED: SOMEONE to teach me PIC and/or single board computers. I have some knowledge, but need more! I have a project that needs stepper motor controls, among other things. Would like to find someone in the central NJ area if possible. E-MAIL: GARYBAL@AOL.COM

BUSINESS OPPORTUNITIES

MILITARY COMPONENTS wanted. Capacitors, resistors, diodes, transistors, semiconductors, ICs. Electronic Material Industries, 818-769-1002, FAX: 818-769-1084.

COUNTER SURVEILLANCE=$250 HR! Electronic eavesdropping is unbelievably widespread! Are you sure you're safe? Learn how others (without prior experience) earn **$250 HR** in the fascinating field of COUNTER-SURVEILLANCE! For FREE catalog call: **1-800-732-5000.**

MILLIONS $$$ in "scrap gold" from old computers and electronics junk. Message: 603-645-4776 or www.tiac.net/users/quiksand/goldtek.htm

START YOUR OWN TECHNICAL VENTURE! Don Lancaster's newly updated **INCREDIBLE SECRET MONEY MACHINE II** tells how. We now have autographed copies of the Guru's underground classic for $18.50. Synergetics Press, Box 809-K, Thatcher, AZ 85552. 520-428-4073. VISA/MC.

THE CASE AGAINST PATENTS. Thoroughly tested and proven alternatives that work in the real world, $28.50. **SYNERGETICS PRESS,** Box 809-N, Thatcher, AZ 85552. 520-428-4073. Visa/MC.

REPAIRS – SERVICES

AVANTEC COMPANY: we provide **low cost SMT,** thru-hole, electromechanical assembly, reworks, test fixtures, cables, PCB layout design, **programmable logic controller** consulting. **714-532-6191.**

WELD ALUMINUM WITH PROPANE! EZ, INEXPENSIVE, STRONG. DETAILS: WEEKS, 36 CAROLINA ST., TAYLORS, SC 29687. 1-800-547-WELD(9353) FAX 864-244-6349. http://www.dura-fix.com

SERVICE REPAIR TIPS for **FREE! PROFESSIONAL BOARD LEVEL & COMPONENT LEVEL REPAIRS for TVs, VCRs, projection TVs, CAMCORDERs,** CD players, audio and other repairs on computer disk. **ADD** your repairs. **PRINT** out repairs. **BACKUP** & save **your** repairs. Want to share your repair tips? If you do, we'll send you **FREE** updates! Ask about our TIP EXCHANGE policy. For IBM compatible computers with a hard drive. Get your **FREE Stage 1 SERVICE TIPS Now! FREE CALL. CALL NOW 1-800-215-5081.**

PICS, GALS READ if you've lost your masters. Programming service available. Call for info. Network Sales, 616-683-0500.

Unlock a World of Performance!

ACE COMPUTERS

Delivering Power and Performance for Less Since 1983

1425 East Algonquin Road
Arlington Heights, IL 60005



(847) 952-6900
(847) 952-6901 FAX
1-800-ACE-5936
www.acecomputers.com

"A Power User's Delight. " - **Computer Buyer's Guide, Summer 1998**

"Fast all around and affordable - an excellent value " - **Computer Buyer's Guide and Handbook, July 1998**

"High quality components, Fast speed and Reasonable price - A real business workhorse!" - **PC Today, June 1998**

"Ace loads its system with enough high end components to turn a power user's head." - **Computer Shopper, August 1997**

Top 100 Direct Vendor - PC Computing, February 1998

"A fine system that would be valuable to any business - A great value" - **PC Today, July 1998**

"BEST BUY - Ace has put together a system that's sure to please just about any consumer." - **Computer Buyer's Guide and Handbook, May, 1998**

"BEST BUY - The right blend of nice touches - a computer worth seriously thinking about when it's time to buy." - **Computer Buyer's Guide and Handbook, August 1998**

***Optional on-site warranties available on all systems!**

Intel® FINANCIAL Leasing Available!

SERVICES

"We accept all major credit cards. We accept Fortune 1000, Government, and Educational Institution Purchase Orders. We respond to invitations for governmental and educational open bids. Business leasing available to qualified applicants. Prices, appearance, and specifications subject to change without notice. 17" monitors are 15.9" VIS or better, 19" monitors are 18.0" VIS or better. Certain models may include upgraded components. All custom configurations are available. 15% restocking fee on returns of custom-built systems. 30 day return policy does not include shipping charges, incurred damages, or service charges. All returns must include original packaging, accessories, and documentation in as-new condition. Monitors may be manufactured by third parties. Viewable sizes of monitors vary. The Intel inside logo and Pentium are registered trademarks of Intel Corp.

Pro Series Notebooks

TRACER SERIES
- Intel Pentium® 233MHz Processor with MMX® Technology
- 12.1" Active Matrix
- 20X CD-ROM and 1.44M Floppy
- 64 Megs SDRAM
- 3GB Hard Drive
- 56KB Fax/Modem
- 3D Sound with speakers
- Touchpad Mouse
- Full Travel Keyboard
- Carrying Case Included!
- Windows 98 Included!
- 1 Year Warranty

INTEL PENTIUM® 200 w/ MMX® - $1669
INTEL PENTIUM® 233 w/ MMX® - $1699
Business/Personal lease as low as $64/Mo, 36 Months

TRAVELER 2000 SERIES
- Intel Mobile Pentium® II Processor
- 14.1" Active Matrix Screen - 4M RAM!
- 24X-CD ROM and 1.44M Floppy
- 32 Megs SDRAM
- 3 GB Hard Drive
- 512K L2 Cache
- 56KB Fax/Modem
- 3D Sound with speakers
- Touchpad Mouse and Full Keyboard
- Smart Lithium Ion Battery
- Carrying Case Included!
- Windows 98 Included!
- 1 Year Warranty

INTEL PENTIUM® II 233 - $2989
INTEL PENTIUM® II 266 - $3289
Lease for as low as $99/Mo, 36 Months

Discovery Station
- Intel Pentium® II or Celeron® Processors
- 32 Megs SDRAM/4.3 GB Ultra ATA Hard Drive
- 32X Speed CD-ROM Drive/1.44M Floppy
- USR 56K - V.90 Fax/Modem
- ATI Rage Pro 3D-AGP w/4M RAM
- 17" Monitor - 0.28 Dot Pitch
- Yamaha 3D Sound with Speakers
- Microsoft Intellimouse Mouse/104 Kb
- Mini-Tower or Desktop Case w/6 Bays
- Windows 95/98 or Windows NT 4.0(Add $99 for NT)
- 3 Year Complete Warranty Included

CELERON® 266 -$ · CELERON® 300 -$ · CELERON® 300A-$ · CELERON® 333A-$
PENTIUM®II 266 - $1249 · PENTIUM®II 300 - $1299 · PENTIUM®II 333 - $1399 ·

Business/Personal lease as low as $47/Mo, 36 Months

Discovery Station
- Intel Pentium® II Processor w/512K Cache
- 32 Megs SDRAM/4.3 GB Ultra ATA Hard Drive
- 32X Speed CD-ROM Drive/1.44M Floppy
- USR 56K - V.90 Fax/Modem
- Diamond Stealth 3D-4000 AGP w/4M RAM
- 17" Monitor - 0.28 Dot Pitch
- Creative® PCI Wavetable Sound with Speakers
- Microsoft Intellimouse Mouse/104 Kb
- Mini-Tower or Desktop Case w/6 Bays
- Windows 95/98 or Windows NT 4.0(Add $99 for NT)
- 3 Year Complete Warranty Included

PENTIUM®II 266 - $1249 · PENTIUM®II 350 - $1549
PENTIUM®II 300 - $1299 · PENTIUM®II 400 - $1749
PENTIUM®II 333 - $1399 · PENTIUM®II 450 - $1949
Business/Personal lease as low as $47/Mo, 36 Months

Home/Office Pro +
- Intel Pentium® II Processor w/512K Cache
- 64 Megs SDRAM / 6.5GB Ultra ATA Hard Drive
- 32X Speed CD-ROM Drive/1.44M FDD
- US Robotics 56KB V.90 Fax/Modem
- Matrox Productiva G100 AGP with 8M
- Goldstar 17" Monitor - 0.26 Dot Pitch
- Sound Blaster 64 AWE with Subwoofer
- Microsoft Ergonomic Style Mouse/104 KB
- Mini-Tower or Desktop Case w/6 Bays
- Win 95/98 or Windows NT 4.0(Add $99 for NT)
- Microsoft Office 97 Included!
- 3 Year Complete Warranty Included

PENTIUM®II 266 - $1649 · PENTIUM®II 350 - $1949
PENTIUM®II 300 - $1699 · PENTIUM®II 400 - $2149
PENTIUM®II 333 - $1799 · PENTIUM®II 450 - $2349
Business/Personal lease as low as $61/Mo, 36 Months

Dreamedia System
- Intel Pentium® II Processor w/512K Cache
- 64 Megs SDRAM/ 13.6GB Ultra ATA Hard Drive
- Creative Labs 2X DVD-ROM Drive/1.44M Floppy
- US Robotics 56KB V.90 Fax/Modem
- Matrox G200 AGP with 8M SGRAM
- 19" SVGA Monitor with 1600 x 1280 Res.
- Sound Blaster 64 with Subwoofer Speakers
- Microsoft Ergonomic Style Mouse/104 Kb
- Mini-Tower Case w/6 Bays
- Windows 98 or Windows NT 4.0(Add $99 for NT)
- Microsoft Office 97 Included!
- 3 Year Complete Warranty Included

PENTIUM®II 266 - $2199 · PENTIUM®II 350 - $2499
PENTIUM®II 300 - $2249 · PENTIUM®II 400 - $2699
PENTIUM®II 333 - $2349 · PENTIUM®II 450 - $2899
Business/Personal lease as low as $78/Mo, 36 Months

Subscribe to Nuts & Volts.

Check out our web site and take advantage of our special subscription offer.

http://www.nutsvolts.com

For new subscribers OR renewals!

order toll-free 1-800-669-5810

AMAZING MINI MICRO FM RADIO!
$7.50

Much lighter than a heavy jam box with really good sound! This tiny radio (1.5"x1.06"x0.38") has a seek button, reset control, and an on/off switch. Personal listening has never sounded better! Ideal for ballgames, studyhall, and workouts.

Battery and nugget style earphones included.

Precision Security Screwdriver Set $6.95

An assortment of torx screwdrivers designed for regular or tamperproof screws. Five different precision sizes, from T6 - T10. Great for computer work, audio components, and other applications requiring precision and/or security screwdrivers. Color coded handles make finding the right size easy. A must for every technician's toolbox!

megamagnets!

Neodymium 'rare earth' magnets are super strong! Only 1/4" thick, we've made these magnets cling together through your hand, a door, even a paperback novel! Approx. Dimensions: 1-3/8" x 1-3/4" x 3/8", slightly curved. Caution: These Magnets are very strong, not for use with small children, computer disks, or credit cards!
Megamagnets $12.50/pair

$5.00 OFF

You can find Gateway Electronics on the Internet **www.gatewayelex.com** and now we offer shopcart online ordering. When you place your order, reference coupon nv981 and receive $5.00 off* your purchase.

*this coupon is only valid on orders shipped UPS. Coupon expires January 31, 1999. One coupon per customer / address. Coupon cannot be used for amateur radios. Not valid with any other offer. No cash value. $10.00 mailorder minimum applies after coupon.

GLOBE Gearhead Motor *with shaft encoder* $14.50

Perfect for many projects, this little DC motor operates on 3-24 volts. It features a 1/4" dia. shaft (machined flat) about 3/4" long. The body diameter is 1-3/16", and the gear box diameter is 1-3/8". The overall length (excluding the shaft) is 3-1/2". The no-load speed at 3v is 7rpm, at 6v 18rpm, and at 9v 29rpm. If you want more, try 12v for 41rpm, or at 24v you'll get 85rpm. Whether you are building a super robot, creating a laser display, or anything in between, this motor provides flexibility of design at a low cost. (Data sheet included)

PHOTON II MICROLIGHT

The popular photon microlight has been improved. These super-bright (better than 8 candellas!) LED lights are visible over a mile away. The LED is secured in a tough ABS case and offers a squeeze button for quick use, and a constant on slide switch for prolonged lighting needs. The lithium batteries last a very long time (10 year shelf life!) and are included. The light won't burn out because it is an LED! Specify your choice of five incredible bright colors. Great for home or office use, popular with fire and rescue professionals, pyrotechnicians, stage performers, and dimly lit restaurant patrons. PHOTON II microlights include a keyring and come in ruby red ($13.50), amber yellow ($13.50), sapphire blue ($17.50), diamond white ($17.50), and emerald green ($17.50). Includes two replaceable 2016 lithium batteries.

ANIMAL SOUNDS PIANO KIT
$29.95

This project kit has ten keys for playing notes of the scale and eight buttons to select the sounds associated with each note. Select the piano mode and the kit will synthesize piano sounds for each key. OR select one of seven different animal voices including cat, dog, pig, bird, chicken, duck, and sheep. Old MacDonald never had a choir like this! The circuit features an auto power-off function, a demo mode, and easy step-by-step instructions. Requires 2 AA batteries not included.

THE FINE PRINT : PRICES SUBJECT TO CHANGE WITHOUT NOTICE * GATEWAY IS NOT RESPONSIBLE FOR PRINTING ERRORS * MASTERCARD, VISA AND DISCOVER ACCEPTED * YES, WE'LL TAKE YOUR CHECK -- SORRY, NO C.O.D.s * $10 MERCHANDISE MINIMUM ON MAIL ORDERS * SUPPLY OF SOME ITEMS IS LIMITED * PRICES DO NOT INCLUDE SHIPPING * UPS GROUND SHIPPING/HANDLING WITHIN THE CONTINENTAL U.S. (ITEMS REQUIRING ADDITIONAL AMOUNTS ARE NOTED)...$4.25 FOR THE FIRST ITEM, $0.50 FOR EACH ADDITIONAL ITEM. RESTOCKING CHARGE MAY BE ASSESSED ON RETURNED ITEMS. WHERE ARE WE GOING? AND WHAT'S WITH THIS HANDBASKET?

BE A FLY ON THE WALL!!!

Well, actually, those little wings would look pretty stupid on you, but you can build a miniature "bug". Surface mount technology is the latest techno-buzz word, and a challenging new frontier for kit builders. The manufacturer understood that the first try might be a bit rough, so they included enough components to assemble two units. (so it is o.k. to lose or damage a SMT component!) With the entire FM broadcast band (from 88 - 108 MHz) for your receiver, and a transmit range of 300 feet, even James Bond would like this kit! This unit is powered by a 1.5 volt watch battery (included) and features an electret type high gain microphone for superior audio quality and extended pick up range - hear a whisper at 10 feet.
A lot of fun in less than a square inch!!!
Micro Size FM Wireless Transmitter Kit $19.95

Lighted Screwdriver Supertool!
$9.95

At first glance, this appears to be an ordinary screwdriver, but press a button on the base and two lights illuminate the area you are working on. Nifty, huh? But wait, there's more! The seven interchangeable bits are stored right there at the base of the screwdriver (6 storage slots) for easy access. No handles to unscrew or tool boxes to dig through. Hey, you ain't seen nothin' yet...remove the bit and the magnetic retrieval tool telescopes from the screwdriver shaft! Incredible!!! Of course, the comfort grip handle and rugged construction are icing on the cake! Definitely a 'gotta have it' tool!

for other neat stuff surf the internet
www.gatewayelex.com

gateway
ELECTRONICS, INC
8123 PAGE BLVD
ST. LOUIS, MO 63130
(314)427-6116

9222 CHESAPEAKE DR.
SAN DIEGO, CA 92123
(619)279-6802

2525 FEDERAL BLVD.
DENVER, CO 80211
(303)458-5444

MAIL ORDERS CALL
TOLL-FREE
1-800-669-5810

FAX ORDERS (314)427-3147

PINBALL MACHINES! Books, Magazines, Manuals, Diagrams, Supplies, Parts. $2 catalog, Marco Specialties, 5290-N Platt Springs Rd., Lexington, SC 29073-9252. 803-957-5500. FAX 803-957-6974. E-Mail: tilt@ix.netcom.com http://pinballmachine.com

(E)EPROM PROGRAMMING done quickly and economically. One day turn around typical. Simple copy $3 per device. Also prototyping, design, and consulting services available. Call or send SASE to: **Luzer Electronics, 4023 North Bayberry, Wichita, KS 67226. 316-687-2127, FAX 316-687-3103.**



SEMICONDUCTOR CROSS-REFERENCE LIBRARY (SCRL) software with 378,000+ devices, drawings, and descriptions for the PC, $69 plus $6 S&H. Add on modules: **ELECTRONIC REPAIR TIPS,** 74,000+ original tips, $30. **FCC ID CODES** listings, $10. **SAMS PHOTOFACTS** complete listing, $10. **SEMICONDUCTOR MANUFACTURERS LISTINGS,** 107,000+ devices $20. Subscribe to our monthly updates and $ave. Checks & credit cards accepted. E-Mail: sales@electronic-repair.com Web: http://www.electronic-repair.com Custom Software Creators, PO Box 30415, Clarksville, TN 37040 931-647-6120. Fax 931-551-4128.

PC BOARDS REPAIRED. Prices start at $5. Minimum 5 of one type. Network Sales, 616-683-0500.

ENGINEERING CONSULTING. Product development from conceptual to manufacturing stages. Digital, analog, and RF expertise. Microcontroller designs for HC05xx, HC11xx, and PIC families. Software design for IBM PC. XILINX and Altera FPGA design. In-house schematic capture and PWB. Hicks Electronic Design, PO Box 7366, Loveland, CO 80537-0366. Toll Free 1-888-849-6792 E-Mail: steve@hickseng ineering.com website: www.hickseng ineering.com

WE ARE LOOKING FOR NEW DISTRIBUTORS FOR NUTS & VOLTS MAGAZINE.

If you are interested in selling Nuts & Volts in your store or on your newsstand, we have a great deal for you!

FOR COMPLETE INFORMATION, ASK FOR OUR NEW DISTRIBUTOR FLYER.

Nuts & Volts Magazine
430 Princeland Court
Corona, CA 91719
phone 909-371-8497
fax 909-371-3052
E-Mail
distributors@nutsvolts.com

Write in 69 on Reader Service Card.

Continued from page 13

software companies immediately abandoned floppy stacks in favor of using CD-ROMs to distribute software. It was cheaper by far, and cooler, too.

Consequently, no one has 2.88 floppy drives, no one needs them, and no one sells them or the disks. 1.44 floppy disks are not compatible with 2.88s.

Evan Weaver
Hockessin, DE

ANSWER TO #9983 - SEPT. 1998

Omega (www.omega.com, **1-800-826 6342**) makes salinity meters, but they are not cheap. CDH-287-KIT (which is not a construction kit) is $740.00 and their CDH-420 is $815.00.

These meters measure salinity indirectly by measuring the conductivity and the temperature of the sample. When salt dissolves in water, its constituent ions (e.g., Na+ and Cl-) separate. The ions will support a current flow, and more salt means more ions and higher conductivity.

Unfortunately, the conductivity is temperature dependent, so the meter must also measure the temperature and estimate the conductivity at standard temperature.

The standard conditions for measuring salinity are 15 degrees Celsius and one atmosphere, so the meter calculates what the conductivity would be if the sample were at 15 degrees.

The salinity in percent is calculated by dividing that conductivity by the conductivity of a solution of KCl (mass fraction = 32.4356e-3) at 15 degrees.

You could do the calculations yourself if you had a thermometer and a conductivity meter. The problem is salt water is very conductive and exceeds the range of Omega's inexpensive conductivity meters. An appropriate conductivity meter would cost about $400.00

Making your own conductivity meter is possible, but there are many subtle problems. You could buy a cheap conductivity meter less than $100.00 and dilute the sample to put it within the meter's range, but then you wouldn't want to make many measurements.

Gerald Roylance
Mountain View, CA

ANSWER TO #99810 - SEPT. 1998

The best answer to your steering problem would be to de-couple the motor from one of the two sets of wheels, providing another motor for the de-coupled wheels. This way you would have full control of a dual-motor vehicle. But this solution is easier said than done, so here is a more practical alternative.

Allow all wheels to remain driven by the single drive motor, but add a small device to the front of the vehicle that will be your steering module. This module will simply contain two elements: a servo motor (like the ones used in model R/C planes and cars), and a guide wheel approximately 3" or 4" in diameter (available at hobby stores).

The wheel will provide a direction of movement for the vehicle, like the rudder of a ship. The direction will be determined by the servo motor which simply places the wheel in the desired angle for turning.

Your vehicle will resist turning, tending to drive straight ahead, so you will have to mount the steering module in such a way that the front end of the vehicle is lifted off the ground slightly, say a couple of 1/16 of an inch or so. You'll have to experiment to determine the right amount of elevation.

The beauty of this approach is that you now have a couple of interesting alternatives for controlling your vehicle.

If you're into computers and programming, you could use a BASIC Stamp to control the vehicle and its steering module.

If you desire control via radio frequency, you could employ a multi-channel transmitter/receiver system (also available at hobby stores) which could easily control not only

Quality Reconditioned
TEST EQUIPMENT

Hewlett-Packard 8657A
$3,900.00
Signal Generator, 100 kHz to 1040 MHz, 10 Hz resolution, output power +13 to -143.5 dBm into 50Ω. Option 002, RF connectors on rear panel.

Hewlett-Packard 3561A
$8,250.00
Dynamic Signal Analyzer, .000125 Hz to 100 kHz, +27 to -120 dBV, 80 dB dynamic range, to 640 µHz resolution bw.
3561A Opt 001 $8,750.00
(extended non-volatile memory)

Hewlett-Packard 8566B
$39,500.00
Spectrum Analyzer, 100 Hz to 325 GHz with external mixers (not provided), amplitude range of -134 to + 30 dBm.

Hewlett-Packard 3325B
$4,350.00
Synthesized/Function Generator, 1 µHz to 21 MHz, functions include; sine, square, triangle, ramps, dc offset, internal programmable modulation source, LOG, LIN, & discrete sweep. Excellent signal purity.

Hewlett-Packard 5342A
Special $1,350.00
Microwave Frequency Counter, 500 MHz to 18.0 GHz, wide FM tolerance, 11 digit led display, sensitivity to -25 dBm. Opt 001, high stability time base; 011, HP-IB.

Hewlett-Packard 8903B
$3,500.00
Audio Analyzer, 20 Hz to 100 kHz, combines the functionability of a low distortion audio source, frequency counter, high performance distortion analyzer, SINAD meter, and a ac/dc voltmeter.

Hewlett-Packard 8350A/83545A
$3,250.00
Sweep Oscillator Mainframe with Sweep Oscillator plug-in. Plug-in capabilities; 5.9 to 12.4 GHz frequency range, 50 mW max leveled power, complete HP-IB programmability.

Hewlett-Packard 3586B
Special $850.00
Selective Level Meter, makes carrier measurements to 32.5 MHz, voice channel measurements from 50 Hz to 100 kHz, can use 3336B level generator as an automatic tracking generator. Options available.

Hewlett-Packard 3336B
Special $850.00
Synthesizer/Level Generator, excellent precision source from 10 Hz to 21 MHz, frequency resolution of .001 Hz, level accuracy within .15 dB over full range, AM and phase modulation.

Hewlett-Packard 54504A
$3,750.00
Digitizing Oscilloscope, 400 MHz repetive bw, 50 MHz single-shot bw, 250 ps repetative time interval, 2 channel, 200 MSa/s digitizing rate.

Hewlett-Packard 54112D
$2,750.00
Digitizing Oscilloscope, 400 MSa/s, 4 channel, 64 k samples of memory, 100 MHz repetive and single-shot bw.

Hewlett-Packard 8349A
$2,250.00
Microwave Amplifier, 2 to 20 GHz coverage, 15 dB gain to 18.6 GHz.

Hewlett-Packard 8349B
$3,900.00
Microwave Amplifier, 2 to 20 GHz coverage, 15 dB gain to 18.6 GHz.

Hewlett-Packard 8671A
$4,250.00
Microwave Frequency Synthesizer, 2.0 to 6.2 GHz, +8 dBm minimum output power.

EIP 545
Special $750.00
Microwave Frequency Counter, 10 Hz to 18 GHz frequency range(3 bands), 12 digit LED display, time base: 10 MHz, aging rate <3x10⁻⁷/month, 50Ω input.

EIP 545A
Special $895.00
Microwave Frequency Counter, 10 MHz 18 GHz frequency range(3 bands),12 digit LED display, time base: 10 MHz, aging rate <3x10⁻⁷/month, 50Ω input.

Wavetek 3520
$$3250.00
Signal Generator, 1 to 2800 MHz, -137 to +10 dBm, frequency resolution is 100 Hz to 1040 MHz and 200 Hz to 2800 MHz, GPIB , 32 front panel stored settings.

Tektronix 2213A
Special $600.00
60 MHz Oscilloscope, 2mV sensitivity, 5 nS/div sweep speed, advanced trigger system. Includes 2 probes.

Tektronix 2430A
Special $3750.00
150 MHz Digital Oscilloscope, 100 MS/s digitizing rate, simultaneous acquisition on 2 channels, envelope mode with 2 ns glitch capture. Has Opt. 05, TV/Video waveform measurement; 11, probe power.

Tektronix 2465A
$3950.00
350 MHz Oscilloscope, 4 channel, 1 ns risetime, 2 mV/div vertical sensitivity at 350 MHz, auto setup, save and recall setups, on-screen trigger-level readout, volts and time cursors with on-screen readout. Has Opt. 05, TV/Video waveform measurement; 11, rear panel probe power.

Tektronix 466
Special $575.00
100 MHz Storage Oscilloscope, dual trace, 5 mV/div, stored writing speed of 3000 div/µs variable persistence. Includes 2 probes.

Tektronix 465
Special $550.00
100 MHz Oscilloscope, dual trace, 5 mV/div sensitivity, 5 nS/div sweep rate. Includes 2 probes.

Visit us at our website www.danbar.com

WANTED USED TEST EQUIPMENT

(602) 483-6202
Fax (602) 483-6403
14455 North 79th Street, Unit #C • Scottsdale, Arizona 85260

DANBAR SALES COMPANY

Write in 95 on Reader Service Card.

your steering module, but provides additional channels for controlling other items such as a wireless camera, remote arm, etc.

K. A. Delahoussaye
Melbourne, FL

ANSWER TO #9989 - SEPT. 1998

The idea to use the early IBM PC monochrome monitor is interesting, but not very feasible. The IBM monochrome units works so well because the coating (phosphor) that lights up to form the dots on the screen has a very slow decay characteristic.

After the electron beam strikes the phosphor, it takes a long time to stop emitting light. This is great for a static computer display, but with moving video images will give a terrible ghosting to the image. I do not reccomend trying this idea.

It may be possible to use this for a monitor with a notebook PC. You will need to see if you have a driver to get the display output to support the old monochrome standard. It is a long shot!

Bob Kelly
Poway, CA

ANSWER TO #9986 - SEPT. 1998

The best way to get all four drives working is to use a secondary IDE controller, assuming all four drives are IDE. The Promise EIDEMax is about $20.00 in stores and works with an existing IDE controller, plus large drive support.

If parallel/IDE support is still needed, H45 has an IDE/parallel adaptor kit for about $70.00. It can be ordered via http://www.necx.com.

Kuo-Sheng Chang
San Francisco, CA

ANSWER TO #9984 - SEPT. 1998

Rather than modifying the CCD camera, I suggest that you make a simple change to the viewing monitor. If you reverse the horizontal deflection coil wiring, you will conveniently convert the CRT to display a "mirror" image.

The deflection coil is found on the neck of the monitor's CRT (picture tube). You will see four taps: two for vertical and two for horizontal. If you unsolder the horizontal related connections and merely swap them, the image will be backwards (or upside down if you choose the wrong set).

If you want normal operation from the monitor, install a DPDT toggle switch that flips the wiring when desired.

T. Black
Folsom, CA

ANSWER TO #9985 - SEPT. 1998

The power output and frequency of your transmitter is regulated by the FCC and unless they okay that frequency which you are using to be used at a higher power, then you're stuck.

Stationary relay transmitters are commonly used in large cities, but mobile repeaters? Check with the FCC.

You will probably have to go with a more powerful legal radio or use a cell phone.

Chris
Bieber, CA

ANSWER TO #9987 - SEPT. 1998

I doubt very seriously that the device you mention works in the microwave range because microwaves don't stop at the wood, they bounce heavily, and are absorbed by any hydrogen atom including the water molecules in your body.

Ultra Sonics on the other hand do a similar trick with a more localized effect and are harmful only at very short distances.

Ultra Sonic welders are designed for welding plastics, melting plastics, curing glues, and are widely available to most industries.

To get the parts and information that you will need to build a unit you should inquire with a manufacturer or distributor of Ultra Sonic equipment, which you can find in the yellow pages under welding equipment, or Ultra Sonics depending on where you live.

Also the Dealer Direct, Business-

ALL ELECTRONICS CORPORATION

QUALITY PARTS
FAST SHIPPING
DISCOUNT PRICING

CALL, WRITE, FAX or E-MAIL For A Free 96 Page CATALOG.
Outside the U.S.A. send $3.00 postage.

Special Low Price! AA NICKEL-CADMIUM RECHARGEABLE BATTERY
Motorola
0.56" dia.X 1.97" long
CAT# NCB-AA
$1.25 each
10 for $11.00
100 for $100.00

104 KEY WINDOWS 95 KEYBOARD

Windows 95' compatible, light touch membrane keypad. Spill resistant. Five foot cord with small din connector - fits most late-model machines. LED indicators for Numbers, Caps and Scroll Lock. Very sharp looking keyboard with charcoal background and dark rose colored keys.
CAT # KBD-4
10 for $60.00
$7.00 each

RED Ultrabright LED
PAINFULLY BRIGHT RED LED
2500 to 4000 mcd @ 20 ma. These T 1 3/4 (5 mm diameter) red LEDs are significantly brighter than conventional LEDs. At close range, they are painful to look at. They are great for attention getting displays that can be seen from a distance. Water clear in off-state.
CAT # LED-42
2 for $1.20
10 for $5.00
100 for $45.00
1000 for $400.00

Piezoelectric Element
1.32 DIAMETER X 0.16"
AVX/Kyocera # KBT-33RB-2CN
Metal encased piezoelectric acoustic generator. High durability. Small, thin shape. Designed for telephone use. Inside the metal case is a 1.28" diameter piezo element with 5.5" leads attached. If you're looking for a plain element with leads, the case can be pried apart fairly easily. CAT# PE-39
2 for $1.00
100 for $40.00
1000 for $250.00
(25¢ each)

1.5 Vdc Vibration Motor
Namiki # 3L
Designed for use as a signalling device in pagers and cell phones. Overall length, including weighted shaft, 0.83". 0.23" diameter. Shaft diameter, 2 mm. Operates on 1.5 Vdc @ 65 mA.
CAT # DCM-108
$1.75 each

6 Amp RFI/EMI Filter
CDE # APF600CET
1.18" x 0.8" x 1.63".
Solder terminals
CAT # EMI-62
$1.50 each
10 for $12.00 • 100 for $85.00

"White" LED
1100 mcd white led
T 1 3/4 (5mm) diameter Jumbo LED emits a bright white light. 3.6-4 Volt @ 20 ma. 45º viewing angle when lit.
CAT# LED-48 $4.75 each

UV Blacklight
New black-light lamps designed by Avon Cosmetics to highlight dry skin. They have a built-in timer that shuts-off the lamp after approximately one minute. Ideal for lighting fluorescence in black-light posters, gemstones, hand stamps and US currency. 5" lamp, F4T5BLB, is housed in a lightweight plastic case. 7" x 3.25" x 2.3" high. Powered by a 12 Vdc, 500 ma wall transformer (included). Individually boxed.
CAT# UVL-1
$10.00 each
F4T5-BLB. Replacement lamp for fixture above. CAT # BLB-5 $3.00 ea.

1" SPEAKER WITH POLYPROPYLENE CONE
8 ohm, 0.1 watt speaker with clear polypropylene cone. Only 0.15" thick. Good sound quality for its size. Large quantity available.
CAT # SK-218
$1.00 each
10 for $8.50
100 for $70.00
1000 for $500.00

Great Price! "EAR BUD" STEREO EARPHONES
Miniature "in-ear" earphones for use with most portable CD, radio and tape players. Gold-plated 3.5 mm stereo phone plug. 32 ohm impedance.
Large Quantity Available
CAT #HP-6
85¢ each
10 for $7.50
100 for $50.00

"HI-8" Video Cassette
SONY Hi-8 Top quality, metal particle 120 minute video cassettes. *Used for a short time, then bulk-erased.* Each cassette has its own plastic storage box.
CAT # VCU-8
$3.00 each
10 for $28.00 • 100 for $250.00

ORDER TOLL FREE 1-800-826-5432
MAIL ORDERS TO:
ALL ELECTRONICS CORP.
P.O. BOX 567
VAN NUYS, CA 91408-0567
FAX (818) 781-2653 • INFO (818) 904-0524
INTERNET http://www.allcorp.com/
E-MAIL allcorp@allcorp.com

NO MINIMUM ORDER • All Orders Can Be Charged to Visa, Mastercard, American Express or Discover • Checks and Money Orders Accepted by Mail • Orders Delivered in the State of California must include California State Sales Tax • NO C.O.D • Shipping and Handling $5.00 for the 48 Continental United States - ALL OTHERS including Alaska, Hawaii, P.R. and Canada Must Pay Full Shipping • Quantities Limited • Prices Subject to change without notice.

MANUFACTURERS - We Purchase EXCESS INVENTORIES... Call, Write, E-MAIL or Fax YOUR LIST.

Write in 96 on Reader Service Card.

to-Business, or several other larger city yellow page books will have the information you need.

With any luck and a good prying technique, they will tell you the operating frequency and power of their units.

Having seen inside a few machines, they range from primitive CW power units to transistorized switching units which allows the power to be more focused and adjustable.

Chris
Bieber, CA

ANSWER TO #9988 - SEPT. 1998

DTMF decoder/recorders can be purchased from several sources, including Mike Sandman Enterprises, www.sandman.com and Optoelectronics ww.optoelectronics.com.

If you want to build your own, then consider the BASIC Stamp microcontroller from Parallax, Inc. (www.parallaxinc.com).

You will need a BASIC Stamp, their 8K Serial EEPROM AppKit, and their DTMF transceiver Appkit.

You will also need to gather a few other low-cost components.

You will need to write a little S/W (the Stamp is quite fun to use).

T. Black
Folsom, CA

ANSWERS TO #99811 - SEPT. 1998

An outdoor thermal (IR) sensor is incorporated into those motion sensing lights that are readily available in the hardware stores. I have seen the assembly with two floodlight sockets for $10.00. An item in the Sept. '98 *Nuts & Volts* "Electronics Q & A" (page 48) shows a way to get a contact closure signal from the sensor.

There are computer boards that sense and create switch closures to tie that signal to your PC. It would also allow you to operate other equipment such as a bell or light when the PC program decides there is reason to sound the alert.

As far as an indoor sensor, All Electronics 1-800-826-5432, has a passive infrared detector (PIR) Cat# IR-145 that has a 40-foot detection range.

Denis Kuwahara
via Internet

ANSWERS TO #99811 - SEPT. 1998

If Nick wants to detect someone outside his house, my method will do the job and not tie up his PC.

Purchase a $12.00 floodlight motion detector (with four-second walk/test feature) and do this:

Run #14 three-wire cable to the unit. Discard the floodlight sockets, tie the hot lead from the detector to the red wire and bring it to a duplex outlet (the neutral will be there). Use a 12-volt AC wall transformer to a buzzer circuit. When the motion detector is activated the buzzer will sound (for four seconds).

This is an effective and inexpensive detection system.

Arlin Hatfield
via Internet

ANSWERS TO #99811 - SEPT. 1998

Nick, you can purchase ready-made IR motion detector circuits, and you can get controller modules that hook them up to the PC via the X-10 standard.

By setting up two detectors in a row on the path to the door, you can see whether the subject is approaching or moving away from your house. By setting up at least one detector per room and/or doorway, you can see who is where inside the house.

Some of the current X-10 modules even includes color cameras, universal remotes, and so on.

Here are some URLs to check out: **http://www.x-10.com, http://www.smarthome.com,** and **http://www.smarthomesystemsusa.com**

Kuo-Sheng Chang
San Francisco, CA

Looking for a great value? Subscriptions to *Nuts & Volts* are only $19 for a full year. Call *Toll Free* and use your Visa or MasterCard to order! 1-800-783-4624

RAMSEY

World's Smallest TV Transmitters

We call them the 'Cubes'.... Perfect video transmission from a transmitter you can hide under a quarter and only as thick as a stack of four pennies- that's a nickel in the picture!

Transmits color or B&W with fantastic quality - almost like a direct wired connection to any TV tuned to cable channel 59. Crystal controlled for no frequency drift with performance that equals law enforcement models that cost hundreds more! Basic 20 mW model transmits up to 300' while the high power 100 mW unit goes up to 1/4 mile. Audio units include sound using a sensitive built-in mike that will hear a whisper 15 feet away! Units run on 9 volts and hook-up to most any CCD camera. Any of our cameras have been tested to mate perfectly with our Cubes and work great. Fully assembled - just hook-up power and you're on the air!

C-2000, Basic Video Transmitter Cube.....$89.95
C-3000, Basic Video and Audio Transmitter Cube.....$149.95
C-2001, High Power Video Transmitter Cube.....$179.95
C-3001, High Power Video and Audio Transmitter Cube.....$229.95

Super Pro FM Stereo Radio Transmitter

A truly professional frequency synthesized FM Stereo transmitter station in one easy to use, handsome cabinet. Most radio stations require a whole equipment rack to hold all the features we've packed into the FM-100. Set frequency easily with the Up/Down freq buttons and the big LED digital display. Plus there's input low pass filtering that gives great sound no matter what the source (no more squeals or swishing sounds from cheap CD player inputs!) Peak limiters for maximum 'punch' in your audio - without over modulation, LED bargraph meters for easy setting of audio levels and a built-in mixer with mike and line level inputs. Churches, drive-ins, schools and colleges find the FM-100 to be the answer to their transmitting needs, you will too. No one offers all these features at this price! Kit includes cabinet, whip antenna and 120 VAC supply.

We also offer a high power export version of the FM-100 that's fully assembled with one watt of RF power, for miles of program coverage. The export version can only be shipped outside the USA, or within the US if accompanied by a signed statement that the unit will be exported.

FM-100, Professional FM Stereo Transmitter Kit.....$299.95
FM-100WT, Fully Wired High Power FM Transmitter.....$429.95

AM Band Radio Transmitter

Ramsey AM radio transmitters operate in the standard AM broadcast band and are easily set to any clear channel in your area. Our AM-25, 'pro' version, fully synthesized transmitter features easy frequency setting DIP switches for stable, no-drift frequency control, while being jumper setable for higher power output where regulations allow. The entry-level AM-1 uses a tunable transmit oscillator and runs the maximum 100 milliwatts of power. No FCC license is required, expected range is up to 1/4 mile depending upon antenna and conditions. Transmitters accept standard line-level inputs from tape decks, CD players or mike mixers, and run on 12 volts DC. The Pro AM-25 comes complete with AC power adapter, matching case set and bottom loaded wire antenna. Our entry-level AM-1 has an available matching case and knob set for a finished, professional look.

AM-25, Professional AM Transmitter Kit.....$129.95
AM-1, Entry level AM Radio Transmitter Kit.....$29.95
CAM, Matching Case Set for AM-1.....$14.95

CCD Video Cameras

If you're looking for a good quality CCD board camera, stop right here! Our cameras use top quality Japanese Class 'A' CCD arrays with over 440 line line resolution, not the off-spec arrays that are found on many other cameras. You see, the Japanese suppliers grade the CCDs at manufacture and some manufacturers end up with the off-grade chips due to either cost constraints or lack of buying 'clout'. Also, a new strain of CMOS single chip cameras are entering the market, those units have about 1/2 the resolution and draw over twice the current that these cameras do - don't be fooled! Our cameras have nice clean fields and excellent light sensitivity, you'll really see the difference, and if you want to see in the dark, the black & white models are super IR (Infra-Red) sensitive. Our IR-1 Illuminator kit is invisible to the human eye, but lights the scene like a flashlight at night! Color camera has Auto White Balance, Auto Gain, Back Light Compensation and DSP! Available with Wide-angle (80°) or super slim Pin-hole style lens. They run on 9 VDC and produce standard 1 volt p-p video. Add one of our transmitter units for wireless transmission to any TV set, or add our IB-1 Interface board for audio sound pick-up and super easy direct wire hook-up connection to any Video monitor, VCR or TV with video/audio input jacks. Cameras fully assembled, including pre-wired connector.

CCDWA-2, B&W CCD Camera, wide-angle lens.....$99.95
CCDPH-2, B&W CCD Camera, slim fit pin-hole len.....$99.95
CCDPH-2, Color CCD Camera, wide-angle lens.....$149.95
IR-1, IR Illuminator Kit for B&W cameras.....$24.95
IB-1, Interface Board Kit.....$24.95

FM Stereo Radio Transmitters

Microprocessor controlled for easy frequency programming using DIP switches, no drift, your signal is rock solid all the time - just like the commercial stations. Audio quality is excellent, connect to the line output of any CD player, tape deck or mike mixer and you're on-the-air. Foreign buyers will appreciate the high power output capability of the FM-25; many Caribbean folks use a single FM-25 to cover the whole island! New, improved, clean and hum-free runs on either 12 VDC or 120 VAC. Kit comes complete with case set, whip antenna, 120 VAC power adapter - easy one evening assembly.

FM-25, Synthesized FM Stereo Transmitter Kit.....$129.95

A lower cost alternative to our high performance transmitters. Offers great value, tunable over the 88-108 MHz FM broadcast band, plenty of power and our manual goes into great detail outlining aspects of antennas, transmitting range and the FCC rules and regulations. Connects to any cassette deck, CD player or mixer and you're on-the-air, you'll be amazed at the exceptional audio quality! Runs on internal 9V battery or external power from 5 to 15 VDC. Add our matching case and whip antenna set for a nice finished look.

FM-10A, Tunable FM Stereo Transmitter Kit.....$34.95
CFM, Matching Case and Antenna Set.....$14.95
AC12-5, 12 Volt DC Wall Plug Adapter.....$9.95

RF Power Booster

Add some serious muscle to your signal, boost power up to 1 watt over a frequency range of 100 KHz to over 1000 MHz! Use as a lab amp for signal generators, plus many foreign users employ the LPA-1 to boost the power of their FM Stereo transmitters, providing radio service through an entire town. Runs on 12 VDC. For a neat, professionally finished look, add the optional matching case set.

LPA-1, Power Booster Amplifier Kit.....$39.95
CLPA, Matching Case Set for LPA-1 Kit.....$14.95
LPA-1WT, Fully Wired LPA-1 with Case.....$99.95

Treasure Finder Kit

Search for buried treasure at the beach, backyard or park. This professional quality kit can detect metal at a depth of up to 6 inches. Easy to use, just listen for the change in tone as you 'sweep' the unit across the surface - the larger the tone change - the larger the object. Has built-in speaker or earphone connection, runs on standard 9 volt battery. Complete kit includes handsome case, rugged PVC handle assembly that 'breaks down' for easy transportation and shielded Faraday search coil. Easy one evening assembly. This nifty kit will literally pay for itself! That guy in the picture looks like he found something - what do you think it is - gold, silver, Rogaine, Viagra? You'll have fun with this kit.

TF-1, Treasure Finder Kit.....$39.95

Binocular Special

We came across these nice binoculars in an importers close-out deal. Not some cheap in-line lens jobs, these beauties have roof prisms, a super nice rubber armored housing over light weight aluminum. 10 x 25 power with fully coated optics. Includes lens cleaner cloth, neck lanyard and nice carry case. For extra demanding use in bright sun, choose the EX module with ruby coated Objective lens. First quality at a close-out price! We've seen the exact same units with the 'Bushnell' name on them being sold for $30 more!

BNO-1, Binoculars and case.....$24.95
BNO-1EX, Ruby Coated Lens Binoculars and case.....$29.95

Speech Descrambler

Decode all that gibberish! This is the popular descrambler / scrambler that you've read about in all the Scanner and Electronic magazines. Speech inversion technology is used, which is compatible with most cordless phones and many police department systems, hook it up to your scanner speaker terminals and you're in business. Easily configured for any use: mike, line level and speaker output/inputs are provided. Also communicate in total privacy over telephone or radio, full duplex operation - scramble and unscramble at the same time. Easy to build, all complex circuitry contained in new custom ASIC chip for clear, clean audio. Runs on 9 to 15VDC. Our matching case set adds a professional look to your kit.

SS-70A, Speech Descrambler/Scrambler Kit.....$39.95
CSS, Custom Matching Case and Knob Set.....$14.95
SS-70AWT, Fully Wired SS-70A with Case.....$79.95
AC12-5, 12 Volt DC Wall Plug Adapter.....$9.95

Call for our Free Catalog !
See our complete catalog and order on-line with our secure server at:
www.ramseyelectronics.com

RAMSEY ELECTRONICS, INC.
793 Canning Parkway Victor, NY 14564

Order Toll-free: 800-446-2295
Sorry, no tech info, order status at this number

Technical Info, Order Status
Call Factory direct: 716-924-4560
Fax: 716-924-4555

VISA MasterCard DISCOVER

ORDERING INFO: Satisfaction Guaranteed. Examine for 10 days, if not pleased, return in original form for refund. Add $6.95 for shipping, handling and insurance. Orders under $20, add $3.00. NY residents add 7% sales tax. Sorry, no CODs. Foreign orders, add 20% for surface mail or use credit card and specify shipping method.

Write in 97 on Reader Service Card.

Continued from page 15

ly and easily; pinpointing unexpected and unwanted files and directories as well as important changes over time. Space Watch v3 is the first and only program to provide space ownership search and analyzes on both Netware and NT systems — at the same time.

For more information contact SharpeWare, 10 Gallow Hill, Peebles EH45 9BG, Scotland. E-Mail sales@sharpeware.com, Web http://sharpeware.com. A free full function 30-day shareware version is available for download from: http://www.sharpeware.com/pub/swatch3.zip.

ORGANIZE YOUR IMAGES — WITH PHOTO BASE DELUXE

AxisSoft has released Photo Base Deluxe 1.2 for Windows 95, a program for organizing your pictures into a neat database.

Photo Base Deluxe is a picture-database. The program is very useful in situations where you have a lot of pictures and want to organize these in a friendly system. You can put all the pictures into one database and organize them into 24 categories. The original file-format of the pictures is maintained in the database, so it's easy to get the original back again.

Photo Base Deluxe 1.2 for Windows 95 costs $49.95 for a single user license. Site licenses are available. For more information, contact AxisSoft, Rijnweg 17, 1628 PB, Hoorn, Netherlands. Voice: (31) 229-211626. Fax (31) 229-213379 or visit our URL: http://www.axissoft.com.

CREATE CLOUDS OF SOUND WITH ARP-X8

Metaphoric Software has released Arp-X8, the newest member of the Techno Toys family of electronic music production programs for Windows 95, 98, and NT.

Arp-X8 is an "octal arpeggiator," which uses the input from a standard MIDI keyboard to produce up to eight simultaneous, independent melodic lines.

Each of the eight arpeggiators has separate controls for MIDI channel, program, motion algorithm, rhythm, and more. Arp-X8 combines these settings with input from the keyboard to produce music that can range from simple arpeggios to rich, rhythmically complex clouds of sound.

Like all Techno Toys, Arp-X8 is fully interactive, with all output automatically recorded to a MIDI file for export to conventional sequencers. Multiple instances of Arp-X8 are automatically synchronized, and can sync to any other program or device that utilizes MIDI clock messages.

Arp-X8 sells for $24.95, and can be downloaded from the Techno Toys web site at http://www.technotoys.com. For more information, send E-Mail to info@technotoys.com.

LANGUAGE TUTOR GOES JAVA

Arro & Wartoft has released Selingua in Java — a Java version of the award-winning language tutor Selingua.

Selingua is an easy-to-use program that helps you learn 2,000 words in any of the languages English, French, German, Spanish, and Swedish. Seven varied exercises, including a crossword exercise, let you quickly build your vocabulary.

A pleasant way to make your five-minute breaks productive! You are welcome to try the demo version at http://www.aw.nu/java.

24 Hr. Shipping

To Order Call 1-800-292-7711 Fax: (847) 541-9904

Quality Kits for Hobbyist and Students

All Kits include PCB, all parts, and detailed assembly manuals.

XK-700 Digital / Analog Trainer

Elenco's newest advanced designed Digital / Analog Trainer is specially designed for school projects. It is built on a single PC board for maximum reliability. It includes 5 built-in power supplies, a function generator with continuously sine, triangular and square wave forms. 1560 tie point breadboard area. Tools and meter shown optional (Mounted in a professional tool case made of reinforced metal).

XK-700 Assembled and Tested $189.95

XK-700-SEMI KIT w/ Fully Assembled PC Board $174.95

XK-700K - Kit $159.95

Made in the USA

SOLDERLESS KITS NEW

TALKING CLOCK KIT AK-220 $14.95
- Dual analog/digital
- Rooster crows every hour.
- Easy-to-build

No Soldering Required

35mm Camera Kit AK-540 $14.95
Learn all about Photography
No Soldering Required

ELECTRONIC KEYBOARD KIT AK-900 $24.95
- 37 mini-size keys
- 8 tempo rhythms
- 4 custom drums

Call for a FREE 64 page catalog! (800) 445-3201

REMOTE CONTROL CAR KIT AK-870 $24.95
- 7 functions
- Remote control included

No Soldering Required

Hobbiest Tool Kit TK-1000 $39.95
All the tools you'll need to build these kits. 25 tools contained in a heavy-duty carrying case.

Stereo Cassette Player Kit AK-200 $14.95
- Transparent Case
- Belt Clip
- High Resolution
- Includes Headphones

M-1005K Digital Multimeter Kit $19.95
Low cost, 3 1/2 digit LCD, 18 ranges, transistor test, diode test, overload protection and pocket-size.

AM/FM-108K $29.95
AM/FM Radio Kit and Training Course 14 Transistors and 5 Diodes

AM Radio Kit and Training Course 7 Transistors and 1 Diode $19.95

FO-30K Fiber Optics Technology with Training Course $24.95
Learn the basics of fiber optics data communications while you build this exciting kit. Comes complete with all necessary components.

Telephone Kit Model AK-700 $15.95
Build this high-tech see-thru plastic telephone. Learn theory on how telephones work and then proudly show off your work with the transparent phone case. Complete with all parts and manual. Neon lamps flash when the phone rings.

AR-2N6K 2 meter / 6 meter Amateur Radio Kit $34.95

Elenco XP-720K Power Supply Kit $54.95
Made in USA
- 3 fully regulated stackable DC supplies. +1.5VDC to 15VDC @ 1A - 1.5VDC to 15VDC @ 1A +5VDC @ 3A
- Plus 2 AC supplies: 6.3VAC @ 1A 12.6VAC @ 1A

Strobe Light Kit Model AK-520 $54.95
You will have fun building this kit and learn how strobe lights work. Complete with all parts and case.

AK-300 Digital Roulette Kit $14.95
This Digital Roulette Kit is just like the real thing. With a push of a button, the LEDs spin round and round. Where they stop is anybody's guess. It's unique design includes "pop out" chips of different values. Enjoy hours of fun with this game of chance. Requires one (1) 9V battery.

Sound Activated Switch Model K-35
Clap and the light comes on, clap again and it goes off.

Telephone Bug Model K-35 $7.95
Size of a dime, yet transmits both sides of a phone conversation to any FM radio. No battery needed.

Motion Detector Kit Model AK-510 $14.95
Simple and fun to build. Compact, portable, and adds safety to your home or office. Requires one (1) 9V battery.

Guaranteed Lowest Prices
UPS SHIPPING: 48 STATES 5%
OTHERS CALL FOR DETAILS
IL Residents add 8.25% Sales Tax

C&S SALES, INC.
150 W. CARPENTER AVENUE
WHEELING, IL 60090
FAX: (847) 541-9904 • (847) 541-0710
http://www.elenco.com/cs_sales

15 DAY MONEY BACK GUARANTEE
FULL FACTORY WARRANTY
PRICES SUBJECT TO CHANGE WITHOUT NOTICE

Write in 160 on Reader Service Card.

Don Lancaster's

RESOURCE BIN

number eighty one

New secrets of military surplus (Part 1).

Our usual reminder here that the *Resource Bin* is a two-way column. You can get tech help, consultant referrals, and off-the-wall networking on nearly any electronic, *tinaja questing*, personal publishing, money machine, or computer topic by calling me at **(520) 428-4073** weekdays 8-5 Mountain Standard Time.

Secrets of Mil Surplus

Something around $687.54 worth of US military surplus will get sold *each second*. Day in and day out. At prices which average well under one penny per dollar of initial acquisition costs. Everything from superb commercial electronic test equipment through aerobic exercise gear to live horses.

A few major changes have recently happened that can make bidding and participating in military surplus sales ridiculously simpler and much easier than it once was.

You can now handle nearly everything on the web and pay by VISA. Sometimes the goodies are even delivered right to your door.

On the other hand, at least one of their new bidding methods is not at all small scale or end-user friendly. And around half of the DRMO outlets are scheduled to close within a very few months or so.

I've been playing around with mil surplus. So I thought I'd share some of their secret insider stuff with you. Because your needed resource listings are unusually detailed, I will split this topic into two columns. Your first starting point on all this involves visiting ...

http://www.drms.com

This url is the federal surplus home page. Both this site and their overall operation is called DRMS. Or short for *Defense Reutilization Marketing Service*. Their individual base stores are called DRMOs. Brief for *Defense Reutilization Marketing Offices*.

Your first thing to do is to click on *Public Sales* and then go to *Catalogs*, followed by *Listed by DRMS/DRMO Location*. This should give you a quick picture of just what is being offered where. Next, you use the list and your own knowledge and the addresses in our resource sidebars to pin down the bases you can easily travel to; those bases that you can possibly get to; and those bases your cousin in Omaha or a business associate can reach.

Every DRMO site is not necessarily having a sale all the time.

NEXT MONTH:
Part II of major new opportunities in mil surplus electronics.

So, it pays to verify their catalog list every few days or so to see what pops up.

In my own case, those "we deliver" RCP sites plus *Huachucha*, *Tucson*, and *Luke* are fairly close by. *Kirtland* and *Hollomon* are painful but useful. I will sometimes bid at harder-to-reach sites such as *Bliss*, *Cannon*, *Nellis*, *29 Palms*, *Barstow*, at *Fort Irwin*, or *Edwards*. But only if something exceptional is really worth making the lengthy trip will I purposely underbid by my travel and pickup expenses. Plus a tad more.

Finding Offered Items

There are three kinds of documents you'll find associated with each sale. The *Dynamic Listing* is a rather brief summary which more or less itemizes what is offered in each lot number. The dynamic listings supposedly will become stable 10 days before the bid close. But any item can be withdrawn at any time for internal reuse.

The *Official Catalog* has the brief but guaranteed description for each item or lot. Dynamic listings tend to go up earlier. The official catalogs may miss their web posting or go up late. In these cases, you have to use a polling fax or snail mail instead.

The third type is an *Inventory Value* document you'll have to generate all by yourself. You do this by using the fine DRMS search service to dump a list of the current inventory for your target site. These sheets show you the acquisition costs for each item, the bid dates, and the condition codes.

They also give you the FSC (Federal Supply Code) number. Your first four digits of this number can give you a clue as to exactly what type of item is being offered. Note that a "bowser" in class 2330 is literally a totally different animal than a class 8820 "bowser."

By searching for everything in a four-digit class, you can get a feel for the type of beast you are bidding on.

You may have to use smaller print and a landscape output to get all the columns to list properly.

Note that obvious misprints may or may not be. A "tirpod" could indeed be a useful thing to sit a video camera on. Or it could be part of the de-icing mechanism for some C-130 wing spar. While fiction and satire writers may be attracted to the "irony aluminum," I believe that this term really means aluminum scrap with hard-to-remove steel parts stuck to it.

Beware of listed "even value" costs such as $10.00 or $50.00. These are probably made up fictions that may or may not represent true prices.

There are several different types of sales. Each has its unique problems and opportunities. Let's list them here in the order I find most useful ...

Local Sealed Bid Sales

These are often your best bet. They typically consist of mixed lots of old and new stuff. Like salting a heap of Tektronix 565 doghouse scopes with a single newer 465. Rather often, there are very few bidders or no bidders at all on certain items. So you might be able to name your own price. Your usual ploy is to make reasonable bids on stuff you want and token bids on anything even remotely useful.

These sales usually start off with a 26-XXXX for Eastern US sales or else a 46-XXXX for Western US. Or at least in the "20s" or "40s."

The feds quite strongly suggest you *carefully inspect before you bid!* Which often prevents rude surprises such as ending up with poorly misdescribed trash. Or my finding out a load bank I won was ridiculously larger and far heavier than I thought it would be.

On one hand, inspection is plain old common sense. But on the other, there's no way to tell if an otherwise clean piece of test equipment has an internal problem. Even with a close look. And you can bid higher if you do not have the time and expense of a special inspection trip.

National Sales

A *National Sale* gathers together the *listed* offerings of a dozen bases into one combined catalog. Items tend to be of better quality and are much less assorted. Prices tend to end up higher because more bidders are attract-

new from
DON LANCASTER

ACTIVE FILTER COOKBOOK
The sixteenth (!) printing of Don's bible on analog op-amp lowpass, bandpass, and highpass active filters. De-mystified instant designs. $28.50

CMOS AND TTL COOKBOOKS
Millions of copies in print worldwide. THE two books for digital integrated circuit fundamentals. About as hands-on as you can get. $28.50 each.

RESEARCH INFOPACKS
Don's instant cash-and-carry flat rate consulting service. Ask any reasonable technical question for a detailed analysis and complete report. See www.tinaja.com/info01 for specifics. $75.00

INCREDIBLE SECRET MONEY MACHINE II
Updated 2nd edition of Don's classic on setting up your own technical or craft venture. $18.50

LANCASTER CLASSICS LIBRARY
Don's best early stuff at a bargain price. Includes the CMOS Cookbook, The TTL Cookbook, Active Filter Cookbook, PostScript video, Case Against Patents, Incredible Secret Money Machine II, and Hardware Hacker II reprints. $119.50

LOTS OF OTHER GOODIES

Tech Musings V or VI	$24.50
Ask the Guru I or II or III	$24.50
Hardware Hacker II, III or IV	$24.50
Micro Cookbook I	$19.50
PostScript Beginner Stuff	$29.50
PostScript Show and Tell	$29.50
Intro to PostScript Video	$29.50
PostScript Reference II	$34.50
PostScript Tutorial/Cookbook	$22.50
PostScript by Example	$32.50
Understanding PS Programming	$29.50
PostScript: A Visual Approach	$22.50
PostScript Program Design	$24.50
Thinking in PostScript	$22.50
LaserWriter Reference	$19.50
Type 1 Font Format	$16.50
Acrobat Reference	$24.50
Whole works (all PostScript)	$380.00
Technical Insider Secrets	FREE

BOOK-ON-DEMAND PUB KIT
Ongoing details on Book-on-demand publishing, a new method of producing books only when and as ordered. Reprints, sources, samples. $39.50

THE CASE AGAINST PATENTS
For most individuals, patents are virtually certain to result in a net loss of sanity, energy, time, and money. This reprint set shows you Don's tested and proven real-world alternatives. 28.50

BLATANT OPPORTUNIST I
The reprints from all Don's Midnight Engineering columns. Includes a broad range of real world, proven coverage on small scale technical startup ventures. Stuff you can use right now. $24.50

RESOURCE BIN I
A complete collection of all Don's Nuts & Volts columns to date, including a new index and his master names and numbers list. $24.50

FREE SAMPLES
Check Don's Guru's Lair at *http://www.tinaja.com* for interactive catalogs and online samples of Don's unique products. Searchable reprints and reference resouces, too. Tech help, hot links to cool sites, consultants. email: *don@tinaja.com*

FREE US VOICE HELPLINE VISA/MC

SYNERGETICS
Box 809-NV
Thatcher, AZ 85552
(520) 428-4073

RESOURCE BIN

MIL SURPLUS DRMO OFFICE LISTINGS (PART 1)

DRMO Alpha
Operation Joint Guard
Taszar, Hungary
APO AE 09793
Phone: 0036-82-426-740
Fax: 0036-82-426-739

DRMO Aberdeen (*)
Bldg 3620
Aberdeen PG MD 21005
Phone: 410-278-2235
Fax: 410-278-9220

DRMO Albany (*)
Bldg 1331 Dr 12 Topside
Marine Corps Logistics
Albany GA 31704
Phone: 912-439-5966
Fax: 912-439-5972

DRMO Anchorage
Bldg 34-600 Davis Highway
Elmedorf AFB AK 99506
Phone: 907-552-3733
Fax: 907-552-7548

DRMO Anniston
Bldg 282 AAD
7 Frankford Ave
Anniston AL 36201
Phone: 205-235-7837
Fax: 205-235-4468

DRMO Barstow
Marine Corps Logistics
Base Bldg 226 Boll Ave
Barstow CA 92311
Phone: 760-577-6568
Fax: 760-577-6526

DRMO Beaufort (*)
Box 55021
Bldg 1173
Beaufort, SC 29401
Phone: 803-522-7499
Fax: 803-522-7048

DRMO Belvoir (*)
8150 Beulah Street #101
Fort Belvoir VA 22060
Phone: 703-806-5632
Fax: 703-806-5567

DRMO Benning
Bldg 470
10th Mountain Div Rd
Benning GA 31905
Phone: 706-545-7214
Fax: 706-545-5125

DRMO Bitburg, Germany
Unit 4025
Bldg 1093
54634 Bitburg Germany
Phone: 011-49-6561-2484
Fax: 011-49-6561-2484

DRMO Bragg
Bldg J-1334 Knox St
Ft Bragg NC 28307
Phone: 910-396-5298
Fax: 910-396-7364

DRMO Bupyong
Unit #15395
APO AP 96283-0120
Phone: 011-82-32-524-4629
Fax: 011-82-32-520-6889

DRMO Campbell
Box 555 Bldg 5212
Fort Campbell KY 42223
Phone: 502-798-3525
Fax: 502-798-5183

DRMO Cannon
110 W Street
Cannon AFB NM 88103
Phone: 505-784-2436
Fax: 505-784-2012

DRMO Cherry Point
Bldg 154 D, Cleveland Dr
Marine Corps Air Station
Cherry Point NC 28533
Phone: 919-466-2743
Fax: 919-466-4075

DRMO Chievres, Belg
Unit #451 Bldg 66
Chievres Air Base
7950 Chievres Belgium
Phone: 011-32-68-27-5484
Fax: 011-49-06-31-4617

DRMO China Lake (*)
Naval Air Weapons Station
China Lake CA 93555
Phone: 760-939-2502
Fax: 760-939-0162

DRMO Colorado Springs
Bldg 318
Fort Carson CO 80913
Phone: 719-526-9678
Fax: 719-526-3656

DRMO Columbus
3990 E Broad St
Bldg 14
Columbus OH 43213
Phone: 614-692-3244
Fax: 614-692-3149

DRMO Corpus Christi
Bldg 22 Naval Air Station
Corpus Christi TX 78419
Phone: 512-961-2936
Fax: 512-961-3203

DRMO Crane
Naval Surface Warfare Ctr
Bldg 300 Highway 361
Crane IN 47522
Phone: 812-854-1554
Fax: 812-854-1998

DRMO Denver (*)
Bldg 621 Rocky Mtn Arsenal
Commerce City CO 80022
Phone: 303-289-0376
Fax: 303-289-0523

DRMO Drum Annex
10th Mountain Division
Bldg S-1350
Ft Drum NY 13602
Phone: 315-772-4592
Fax: 315-772-5809

DRMO Duluth
4997 Airport Rd
Duluth MN 55811-1517
Phone: 218-723-7441
Fax: 218-722-2611

DRMO Dyess
box 9545
358 Ammo Rd
Dyess AFB TX 79607
Phone: 915-696-2578
Fax: 915-696-3450

DRMO Edwards (*)
70 East Forbes Avenue
Edwards AFB CA 93524
Phone: 805-277-2209
Fax: 805-277-7039

DRMO Eglin
Bldg 525
Transportation Rd
Eglin AFB FL 32542
Phone: 850-882-2822
Fax: 850-882-4789

DRMO El Toro (*)
Bldg 319
Marine Corp Air Station ET
Santa Ana CA 92709
Phone: 714-726-4937
Fax: 714-726-3151

DRMO Ellsworth
650 Twining
Ellsworth AFB SD 57706
Phone: 605-385-1018
Fax: 605-385-1615

DRMO F E Warren (*)
7700 Booker Rd Bldg 930
Cheyenne WY 82005
Phone: 307-773-3970
Fax: 307-773-4160

DRMO Fairbanks
Bldg 5001
1/4 Mile Badger Rd
Fort Wainwright AK 99703
Phone: 907-353-7406
Fax: 907-353-7416

DRMO Fairchild
120 N Foulois Ave.
Fairchild AFB WA 99011
Phone: 509-247-4228
Fax: 206-967-8375

DRMO Forest Park (*)
Ft Gillem Bldg 310-B
Forest Park GA 30050
Phone: 404-363-5117/5118
Fax: 404-362-7424

DRMO Ft Bliss (*)
1733 Pleasonton Rd
Bldg 11126 Biggs Field
Ft Bliss TX 79916
Phone: 915-568-8503
Fax: 915-568-8161

DRMO Gordon (*)
Bldg 994
10th Street
Ft Gordon GA 30905
Phone: 706-791-3749
Fax: 706-791-8623

DRMO Grand Forks (*)
548 3rd Ave
GF AFB ND 58205
Phone: 701-747-3783
Fax: 701-747-4594

DRMO Great Falls
8035 Pole Yard Rd
Malmstrom AFB MT 59402
Phone: 406-731-6346
Fax: 406-731-6560

DRMO Great Lakes
Bldg 3212A
3012 Mississippi Street
Great Lakes, IL 60088
Phone: 708-847-3655
Fax: 708-847-2510

DRMO Groton
NSBase New London
Bldg 397 Box 12
Groton CT 06349
Phone: 860-449-3523
Fax: 860-694-2866

DRMO Guam
PSC 455 Box 151
FPO AP 96540-1900
Phone: 011-671-339-5227
Fax: 011-671-339-4228

DRMO Guantanamo
Bldg 696B PSC 1005
Box 33 Code 230
FPO AE 09593
Phone: 0-115-399-4184
Fax: 0-115-399-4184

DRMO Hawaii
Barbers Pt B140
Enterprise & Midway St
NAS Barbers Pt HI 96862
Phone: 808-684-5980
Fax: 808-684-6670

DRMO Hill
Bldg 890 7844 Arsenal Rd
Hill AFB UT 84056
Phone: 801-777-7422
Fax: 801-777-2695

DRMO Holloman
241 Arkansas
Holloman AFB NM 88330
Phone: 505-475-3748
Fax: 505-475-3235

DRMO Homestead Annex
29050 Coral Sea Blvd
Homestead ARS, FL 33039
Phone: 305-224-7300
Fax: 305-224-7451

DRMO Hood
80th Street Bldg 4289
Tank Destroyer & 80th Street
Ft Hood TX 76544-0210
Phone: 254-287-7763
Fax: 254-288-6794

DRMO Huachuca (*)
Bldg 90507
104 Brainard and Jim Ave
Sierra Vista AZ 85613
Phone: 520-533-2074
Fax: 520-533-7078

DRMO Huntsville
Bldg 7408 Warehouse Road
Redstone Arsenal AL 35898
Phone: 205-876-2453
Fax: 205-955-6687

DRMO Jackson
Bldg 1902 Ewell Road
Ft Jackson SC 29207
Phone: 803-751-7912
Fax: 803-751-3506

DRMO Jacksonville
Naval Air Station
8297 Roosevelt Blvd B174
Jacksonville FL 32212
Phone: 904-542-3411
Fax: 904-542-3418

DRMO Keesler
607 Parade Lane VHI Rm 1
Keesler AFB Bldg 4422
Biloxi MS 39534
Phone: 850-882-2822
Fax: 850-882-4789

DRMO Keflavik, Iceland
Bldg 866
PSC 1003 Box 29
235 Keflavik Airport Iceland
Phone: 011-354-425-7306
Fax: 011-354-425-7092

DRMO Key West
Bldg 931
Naval Air Station
Key West FL 33040
Phone: 305-293-5271
Fax: 305-293-5274

DRMO Kirtland
5050 Randolph Aveunue
Kirtland AFB NM 87117
Phone: 505-846-6959
Fax: 505-846-1825

DRMO Knox
2962 Frazier Road
Ft Knox KY 40121-5640
Phone: 502-624-3244
Fax: 502-624-7321

(*) Scheduled to close in the next few months.

ed to the sale. All the items *remain* on the supplying base. Inspection is *highly* encouraged. These sales often do start with 31-XXXX. Or other "30s."

Back in the old days of printed and snail mail catalogs, putting everything into one listing made sense. But with online listings and a polling faxback access, I don't see the point. You have to wade through all sorts of stuff that you couldn't possibly pick up to get at one or two reachable items.

Certain items in these sales may need a signed *End User Agreement*. In which you promise not to drop ship your winnings to Saddam or Fidel. These forms usually have to be faxed or remailed each time.

RCP Sales

These are the *Recycling Control Point* sales. They often have more detailed catalog descriptions and *they will ship to you*. Unlike regular sales, inspection is *not* permitted. These sales typically start with 01-XXXX. They are usually sorted into aircraft parts, instruments, test equipment, electronic parts, and miscellaneous hardware.

There seems to be a "one size fits all" shipping charge of $50.00 *added* for most items. This sort of has the effect of *raising* the minimimum bid to $60.00. Which is often much too high for a possibly broken single piece of older test equipment. The trick, of course, is to bid on lots that can share the $50.00 among several items. Or for heavier trophies on which such a charge can end up a real bargain.

RCP Group Sales

This one is raising quite a howl on my website and elsewhere. Because it seems so grossly unfair to individual bidders and most small scale startups. Group sales also start with 01-XXXX. Like the regular RCP sales, there are good descriptions, no inspection, and prepaid shipping.

Only this time, you have to bid on an *entire* one-bid-takes-all pile called a *group*. Which can be everything that a chosen base added to the sale. Often, there will be seven groups instead of several hundred lots.

From the feds standpoint, disposal costs are way lower, admin is a lot simpler, and there's no problems with unbid items. But the bidder now has to risk thousands or tens of thousands of dollars instead of pocket change. And you have to take all the junk to get at the goodies. Which leaves you with a "iffen yew cain't hunt with the big dogs, stay on the porch" situation.

On the other hand, the higher risks and minimums might drive down the individual item prices. Way down so far. But note that the shipping charges alone sometimes exceed $3,000.00.

The secret is to carefully add up the maximum you are willing to pay *only* for each item you *really* can use. Then, you internalize the shipping charges before you bid. If you end up with less value than your charges, then you obviously do not bid. Otherwise, you bid only the difference.

In a recent example, two mil worth of test equipment went for *three cents on the dollar* at $60,000.00. Plus the $3,700.00 worth of shipping charges.

Fully one third of the stash was HP spectrum analyzers described in "fair" condition. In other examples of much less obvious or less desirable stuff, the winning bids ended up way *under* the shipping charges.

While in the running, I have yet to hit on one of these group sales. But scoring places you in the surplus biz big time. And very conveniently.

Other Sales

There's several other types of less popular and less useful sales. A RCP LDV or *low dollar value* sales start with 02-XXXX and works just like a group sale. There is *one* winner-takes-all bid for a whole truck or two full of junk. Typically two-thirds aircraft parts and one-third electronic pieces. Maybe 1,500 items in mixed quantities. Mostly new. These would be more useful if they split the electrics out.

The *international* sales are normally held at places that you cannot get to. Driving to Guam or the Azores can be a real drowner. International sales may start with 50-XXXX.

Special sales are put on for larger boats (destroyers go for $200K), for general scrap (used cooking grease seems fairly popular) or for classified electronic scrap where you'll have to give proof of strict security controls before you are allowed to bid.

Some DRMO sites also offer a retail store where the stuff is sitting around with marked prices. Desks and filing cabinets are often popular here. Their hours tend to be short and unusual, so call before attending.

Live auctions are also rarely held.

Condition Codes

The feds try to indicate the quality of each item by using *condition codes*. One obvious set of

codes runs *unused*, *good*, *fair*, *poor*, *residue*, and *scrap*.

Their fancier set consists of a letter followed by a number. A1 means new and perfect. A4 implies like new. F7 means probably easily repairable F8 means probably *not* easily repairable. H7 means pretty bad. HX means scrap plus hazardous materials that may be illegal to dispose of.

Most "F" test equipment does not include manuals, probes, and some plug-ins. We looked at finding older test equipment manuals last month back in RESBN80.PDF.

Additional details of these specific meanings are shown on their website. The bottom line: Use caution with any "F" item and extreme caution with any "H." Unless you token bid. Even then, the pickup and triage expenses may not be worth the hassle.

But a stack of identical bad items can often be rebuilt into a smaller pile of good ones. Provided they all failed in different ways.

Efficient Markets

An economist defines an *efficient market* in which there are lots of very smart buyers that force a "fair" price. With rather few exceptions, most mil surplus does not come even remotely close. As much as *one third* or so of the items will have no bidders at all. Or at most, only a single bidder. Whose bid price was obviously too high. Certain older specialized electronics may go for tenths of a cent on the dollar.

Older electronics do tend to be uselessly bulky and heavy. And may have zero market, except as scrap.

Some popular items do get bid up to respectable prices, though. Most of the "army-navy store" items go for 10 or 20 percent of cost. Modern Tek scopes "A4" and by themselves might hit 20 percent, while a like-new HP Spectrum analyzer might go for 35. A few high demand lathes and milling machines may actually go for 300% of mil cost. Owing to some recent dramatic price increases.

The vacuum tube nuts have been having a feeding frenzy lately. Seems your feds have of late been dumping mountains of tubes. Perhaps 80,000 of one number at a whack. Some of these are actually going for 130 percent of original cost! **NV**

(To be continued next month)

Don is the webmaster of his Guru's Lair found at ***http://www.tinaja.com***

AT&T 6300 Monitor Pinout

Q & A – Continued from page 33

Q. My wife bought a computer at a yard sale: an AT&T model 6300 made in Italy with a 1990 date on the back panel. It has a 20 MB hard disk and 640K of RAM. The machine seems to boot, but without an operating system. I tried installing DOS 3.3, but it wouldn't take. DOS 4.0 displays an illegal interrupt that causes the screen to roll out of control, like a TV with a bad vertical hold. If you can tell me how to get it working, I'd be grateful. More importantly, though, is whether or not I can use the color monitor on a VGA computer. There's a cord coming from the monitor with a DB25 connector at the end.

Stanley Kelember
skele@ccny.com

A. *This is an IBM PC AT clone made for export and assembled outside the country. As such, part of the operating system (DOS) is contained in the BIOS, which means you need a copy of the original DOS to get the system up and running. This was – and still is – done because certain types of software, like encryption software, can't be exported. Perhaps one of our readers has a copy. As for the monitor, it will work with your VGA computer. Here's the pinout with a VGA cross-reference.*

	AT&T 25-pin	VGA 15-pin
Pin	***Function***	***Pin***
1	Horizontal sync	13
2	ID0	11
3	Vertical Sync	14
4	Red	1
5	Green	2
6	Blue	3
7	not used	–
8	not used	–
9	not used	–
10	ID1	12
11	Mode	0
12	not used	–
13	- Degauss	–
14	GND	6
15	GND	7
16	GND	8
17	GND	10
18	GND	–
19	GND	–
20	GND	–
21	GND	–
22	not used	–
23	not used	–
24	+15V	–
25	+15V	–

For monochrome, ID0 and ID1 are open. For color, ID0 is 0, and ID1 is 1 (+5V).

MAILBAG

I downloaded TEST2000.ZIP and ran it. It says I'm not Year 2000 compliant, but could be if I used the program Y2KPCPro. How do I obtain this program?

Chaurlle Eakin
via Internet

Response:
At present Y2KPCPro is only sold in volume to organizations, with a minimum license for 10 PCs. However, individual users can find Y2KPCPro under the name CHECK 2000 PC, manufactured by Greenwich Mean Time. It's available from the following retailers for about $49.95.

CompUSA, Computer City, Micro Center, Office Depot, OfficeMax, J&R, Electronics Boutique, Chapters, London Drugs, @Computers Plus, Compucentre, Crazy Irving, Adventure Electronic, Future Shop, Costco, Bureau En Gros, RadioShack, Business Depot

Dear Mr. Byers:

In the July '98 issue, you answered a question about a clock that automatically receives a time signal through the airwaves. My Sony VCR (SLV-975-HF) does the same thing. Here's a quote from the owner's manual. "Some TV and cable channels transmit time signals with their broadcasts. Your VCR can pick up this time signal to automatically set the clock." Hope this helps.

Detroit
via Internet

Response:

My Samsung VCR does the same thing! The problem is that the time signal hitches a ride on your PBS channel, which isn't always strong enough to set the clock. Yes, it always works with cable, but I've found airwave signals to be sometimes questionable. Makes you wish our WWVB network were as reliable as Germany's.

TJ Byers
Q & A Editor

Great Books for Hobbyists, Students, Engineers . . .

Simple, Low-Cost Electronics Projects

by Fred Blechman

NEW!



Learn electronics with Fred Blechman's exciting new book. Begin with simple designs and progress to more sophisticated projects. Each project comes with a complete discussion of circuit theory and parts list, as well as information on troubleshooting and testing. Build voltmeters and multimeters, inductance and semiconductor testers, variable frequency audio oscillators, a photoelectric counter, and much more!
1-878707-46-9/224 pages/$19.95

Controlling the World with Your PC

by Paul Bergsman



PC Disk Included! Connect your computer to the real world and make it do useful work like controlling stepper motors, turning appliances on and off, or monitoring fluid levels. PC disk contains software files in ready-to-use form.
1-878707-15-9/208 pages/$35.00

The Forrest Mims Engineer's Notebook

by Forrest Mims III

This revised edition of Forrest's classic book includes hundreds of useful circuits built from integrated circuits and other parts available from convenient sources.
1-878707-03-5/156 pages/$19.95

The Integrated Circuit Hobbyist's Handbook

by Thomas R. Powers



Covers the major types of integrated circuit devices—linear, TTL, and CMOS—and provides complete details and theory about their operation. Contains lots of useful application circuits—an essential reference for every hobbyist. **1-878707-12-4/256 pages/$19.95**

Order on the Web!
For these and other great books on electronics, visit:
www.LLH-Publishing.com
or
call 1-800-247-6553 to use a major credit card, or send check or money order to:

LLH
Technology Publishing
3578 Old Rail Road
Eagle Rock, VA 24085

Scott Edwards Electronics

NEW! **Graphics LCD Module with Serial Interface**



3.66" by 2.76"

The new G12864 makes it easy to display text and graphics on a 128-by-64-pixel LCD. It interfaces with a computer through a 2400 or 9600-baud RS-232 serial hookup.

Text Features

The G12864 works like a serial-receive terminal. It displays text in a 4-line by 16-character format. Text is displayed in a large 8- by 16-pixel font, which can be edited to include custom symbols.

Graphics Features

The display lets you plot points, draw lines, and display full-screen graphics using easy instructions. Its flash memory stores the text font plus 14 screens. You can create fonts and graphics on your PC, then download them to the G12864 using the included software.

Convenience Features

A power supply and DB9 serial-port connector are built in. Connect the display to the (included) AC adapter; plug the (included) serial cable into your PC or other computer, and you're ready to go. Current draw ranges from 15mA (typical, backlight off) to 100mA (max, backlight on). For complete specifications, see our web site: **www.seetron.com.**

Display, with starter pack: **$199** Display alone (OEM qty 1): **$179**

Scott Edwards Electronics • PO Box 160 • Sierra Vista • AZ • 85636-0160
ph: 520-459-4802 • fax: 520-459-0623 • e-mail: info@seetron.com
Internet: www.seetron.com

reader FeedBack

Continued from page 14

herein are represented up to 1/2 mile east of their actual location and occasional N-S errors of approximately the same magnitude.

In addition, the GPS III shows the head of lake navigation to be at N37° 47.6', W120° 23.6' whereas, with the lake at least 20 feet below the high water mark, the head of lake navigation is upriver at least seven to eight miles on three separate arms, none shown on the GPS III. This display also shows the lake as it would be if its level were 150-200 feet below the high water mark.

I found similar errors on other bodies of water as well. This is not only misleading, it could be dangerous to boaters. I realize that your warning disclaimer on the second screen to appear after power up is intended to deflect complaints and liability, but accurate shoreline representation is what I purchased the unit for. The level of detail shown is satisfactory, it just should be at the correct location.

The GPS location reported out of the NMEA port is usually accurate as evidenced by tracking along the highway with a DeLorme CD-ROM map on a notebook computer. (I do not use the computer in my boat.) Once on shore, the GPS position display on the notebook computer did correspond with the actual shoreline quite well at the few places that I observed it (usually at or near the launch ramp).

Although I did not purchase this unit for highway navigation (maps and signs are usually good enough), I find that the highway locations are likewise often misplaced — in some places perhaps at lease 1,000 feet off. At times, the railroads location is even shown on the wrong side of the highway.

Given a choice between highway maps and accurate representation of bodies of water, I will take accurate lake or ocean shores anytime. Location of small boat harbors (Newport Beach, Dana Point, Oceanside, CA, etc.) and breakwaters would likewise be extremely useful on your map display.

The altitude calculation and display on the GPS III is totally worthless. At my home location at about 600 feet elevation, the displayed altitude varies from -1,000 to +2,000 feet. You do not publish an altitude accuracy specification, but plus or minus 1,500 feet does nobody any good.

One further comment, the backlight is too dim (even at its brightest) for use inside a recreational vehicle in the daytime or anywhere at twilight.

My question is, does Gordon plan to offer a software and/or land data upgrade at a later date to correct these deficiencies?

John E. Lemmer

Response:

I agree with your findings, and again I say to all GPS users, don't rely on embedded land mapping information for coastal boating or navigating in tight spots on lakes and rivers. The land maps should be considered a "bonus" for those driving on major highways who want to take a look and see how many miles away the next town is, or the next big interstate turn-off. You might call this a "gee whiz" feature that might be useful out on the road.

But trying to safely navigate in harbors, oceans, lakes, and rivers with this type of information can be quite dangerous.

In fact, I would never go out on any body of water without a good local paper map or chart, and a GPS that would run off of specific C-Map or Navionics chart cartridges. Or I would tie the output of my GPS set into a professional CD-ROM land or marine charting program, and have the best of all worlds.

As Mr. Lemmer indicates in his letter, the GPS was indeed accurate, but the embedded no-local-cartridge cartography was not close enough for precise navigation.

This letter should serve as an important warning to anyone using GPS with pre-stored, embedded cartography.

Gordon West

Dear Nuts & Volts:

After reading yet one more article about the Y2K problem, the only thing that comes to mind about this bug is that its sole purpose in life is to sell articles and books for the purpose of fanning the hysteria flames.

Nowhere in any of these well-written articles is it mentioned that most computer controlled machinery other than financial institutions don't care what decade it is let alone what century.

A traffic light is quite happy living in the 18th century let alone the 21st, and will work just fine even if it prints out to its master the wrong information about its date status. Cat scanners, air conditioners, and water pumps work just fine with "00" instead of "99," and so will 99 percent of all other computers.

Financial institutions that haven't been upgraded before the change over "will be closed (and presumably forced to do manual calculations) according to the FED.

Even pre 90s Taiwan imitation PCs such as the one writing this letter don't have a problem with "00" and I doubt most other PCs will have a problem either.

Yes, there are a few systems in this country that will crash, but as far as the financial systems go, the latest figures are 98% and climbing referring to the fact that most computer programs have already been fixed. Panic and hysteria will cause more problems than the Y2K bug ever will.

Computer programs designed to seek and destroy (modify) the bug can, in effect, repair or rewrite a complete system within hours — not days or months — lowering the cost.

The idea that individual systems have to be reset manually by human hands and eyes is absurd. The purpose of computers is to speed up this process and programs such as Cobol and DOS were invented and designed to work universally on individual systems and work without the need of programmers at each station.

Once a language was written it was put to magnetic media and copied, transferred, and used at many different locations. A magnetic solution done at one location can also be copied, transferred, and distributed to other locations to fix, upgrade, or rewrite an entire system simply by inserting the new magnetic media or disk.

Individual company information doesn't reside within the realm of the date code, with the date being the only informational change needed. All other information such as shape, size, and direction will follow blindly the time code, once changed.

Even if a company opts to keep "00" representing the date "1900," all computations will follow blindly and happily thinking it is the year 1900, and will perform as intended without the slightest glitch. Only financial institutions with monetary interests in mind such as percentages, dollars, and interest rates need worry or change the date codes.

Traffic lights will regulate model "Ts" or "T-Birds" without even considering what century it is. If money isn't involved, then time and dates won't affect the running of switches, pumps, or even doors and elevators.

Reading an expired date code on my milk that says January 5, 1900 isn't going to lock up my arm and stop me from pouring it over my cereal unless hysteria and stupidity take control of my motor functions! I usually sniff the milk first and I suspect most americans also use this high-tech approach.

The fact that the date code will either read exactly correct or will be one century off doesn't take rocket science to figure out and I doubt a single citizen in this country will have a problem figuring out which is which?

The problems that reside within the Y2K bug are mostly in the financial district and the government has stated that any company that doesn't fix the problem before the year 2000 will be closed before that date and not allowed to trade until the upgrade has been installed.

The fact that the date code which is embedded in the chip or program allows for a date to exist that goes back to the year 1900, and is acceptable as a legitimate date code, means that aside from the financial institutions, there is nothing wrong with the year 1900 and most systems will run on that year code as if nothing was wrong.

I realize that I too have over-simplified the problem and that there will be some problems that will occur, but most articles over-play the problem and risk causing a panic that need not exist, and if unattended will likely cause a crash in the stock market and financial arenas simply because these institutions are run by ego, speculation, and blind trust to begin with.

Chris Bieber, Ca

GRAPHIC LCD DISPLAYS: PART 2

by Ryan Sheldon, National Control Devices (404) 244-2432 http://members.aol.com/ncdcat

Control up to Eight Graphic LCD Displays from Visual Basic 5 for Windows

Last month, I discussed graphic LCDs and how they can be controlled from Qbasic. And, once again, my Windows readers can learn how to add the power of graphic LCDs to their next custom Visual Basic application.

Graphic LCDs are not difficult to control, but they do require some time and patience. I have spent nearly 10 months packaging the LCD Animator 128 into a usable collection of information, both in the form of hardware and software. As a result, many users of the LCD Animator 128 are loading and displaying images and text within 15 minutes of taking it out of the box.

The most valuable part of this learning process — in my opinion— is that first-time users are able to skip the complexities of how the display controller works. As their curiosity is peaked, they can go back and read about their particular topic of interest. By allowing people to learn at their own pace, they are often less frustrated with the technicalities ... and I might add that graphic LCDs can be full of technicalities.

I guess it's easy for me to say that it is easy to control an LCD display but, in reality, I need to show users exactly what I am talking about before they think it's easy too. But to do this effectively, I am going to need some room for illustrations. So, I have broken this article into two parts. Next month will be a little more exciting, but for now, I want to get into the mechanics of controlling the LCD Animator 128 from Visual Basic.

So this month, I want to show you how to use simple commands to control these LCDs by making simple use of subroutine calls. The subroutines have already been written for you, so all you need to do is use them appropriately to control the display.

Step 1

To get started, you will need to connect

FIGURE 1



Figure 2: Jumper Settings

RS-232 Connections:

DB-25 Female Connector Shown from Solder Side.





DB-9 Female Connector Shown from Solder Side.

Jumper	Function	Install Notes	Default Setting
J1	Animator Address 1	-	Not Installed
J2	Animator Address 2	-	Not Installed
J3	Animator Address 3	-	Not Installed
J4	Animator Baud 1	-	Installed
J5	Animator Baud 2	-	Not Installed
J6-J10	Reserved	Reserved	Never Installed
J11	Display Type	128 Frames of Graphics (Install Left) 64 Frames of Graphics/Test (Install Right)	Install Between Right Terminals
J12	Display Compatibility	High-Impedence Interface (Install Up) Direct Drive Interface (Install Down)	Install Between Upper Terminals
J13	Display Compatibility	High-Impedence Interface (Install Up) Direct Drive Interface (Install Down)	Install Between Upper Terminals
J14	Animator RS-232 Select	Data From RF Receiver (Install Left) Data from RS-232 (Install Right)	Install Between Right Terminals

Address Setup:

NCD Address	J1	J2	J3
0,8	Removed	Removed	Removed
1,9	Installed	Removed	Removed
2,10	Removed	Installed	Removed
3,11	Installed	Installed	Removed
4,12	Removed	Removed	Installed
5,13	Installed	Removed	Installed
6,14	Removed	Installed	Installed
7,15	Installed	Installed	Installed

Baud Rate Setup:

Baud Rate	J4	J5
9600	Removed	Removed
19,200	Installed	Removed
38,400	Removed	Installed
115,200	Installed	Installed

FIGURE 2



FIGURE 5



FIGURE 3



FIGURE 6



FIGURE 4



FIGURE 7

the LCD Animator 128 as shown in Figure 1. Set all jumpers to their default setting as shown. Make sure batteries are attached to the battery backup system. Batteries are not an option; they are a necessary component required for proper operation. The display controller was designed to use batteries sparingly. A pair of AAs should last five to seven years. Also, you should run the included Windows program, "LCD Animator Setup Utility" to initialize the display. Once initialized, the LCD Animator 128 will be waiting for commands.

Step 2

Start Visual Basic 5 and select "Standard EXE" to begin a standard project.

Step 3

Next, select "Components" from the "Project" pull-down menu. The Components dialog box is used to add functionality to your VB applications. To add serial communications to your VB project, put an "X" in the box next to the "Microsoft Comm Control" label and select "OK."

Step 4

The toolbox will be updated with a telephone icon as shown in Figure 2. Double-click on the telephone icon to add RS-232 communications to your new program. The MSComm control will appear in your project as shown in Figure 3. The telephone icon will not be visible when the application is run. This icon is called an object in VB terminology. Your program will speak to this object each time you want to send data out the serial port.

Step 5

Select the MSComm icon on your application form. Use the "Properties" window to change the attributes of the MSComm control. Change the "Setting" attribute to 19.2K baud as shown in Figure 4. Note that the "CommPort" property should also be set to communicate with any available COM port on your computer. By default, the "CommPort" property is set to 1. An error may be generated if an unavailable COM port is chosen.

Step 6

Double-click on the form of your project (anywhere in the gray box that has the telephone icon on it) to open the "Form" "Load" window. Type in the code as shown in Figure 5. This command will open communications to the serial port when the project is first run.



FIGURE 8

FIGURE 9



FIGURE 11



FIGURE 10



FIGURE 12



FIGURE 13

Step 7

Cheat. Instead of having you type in the core subroutines used to control the LCD Animator, I will have you download them from my web site at http://members.aol.com/ncdcat/. You can then load them into your project; effectively adding a complete command set to Visual Basic for communication to the LCD Animator 128 controller. While this does not save much programming, it does save magazine space. You can easily add this command set to your application by selecting "Add Module" from the "Project" menu as shown in Figure 6.

NOTE: Download the file "CCW0007.ZIP" to obtain all the source-code and images required for this article. Once you have downloaded this file, you should unzip the contents onto a floppy disk. All future references to files can be found on this disk.

Step 8

Select the "Existing" tab and the file "LCDA128.BAS" (and don't forget; this will be on your floppy disk, see note above). See Figure 7. This collection of subroutines will speak directly to the LCD Animator. You can view this small collection of subroutines by double-clicking on the "LCDA128.BAS" module shown in the project window (Figure 8).

Step 9

Select the button tool as shown in Figure 9 and draw eight buttons as shown in Figure 10.

Step 10

Use the "Properties" window shown in Figure 11 to caption each of the buttons as shown in Figure 12.

Step 11

It's time to add functionality to these eight buttons. Double-click the "Turn Backlight Off" button to reveal an empty window. Enter the code shown in Figure 13. If you are not familiar with Visual Basic, then you will probably appreciate how subroutines are stored within modules. A module is simply a collection of subroutines. In this case, LCDA128 is the name of the collection. This collection is used specifically to control the LCD Animator 128. A different collection of subroutines would be used to control other devices.

Figure 13 simply tells the module (LCDA128) to execute a subroutine for controlling the backlight (LIGHT). Later, you will see how you can easily send other commands to the LCD Animator by calling other subroutines from within the LCDA128 module.



FIGURE 14



FIGURE 15



FIGURE 16



FIGURE 17

Step 12

Double-click the "Turn Backlight On" button and add the code shown in Figure 14. Note that two parameters are passed to the LIGHT subroutine stored within the LCDA128 module. The first parameter is "Device" and is a number from 0 to 7 used to send commands to a specific LCD Animator. Remember, up to eight LCD Animators can be attached to and controlled from a single serial port. The device number simply determines which of eight LCD Animator modules will receive the command to turn on the backlight.

Step 13

Double-click on the "Put Display to Sleep" button and add the code shown in Figure 15. This command will put the LCD Animator into low-power sleep mode.

Step 14

Double-click on the "Wake Display" and add the code shown in Figure 16. This command will wake the LCD Animator from low-power sleep mode.

Step 15

Next, double-click on the "Clear Graphics and Text Layer" and add the code shown in Figure 17. This command will clear the graphics layer, then the text layer. Since each layer is controlled independently, you will later be able to change the text displayed on top of a graphic image without affecting the graphics.

Step 16

Double-click on the "Display a Bargraph" button and add the code shown in Figure 18. This subroutine shows how you can easily display bargraphs on the LCD screen.

Step 17

Double-click on the "Load Image and Text Animation Into Controller" button and add the code shown in Figure 19. This program will load 16 different graphic images into the controller when the button is pressed.

Step 18

Double-click on the "Show LCD Animation" button and add the code shown in Figure 20. This short subroutine animates the images stored in the first 16 frames of the controller's memory. You must click the "Load Image and Text Animation Into Controller" button to load the images into the first 16 frames of memory. Otherwise, the screen will show garbage as you cycle through the animation frames.

Step 19

Now you can run your Visual Basic application. Try clicking on these eight buttons and watch the results on the screen of the LCD Animator.

Applications

Many readers have written to tell me about the projects they are working on and how they are using my devices to control the world from their PC. One reader wrote with a very creative control solution.

He is a big home-automation fan. He has a low-end Pentium computer stashed in his basement running Windows 95 and Visual Basic. He ran RS-232 wires throughout his house and yard. He uses our 8SC input scanner to read inputs connected to motion detectors. He uses a couple of AD8s to read temperature, light, and moisture levels in his yard. He also uses our ASEL connected to 12 cameras strategically placed throughout the premises. He uses our R85 to control various alarms, lights, and the sprinkler system in his yard. And finally, the LCD Animator is used to display messages of text and graphics based on data retrieved throughout his house, in his office.

When you walk through his house, motion is detected by the 8SC input scanner. The ASEL automatically switches to the video camera closest to that area. Data is sent to the LCD Animator informing him of the detected motion, a monitor shows him the area in which motion was detected. If he is not at home, alarms will sound and lights will flash.

Additionally, the AD8 monitors the temperature of his house and regulates the heating and cooling system using the R85. During the day, if the ground gets too dry and it is not raining, sprinklers will automatically activate. The cooling system in his

house is kept off during weekdays, and activates 30 minutes before he comes home from work to conserve energy. These are the types of things our control network is used for. We have found many people who are using the LCD Animator in kiosks, movies, home, and industrial automation control applications.

By combining the power of these specific devices, you will be able to build a computer control system suited to your specific needs, with readily available off-the-shelf components.

Well, I hope you have been able to see a good working demo of how to send images and text to the LCD Animator 128 controller. Next month, I will continue the subject of LCD Animation by showing you some practical real-world control applications. Until then, feel free to call or write with your questions and comments.

Remember: the LCD Animator 128 is available to readers of this article for a special low price of $199.00. **NV**

Project1 - Form1 (Code)

Command6 | Click

```
Private Sub Command6_Click()
    'Cycle through all 32 columns of text
    For Column = 0 To 31
        'Randomly pick a level
        Level = Int(Rnd(1) * 17)
        'Display Level on Screen
        LCDA128.VerticalTextGraph Device, Column, Level
    Next Column
End Sub
```

FIGURE 18

Project1 - Form1 (Code)

Command7 | Click

```
Private Sub Command7_Click()
    'Count Frames from 1 to 16
    For FRAM = 1 To 16
        LCDA128.FRAME Device, FRAM: Rem Set the Current Frame
        LCDA128.CLRTXT Device: Rem Clear the Text Layer on the Current Frame
        File$ = "A:\FRAME" + Str$(FRAM) + ".BMP": Rem Create Filename of Image to Load
        LCDA128.SPEEDFILE Device, File$: Rem Load Image File into Display
    Next FRAM
End Sub
```

FIGURE 19

Project1 - Form1 (Code)

Command8 | Click

```
Private Sub Command8_Click()
    'Cycle Through 16 Frames of Animation
    For FRAME = 1 To 16
        LCDA128.FRAME Device, FRAME
    Next FRAME
End Sub
```

FIGURE 20

Boards and Chips Available

Contact Ryan Sheldon
National Control Devices
Phone: **(404) 244-2432**
Fax: **(417) 646-8302**
E-Mail: **NCDRyan@aol.com**
http://members.aol.com/ncdcat/

The LCD Animator and EL Backlit LCD Display are available to readers of this article for just $199.00. You must mention this article when ordering.

THE COMPUTER CONTROLLED WORLD

13" COLOR MONITOR



Composite input, RGB, EGA, & CGA compatible. Green switch and black and white switch. Following controls: Hue, saturation, contrast, & brightness. Used, but in great shape.

$50.00 ea.
10 for $400.00
Shipping $12.00 ea.
VISA & MC
Call Roger @
General Science & Engineering.
716-338-7001

Computers & Components

Wholesale Prices!
Memory, Hard Drives, Much More!
VOLTEX
(800) 211-5554
Call for best prices!
www.pc4me.com

New Product News

Continued from page 9

PALM PILOT



Whether traveling for business or pleasure 3-Com Connected Organizer – Palm Pilot – users can now turn their electronic organizer into a handheld navigation system, complete with maps and an electronic compass with The Palm Navigator by Precision Navigation, Inc.

the Palm Navigator, available for only $39.95, is a hardware sensor module that plugs into the bottom of the Palm Pilot (like a modem) turning it into a map navigation system and state-of-the-art electronic compass.

Included with the Palm Navigator is free MapSync software that allows for the easy downloading and storing multiple maps from the web onto the Palm Pilot.

The Palm Navigator provides direction information instantaneously and continuously whether moving or not. In addition, the Palm Navigator works even when under trees, near tall buildings or in a canyon, which GPS cannot do.

The Palm Navigator has no limit to how many maps can be stored or how small or large the maps can be displayed on the screen.

For more information, contact:

PRECISION NAVIGATION, INC.
1235 PEAR AVE., STE. 111, DEPT. NV
MOUNTAIN VIEW, CA 94043
650-962-8777 FAX: 650-962-8776
1-888-4-A-COMPASS
WEB: www.precisionnav.com

MULTITEST 100/200 MULTISYSTEM SIGNAL GENERATOR

MultiTest 100 and MultiTest 200 are high-performance digital video generators specially designed for the serious home theater enthusiast to optimize and check TVs and video projectors quality and performance.

Large screen TVs and video projectors may become misadjusted or misaligned due to vibrations, presence of magnetic fields generated by electronic equipment, speakers, etc. Even brand-new units quality may be improved by optimizing factory settings and adjustments.

MultiTest 100/200 generate high precision professional patters that TV stations, engineers, and technicians use themselves to test TV and video equipment. A comprehensive instruction booklet shows how to check for accuracy in color purity, focus, white balance, convergence, tint, sharpness, etc.

For more information, contact:

TENLAB
27346 OAK SUMMIT RD., DEPT. NV
AGOURA HILLS, CA 91301-3612
818-706-8120
FAX: 818-706-3643
E-MAIL: info@tenlab.com
WEB: http://www.tenlab.com

DELUXE TWO-METER VHF AMPLIFIER

Mirage's new professional grade two-meter amplifier has a host of unique features plus adjustable output power ... only $224.95.

The new Mirage B-510-G has front panel adjustable output power from 5-100 watts. You pick the amount of power you need or want to achieve. Mirage's LED PowerGraph indicator makes this power adjustment easy. It tells you when you're at the power level you need.

You can use two-meter handheld or mobile transceivers in any mode, FM/SSB/CW. You can select an adjustable gain (5 to 15 dB) low-noise GaAsFET preamp for weak stations, a 15 dB attenuator to reduce intermod or bypass.

Mirage gives you all protection modes. High SWR protection has LED indicator, over temperature protection has an LED indicator, reverse polarity protection, and an on-air LED.

The new Mirage B-510-G amplifier price is $224.95.

For more information, contact:

MIRAGE COMMUNICATIONS EQUIPMENT
300 INDUSTRIAL PARK RD., DEPT. NV
STARKVILLE, MS 39759
601-323-8287 FAX: 601-323-6551
1-800-647-1800
E-MAIL: mirage@mfj@mfjenterprises.com
WEB: http://www.mirageamp.com

DP-9 AND DP-9S MULTIBAND HF ANTENNAS

Dynamic Technologies, Inc. announces the release of DP-9 and DP-9S multiband HF antennas.

The DP-9 consists of nine full-size dipole antennas separated about two inches with PVC spacers for 160, 80-75, 40, 30, 20, 17, 15, 12, and 10 meters.

The bandwidth is approximately the same as a single dipole on each band. The SWR is less than 2:1 on each band allowing operation without an antenna tuner. Each antenna can be individually adjusted for resonance at any frequency within its band. There are no traps to fail allowing the antennas to handle maximum power. The DP-9 is 240' long.

The DP-9S is the same as the DP-9 except the 160 meter antenna has coils placed in the center of each side. The DP-9S is only 140' long and has a 2:1 SWR bandwidth of approximately 30 KHz on 160 meters and full bandwidth on the other bands.

DP-9 costs only $189.00 and the DP-9S costs $210.00 plus $10.00 shipping to USA locations.

For more information, contact:

DYNAMIC ELECTRONICS, INC.
P.O. BOX 896, DEPT. NV
HARTSELLE, AL 35640
256-773-2758 FAX: 256-773-7295
E-MAIL: dei@whnt19.com
WEB: http://www.hsv.tis.net/~dei

CODE TUTOR

MFJs new professional classroom Code Tutor was specially designed for VE Examiners, Vo-Tech/ham radio schools, ham clubs, and teachers.

Professional features include an LCD readout, printer port, audio tape recording output, powerful audio with true sinewave, computer interface, stores 16 FCC exams for VECs, HF/VHF radio interface for on-the-air practice, and is a full featured memory keyer.

The Code Tutor is available for $199.95.

CODE PRACTICE OSCILLATOR

MFJ introduces their new Code Practice Oscillator. It was specially designed for demanding classroom use.

It produces a true pure sinewave. It has low distortion CW – typically less than .2% total harmonic distortion from its BTL amplifier.

The Code Practice Oscillator removes all traces of harsh key click. Five milliseconds of symmetrical rise and fall time shapes the keyed oscillator wave form to remove key clicks.

MFJ's special deal includes MFJ-554 Practice Code Oscillator, MFJ-281 ClearTone Communications Speaker, MFJ-550 Telegraph Straight Key, and MFJ-1315 AC adapter for only $99.95.

For more information, contact:

MFJ ENTERPRISES, INC.
P.O. BOX 494, DEPT. NV
MISSISSIPPI STATE, MS 39762
601-323-5869 FAX: 601-323-6551
1-800-647-1800
E-MAIL: mfj@mfjenterprises.com
WEB: http://www.mfjenterprises.com

Big sound from a stereo radio—without the big price!

Zenith Audio, a leading electronics manufacturer designs a "Small Footprint", "Big Sound" stereo system that's perfect for the home or office and priced below $100.

by John Jameson

I leaned back slowly in my chair with my eyes closed, listening to the haunting melody of a Mozart symphony. The acoustics were flawless, and the room was soon filled with full, rich stereo sound. From the crisp highs of the flutes to the tooth-rattling bass of the kettle drums, the music was crystal-clear and powerful. I could distinguish the distinct sounds from each individual musician, and as the orchestra reached the finale I almost fell out of my seat from the awesome force of the music. As the music faded, I leaned forward and hit a button on the stereo clock radio. I had a concert to go to that night—it was time to check the weather.

Ultimate sound machine. Zenith Audio has developed a Digital Stereo Clock Radio that boasts the acoustic quality and practical features of stereo radios four times as expensive. You'll be amazed at the sound quality and powerful bass you get from a radio this small and this affordable. This stereo radio features an 11-key handheld remote control and an input jack for CD players or other audio sources.

The best bass. Many small stereo radios can sound tiny and weak. This unit has an exclusive EXB button for expanded bass performance. It intensifies the lower tones for CD or FM stations, giving you rich, full and powerful stereo sound. If you want to listen to the stereo in private, there is a headphone jack on the side of the unit.

Compact Speakers with a Big Sound



The Zenith Audio Clock Radio has an exclusive EXB button for expanded bass performance. It intensifies the lower tones for CD or FM stations, giving you rich, full and powerful stereo sound.

Micro-Electronic Sound Breakthrough

State of the art stereo sound quality in a stylish cabinet

- AM/FM/TV Bands
- Stereo Speakers with Crystal Sound System
- Digital Weather Band
- 37 Preset Station Memories
- Ascending Tone Alarm
- Wake/Sleep to Radio, Weather or TV Band
- "Fail-safe" Alarm System

Loaded with features. You won't find a tabletop stereo with more added options. The AM/FM radio features digital tuning for pinpoint reception and crystal-clear sound. The STEREO indicator allows you to tune in to the stereo signal. It also picks up **TV** and **WEATHER** signals with 13 TV channels and 7 Weather channels, so your Zenith Audio Clock Radio is a great source of news, entertainment and information. You can program the unit's memory for 37 preset stations, and the tuning buttons can operate either manually or in a automatic search mode.

Practical functions. The backlit clock has several alarm functions, so you can wake to either radio, TV, weather or a buzzer. The sleep timer allows you to fall asleep to up to 90 minutes of music, TV or weather and then shuts off automatically. In the morning, if you need a few extra minutes of sleep, press the SNOOZE bar on the control panel or on the remote. The radio or alarm tone stops for 10 minutes and then sounds again. The process can be repeated several times as required. The unit's battery backup system will maintain the time, alarm and preset station memories in the event of a temporary power interruption. There is even a low battery indicator so you'll never oversleep in the event of a power failure.

Factory direct risk-free offer. You can spend hundreds of dollars more on a stereo radio, but why do it? We get the Stereo Clock Radio direct from Zenith Audio and pass the savings on to you. This product comes with a one-year manufacturer's limited warranty and Comtrad's exclusive risk-free home trial. If you are not satisfied for any reason, simply return it within 90 days for a full "No Questions Asked" refund.

1. Mute
2. Power
3. Volume
4. Band
5. Preset
6. Tuning
7. Alarm
8. Sleep
9. Snooze



11-key full function remote works up to 15 feet away.

The Zenith Crystal Clear Stereo comes in white or black.

Zenith Crystal Clear Stereo $99.95 $12 S&H

Please specify white or black.

Please mention promotional code **4244-14254.**

For fastest service, call toll-free 24 hours a day

800-992-2966

To order by mail, send check or money order for the total amount including S&H. To charge it to your credit card, enclose your account number and expiration date.

Virginia residents only—please include 4.5% sales tax.

comtrad industries
2820 Waterford Lake Dr., Suite 102
Midlothian, Virginia 23113

IDE DUPLICATOR
ONLY $395

IDE & SCSI DUPLICATOR
ONLY $595

PRO MODEL SUPPORTS IDE, SCSI, AND SCA
$995



CLONE, TEST OR REPAIR ANY HARD DRIVE

"THE MOST COMPLETE HARD DRIVE WORKSTATION WE'VE SEEN!" BOB ROSENBLOOM, DIGITAL VIDEO, INC.

DRIVE SERVICE STATION

Copy entire hard drives with ease. Drive duplicators are essential tools for dealers and system builders. Don't spend hours installing and formatting drives. Do it instantly with the Drive Dupe-It. Set up any SCSI or IDE drive with your original software. Connect blank drives to the Drive Dupe-It and presss start. You'll copy entire drives faster and more accurately than is possible on any PC. With our combination IDE and SCSI model, you can even copy data between diffferent interfaces. All models include both 2.5" and 3.5" interface adapters. The Pro also supports SCA and Wide SCSI drives.

Choose the Pro, and you'll also have an entire factory drive test and repair system for under $1000. The Pro gives you the ability to copy, reformat, repair, translate, and test any hard drive. Use the Pro to put any hard drive through its paces. A full factory final test and performance analysis is performed. Complete test and repair reports are sent to any standard printer.

BUY MANUFACTURER DIRECT
408 330-5525

The Pro will also reassign and eliminate drive defects. Here's how it works: First, a precise media analysis system scans the disk for errors. Defects are mapped out, and effectively "erased." The error correcting system then "trains" the drive to permanently avoid defective areas. Data is stored only on the safe areas of the disk. Capacity is reduced by an insignificant amount, and the drive works flawlessly once again. Get the technology used by major repair shops and data recovery centers. The Pro repairs all disk defects caused by normal wear. Drives with mechanical damage may not be repairable.

CORPORATE SYSTEMS CENTER
3310 WOODWARD AVE., SANTA CLARA, CA 95054
WWW.CORPSYS.COM

Call today for high volume multi-drive copiers and CD Duplicators

Write In 84 on Reader Service Card.

Opto Hits The Spot

SCOUT

- 10MHz - 1.4GHz
- Stores 400 frequencies in memory
- Reaction Tune the ICOM R7000, R7100, R8500, R9000, R10, AOR 8000, AOR 8200, and Opto R11
- 10 digit LCD with signal strength bargraph
- Vibrator and beeper alert mode

$349 SAVE $100

DB32 Antenna Sold Separately ($29)

R11

- 30MHz - 2GHz wide band receiver (Cellular Blocked)
- Built-in speaker for instant audio demodulation
- LED frequency range indication display
- Reaction Tune with Scout
- Capture 5 watt UHF signal from 500 feet
- 1000 frequency lockout

$299

TA100S Antenna Included

XPLORER

- 30MHz - 2GHz (Cellular Blocked)
- Two line LCD frequency display
- Decode CTCSS, DCS, and DTMF
- 500 memories
- 1000 frequency lockout
- Built-in PC interface
- Capture 5 watt UHF signal from 800 feet

$799 SAVE $100

TA100S Antenna Included

In The Spotlight



OPTOCOM

- High speed triple conversion GRE receiver
- Track Motorola 400, 500, 800, and 900MHz systems
- Decode CTCSS, DCS, LTR, DTMF, and Motorola talk group IDs
- Scan trunked and conventional frequencies simultaneously
- Reaction Tune with Scout Frequency Recorder
- Software Controlled volume & squelch for remote control operation
- Store & Scan, download up to 28 different frequencies or one talk group ID for scanning without computer control
- Supplied with the all new Trakkstar software
- Trunk Track LTR systems
- Scans conventional frequencies from 25-250, 760-823.995, 849.005-868.995, 894.005-1300MHz (Cellular frequencies blocked)

Special Prices are for a Limited Time Only!!

COUNTERS

Handheld frequency counters, all incorporating patented Digital Filter and Digital Auto Capture. All counters come with initial accuracy of +/- 1ppm. High impedance amplifiers standard on M1 and 3000APlus. Call for additional features on all three counters.

CUB **$149**
M1 **$199**
3000A+ **$299**

SAVE $50 on the M1 & 3000A+

Antennas Sold Separately

OPTOTRAKKER

- Decodes CTCSS, DCS, LTR, Motorola Type I and II, and DTMF
- Scan multiple trunked systems at the same time under computer control
- All trunked frequency bands supported, including 400MHz, 500MHz, 800MHz and 900MHz
- Built-in Data Slicer Circuit
- Pass through technology requires only one com port

$299 Includes Software

Receivers supported under computer control: Icom R7000, R7100, R8500, R9000 and R10, AOR AR8000, AR3000A, AR5000, and Pro 2005/6 with OS456/OSLite, Pro 2035/42 with OS535

OPTOSCAN

- Computer control scanning interface board for the popular RadioShack Pro 2005/6 (OSLite) and Pro 2035/42(OS535).
- Decode CTCSS, DCS, and DTMF with OS535 only
- Supported by popular third party software

$175 SAVE $24

OS456Lite: $99

TECHTOYZ

Micro Test equipment in pager style cases featuring a 2000 character DTMF decoder, a Frequency Counter with three memory hold, and an RF Detector with setable threshold alarm.

MicroCounter **$99**
MicroDTMF **$99**
MicroRF Detector **$149**

Purchase all three for $299 Save $48

TMC100 Antenna Sold Separately ($9)

FACTORY DIRECT ORDER LINE 800-327-5912

Made in the **U.S.A**

www.optoelectronics.com

OPTOELECTRONICS®

5821 N.E. 14th Avenue • Ft. Lauderdale, FL • 33334

Telephone: (954)•771•2050 Fax: (954)•771•2052 EMail: sales@optoelectronics.com

Prices and Specifications are subject to change without notice or obligation

The OptoCom has not been approved by the Federal Communications Commission. This device may not be sold or offered for sale until the approval of FCC has been obtained. Contact Optoelectronics for information on availability. Optoelectronics, ScanStar, Motorola, EF Johnson LTR and Microsoft Windows are all registered trademarks. Scout, 3000A+, R11, Xplorer, MicroCounter, M1, Cub are covered by U.S. Patent No. 5,471,402.

Write in 83 on Reader Service Card.

BASIC Stamp® Computers

Application ideas and Parallax Fall events

BASIC Stamps are small computers programmed in Parallax BASIC (PBASIC), a simple programming language with powerful I/O instructions to control external circuitry. There's no shortage of application ideas using BASIC Stamps. Take a look at our manual (23 AppNotes), Scott Edwards Programming and Customizing the BASIC Stamp book (11 AppNotes), and Nuts and Volts Magazine (over 30 regular columns). If you've got an idea and want to know if it will work with a BASIC Stamp, please call and ask for one of our tech support staff.



JP Aerospace, "America's other space program" is a competitor in the private race to space. The Davis, California, group has flown to 100,000 feet at speeds over Mach 2 miles. With their 8-foot rocket, they hope to reach space by the end of 1998. Camera control, altimeter data logging, and parachute deployment are controlled by a BS1-IC module. Program details are shown at **http://www.jpaerospace.com**

BASIC Stamp II Starter Kit #27203 - $149
BASIC Stamp II module #BS2-IC - $49

BASIC Stamp I Starter Kit #27205 - $99
BASIC Stamp I module #BS1-IC - $34

BASIC Stamp Rev.D Starter Kit #27202 - $79
BASIC Stamp Rev.D module #27100 - $34
(Rev.D not shown)



BASIC Stamp I module

BASIC Stamp II module

Visit Parallax, Inc. at COMDEX!

COMDEX®

BOOTH S8152 Sands Lower Level
November 16 through 20, 1998
Las Vegas, Nevada
Free tickets available at our website **http://www.parallaxinc.com**

EMBEDDED SYSTEMS CONFERENCE

...and Embedded Systems too!
Ideal place to learn about our range of development tools for the SX microcontroller.
Booth 5061, San Jose Convention Center
San Jose, California
November 1 to November 5, 1998
Register at **http://www.embedded.com**

Programming & Customizing the BASIC Stamp Computer book by Scott Edwards #27951 - $34

http://www.parallaxinc.com

PARALLAX inc

to order call toll free 888.512.1024
additional shipping & handling on all orders

BASIC Stamp and the Parallax, Inc. logo are registered trademarks of Parallax, Inc. Comdex and the Comdex logo are registered trademarks of ZD Events, Inc.

ATTENTION: NUTS & VOLTS MONTHLY PRIZE DRAWING!

WIN a BASIC Stamp II Professional Package in the Nuts & Volts monthly prize drawing!

This kit has been specially assembled by Parallax, Inc. and includes the following:

- (1) BASIC Stamp II Starter Kit
- (1) additional BS2-IC Module
- (1) BASIC Stamp Activity Board
- (1) DS1620 Digital Thermometer AppKit (not shown)
- (1) LTC1298 A/D AppKit (not shown)
- Standard Servo

BASIC Stamp II Professional Package
a $350 value!

Write in 195 on Reader Service Card.

NUTS & VOLTS MAGAZINE
430 PRINCELAND COURT
CORONA, CA 91719

CHANGE SERVICE REQUESTED

BULK RATE
U.S. POSTAGE
PAID
PERMIT No. 359
LONG BEACH CA